

SAMSUNG



SAMSUNG Inkjet Telephone Fax User's Guide

SF-340 series



www.samsungprinter.com

P/N:JB68-00903A Rev.4.00

For UK customers:
To reorder your consumables
Call 0800 3164060
For Technical Assistance
Call 0870 2420303

Important Precautions and Safety Information

When using this fax machine, these basic safety precautions should always be followed to reduce risk of fire, electric shock, and injury to persons:

- 1** Read and understand all instructions.
- 2** Use common sense whenever operating electrical appliances.
- 3** Follow all warnings and instructions marked on the product and in the literature accompanying the product.
- 4** If an operating instruction appears to conflict with safety information, heed the safety information. You may have misunderstood the operating instruction. If you cannot resolve the conflict, contact your sales or service representative for assistance.
- 5** Unplug the fax machine from the AC wall socket and telephone jack before cleaning. Do not use liquid or aerosol cleaners. Use only a damp cloth for cleaning.
- 6** Do not place the fax machine on an unstable cart, stand, or table. It may fall, causing serious damage.
- 7** Your fax machine should never be placed on, near, or over a radiator, heater, air conditioner, or ventilation duct.
- 8** Do not allow anything to rest on the power or telephone cords. Do not locate your fax machine where the cables may be damaged by people walking on them. Do not place the machine where the power or telephone cord may be bent. Any case of above may cause the hazardous result or malfunction.
- 9** Do not overload wall outlets and extension cords. This can diminish performance, and may result in the risk of fire or electric shock.
- 10** Do not allow pets to chew on the AC power, telephone, or PC interface cords.
- 11** Never push objects of any kind into the fax machine through case or cabinet openings. They may touch dangerous voltage points, creating a risk of fire or shock. Never spill liquid of any kind onto or into the fax machine.
- 12** To reduce the risk of electric shock, do not disassemble the fax machine. Take it to a qualified service technician when repair work is required. Opening or removing covers may expose you to dangerous voltages or other risks. Incorrect reassembly could cause electric shock when the unit is subsequently used.

- 13** Unplug the machine from the telephone jack, PC, and AC wall outlet, and refer servicing to qualified service personnel under the following conditions:
- *When any part of the power cord, plug, or connecting cable is damaged or frayed.*
 - *If liquid has been spilled into the product.*
 - *If the product has been exposed to rain or water.*
 - *If the product does not operate properly after instructions have been followed.*
 - *If the product has been dropped, or the cabinet appears damaged.*
 - *If the product exhibits a sudden and distinct change in performance*
- 14** Adjust only those controls covered by the operating instructions. Improper adjustment of other controls may result in damage, and may require extensive work by a qualified service technician to restore the product to normal operation.
- 15** Avoid using this fax machine during a lightning storm. There may be a remote risk of electric shock from lightning. If possible, unplug the AC power and telephone for the duration of the lightning storm.
- 16** Do not install the machine on a wet place. This may raise a risk of fire or shock.
- 17** SAVE THESE INSTRUCTIONS.
- 18** CAUTION : For electrical safety reasons disconnect from telecommunications network before touching metal/conductive parts.
- 19** CAUTION : To reduce the risk of fire, use only No.26 AWG or larger telecommunication line cord.

Contents

Chapter 1: Setup and Copying

List of features	1.2
Familiarizing yourself with your new machine	1.3
Front view	1.3
Rear view	1.3
Control Panel	1.4
Loading paper	1.5
Paper type and sizes	1.5
Making a copy	1.6
Setting date and time	1.6
Setting fax number/name	1.7
How to enter letters	1.7
Copying/receiving in Ink Save mode	1.8
Adjusting ring volume	1.8
Adjusting speaker volume	1.8

Chapter 2: Programming and Dialling

Making a phone call	2.2
On-Hook dialling	2.2
Phonebook dialling	2.2
Storing a number in the Phonebook	2.2
One-Touch dialling	2.3
Speed dialling	2.3
Searching for a number in memory (Directory dialling)	2.3
Searching sequentially through the Phonebook	2.3
Searching for a particular first letter	2.4
Redialling	2.4
To redial the last number called	2.4
To redial the number in memory	2.4
To find a number received via the Caller ID service	2.4

Chapter 3: The Fax Machine

Sending a fax	3.2
Loading documents	3.2
Acceptable documents	3.2
Setting document resolution and contrast	3.3
Sending a fax manually	3.3
Sending a fax automatically	3.3
Automatic redial	3.4
Receiving a fax	3.4
Reception modes	3.4
Receiving in FAX mode	3.5
Receiving in TEL mode	3.5
Receiving in AUTO mode	3.5
Receiving in TAM mode	3.5
Receiving in TAM mode (SF-345TP)	3.6
Receiving in DRPD mode	3.6
Receiving via an extension telephone	3.6

Chapter 4: The Answering Machine

Recording your TAM message	4.2
Checking your TAM message	4.2
Monitoring an incoming call	4.2
Playing back messages	4.3
Playing back newly received caller messages	4.3
Playing back all messages	4.3

Skipping backward or forward	4.3
Erasing old messages you've heard	4.4
To erase a selected message	4.4
To erase all recorded messages	4.4
Using the answering machine from a remote phone	4.5
Accessing the machine	4.5
Using remote commands	4.5

Chapter 5: Advanced Fax

Broadcasting	5.2
Delayed fax	5.2
Using My Favorites	5.3
Saving documents	5.3
Deleting stored documents	5.3
Sending stored documents	5.3
Printing stored documents	5.3
Polling	5.4
Setting send polling	5.4
Setting receive polling	5.4
To cancel the scheduled job	5.4
Forwarding a fax or message	5.5
Fax forwarding	5.5
Message forwarding (SF-345TP only)	5.5
Received fax remote notification (SF-345TP only)	5.6

Chapter 6: Special Features

Inserting a pause	6.2
Using Recall (R or Flash)	6.2
Using Caller ID	6.2
Using the Mute	6.3
To mute a call	6.3
To release the mute	6.3
Recording a conversation (SF-345TP only)	6.3
Sound setup	6.3
User reports	6.4
To print a report	6.4
Re-Printing faxes	6.5
Registering/deleting the junk fax numbers	6.5
Entering junk fax setup mode	6.5
Using Short Message Service (SMS)	6.6
Reading SMS messages	6.6
Printing SMS messages	6.6
Deleting stored SMS messages	6.6
Setup SMS messages	6.7
Clearing memory	6.8
User options	6.8
Setting system/TAM options	6.8

Chapter 7: Using Printing

Making Connection	7.2
Installing Samsung Software	7.2
System Requirements	7.2
Installing Printer Software	7.2
Setting the default printer	7.4
Reinstalling Software	7.4
Uninstalling Software	7.5
Printing a Document	7.5

Cancelling a Print Job	7.7
Using Help	7.7

Chapter 8: Care and Maintenance

Cleaning the document scanner	8.2
Replacing the print cartridge	8.3
Cleaning the printhead	8.4
Aligning the printhead	8.4
Ink level view	8.4
Shading adjustment	8.4
Self testing	8.5
Print cartridge maintenance	8.5
Cleaning the cartridge	8.5
Wiping the print nozzles and contacts	8.5
Cleaning the cartridge carrier contacts	8.6
LCD error messages	8.7
Fixing Problems	8.9
Fax problems	8.9
Print quality problems	8.10
Paper feeding problems	8.10
Clearing jams	8.11
Document jams during transmission	8.11
Paper jams during printing	8.11

Chapter 9: Appendix

Specifications	9.2
A sample of ITU #1 chart (reduced to 60.5%)	9.3
Font List for Print	9.4
Font List for LCD	9.5
Replacing the fitted plug (UK)	9.6
Notes for use of this device (New Zealand)	9.6
Declaration of conformity (European countries)	9.7
In case of interference (US)	9.9
Fax branding (US)	9.9
Telephone company information (US)	9.10

Index

CHAPTER 1

SETUP AND COPYING

This chapter describes the preliminary setup procedure. A full installation instruction is explained in the separate Installation Guide. If you are installing or reinstalling the machine from the beginning, refer to the Installation Guide provided with the machine.

List of features

This machine was designed using the latest technology. It is a full-featured, high-performance machine that not only meets, but also exceeds industry standards. The following is a list of its many exciting features:

Common features to SF-340 Series (SF-340/SF-345TP)

- *Save Ink (see "Copying/receiving in Ink Save mode" on page 1.8.)*
- *Inkjet printing on plain paper*
- *14.4Kbps high speed faxing*
- *40 page holding memory(SF-340), 100 page holding memory(SF-345TP)*
- *Multilingual display and report; English, German, French, Italian, Spanish, Portuguese and Dutch (see "Language" on page 6.9.)*
- *Stand-alone, full-function fax machine*
- *Convenient 50 page desktop copier*
- *10 page Skew Free Document Feeder*
- *80 Speed Dialling locations (10 One-Touch included)*
- *Five reception modes; TEL, FAX, AUTO, TAM¹(Telephone Answering Machine) and DRPD*
- *Broadcasting to send the same document to multiple destinations*
- *Delayed FAX to send the document at a later time*
- *Send/Receive Polling*
- *Last 10 number redial*
- *Report management; sending confirmation, Journal report and Phonebook, etc*
- *Receive short messages*
- *Stored FAX to send the document without original document*
- *My Favorites*
- *Wake up Sound*

Features for SF-345TP only

- *PC printing capability*
- *Compatible with the most recent operating system*
- *Network sharing*
- *Built-in digital TAM*
- *Access from a remote telephone*
- *Message Forwarding (you can have the machine transfer a call when the caller leaves a message.)*
- *Call monitor*
- *FAX Receiving Notice (you can know with Voice Message when the machine receives a new fax.)*
- *Speaker Phone*
- *This printer supports only black print.*

SF-340 : Inkjet Facsimile

SF-345TP : Inkjet Multi Function Device

1. If your machine is an SF-340, you need to have an answering machine attached.


Familiarizing yourself with your new machine

Take a moment to familiarise yourself with your new machine by looking at the pictures on the next few pages.

Front view²



Rear view



2. Note that all of illustrations on this User Guide are from SF-345TP, so some parts may be different from your machine.

Control Panel



Button name	Function
Ink Save	Used for less ink consumption. It toggles On and Off.
Silent	Used when you want to turn off all sounds made by the machine.
My Favorites	Used to store the document used frequently and send it conveniently.
Cartridge Change	Used to install a new cartridge or replace an old one.
Resolution	Improves the clarity of a document you are sending.
Rcv.Mode/Darkness	This button has two functions: When no document is loaded, pressing this button changes the Receive Mode. When a document is loaded, the pressing this button changes the contrast.
OGM (SF-345TP only)	Used to record or play the outgoing message used in TAM Mode.
Play/Record (SF-345TP only)	Plays incoming messages. Used to record a phone conversation.
Erase (SF-345TP only)	Used to erase a message or all messages.
TAM (SF-345TP only)	Switches the TAM mode on/off. It lights when in TAM Mode and blinks when a new message is received.
◀◀ (SF-345TP only)	Used to repeat the current message, or to skip back to the previous one.
▶▶ (SF-345TP only)	Used to skip forward to the next message.
Number keypad	Dial numbers manually as you would usually do with the telephone, or enter letters while setting up your machine.
Symbols	Used to enter special characters when entering a name in edit mode.
Speed	Used to store and dial the most frequently used 80 telephone/fax numbers with two-digit location number.
Recall (R/Flash)	Performs a switch-hook operation.
Redial/Pause	Used to redial the last number called. You can also use it to add a pause while storing a number in memory.
Phone Book/Mute	To mute the phone while you are speaking via the microphone. To search for a number in memory.
Speaker Phone (or On Hook Dial)^a	Used to speak without picking up the handset (SF-345TP only), or dial numbers.
Menu	Used to choose special functions such as system setup and maintenance, etc.

Button name	Function
 Scroll/Volume	Used to display the previous or next menu item, to adjust the volume, or to move the cursor to the digit you want to edit.
Enter	Used to activate the selection shown in the display.
Upper Level	Used to return to the previous menu level.
Start Copy	Used to copy a document.
Start Fax	Used to start a job.
Stop/Clear	Stops an operation at any time. Or used to delete digits in the edit mode.


a.Speaker Phone : SF-345TP only
On Hook Dial : SF-340 only

Loading paper

To receive faxes or make copies, you should load the paper in the ASF³. You can load approximately 50 sheets of paper. Before loading the paper, see if the paper size is set correctly in the System Setup.

For more information, see "Paper Size" on page 6.9.

- 1 Flip the Paper Support open.
- 2 Pull the Dust Cover toward you.
- 3 Fan the papers and insert them into the ASF with the print side face up.
- 4 Squeeze the Paper Guide, and move it to the right to match the width of the paper.
- 5 When completed, replace the Dust Cover to its original position.



Paper type and sizes

Satisfactory print and receive quality can be obtained with many types of plain paper. Since the quality of plain paper varies widely, test the print quality before buying large quantities of paper. Your machine uses a variety of papers including:

- Xerographic paper
- Bond paper
- Dual-purpose paper

Because all paper varies in physical characteristics, you can receive mixed results from different packages of paper even though the packages contain the same type of paper. If you encounter undesirable results, try the other side of the paper, a different type, or another package of the same kind of paper.

DO NOT use the following types of paper with your machine:

- Continuous form feed paper
- Synthetic paper
- Thermal paper
- Multi-sheet forms and documents
- Chemically treated paper
- Papers with raised, embossed lettering

3. Automatic Sheet Feeder.


The following print media can be used with your machine:

Paper size	Dimensions	Paper weight
A4	210mm x 297mm (8.3" x 11.7")	70 ~ 90g/m ² (20 ~ 24lbs)
Letter	216mm x 279mm (8.5" x 11.0")	
Legal	216mm x 356mm (8.5" x 14.0")	

Making a copy

If you want to save ink while copying or receiving a fax, see "Copying/receiving in Ink Save mode" on page 1.8.

- 1 Turn the page face down and insert it into the document feeder.
- 2 Adjust the document guide to match the width of the document.
- 3 Feed the document into the machine.
- 4 Adjust the resolution by pressing **Resolution**.
 - In case you selected the Standard, it automatically changes to Fine mode.
- 5 Press **Start Copy**.
 - The display shows Number of Copies.
- 6 Enter the number of copies you want, and press **Enter**.
 - The display shows Zoom Rate.
 - If you want one copy without specific copy options, you can press **Start Copy** again at this time, and copying will start immediately.
- 7 Select the zoom rate you want by pressing < or >, and then press **Enter**.
 - You can scale the document from 50% to 150% by selecting a pre-defined rate. The default rate is 97%.
- 8 Choose if you want to collate document.
 - When collation is selected, you need to select the sorting order; Normal, Reverse.
- 9 Press **Enter** when all options have been selected.
 - When the machine runs out of paper, Load paper and press Enter appears in the display. Supply additional paper and press Enter.



Setting date and time

The current date and time are shown in the display when the machine is on and ready for use (Standby Mode).

The date and time will be printed on all faxes you send.

- 1 Press **Menu**.
- 2 Press < or > to choose SET DATE & TIME and press **Enter**.
- 3 Press **Enter** when the display shows Date Format.
- 4 Press < or > to select either Europe(D-M-Y) or USA(M-D-Y) and press **Enter**.

- 5 Press **Enter** when the display shows Date & Time.
- 6 Set the date and time. You can move the cursor by pressing < or >.
 - If you enter an invalid number, the machine beeps and doesn't proceed to the next step. If this happens, just re-enter the correct number.
 - When entering the hour, you should enter it in 24-hour format.
- 7 Press **Enter** when the date and time appear correctly.
 - The display shows the date and time you have set, then returns to Standby Mode.

Setting fax number/name

If this option is not selectable even though you followed the described steps, you have to consult the service technician or your dealer.

This is very useful information for the recipient. It allows them to see who sent a fax and what number they should send a response to.

- 1 Press **Menu**.
- 2 Press < or > to choose SET SYSTEM ID and press **Enter**.
- 3 Press **Enter** when the display shows Fax Number.
- 4 Enter the fax number to which your machine is connected.
 - You can enter up to 20 digits, and include special characters (space, plus sign, etc.)
 - To enter a delimiter, press #.
 - To enter plus symbol (+), press *.
 - If you enter a wrong number, use < or > to move to the number and correct it.
- 5 Press **Enter** when finished.
- 6 Press **Enter** when the display shows Fax Name.
- 7 Enter the fax name (up to 40 characters) by using the number keypad.
 - You can include special characters (space, plus sign, etc.).
- 8 Press **Enter** when the name in the display is correct.
 - The machine returns to Standby Mode when you have finished or when **Stop/Clear** has been pressed.

How to enter letters

These instructions assume that the display is asking you to enter a name.

- 1 Press the appropriate button for the letter you want.
 - To enter an O, for example, press the 6 button three times. Each time you press the button, the display shows a different letter: first M, then N, an O, and finally 6.
 - For a list of letters and corresponding buttons, see "Keypad character assignments" on page 1.8.
- 2 Select the next letter in the same way.
 - The blinking cursor moves right and the next letter appears in the display.
 - If the letter is assigned to the same button you have pressed in step 1, then first move the cursor by pressing < or >, then press the button.
- 3 Press **Enter** when you're finished entering letters.

Keypad character assignments

Key	Assigned numbers, letters, or characters	Key	Assigned numbers, letters, or characters
1	(Space) 1	6	M N O 6
2	A B C 2	7	P Q R S 7
3	D E F 3	8	T U V 8
4	G H I 4	9	W X Y Z 9
5	J K L 5	0 (Symbols)	+ - , . ' / * # & 0

Copying/receiving in Ink Save mode

Your machine has an Ink Save mode to optimize consumption of ink when copying and receiving a fax.

Press **Ink Save**.

- The button backlights to indicate Ink Save mode is active. From now on, every printout except reports will consume less ink.
- If you feel the print quality is not good enough, exit the Ink Save mode by pressing the **Ink Save** button again and print quality will return to normal mode.

Adjusting ring volume

Your machine has several levels of ring volume. Adjust it as you prefer.

Press **Scroll/Volume** with machine in standby.

- Whenever you press the button, different ring is ringing.
- The volume 0 indicates that the machine will not ring when the call is received.

Adjusting speaker volume

When you are speaking via the speaker phone, you can adjust the volume as you follows:

1 Press **Speaker Phone (or On Hook Dial)**.

- You can adjust it when you are talking as well.

2 Press **Scroll/Volume** as many times as you want.

- Whenever you press the button, it will increase or decrease the volume.



CHAPTER 2
PROGRAMMING AND DIALLING

Making a phone call

Your new machine provides many ways for making a phone call. You can use either of following:

- *On-Hook dialling*
- *Phonebook dialling (One-Touch and Speed dial)*
- *Directory dialling*
- *redialling*
- *manual dialling via the handset as you do with a regular telephone*

On-Hook dialling

You do not need to pick up the handset to make a phone call. When dialling, just press the **Speaker Phone (or On Hook Dial)** button and enter the numbers. Depending on your machine, you need to pick up the handset or keep speaking through the microphone.

If you have an SF-340

- *You have to pick up the handset to speak after the call is answered.*
- *If you want to share the conversation with somebody beside you, pick up the handset and press **On Hook Dial**. The line is still connected and everybody can listen to the conversation. This is called a 1-way conversation.*
- *While you are using 1-way conversation, do not place the handset beside the speaker, as this may result in howling.*

If you have an SF-345TP

- *You do not need to pick up the handset. Speak into the microphone on the Control Panel when the call is answered.*

Phonebook dialling

There are two types of Phonebook dialling; One-Touch and Speed dial. The way to programme numbers into memory is the same for both but how you dial stored numbers is different. To One-Touch dial, you just press and hold a number (0-9) on the keypad and the number will be dialled. To Speed dial, you need to first press the **Speed** button and then the two-digit location number.

Phonebook dialling provides you with quick access to your most frequently used numbers. Before using Phonebook dialling, you must first programme the numbers into the memory.

Storing a number in the Phonebook

- 1** Press and hold the **Speed** button for about two seconds.
 - *The display shows Speed [00-80]>##.*
- 2** Enter a two-digit (00~80) number and press **Enter**.
 - *From 00 to 09 will be used for One-Touch dialling, and from 10 to 80 for Speed dialling.*
- 3** Enter the telephone/fax number you want to store (up to 40 digits) and press **Enter**.
 - *If you want a pause between numbers, press **Redial/Pause**; a 'P' appears in the display.*
 - *If you make a mistake while entering a number, use < or > to move the cursor under the digit, then enter the correct digit.*

4 Enter the name and press **Enter**.

- If you do not want a name, just skip this step by pressing **Enter**. If you have subscribed to a Caller ID service, it is recommended you enter a name.
- You can assign up to 20 characters to a name. see "How to enter letters" on page 1.7.

5 Press **Stop/Clear** to exit.

One-Touch dialling

1 Place document(s) if you are sending a fax.

2 Press and hold one of the number keypad. (0 through 9)

- The display briefly shows the name or number and the number is then automatically dialled. You hear the dialling process through the speaker.
- When the remote fax machine answers, the machine scans the document into memory and begins to transmit if a document is loaded in the document feeder.
- To send a fax directly without scanning into memory, turn off the Send From Memory option. (see "Send From Memory" on page 6.9.)
- You can refer to the number assigned to each location by printing the Phonebook. see "To print a report" on page 6.4.
- Regardless of the setting of the Send From Memory option, the machine will first dial and then send a fax if you set the resolution to Super Fine.

Speed dialling

1 Press **Speed**.

2 Enter a two-digit speed dial location number.

3 Press **Enter** to dial the number.

- The display briefly shows the name or number and the number is then automatically dialled. You hear the dialling process through the speaker.
- When the remote fax machine answers, the machine scans the document into memory and begins to transmit if a document is loaded in the document feeder.
- To send a fax directly without scanning into memory, turn off the Send From Memory option (see "Send From Memory" on page 6.9.)
- You can refer to the number assigned to each location by printing the Phonebook. see "To print a report" on page 6.4.
- Regardless of the setting of the Send From Memory option, the machine will first dial and then send a fax if you set the resolution to Super Fine.

Searching for a number in memory (Directory dialling)

You can search the entire Phonebook to find the number you want to dial.

Searching sequentially through the Phonebook

1 Press **Phone Book/Mute**.

2 Press < or > to move upward or downward through the directory until you find the number you want.

- Pressing > allows you to search downward through the entire Phonebook by incremental order of location number, and < allows you to search upward in decreasing order.

3 When the number you want appears in the display, press **Start Fax** to dial.

Searching for a particular first letter

- 1 Press **Phone Book/Mute**.
- 2 Press the button labelled with the letter you want to search for.
 - For example, if you want to find the name 'NEW YORK', press the '6' button, which is labelled with 'MNO'.
 - The machine finds the closest entry so you may need to specify as clearly as you can.
 - If the machine cannot find a name that begins with the given letter, the machine shows the message Not Found.
- 3 When the name and number you want appears correctly in the display, press **Start Fax** to dial.

Redialling

You can redial the number last called or one of ten unique numbers recently stored in memory.

To redial the last number called

- 1 Press **Redial/Pause**.
 - The number is dialled automatically.
 - If a document is loaded, the machine automatically begins to send. If there is no number stored, the machine will beep.
- 2 Speak into the microphone when the call is answered.
 - Pick up the handset, if you are an SF-340 user.

To redial the number in memory

- 1 Press and hold **Redial/Pause** for about two seconds.
- 2 Select Recent Numbers and press **Start Fax**.
 - The display shows the most recent numbers.
- 3 Press < or > to find the number you are dialling.
- 4 Press **Start Fax** when the correct number appears.
 - If a document is loaded, the machine automatically begins to send.

To find a number received via the Caller ID service

You sometimes need to see who has called you. To see the number or name follow the instructions below:

- 1 Press and hold **Redial/Pause** for about two seconds.
- 2 Select Caller ID and press **Enter**.
- 3 Scroll through the numbers by pressing < or >.
 - The Caller ID displays in two ways. One is by name and other is by number. If the number is the same as the one you saved to a One-Touch or Speed dial location and you assigned a name to that location, the machine shows the name instead of the number.




CHAPTER 3
THE FAX MACHINE

Sending a fax

Sending a fax is very simple if you follow the instructions starting from here. They will describe how to load the document, set the resolution/contrast and dial the number.

Loading documents

- 1 Load your document(s) top down in the document tray with the printed side facing away from you.
 - *Be sure that your document is dry and free of staples, paper clips, and other foreign objects.*
 - *For more information on what kind of paper you can use for documents, see "Acceptable documents" on page 3.2.*
- 2 Adjust the document guides to match the width of the document, and load document consisting of up to 10 sheets until the Automatic Document Feeder seizes and pulls it in. The display will indicate Document Ready when it senses that a document has been loaded.
 - *If you are sending more than one sheet, make sure the bottom sheet enters first. Insert the sheets with a slight push to ensure smooth feeding.*
 - *If you're loading pages that are unusually thick or thin, feed one sheet at a time. If the document doesn't feed correctly, open the Control Panel, remove the document, and try loading it again.*
- 3 Choose the proper resolution and contrast by pressing **Rcv.Mode/Darkness** and **Resolution** respectively.



Acceptable documents

		Single sheet	2 or more sheets
Document size	Max	216mm (W) x 356mm (L) ^a	216mm (W) x 297mm (L)
	Min.	148mm (W) x 128mm (L)	
Effective scanning width		210mm	
Number of sheets which can be loaded at a time		-	Up to 10
Thickness of document		0.07mm ~ 0.15mm	0.075mm ~ 0.12mm
Paper quality		Uncoated on both sides	

a. When sending a document that is longer than A4 in size, you must immediately take out each sheet as soon as it has been scanned. Otherwise, the document may jam.

For multiple sheets, all pages of the document must be the same size and paper type.

DO NOT try to send documents that are:

- *wet*
- *covered with wet ink or paste*
- *wrinkled, curled, or folded*
- *too thin (less than 0.07mm thick-onionskin, airmail paper, etc.)*
- *too thick (more than 0.15mm thick)*
- *chemically processed (pressure-sensitive paper, carbon-coated paper, etc.)*
- *coated (glossy, etc.)*
- *too small or short (such as a label, voucher, etc.)*
- *made of cloth or metal*

To send these documents, use an office copier to make a photocopy first, and then send the copy.

Setting document resolution and contrast

We recommend you send documents printed using a typewriter, felt tip pen, black ink, or LaserWriter. The paper should be white or very light, and of normal weight not cardboard.

Blue lines on a ruled pad don't fax well. For more information on what kind of paper you can use for documents, see "Paper type and sizes" on page 1.5. When you send/copy normal documents, you need not adjust the resolution and the contrast.

If you send/copy documents with unusual contrast characteristics, including photographs, you can adjust the resolution and contrast to send a high-quality transmission of the documents.

To adjust the resolution and contrast

- 1 Turn the page face down and insert it into the document feeder.
For more information, see "Loading documents" on page 3.2.
- 2 Press **Resolution** as many times as you want to adjust the sharpness and clarity.
 - *STANDARD works well for printed or typewritten originals with normal-sized characters.*
 - *FINE is good for documents containing a lot of detail.*
 - *SUPER FINE works well for documents containing extremely fine detail. SUPER FINE only works if the remote machine also has the SUPER FINE feature.*
 - *SUPER FINE mode is not used when sending documents scanned into memory (i.e. Smart Sending, Broadcasting and Delayed Fax).*
 - *If you are sending document by using memory (broadcasting, delayed tx, for example), SUPER FINE will be changed back to FINE even though you selected SUPER FINE.*
- 3 Press **Rcv.Mode/Darkness** as many times as you want to adjust the darkness.
 - *NORMAL works well for normal handwritten, typed, or printed documents.*
 - *LIGHTEN works with very dark print.*
 - *DARKEN works with light print or faint pencil markings.*
 - *PHOTO is used when faxing photographs or other documents containing color or gray shades. When Photo is chosen, the resolution is automatically set to FINE.*
 - *When sending/copying is executed, resolution/contrast automatically returns to default.*

Sending a fax manually

- 1 Turn the page face down and insert it into the document feeder.
For more information, see "Loading documents" on page 3.2.
- 2 Pick up the handset or press **Speaker Phone (or On Hook Dial)**.
- 3 Enter the number of the remote fax machine by using the number keypad.
- 4 Press **Start Fax** when you hear the fax tone.
- 5 Replace the handset.

Sending a fax automatically

To send a fax automatically, you must have already stored numbers into Speed Dial locations. To learn how to register One-Touch Dial or Speed Dial, see "Storing a number in the Phonebook" on page 2.2.

- 1 Turn the page face down and insert it into the document feeder.
For more information, see "Loading documents" on page 3.2.
- 2 Enter the One-Touch or Speed Dial location.
If you are using the Speed Dial, you have to press **Enter**.
 - *The machine scans the document into memory and begins to transmit. If you turned off the Send From Memory option, the machine will first dial and send.*
 - *You can set your machine to print out a Sending Confirm automatically. For more information, see "Sending Confirm" on page 6.9.*

Automatic redial

When you send a fax, if the number you have dialled is busy or there is no answer, the machine will attempt to redial the number every three minutes up to two times.

Before redialling, the display shows *To redial now, press Start Fax.*

If you want to redial the number immediately, press **Start Fax**.

Or, press **Stop/Clear** to cancel redialling and then the machine returns to Standby Mode.

Receiving a fax

Before you receive a fax, be sure to load one of the supported paper sizes for receiving faxes. For information on what paper types you can use, see "Paper type and sizes" on page 1.5.

Reception modes

Your fax machine has various reception modes; FAX, TEL, AUTO, TAM and DRPD. For DRPD Mode, see "DRPD Mode" on page 6.10. first. If you are an SF-345TP user, you have to press the **TAM** button to select TAM mode. Do not press the **Rcv.Mode/Darkness** button. You can change the reception mode by pressing **Rcv.Mode/Darkness** when no document is loaded. The following chart describes how each reception mode works:

Reception mode	Your model	How it works	Reference section
FAX	All	The machine answers an incoming call and immediately goes into receive mode, expecting a fax to be received.	Receiving in FAX mode on page 3.5.
TEL		The automatic fax reception is turned off. You can receive a fax only by manually pressing Start Fax .	Receiving in TEL mode on page 3.5.
AUTO		Your fax machine will answer faxes automatically after the number of rings you specify. If the machine does not pick up a fax signal, it will give another ringing tone to tell you it is a phone call. You should lift the handset to answer the call. If you do not pick up the handset on your fax machine, it will switch to the automatic reception mode.	Receiving in AUTO mode on page 3.5.
TAM	SF-345TP	Your machine plays a greeting message to callers, and then the caller can leave an incoming message on your machine as well as a fax.	Receiving in TAM mode (SF-345TP) on page 3.6.
	SF-340	You have to have an answering machine attached to the EXT line socket on your fax machine. When the phone rings, the attached answering machine answers and stores the caller's message if they leave one. If your machine senses a fax tone on the line, the call automatically switches over to fax receive mode.	Receiving in TAM mode on page 3.5.

If you rarely use the fax line for voice conversation, set the machine to receive faxes automatically by selecting either FAX or AUTO Mode.

Receiving in FAX mode

To set the machine to FAX Mode, press **Rcv.Mode/Darkness** repeatedly until Fax Mode is displayed.

- In Standby Mode, FAX appears in the right hand corner of the display.
- When you get a call, the machine answers after the second ring, and receives the fax automatically. When reception is complete, the machine returns to Standby Mode.
- If you want to change the 'Rings to Answer' option, see "Rings To Answer" on page 6.9.

Receiving in TEL mode

To set the machine to TEL Mode, press **Rcv.Mode/Darkness** repeatedly until Tel Mode is displayed.

In Standby Mode, TEL appears in the right hand corner of the display.

- 1 Pick up the handset and answer it when the telephone rings.
If your machine is an SF-345TP, and you do not answer the call within pre-defined rings⁴, the TAM OGM will be played.
- 2 Press **Start Fax** if you hear a fax tone, or if the person on the other end asks you to receive a document. Be sure there is no document loaded, or the document will be sent to the caller's fax showing 'Send' in the display.
- 3 Hang up the handset.

Receiving in AUTO mode

To set the machine to AUTO Mode, press **Rcv.Mode/Darkness** repeatedly until Auto Mode is displayed.

- In Standby Mode, AUTO appears in the right hand corner of the display.
- When a call comes in, the machine answers it. If a fax is being received, the machine goes into receive mode. If the machine does not sense a fax signal, it will continue ringing to tell you it is a phone call. You should pick up the handset to answer the call, or it will switch to automatic reception mode, after approximately 25 seconds.

Receiving in TAM mode

To use this receiving mode, you need to have an answering machine attached. To set the machine to TAM Mode, press **Rcv.Mode/Darkness** repeatedly until TAM MODE is displayed.

In Standby Mode, TAM appears in the right hand corner of the display.

- When a call comes in, the answering machine answers and stores the caller's message if they leave one. If the machine detects a fax signal, it goes into receive mode.
- If you have set your machine to TAM Mode and your answering machine is switched off, or the answering machine is not connected to your fax machine, the machine will automatically go into receive mode after several rings.
- If your answering machine has a 'User-Selectable Ring Counter', set the machine to answer an incoming call in less than 4 rings.
- If the sound level of the call is too low due to a poor phone connection, the fax machine or answering machine may not work properly.
- When you set the machine to TEL Mode and you have an answering machine attached, you must make sure you switch off the answering machine, or, the outgoing message will interrupt your phone conversation. Not all answering machines will work with your fax machine.
- When your answering machine answers an incoming call, it records a fax tone until it realizes it is a fax coming through. Due to this, your answering machine may tell you a voice message has been left, even when it is actually a fax.

4. UK: 20, other countries: 13

Receiving in TAM mode (SF-345TP)

If you are an SF-345TP user, you have to activate/deactivate the TAM Mode by pressing the **TAM** button, not by **Rcv.Mode/Darkness**. Once you press **TAM** to turn TAM Mode on, the machine returns to Standby Mode after playing the message back. TAM appears in the right hand corner of the display and the **TAM** button lights.

- When you get a call, the machine answers the call with the TAM greeting message.
- The machine records the caller's message. If a fax tone is sensed, the machine goes into receive mode.
- Anytime the greeting message is playing, or an incoming message is being recorded, you can talk to the other person by picking up the handset. If the memory becomes full while recording, your machine beeps a warning and disconnects the line. The machine will not function as an answering machine unless you make space by erasing unwanted recorded messages.
- If there is a power failure while recording a caller's message, it will not be recorded.
- When you want to talk to a caller on another telephone on the same line while recording an incoming message (ICM), lift its handset and press '#' (hash) and '*' (asterisk).

Receiving in DRPD mode

DRPD stands for Distinctive Ring Pattern Detection, which is a telephone company service. It enables a user to use a single telephone line to answer several different telephone numbers. To receive a fax in DRPD mode, you should first set DRPD and activate it. Once you have activated DRPD mode it can be one of the receiving modes which can be selectable by pressing the **Rcv.Mode/Darkness** button as FAX, TEL and AUTO. To set up DRPD, see "DRPD Mode" on page 6.10.

Press **Rcv.Mode/Darkness** repeatedly until DRPD Mode appears in the display.

- Now, the machine will manage faxes and call as programmed.
- In Standby Mode, DRPD appears in the right hand corner of the display.

DRPD must be set up again if you reassign your fax number, or connect the machine to another telephone line. After DRPD has been set up, call your fax number again to verify that the machine answers with a fax tone, then have a call placed to a different number assigned to that same line to be sure the machine answers the normal phone call.

Receiving via an extension telephone

If you have an extension phone connected to your machine, you can remotely control your fax machine to start receiving.

- 1 Answer the call on the extension phone.
- 2 Press *9* (remote receive start code) in sequence when you hear a fax tone.
 - Your fax machine detects the code and starts to receive the document.
 - The code is preset at the factory. The first and the last asterisks are fixed, but you can change the middle digit to whatever you prefer 0 through 9. For more information, see "Rcv. Start Code" on page 6.9.
- 3 Hang up the phone when your fax machine starts to receive.



CHAPTER 4

THE ANSWERING MACHINE

This chapter is only for SF-345TP users. If your machine is SF-340, please refer to the User's Guide supplied by the answering machine manufacturer.

In this chapter, you will learn how to check your TAM greeting message, monitor incoming calls, play/erase messages, and access your machine from a remote telephone. All the instructions in this chapter assume that your fax machine is set to TAM Mode. The SF-345TP uses electronic memory as a recording medium. Recording time is dependent on the content of the message. The total recording time (TAM OGM + ICM) is about 15 minutes.

Recording your TAM message

The TAM message is an outgoing message (OGM) which plays whenever a call comes in and the machine is in TAM Mode. For more information about reception modes, see "Receiving in TAM mode (SF-345TP)" on page 3.6.

- 1 Press and hold **OGM** until you hear a beep.
- 2 Speak into the microphone on the Control Panel within 30cm range from the time you see Record in the display.
 - You can record a message which lasts up to 20 seconds.
 - You are advised to record a message of less than 15 seconds in duration to prevent the incoming faxes from malfunctioning due to a long message.
 - Press **Stop/Clear** or **OGM** if you want to stop recording before the time is up.
 - After the message has been recorded, the machine briefly displays the date and time when the message was recorded. Then, it displays the elapsed time as the message plays back automatically.

Checking your TAM message

The TAM message plays back when your machine is in TAM Mode and receives a call.

Press **OGM**.

- The display shows the time when the message was recorded. The display then counts down the seconds as the message is playing back.

Monitoring an incoming call

Call Monitoring is useful for screening calls in case you do not want to be disturbed by the person calling. To use this feature, you have to first set Call Monitoring ON through the TAM Options. To learn how to set this feature on or off, see "Call Monitor" on page 6.10.

- 1 When the call monitor option is on and an incoming message is being recorded, you hear the caller's voice through the speaker.
- 2 Lift the handset to speak to the caller.
 - The machine stops recording the caller's message and you can speak directly to the caller.
 - If there is a power failure while recording a caller's message, it will not be recorded.

Playing back messages

When there are messages waiting to be heard, the **TAM** button flashes and the display shows that you have new messages, for example, New: 1 ICM: 3. ('New: 1' indicates there's one new message, and 'ICM: 3' says that there are three incoming messages recorded in total.)

Playing back newly received caller messages

Simply press **Play/Record**.

- *The machine briefly displays recorded time then starts to play the message. This procedure is repeated for all NEW messages.*
- *When the display reads 50s(01/03), '01' is the number of the caller message currently being played and '03' is the total number of new caller messages in memory. '50s' is the play back time for the message currently playing. This time counts down as the message plays back.*

Playing back all messages

Press and hold **Play/Record** until you hear a beep.

- *All the messages are played back. The display briefly shows recorded time of each message, then plays ALL the messages recorded.*
- *When the display reads 50s(01/03), '01' is the number of the caller message currently being played and '03' is the total number of caller messages in memory. '50s' is the play back time for the message currently playing. This time counts down as the message plays back.*
- *Press **Stop/Clear** or **Play/Record** to stop before the last message. While the message is playing back, the display shows a variety of useful information.*

Skipping backward or forward

To skip backward

Press |<<(1) while listening to the message.

- *If you press |<<(1) while playing back the message, the machine will replay it.*
- *The machine skips back to the previous message and plays it if you press |<<(1) twice.*

To skip forward

Press >>(3) while listening to a message.

- *The machine skips forward to the next message and plays it.*
- *If you press >>(3) while playing the last message, the machine beeps and returns to the Standby Mode.*

Erasing old messages you've heard

The memory of your machine fills up as messages are recorded. Make room for new messages by erasing old messages that you have already listened to. If the memory becomes full while recording, your machine beeps a warning and disconnects the line. The machine will not function as an answering machine unless you make space by erasing unwanted recorded messages. This is why you should erase old messages.

To erase a selected message

Press **Erase** while the message is playing.

- *BE CAREFUL! Once you have pressed **Erase** while a message is playing, there's no way to cancel or recover it.*
- *The selected message is erased and Erasing is displayed.*

To erase all recorded messages

1 Press **Erase**. The display asks if you want to erase ALL messages.

2 Press **Enter** if you're sure.

- *All messages in memory are erased while Erasing is displayed.*
- *If you do not want to erase all messages, press **Stop/Clear** when asked and the machine returns to Standby Mode.*

Using the answering machine from a remote phone

You don't need to be at the machine's Control Panel to operate the answering machine. If you have access to a Touch-Tone phone, you can operate many features, such as message playback, regardless of where you are.

To operate your machine from a remote phone, you need to enter a five-character: Remote Password. The Remote Password is preset at the factory to '#139#' and you can change the password to any number you want, through the User Options. For more information, see "Remote Password" on page 6.10.

Accessing the machine

- 1 Place a call to your fax machine from a Touch-Tone phone.
- 2 Enter your Remote Password when the machine answers with the greeting.
 - When the correct password is recognized by the machine, you will hear two short beeps (the confirmation tone).
- 3 Enter the Remote Command corresponding to the operation within 15 seconds.
 - When the specified operation is complete, you hear a short beep. You can then enter another command for another operation. If you enter a remote code while the machine is responding to your command, the unit stops the current operation and performs new operation. For the Remote Commands, see "Using remote commands" on page 4.5.
- 4 Press #0 to finish the remote session.
If you don't enter '#0', your machine might not hang up for several minutes.

Using remote commands

The chart below describes which Remote Code you have to enter for remote operation:

Code;	Operation;
#0	Exits remote control mode.
#1	Skips a message backward. The machine skips the current message and plays the previous one.
#2	Plays back new messages. The machine beeps and plays all new messages. If there are no new messages, the machine beeps four times and waits for another command to be entered.
#3	Skips a message forward. The machine skips the current message and plays the next one.
#4	Changes the TAM message. After entering the command, speak into the handset. When you finish, press #. If you run out of recording time, the machine stops and plays back the message.
#5	Plays back messages. The machine beeps and plays messages one by one. When a message is played back, the machine waits for another command. To listen to next message, press * within 15 seconds. If there are no messages, the machine beeps four times and waits for another command to be entered.
#6	Changes the Paging OGM message. The machine beeps and is ready to record new message. Speak into the handset. When you finish, press #.
#7	Erases the message currently playing, and plays back the next message.
#8	Turns TAM Mode on/off. The machine plays the greeting message when TAM Mode is turned on. Each time you press #8 thereafter, TAM mode is turned off, then back on.
#9	Erases all the messages.
*	Plays the next ICM message if you entered the #5 or #2 command.
#*	Exits the fax machine from answering mode. This code is used at a phone extension connected to the same line as your fax machine



4.6

CHAPTER 5

ADVANCED FAX

In this chapter, you will learn how to use the advanced fax features of your machine. For example, how to send the same documents to many different locations (Broadcasting) or how to set up your machine to send faxes at a preset time (Delayed Fax).

Broadcasting

With Broadcasting you can programme your machine to automatically scan and send documents to a number of different recipients. The documents are automatically erased from memory when Broadcasting is finished.

- 1 Turn the document face down and feed it into the machine.
- 2 Press **Menu**.
- 3 Press < or > to choose **ADVANCED FAX** and press **Enter**.
- 4 Select **Set Broadcasting** by pressing < or >, and press **Enter**.
- 5 Enter the fax number.
 - You can enter a *One-Touch or Speed Dial location number, which consists of two digits.*
 - You can enter *5 fax numbers into one job.*
- 6 Press **Enter** when the correct number appears in the display.
 - *If you have more destinations, select 'Y' and press **Enter** when asked Another? Y/N and repeat steps from 5.*
 - *If you have finished entering all the numbers, answer 'N' and press **Enter**.*
- 7 Press **Start Fax**.
 - *The document will be scanned into memory before transmission.*

Delayed fax

You can set your machine to send a fax at a later time when you will not be present. Normally it is cheaper to send a fax at night because telephone rates are lower than they are during the day.

- 1 Turn the document face down and feed it into the machine.
- 2 Press **Menu** repeatedly until **ADVANCED FAX** appears, and press **Enter**.
- 3 Select **Set Delayed Fax** by pressing < or >, and press **Enter**.
- 4 Enter the fax number.
 - You can enter a *One-Touch or Speed Dial location number, which consists of two digits.*
 - You can enter *5 fax numbers into one job.*
- 5 Press **Enter** when the number appears in the display.
 - *If you have more destinations, select 'Y' and press **Enter** when asked Another? Y/N and repeat steps from 5.*
 - *If you have finished entering all the numbers, answer 'N' and press **Enter**.*
- 6 Enter the name if you want to name the transmission.
If not, skip this step.
- 7 Press **Enter**.
- 8 Enter the time the transmission starts, in 24-hour format.
 - *For example, Enter 2230 for 10:30 P.M.*
- 9 Press **Enter** when the time appears correctly in the display.
 - *The document will be scanned into memory before transmission, and be sent at programmed time.*

Using My Favorites

My Favorites enables you to store documents that are frequently faxed and send them to selected fax numbers without the originals. Store a document into memory and give the document an ID name. When you use this feature, set contrast to *PHOTO* by pressing **Rcv.Mode/Darkness** is not supported.

Saving documents

- 1 Turn the document face down and feed it into the machine.
- 2 Press **My Favorites** repeatedly and press **Enter** when **Save** appears.
- 3 Enter the document ID name (upto /15 characters/ by using the number keypad)
 - *The document will be scanned into memory.*
 - *It shows “Exceeded Job Memory” message, when you save more than three **My Favorites**.*

Deleting stored documents

- 1 Press **My Favorites** repeatedly and press **Enter** when **Delete** appears.
- 2 You can select one or all to delete the stored documents.
- 3 Select the document to be deleted by pressing < or >, and when the correct document ID is displayed, Press **Enter**.
 - *The document will be deleted.*

Sending stored documents

- 1 Press **My Favorites** repeatedly and press **Enter** when **Send** appears.
- 2 Select the document to be sent by pressing < or >, and when the correct document ID is displayed, Press **Enter**.
- 3 Enter the fax number.
- 4 Press **Enter** when the correct number appears on the display.
 - *If you have more destinations, select ‘Y’ and press **Enter** when asked Another? Y/N and repeat from step 3.*

Printing stored documents

- 1 Press **My Favorites** repeatedly and press **Enter** when **Print** appears.
- 2 Select the document to be printed by pressing < or >, you can select one or all to printout the stored document and when the correct document ID is displayed, press **Enter**.
 - *The document will be printed.*

Polling

Polling enables you (or a remote fax machine) to retrieve a document. This is useful when a person who has a document to be sent is leaving the office. The person who wants to receive the document at a later time places a call to the machine holding the original, and requests that the document be sent. In other words, it “requests” the machine holding the original.

Setting send polling

You can programme your fax machine to send documents in your absence when it is requested by a remote fax machine.

- 1 Turn the document face down and feed it into the machine.
- 2 Press **Menu** repeatedly, and press **Enter** when ADVANCED FAX appears.
- 3 Select Set Polling Send by pressing < or >, and press **Enter**.
- 4 Enter the poll code and press **Enter**.
 - The poll code is used to prevent your document from being retrieved by the unauthorized caller.
 - Your machine starts scanning the document(s) into memory and shows POLLING SEND in the display. If the receiving mode was TEL, the machine changes it to FAX mode automatically for being polling.
 - The poll code is preset to 0000 at the factory, which represents no poll code.
 - When it is polled, the page in memory will be deleted automatically and receiving mode returns to the state before setting polling. To cancel Send Polling, see "To cancel the scheduled job" on page 5.4.

Setting receive polling

- 1 Lift the handset or press **Speaker Phone (or On Hook Dial)** and enter the telephone number of the remote machine which is in Send Polling state.
- 2 Press **Menu** when you hear a fax tone from the remote machine.
 - The display shows To poll documents press Enter.
- 3 Press **Start Fax**.
- 4 Enter the Poll Code to retrieve the document, and press **Enter**.
 - The machine starts to receive document and prints.

Not all fax machines have polling capability, and polling incompatibility sometimes occurs between fax machines made by different manufacturers.

To cancel the scheduled job

All scheduled jobs remain in memory after they have been set. Cancel unnecessary scheduled jobs to make more memory available.

- 1 Press **Menu** repeatedly, and press **Enter** when ADVANCED FAX appears.
- 2 Select Cancel Schedule by pressing < or >, and press **Enter**.
- 3 Select the reserved transmission you want to cancel by pressing < or > repeatedly.
- 4 Press **Enter** to cancel the selected schedule.

Forwarding a fax or message

Fax forwarding

While you are away from your home or office, you do not have to miss important faxes. Your machine can forward any faxes it receives to a fax machine at your new location, and it can print a copy for you to review when you get back as well.

1 Press **Menu** repeatedly, and press **Enter** when ADVANCED FAX appears.

2 Select Set Fax Forward by pressing < or >, and press **Enter**.

The display shows Off, Forward or Forward & Print whenever you press < or >.

- *Off: disables fax forwarding*
- *Forward: forwards a fax to your new location*
- *Forward & Print: forwards a fax and prints it to your new location*

3 Press **Enter** after selecting Forward or Forward & Print.

4 Enter the fax number and press **Enter**.

5 Enter the start time and press **Enter**.

6 Enter the end time and press **Enter**

- *The machine returns to Standby Mode and FWD will appear in the display at Fax Forward start time and every fax will be forwarded to your new location till the end time.*
- *During forwarding time, the receive mode temporarily changes to:*

If your model is	Receive mode	In case
SF-340	Fax	-
SF-345TP	TAM	TAM message is recorded
	Fax	no TAM message

Message forwarding (SF-345TP only)

When you're out of the office or home and you want to be notified whenever there's a new message left on your machine, you need to use the Message Forwarding feature supplied with your machine.

1 Press **Menu** repeatedly, and press **Enter** when SETUP TAM appears.

2 Select Message Forward by pressing < or >, and press **Enter**.

The display shows Off or On whenever you press < or >.

- *Off: disables message forwarding*
- *On: forwards a message to your new location*

3 Press **Enter** after selecting On.

4 Enter the fax number and press **Enter**.

If you have ever recorded a Paging OGM before, the machine asks if you want to change.

If there is no recorded OGM, the machine asks to record OGM.

5 To change or record the OGM press **Enter**, and speak into the microphone.

Or, press **Stop/Clear** to keep as it is.

Received fax remote notification (SF-345TP only)

While you are away from your home or office, you can know if there is a new fax or not. Your machine can send a voice message with a recorded number you select when the new fax comes in.

- 1** Press **Menu** repeatedly, and press **Enter** when ADVANCED FAX appears.
- 2** Select Set Fax Notice by pressing < or >, and press **Enter**.
The display shows Off or On whenever you press < or >.
 - *Off: disables auto fax notice*
 - *On: dials the number and leaves the voice message to notify the new fax*
- 3** Press **Enter** after selecting On.
- 4** Enter the telephone number and press **Enter**.
If you have ever recorded a Fax auto notice OGM before, the machine asks if you want to change.
If there is no recorded OGM, the machine asks to record OGM.
- 5** To change or record the OGM press **Enter**, and speak into the microphone.
Or, press **Stop/Clear** to keep as it is.



CHAPTER 6
SPECIAL FEATURES

Inserting a pause

With some private telephone systems, you must dial an access code (9, for example) and listen for a second dial tone before dialling an outside number. In such cases, you need to insert a pause in the number when you are registering Auto Dial such as a One-Touch or Speed Dial number.

If you are asked for the number when setting up Auto Dial, follow this procedure:

Press **Redial/Pause** to insert a pause while entering the number.

- A 'P' is inserted at the point where you pressed **Redial/Pause**. If you need a longer pause, press **Redial/Pause** as many times you want.

Using Recall (R or Flash)

The name of this button (**Recall**) differs depending on your country. The **Recall** button is equivalent to R or Flash.

If you do not have a special service that uses the switch-hook signal, do not press **Recall** during a call. If you do, you could disconnect the line.

If you get a call and you want to transfer it to someone else, press **Recall** and dial the number of that other person. This may not work with some phone systems. Refer to your telephone's instruction manual for more information. The recall is of "Time break" type.

- 1 Press **Recall** when you are on the telephone.
- 2 Enter the phone number to transfer it to someone else.
 - In UK, you may have some problems when you try to use BT services.
- 3 Hang up the handset when the person answers.

Using Caller ID

Many countries have the Caller ID system which enables the receiver to view the numbers or names of callers. Once you have subscribed to Caller ID services, your machine can display caller information. To switch the Caller ID feature on:

- 1 Press **Menu** repeatedly until SETUP SYSTEM appears, and press **Enter**.
- 2 Select Caller ID by pressing < or >, and press **Enter**.
- 3 Choose the desired option, and press **Enter**.
 - On: Activates the Caller ID feature.
 - On /w Junk Fax: Activates Caller ID and ignores any fax registered as a junk fax (see "Registering/deleting the junk fax numbers" on page 6.5.)
 - Off: Deactivates the Caller ID feature.

Using the Mute

While talking on the phone via speaker phone or handset, you may want to mute your voice for secret.

To mute a call

Press **Phone Book/Mute** while speaking.

- *The display shows MUTE to indicate it is activated.*

To release the mute

Press **Phone Book/Mute** to resume conversation.

Recording a conversation (SF-345TP only)

While you are talking on the phone via speaker phone you may need to record the conversation for tracking a story. Your machine provides this convenience for your purpose.

To record the conversation

Press **Play/Record** while you are speaking.

- *The machine starts to record the conversation, and recording time is unlimited before memory is full.*
- *The recorded conversation will be treated as an ICM.*

To stop recording

Press **Stop/Clear** to stop recording.

Sound setup

You can set the alarm, key and wakeup sound.

- 1 Press **Menu** repeatedly until SETUP SOUND appears, and press **Enter**.
 - *The display shows the three options you can set: Wakeup Sound, Alarm Sound and Key Sound.*
- 2 Press < or > to select the option you want, and press **Enter**.
- 3 Select On or Off and press **Enter**.
- 4 If you selected Off, the alarm or key click does not make any sound.
- 5 If you selected On in the WakeUp Sound option, enter the time when the wakeup signal is ringing.
 - *The wakeup signal is sound even though Silent mode is enabled.*

User reports

Your fax machine can print reports containing useful information — Scheduled Info, System Data, Help report, etc.

To print a report

- 1 Press **Menu** respectively until **REPORTS** appears, and press **Enter**.
- 2 Choose the report you want by using **<** or **>**.
- 3 Press **Enter** when the desired report is displayed.

The selected report will be printed. The available reports are shown below:

Report name	Content	How it prints
Help List	This report covers the machine's basic functions and commands. It can also be used as a quick reference guide.	Manual
Sent Journal	This report shows information concerning the transmission activities. They can be printed on command or if the machine is set to do so. It will automatically print after every 40 transmissions.	Manual/Automatic
Received Journal	This report shows information concerning the reception activities. They can be printed on command or if the machine is set to do so. It will automatically print after every 40 receptions.	Manual/Automatic
Phonebook	This report shows all of the numbers currently stored in the fax machine's memory as One-Touch Dial and Speed Dial.	Manual
Sending Confirm	This report shows the fax number, the number of pages, elapsed time of the operation, the communication mode, and the communication results. Set up your machine as described in "Sending Confirm" on page 6.9 to automatically print Sending Confirm.	Manual/Automatic
Schedule Inform	This report shows the document currently stored for Delayed FAX and Send Polling along with the operation number, starting time and type of operation, etc.	Manual
System Data	This report shows the status of the User Options. After you have changed any setting, print this report to check your changes.	Manual
Caller ID	This report shows the information of the most recent 30 callers who have called your machine.	Manual
Junk Fax	This report shows the 20 telephone numbers which was marked as a junk fax.	Manual
TAM Status ^a	This report shows the status of the recorded messages. You can see when you have received a message and if you've listened to it or not.	Manual
Print Fax	Your machine stores fax data into memory as far as the memory is available and lets you print it at later time. For more information, see "Re-Printing faxes" on page 6.5.	Manual
Multi-Communication	This report prints automatically if you have faxed documents to more than one location by using Broadcasting.	Automatic
Power Fail Report	If experience a power failure, this report is printed automatically when power is restored, to notify you that there was a power failure. This report prints only when there was any scheduled job such as Delayed FAX or Send Poll, received job or TAM Message (SF-345TP) or Smart Sending job.	

a. SF-345TP only

Re-Printing faxes

You may sometimes need to re-print a received fax. Your machine stores the most recently received faxes in memory. As this memory is filled, old faxes that have been printed will be erased to make room for new faxes. To access this facility:

- 1 Press **Menu** respectively until **REPORTS** appears, and press **Enter**.
- 2 Press **<** or **>** to choose **Print Fax**, and press **Enter**.
 - If there are only old faxes, the machine will automatically print and returns to *Standby mode* without moving to the next step.
 - If there are no faxes in memory, the machine will inform you by displaying *Memory Empty*.
- 3 Select between **Print New Fax** Or **Reprint Old Fax** and press **Enter**.
 - **Print New Fax:** *The machine prints all new faxes which have never been printed.*
 - **Reprint Old Fax:** *The machine prints all faxes regardless of new or old.*

Registering/deleting the junk fax numbers

Provided you have entered a junk fax number and activated the **Caller ID** option by selecting **On /w Junk Fax**, your machine will not receive any faxes those entered numbers. To set up the **Caller ID**, see "Using Caller ID" on page 6.2.

Entering junk fax setup mode

- 1 Press **Menu** repeatedly until **SETUP SYSTEM** appears, and press **Enter**.
- 2 Select **Set Junk Fax No.**
- 3 Press **Enter** and follow the instructions below depending on the setup type.

To add a number

- 1 Choose **Add** and press **Enter**.
 - The machine shows the first **CID (Caller ID)** number.
 - If the number is the same as one you have programmed in a *One-Touch* or *Speed dial* location and you assigned the name to that location, the machine shows the name instead of the number.
- 2 Select the **CID** number you want to register as a junk fax, and press **Enter**.
 - You can scroll to the next one by pressing **<** or **>**.
 - You can enter up to 20 numbers. Numbers which have already been entered as a junk numbers are marked by ***** at the end of the display.

To delete a number

- 1 Choose **Delete** and press **Enter**.
 - The machine shows the first junk number.
- 2 Select the junk fax number you want to delete, and press **Enter**.
 - You can scroll to the next one by pressing **<** or **>**.

Using Short Message Service (SMS)

Your machine supports the short message receiving service. Using this feature, you can receive short messages coming from other machines such as faxes, computers, or mobile phones.

When you read or print your messages, the font not supported by your machine appears as blank. See page 9.4 and page 9.5 for information about font available with your machine.

Reading SMS messages

You can read messages received from other machines.

- 1 Press **Menu** repeatedly until SHORT MESSAGE appears, and press **Enter**.
- 2 The first available option, Read Message, appears, then press **Enter**.
- 3 The list of messages received appears. Select the message you want to read by pressing < or > and press **Enter**.
 - The messages you do not read are marked with an asterisk (*).
 - The machine can save up to 30 messages. Messages will not be lost even if power is disrupted.

Printing SMS messages

You can print messages received from other machines.

- 1 Press **Menu** repeatedly until SHORT MESSAGE appears, and press **Enter**.
- 2 Select Print Message by pressing < or > and press **Enter**.
- 3 Select Print One by pressing < or > and press **Enter**.
- 4 The list of messages received appears. Select one by pressing < or > and press **Enter**. The selected message prints out.
 - If you select Print All, then all messages stored in the machine will print out.

Deleting stored SMS messages

You can delete messages received from other machines.

- 1 Press **Menu** repeatedly until SHORT MESSAGE appears, and press **Enter**.
- 2 Select Delete Message by pressing < or > and press **Enter**.
- 3 Select Delete One by pressing < or > and press **Enter**.
- 4 The list of messages received appears. Select one by pressing < or > and press **Enter**. The selected message is deleted.
 - If you select Delete All, then all messages stored in the machine will be deleted.

Setup SMS messages

The Message Receiving Center number is preset when you buy your machine. When you need to change SMS settings including the message receiving center number and a subaddress number, you can change settings.

To change the message receiving center number:

- 1 Press **Menu** repeatedly until SHORT MESSAGE appears, and press **Enter**.
- 2 Select SET SMS by pressing < or > and press **Enter**.
- 3 Center Number appears.(SMS Center No.1)
Press **Enter** and enter the Message Receiving Center number.
- 4 Press **Enter** when the center number appears correctly in the display.

To change the subaddress number:

- 1 Press **Menu** repeatedly until SHORT MESSAGE appears, and press **Enter**.
- 2 Select SET SMS by pressing < or > and press **Enter**.
- 3 Select SMS Center No.1 < or > SMS Center No.2 by pressing < or > and press **Enter**.
- 4 Enter the SMS Center No.1 < or > SMS Center No.2 number of the machine.

Register flow:(UK only):

Your machine is capable of receiving SMS text messages from any SMS capable device.

Prior to receiving SMS messages you must subscribe to the Caller Display Service on the line that the facsimile device is to be connected. Please contact your telecoms provider to have this service enabled.

Having subscribed to the Caller Display Service, your machine must be registered with your telecoms provider. The Default SMS Center Number and Registration Number (based on British Telecom system) are preset on your fax machine. To register the device, please follow the instructions below:

- 1 Press **Menu** button repeatedly until SHORT MESSAGE appears, press **Enter**.
- 2 Using < or > keys, scroll along to SET SMS, press **Enter**.
- 3 REGISTER is displayed in LCD, press **Enter**.
- 4 SEND REGISTER is displayed, press **Enter**.

The fax machine will send a registration SMS to the BT SMS Center and register the device.

Registration is now complete.

Note: To edit SMS Center and Registration details please follow the instructions below:

Editing Registration Number:

- 1 Press **Menu** button repeatedly until SHORT MESSAGE appears, press **Enter**.
- 2 Using < or > keys, scroll along to SET SMS, press **Enter**.
- 3 REGISTER is displayed in LCD, press **Enter**.
- 4 Using < or > keys, scroll to EDIT REGISTER, press **Enter**.

- 5 Enter registration number (provided by telecoms company), press **Enter**.

Editing SMS Center Number(s):

- 1 Press **Menu** button repeatedly until SHORT MESSAGE appears, press **Enter**.
- 2 Using < or > keys, scroll along to SET SMS, press **Enter**.
- 3 REGISTER is displayed in LCD, press **Enter**.
- 4 Using < or > keys, scroll to SMS Center No.1,press **Enter**
- 5 Enter new SMS center number (provided by telecoms company), press **Enter**.
- 6 A second SMS center number can be added by editing the SMS Center No.2 field

Clearing memory

You can selectively clear information stored in your machine's memory.

- 1 Press **Menu** repeatedly until MEMORY CLEAR appears, and press **Enter**.
The display shows the type of information you can clear from memory.
- 2 Select what you want to delete by pressing < or >, and press **Enter**.
- 3 Select 'Y' and press **Enter** when the machine asks if you are sure.
 - The types of information you can clear are:

Item	It will
System ID	Delete your system ID.
Dial/Schedule	Clear the stored numbers in the Phonebook. In addition, all the Scheduled Jobs are also cancelled.
Journal	Clear all records of transmissions and receptions.
Default System	Restore user-selectable options to factory default value.

User options

Your fax machine has various user-selectable features. These options are preset at the factory, but you may need to change them.To find out how the options are currently set, print the System Data List. For more information on printing a report, see "To print a report" on page 6.4.

Setting system/TAM options

The System Setup includes settings related to fax operation, and TAM Setup has settings related to answering machine operations.

- 1 Press **Menu**.
- 2 Select SETUP SYSTEM or SETUP TAM (SF-345TP only) by pressing < or >.
- 3 Press **Enter** to enter specified Setup mode.

- 4 Scroll up or down by pressing < or > to select the option you want to change.
- 5 Press **Enter** when the option you want appears in the display.
- 6 Press < or > to choose the desired status.
- 7 Press **Enter** for the status you want.

- To exit Setup mode at any time, press **Stop/Clear**.
- When you press **Stop/Clear**, the machine stores the options you've changed, and returns to the Standby Mode.

System setup options

The chart below shows the options in the left column and their suboptions in the right column.

When you have entered System Setup, now you can see one of the options in the display by selecting < or >. The right column shows the suboptions belonging to the options.

Option	Suboption
Language	There are 7 languages you can use for display and report. The languages are: English, German, French, Italian, Spanish, Portuguese and Dutch.
Sending Confirm	A confirmation report shows whether the transmission was successful or not, how many pages were sent, etc. Choose ON to print a confirmation report automatically each time you send a fax. Choose OFF not to print whatever the result is. Choose ERROR to print only when an error occurs, and the transmission was unsuccessful. Note that a confirmation report of a memory transmission includes the Image TCR (Transmission Confirmation Report) which shows the image of the first page with the various information depending on the value you made as described in "Image TCR" on page 6.10
Paper Size	Select the paper size you will use for fax receive, and copying.
Auto Reduction	When receiving a document as long as or longer than the paper loaded, the machine can reduce the data to fit your paper. If the fax machine cannot fit the data into one page with the feature enabled, the data is divided and printed in actual size on two or more sheets.
Discard Size	If you turn the Automatic Reduction feature off, you can set the fax machine to discard any excess image at the bottom of the page when receiving a document as long as or longer than the paper loaded in your machine. If the incoming fax is out of the margin you have set, it will be printed on two sheets of paper. Enter the desired Discard Size in millimeter.
Rings To Answer	You can select the number of rings before answering an incoming call. If you are using your machine as both a telephone and a fax machine, we suggest you set the ring count to at least 4 to give you time to answer.
Rcv. Start Code ^a	The Rcv. Start Code (Remote Receive Start Code) allows you to start fax receive from an extension phone plugged into the EXT socket (except SF-345TP) or equivalent. If you pick up the extension phone and hear a fax tone, press the Rcv. Start Code then the fax will start receiving. The code is preset to *9* at the factory. Enter the desired code from 0 to 9.
ECM Mode ^b	This mode compensates for poor line quality and ensures accurate, error-free transmission with any other ECM-equipped facsimile machine. If the line quality is poor, transmission time may be increased when ECM is enabled.
Send From Memory	This determines how to transmit the document manually. If it is on, the machine will scan documents into memory and then send a fax. If it is off, the machine will first dial and send.
Caller ID ^{c,e}	You can see the number of the person calling you. Before using the Caller ID feature, Caller ID service must be installed on your telephone line by the telephone company. For more information, see "Using Caller ID" on page 6.2.
Short Message ^{c,e}	You can use the short message service. Before using the Short Message service, it must be installed on your telephone line by the telephone company. For more information, see "Using Short Message Service (SMS)" on page 6.6.
Auto Journal	A journal report shows the specific information concerning transmission or reception activities, the time and date of most recent 40 transmissions or receptions.

Option	Suboption
Set Junk Fax No.	You can prohibit your machine from uncertified or unwanted junk faxes like spam mail. To add a number as a junk fax you should have at least one Caller ID detected by the machine. Even though you have added junk fax numbers, if you turned off the Caller ID option above, the Junk Fax protection will be removed. For more information, see "Registering/deleting the junk fax numbers" on page 6.5.
DRPD Mode ^d	DRPD (Distinctive ring) is a service provided by some telephone companies that assigns two phone numbers to one phone line, each of which makes your phone ring differently. If you subscribe to this service, you can program your machine to learn one phone number and distinctive ring for incoming faxes. As the display shows, call this fax from other fax machine. The machine will learn the ring pattern and displays DRPD OK when finished. Now, you can use the Rcv.Mode/Contrast to select DRPD receiving mode.
Remote Test	This lets the service center check the status of your machine to find out if there is anything wrong.
Silent Mode	You can turn off sounds the machine makes. There are two kinds of this mode; Manual and Daily. • Manual: To activate or deactivate this mode, the user presses Silent Mode . • Daily: Enter start and end time. You have to specify them in 24-hour format.
Resolution	Sets the default resolution when copying and faxing.
Contrast	Sets the default contrast when copying and faxing.
Image TCR	You can prevent the Image TCR from being included in the confirmation report for privacy or security protection.
Dial Mode ^e	Set the dialling mode to the type of the exchange to which you are connected.
Behind PABX ^e	If your machine is connected to the line from PABX (Private Automatic Branch eXchange), you need to enable this option by selection On.

a. SF-340only.

b. Error Correction Mode

c. This option may not work when connected to a PABX.

d. Distinctive Ring Pattern Detection

e. One or more options may not appear in the display depending on your country. If so, it is not applicable to your machine.

TAM options (SF-345TP only)

Options	Suboption
Save Charge	Lets you dial into your machine from a remote phone and check whether anyone has left a message without being charged. When Save Charge is On, the machine answers your call on the number of rings you have specified in the Rings to Answer option. If there is no message, the machine answers on the second ring after the number of Rings to Answer. This gives you time to hang up the phone before the machine answers and saves the price of the call.
Call Monitor	Enables you to hear callers leave messages on your machine.
ICM Record Time	You can select the maximum time allowed for caller messages.
Remote Password	You can change the three-character password used to access your machine from a remote phone. The password is preset to "#139#" at the factory. The first and the last #'s are fixed, but you can change the three middle numbers.
Silence Action	In TAM mode, the machine decides the next action when silence is detected for 10 seconds. Available suboptions are: • Receive Fax: Switches to FAX Receive Mode. • Record Silence: Keeps the recording silent. • Disconnect: Disconnects the line and returns to Standby Mode.
Howler Action	In TAM mode, the machine decides the next action when a howling is detected for 9 seconds. Available suboptions are: • Record Howler: Disregards howling. • Disconnect: Disconnects the line and returns to Standby Mode.
Message Forward	Forwards a message to your new location whenever a caller leaves a message. For more information, see "Message forwarding (SF-345TP only)" on page 5.5.



CHAPTER 7

USING PRINTING

This chapter is only for SF-345TP users.

Making Connection

Connect the USB cable which came with your machine.

- The “New Hardware found” message is shown, click the “cancel” button.

Installing Samsung Software

This printer supports only black print.

You must install software using the supplied CD-ROM after you have set up your machine and connected it to your computer.

System Requirements

Verify the following:

- At least 64MB (Windows 9x/Me), 128 MB (Windows 2000), 256 MB (Windows XP) or more of RAM is installed on your PC.
- There is at least 300 MB or free disk space on your PC.
- All applications are closed on your PC before beginning installation.
- You are using Windows 98, Windows Me, Windows 2000, or Windows XP.
- You are using at least Internet Explorer 5.0.

Installing Printer Software


For Windows 98/Me/2000/XP users, cancel the “New Hardware Found” screen when the computer boots up. Make sure that your machine is plugged in and connected to your computer’s USB port **before installing software** from the CD.

- 1 Insert the supplied CD into your CD-ROM drive.
 - The CD should automatically run and the opening window appear.
 - If the installation window does not appear, click **Start**, and then **Run**. Type **X:setup.exe**, replacing “X” with the letter of your CD-ROM drive, and click **OK**.
- 2 If the following window opens, connect your machine to the computer and turn the printer on. Then click **Next**.



- If the machine is already connected and turned on, this screen does not appear. Skip to the next step.
- If you click **Next** and the machine is not connected to the machine, an alert message window appears. After connecting the machine and turning it on, click **Yes**. Or, if you want to install the software without the machine, Click **No**.

3 Choose the installation type and click **Next**.



- **Typical:** Program will be installed with the most common options and is recommended for most users.
- **Custom:** Allows you to choose the language of the software you want to install. After selecting the language and the printer, click **Next**.



4 After the installation is finished, to register yourself as a user of a Samsung Printers appears. Select the check box and click **Finish**. You are now accessed to the Samsung web site. Otherwise, just click **Finish**.



5 The windows asking you to restart your computer appears. Select **Yes** and restart your computer.

Setting the default printer


To set your printer as the default printer, follow the below steps:

- 1 Click the Windows **Start** menu.
- 2 For Windows 98/Me/2000, select **Settings** and then **Printers**.
For Windows XP, select **Printers and Faxes**.
- 3 Select the Samsung SF-340_CF-340Series printer.
- 4 Click the right mouse button on the printer icon and:
- 5 For Windows 98/Me, select **Set as Default**.
For Windows 2000/XP, select **Set as Default Printer**.

Reinstalling Software

Reinstalling is required if your installation fails or the software does not work properly.

- 1 You can select **Start > Programs > Samsung SF-340_CF-340Series > Maintenance**.
 - *Otherwise, Insert the supplied CD-ROM into your CD-ROM drive.*
- 2 Click **Repair**.



- *If your machine is not connected to the computer, the Connect Samsung SF-340_CF-340Series window opens. After connecting the machine, click Next.*

- 3 Select the printer you want to reinstall and click **Next**.




- 4 When the reinstallation is done, click **Finish**.

Uninstalling Software

Uninstallation is required if you are upgrading the software or if your installation fails. You can uninstall the item using the Windows uninstallShield.

- 1 You can select **Start > Programs > Samsung SF-340_CF-340Series > Maintenance**.
 - *Otherwise, Insert the supplied CD-ROM into your CD-ROM drive.*
- 2 Click **Remove**.
- 3 Then you will see a component list so that you can remove any of them individually.



- 4 After selecting items you wish to remove, click **Next**.
- 5 When your computer asks you to confirm your selection, click **Yes**.
 - *The driver is removed from your computer.*
- 6 When the uninstallation is done, click **Finish**.
- 7 The message box recommends you restart your computer. Click **OK**, then restart your computer.

Printing a Document


This procedure describes the general steps required for printing from various Windows applications. The exact steps for printing a document may vary depending on the application program you are using. Refer to the user's guide of your software application for the exact printing procedure.

The following steps describe the typical process to print from Windows:

- 1 Ensure that your machine is properly connected to the computer, the machine is powered on, and there is paper in the paper tray.
- 2 Verify that you have installed the Samsung software for your computer. For details, see "Installing Samsung Software" on page 7.2.
- 3 Start the program you are using to create the document, and create or open the document you want to print.
- 4 Choose **Print** or **Print Setup** from the **File** menu. The Print window is displayed (It may look slightly different depending on your application). Make sure that Samsung SF-340_CF-450 Series is selected as your default printer.
 - *You can select the basic print settings within the Print window. These settings includes the number of copies and the print range.*


- 5 Click **Properties** if you want to make any adjustments that are appropriate for printing your document.
 - If you see **Setup**, **Printer**, or **Options**, click that button instead. Then click **Properties** in the next screen.
- 6 Now you see the Samsung SF-340_CF-340Series Properties window, which allows you to access all of information you need when using your machine.

The **Setup** tab first displays.



- You can select the printing quality by choosing from **Draft**, **Normal** or **Best**. The higher the setting, the sharper the printed characters and graphics. Higher settings may increase the time it takes to print a document.
- You can choose only in the plain paper in the **Paper Type**.
- **Paper Size** allows you to choose the size of the paper loaded in the tray.

Click the **Features** tab.



The **Orientation** option allows you to select the direction in which information is printed on a page.

- **Portrait** prints across the width of the page, letter style.
- **Landscape** prints across the length of the page, spreadsheet style.
- If you want to print the page mirror view, check the **Mirror Image** box.



▲ Landscape



▲ Portrait

The **Multi Pages per Sheet** option allows you to select the number of pages to print on a single sheet of paper. To print more than one page per sheet, the pages are smaller.

- **2 Pages per Sheet** print 2 pages on one sheet.
- **4 Pages per Sheet** print 4 pages on one sheet
- **Print Page Border** print a border around each page on the sheet.

The **Poster Printing** option allows you to print a single-page document onto 4, 9 or 16 sheets of paper, for the purpose of pasting the sheets together to form one poster-sized document.

The **Start Printing from Last Page** option allows you to print all pages in reversed order.

The **Copies** option allows you to select the number of copies.

7 When you finish setting the properties, click **OK** until the Print window displays.

8 Click **OK** to start printing.

The printer's Properties window may differ, depending on your operating system. This User's Guide shows the Properties window on windows 98.

NOTE: Most Windows applications overrides the settings you specified in the printer driver. Change all of the print settings available in the software application first, and change any remaining settings using the printer driver.

The settings you change remain in effect only while you are using the current program. To make your changes permanent, make them in the **Printers** folder. Follow these steps:

- Click the Windows **Start** menu.
- For Windows 98/Me/2000, select **Settings** and then **Printers**.
For Windows XP, select **Printers and Faxes**.
- Select the **Samsung SF-340_CF-340Series** printer.
- Click the right mouse button on the printer icon and:
 - For Windows 98/Me, select **Properties**.
 - For Windows 2000/XP, select **Printing Preferences**.
- Change the settings on each tab and click **OK**.

Canceling a Print Job

There are two ways to cancel a print job:

To stop a print job from the control panel:

Press Stop/Clear.

Your machine finishes printing the page that is moving through the machine and deletes the rest of the print job. Pressing the button cancels only the current job. If more than one print job is in the machine's memory, you need to press the button once for each job.

To stop a print job from the Printers folder:

If the print job is waiting in a print queue or print spooler, such as the Printer group in Windows, delete the job as follows:

- Click the Windows **Start** menu.
- For Windows 98/2000/Me, Select **Settings** and then **Printers**.
For Windows XP, select **Printers and Faxes**.
- Double-click the **Samsung SF-340_CF-340Series** icon.
- From the **Document** menu:
 - For Windows 98/Me, select **Cancel Printing**.
 - For Windows 2000/XP, select **Cancel**.

NOTE: You can access this window simply by double-clicking the printer icon at the bottom right corner of the Windows desktop.

Using Help

Your machine has a help screen that can be activated using the **Help** button in the printer's Properties window. The help screen gives detailed information about the printer features provided by the printer driver.

You can also click **?** in the upper right hand corner, and then click on any setting.



7.8

CHAPTER 8
CARE AND MAINTENANCE

Cleaning the document scanner



To keep your machine working properly, occasionally clean the White Roller, ADF Rubber, and the Scanning Glass. If they are dirty, documents sent to another fax machine won't be clear.

If you turn the power off to clean the scanner, documents stored in memory will be lost.

1 Open the Control Panel.


2 Remove the White Roller.

- At the right-hand end of the White Roller there is a bushing that is secured with a small tab.
- Push the tab slightly inward, then rotate towards you. Then pull up the right-hand part to take it out.



3 Wipe the roller surface with a soft cloth dampened with water.


4 Clean the ADF Rubber piece at the back of the Control Panel, too.



5 Carefully wipe the Scanning Glass with a soft, dry cloth.

- If the glass is very dirty, first wipe it with a slightly dampened cloth, then with a dry one.
- Be careful not to scratch the glass surface.

6 Replace the roller in reverse order, and then close the Control Panel firmly until it clicks into place.



Replacing the print cartridge

When you notice that the print becomes light or Ink Low. Install new ink cartridge appears in the display, replace the print cartridge. You should replace the cartridge with the same one which was provided with the machine.

The part number for replacement cartridges are:

- *mono: INK-M40*

1 Prepare a cartridge.


- *Take out a cartridge from its packaging and carefully remove the tape covering the printhead.*
- *Hold the cartridge by the colored top or black areas only. Do not touch the copper area.*

2 Press **Cartridge Change**.

The Cartridge Carrier moves to the install position.


3 Open the Control Panel and Cartridge Compartment cover.

4 Push down the cartridge, and remove it.



5 To load the cartridge insert the cartridge below the metal clip and pointing down at the front. When the cartridge is pushed to the back of the cartridge carrier lift the front of the cartridge up until it clicks into place.

- *If the cartridge moves loosely in the Carrier, it has not clicked into place. Repeat this step.*



6 Replace the Cartridge Compartment Cover and Control Panel.

7 Press **Enter**.

8 Press 1 for new cartridge, or 2 for the old one.

- *In case you selected the 1:New, the alignment form will print.*
- *When you put in a new cartridge, you must choose 1:New.*
- *When you put in a used cartridge, choose 2:Used. This helps you to check the correct amount of ink you have left.*
- *If you mix up several used cartridges, it is not possible to check the correct amount of remaining ink. Once you have put in a new cartridge, use it until it is completely exhausted.*

9 Enter the number which represents the straightest line, and press **Enter**.

Cleaning the printhead

If the nozzles seem to be clogged and characters are not printing completely, clean the printhead as described below:

- 1 Press **Menu** repeatedly until MAINTENANCE appears, and press **Enter**.
- 2 Scroll to Clean Head by pressing < or >, and press **Enter**.
- 3 Examine the printed test pattern.
 - *If print quality does not improve, reinstall the cartridge and repeat Clean Head.*
 - *If the line is still broken, wipe the nozzles and contacts.*

For more information, see "Wiping the print nozzles and contacts" on page 8.5.

Aligning the printhead

When the vertical line does not seem to be straight or you want to improve the print quality, you may need to align the cartridge.

- 1 Press **Menu** repeatedly until MAINTENANCE appears, and press **Enter**.
- 2 Scroll to Align Head by pressing < or >, and press **Enter**.
 - *The machine prints a form.*
- 3 Enter the number which represents the straightest line, and press **Enter**.

Ink level view

Your machine allows you to check the amount of ink remaining. To view the current ink level:

- 1 Press **Menu** repeatedly until MAINTENANCE appears, and press **Enter**.
- 2 Scroll to View Ink Level by pressing < or >, and press **Enter**.
 - *The machine displays a fractional number. For examples, '1/8' means that ink is low and you need to replace the cartridge. '8/8' means that a new cartridge is installed.*

Shading adjustment

The shading is adjusted at the factory. If, however, you drop and damage your machine while moving, we recommend you adjust shading for optimized lightness.

To adjust shading, do as follows:

- 1 Press **Menu** repeatedly until MAINTENANCE appears, and press **Enter**.
- 2 Scroll to Adjust Scanner by pressing < or >, and press **Enter**.
- 3 Load a plain WHITE sheet of paper (no writing or graphics) into the loading slot, and press **Enter**.
 - *The machine starts to scan the document to adjust shading.*
 - *Printing quality may be unexpectedly worse if you do not use a plain WHITE paper for the adjustment.*

Self testing

When you want to test if the machine is working correctly, you can check it by running self test.

- 1 Press **Menu** repeatedly until **MAINTENANCE** appears, and press **Enter**.
- 2 Scroll to Self Test by pressing < or >, and press **Enter**.
 - *The machine runs self test and prints a report which shows the current status of the machine.*

Print cartridge maintenance

The print cartridge life is very sensitive to the content of the received fax or a copy you made. To increase its life, we recommend you follow the instructions below:

- *DO NOT* unpack the cartridge until you are ready to use it.
- Store it in the same environment as the printer.
- If you have unpacked the cartridge but are not using it, store it in a storage unit. If you do not have a storage unit, store the cartridge in an airtight plastic bag.
- *DO NOT* leave it exposed for an extended period.
- *DO NOT* refill the cartridge. The warranty will not cover damage caused by using refilled cartridges.

Cleaning the cartridge


To maintain good printing quality, we recommend you occasionally wipe the Print Nozzles and Contacts as described below:

Wiping the print nozzles and contacts

When the print is not clear or dots are missing, the problem may be caused by dried ink on the:

- *Print cartridge nozzles*
- *Print cartridge contacts*
- *Print cartridge carrier contacts*


- 1 Press **Cartridge Change**.
- 2 Open the Control Panel and Cartridge Compartment Cover and remove the cartridge.
- 3 Gently blot and wipe the contacts and nozzles dry.
 - *Use a clean cloth dampened with water only to gently clean the entire copper-colored area, including the nozzles and contacts.*
 - *To dissolve any dried ink, hold the damp cloth against the nozzles for about three seconds.*
- 4 Reinstall the cartridge and close the Cover and Panel.
 - *If you spend a long time cleaning the cartridge, the cartridge carrier may have moved back to the original position. If so, press **Cartridge Change** again to move the carrier to the install position.*
- 5 Press 1 for new cartridge, or 2 for the old one.
 - *If the line is still broken, clean the Cartridge Carrier contacts. For more information, see "Cleaning the cartridge carrier contacts" on page 8.6.*



Cleaning the cartridge carrier contacts

Before cleaning these parts, there should be no scheduled job such as Delayed Fax, Send Polling, or faxes received into memory. Once you have unplugged the power cord from the machine, all data will be lost.

- 1 Press **Cartridge Change**.
- 2 Open the Control Panel and Cartridge Compartment Cover and remove the cartridge.
- 3 Remove the print cartridge.
- 4 Unplug the power cord from the electrical outlet of the rear of the machine.
- 5 Clean the Cartridge Carrier contacts with clean and dry cloth.
- 6 Plug in the power cord and reinstall the cartridge.



LCD error messages

Display	Status/Solution	Related to:
Adjust scanner first in Maintenance menu	The shading waveform to be used as a reference is corrupted due to unknown reason. Adjust the scanner to fix this problem as described in "Shading adjustment" on page 8.4.	Scanner
Check white paper document and try again	The scanning level is too low to compare with reference level. To adjust shading, you should use the plain and white paper.	Scanner
Clean white roller, glass and try again	The scanning level is slightly low, which can affect the image quality. To clean concerned parts, see "Cleaning the document scanner" on page 8.2.	Scanner
Duplicated with [Speed No.xx] The 'xx' indicates the location number.	The same number has already been registered into another speed dial location.	Telephone
Exceeded Job Memory	The machine can hold 3 My Favorites but you tried to add more.	Fax
Exceeded Job Memory Cancel scheduled job and try again	The broadcasting and delayed fax can hold 5 jobs in total. Cancel scheduled job and try again.	Fax
Exceeded Total Message Memory	The machine can hold up to 100 messages (OGM + ICM + recorded conversations). Erase old messages to make a room in the memory.	TAM (SF-345TP only)
ICM Memory Full	The voice memory is full. No more caller's messages can be recorded (Total recording time is about 15 minutes).	TAM (SF-345TP only)
Ink Low. Install new ink cartridge	The print cartridge has run out of ink. To install a new Print Cartridge, see "Replacing the print cartridge" on page 8.3. Although this message is displayed, you can make a copy or print a report. But, stored data in memory can be printed by changing the cartridge.	Cartridge
Install ink cartridge	Print cartridge is not installed or improperly installed.	Cartridge
Invalid Time	The time you set for fax forwarding is wrong.	Fax
Job Not Assigned	You attempted to cancel the scheduled job but there is no jobs scheduled. You attempted to delete or print send the My Favorites document when there is no document stored.	Fax
Junk Fax Empty	You attempted to delete the junk fax number when there is no junk fax number.	Fax
Junk Fax Full	The machine can hold 20 junk fax numbers but you tried to add more.	Fax
Load Document	You have tried to send a fax and there is no document loaded into the machine.	Document
Load paper and press Enter	You have tried to do any job and there is no paper loaded into the machine.	Paper
Memory Full	Memory has become full while receiving a fax or short message.	Fax/Telephone
Memory Full Press Enter to continue	Memory has become full while scanning a document. Press Enter to send or copy the scanned pages only. To cancel the job press Stop/Clear and try again when memory becomes available, or split the new document into smaller parts.	Fax/Copy

Display	Status/Solution	Related to:
Memory Received When it toggles with: Ink Low. Install new ink cartridge Load paper and press Enter Install ink cartridge	The machine has data stored in memory. Depending on the message do as follows: Replace the print cartridge with new one. Load the paper, and press Enter . There might be a jam. Clear the jam as described in "Paper jams during printing" on page 8.11. Install a print cartridge.	Fax
No answer from remote fax	The other machine has not answered after all your attempts to send a fax.	Fax
No CID Number	The machine could not detect the CID (Caller ID) number.	Telephone
No Dial Number	There is no number in the redial memory, which is successfully dialed up to now.	Telephone
No Message	There is no message to play or erase. There is no received short message to read or print.	TAM (SF-345TP only)/Telephone
No New Message	There is no new caller message. There is no received short message.	TAM (SF-345TP only)/Telephone
Not available while reprinting fax	The machine can not receive a new fax while printing the stored faxes.	Fax
Not Found	The number you are searching does not exist in memory.	Telephone
Number already registered	The number you are trying to register already exists in the phonebook or junk fax list.	Telephone
Number Not Assigned	There is no number assigned to the One-Touch or two-digit Speed number.	Telephone
Poll Code Error	The remote user entered wrong poll code.	Fax
Poll job exists already	You have programmed a polling send. Cancel scheduled job and try again.	Fax
Polling Error Check remote site	The machine you want to poll is not ready to answer your poll. The person you are polling should have loaded their fax machine with a document and be in send poll state.	Fax
Receiving Error. Ask sender to try again.	There is an error while receiving a fax.	Fax
Record TAM OGM	To select TAM receive mode, you should record OGM prior to pressing the TAM button.	TAM (SF-345TP only)
Remove jammed document	The document you are sending has jammed in the feeder. To clear the document jam, see "Document jams during transmission" on page 8.11. You tried to copy or fax a document which is longer than 390mm.	Document
Remove jammed paper and press Enter.	The paper has jammed during printing. To clear the paper jam, see "Paper jams during printing" on page 8.11.	Paper
Send Error. Try again.	There is an error while sending a fax.	Fax
System Busy Try again later	There is no available resource to execute job you ordered.	Fax
To redial now, press Start Fax	The machine is waiting to automatically redial the fax number that was busy or did not answer.	Fax
Processing Job	You attempt to enter My Favorites, while sending My Favorites document or printing My Favorites document.	Fax

Fixing Problems

Your problem may be listed in "LCD error messages" on page 8.7. The chart below shows other problems you can solve yourself. If not, call the service company shown in the separate Warranty Card.

Fax problems

Problem	Solution
The machine is not working, there is no display and the buttons are not working.	Unplug the power cord and plug it in again. Check that your socket is live.
No dial tone.	Check that the phone is connected properly. Check the phone socket in the wall by plugging in another phone.
The numbers stored in memory do not dial correctly.	Make sure the numbers are programmed correctly. To print a Phonebook Report, see "To print a report" on page 6.4..
The document does not feed into the machine.	Be sure the document is not wrinkled, and you are putting it in correctly. Check that the document is the right size and not too thick or too thin.
You cannot receive faxes automatically.	Check if TEL appears on the right side of the display. In TEL mode, you cannot receive a fax automatically. Be sure the handset is seated on the cradle properly.
The machine cannot receive faxes manually.	Do not hang up the handset before pressing Start fax .
The machine does not send anything.	Check that the document is loaded face down. Send should show up in the display. You may have hung up the handset before you pressed Start fax . Check if the machine to which you are sending can receive your fax.
You cannot poll another machine.	The fax machine you are polling may be using a poll code.
The fax you received has blank bits on it.	The machine sending to you may be faulty. A noisy phone line can cause line errors. Check your machine by making a copy.
Spots or lines missing from the fax you receive.	Check if your phone line is noisy. Check if the printhead is clean by making a copy.
You are receiving poor quality copies.	The fax machine sending to you may have a dirty scan glass. Check for a noisy phone line.
Some of the stretched words on the fax you receive	The machine sending to you had a temporary document jam.
Your machine does not make copies.	Make sure your document is loaded face down.
There are lines on copies or documents you send.	Check your scan glass for marks and clean it (see "Cleaning the document scanner" on page 8.2.)
The machine dials a number, but fails to make a connection with a remote fax machine.	The remote fax machine may be turned off, or unable to answer incoming calls. Speak with the remote operator and ask for the problem to be rectified.
You cannot store a document in memory.	There may not be enough memory available to hold the document you want to store. If the display shows a Memory Full message, delete any documents you no longer need, then retry the document.
Blank areas appear at the bottom of each page or on continuation pages, with only a small strip of material printed at the top.	You may have selected the wrong paper settings. To select the proper paper size, see "Paper Size" on page 6.9.

Print quality problems

Problem	Solution
Light or blurred characters.	Check Ink Level View as described in "Ink level view" on page 8.4. If the printer cartridge has completely run out, Ink Low. Install new ink cartridge is displayed. To install a new print cartridge, see "Replacing the print cartridge" on page 8.3. Make sure the print cartridge is installed correctly. To clean the print cartridge, see "Cleaning the cartridge" on page 8.5.
Smudged or dark characters.	Make sure the paper is straight and unwrinkled. Let ink dry before handling the paper. To clean the print cartridge, see "Cleaning the cartridge" on page 8.5.
Characters with white lines.	If Ink Low. Install new ink cartridge is displayed, install a new print cartridge as described in "Replacing the print cartridge" on page 8.3. Remove and reinstall the print cartridge. Clean the print cartridge (see "Cleaning the cartridge" on page 8.5.)
Improperly formed or misaligned characters.	Clean the print cartridge (see "Cleaning the cartridge" on page 8.5.)
Abnormal black horizontal lines	Clean the cartridge carrier (see "Cleaning the cartridge carrier contacts" on page 8.6.)

Paper feeding problems

Problem	Solution
Paper is jammed during printing.	Clear paper jam as described in "Paper jams during printing" on page 8.11.
Paper sticks together.	You can load up to 50 sheets in the ASF (Automatic Sheet Feeder). Check if you overloaded. Humid conditions may cause some paper to stick together.
Paper fails to feed.	Remove any obstructions inside the printer.
Multiple sheets of paper feed.	When loading paper, do not force the paper down into the printer. If multiple sheets have caused a paper jam, clear the paper jam. (see "Paper jams during printing" on page 8.11.)
Paper skews or buckles in the automatic sheet feeder.	ASF can hold up to 50 sheets. Make sure the paper guides do not cause the paper to bow in the bin. When loading paper, do not force it down into the printer.


Clearing jams

Document jams during transmission

If a document jams during transmission or copying, Remove jammed document appears in the display. DO NOT pull the document out of the slot. Doing so could harm your machine.

To clear document jam:

- 1 Open the Control Panel.
- 2 Carefully remove the jammed document.
- 3 Close the Control Panel firmly until it clicks into place.




Paper jams during printing

If the fax paper jams while you are receiving or printing, Remove jammed paper and press Stop/Clear appears in the message.


If the paper is jammed in the Received Paper Output Area

- 1 Remove the jammed paper by pulling it out smoothly in the direction of the arrow as shown.
 - If the paper tears when it is being removed check to ensure that no small pieces have been left inside the machine.
- 2 Press **Stop/Clear**.



If the paper is jammed in the Paper Feed Area

- 1 Remove the jammed paper as shown.
 - If the paper tears when it is being removed check to ensure that no small pieces have been left inside the machine.
- 2 Reload new paper with the print side facing toward you.
- 3 Press **Stop/Clear** when finished.





8.12

CHAPTER 9
APPENDIX

Specifications

Item		Specification
Type of unit		Inkjet Desktop Facsimile Transceiver
Communication System		Public Switched Telephone Network (PSTN) and PABX
Compatibility		ITU Group3
Compression scheme		MH, MR, MMR
Modem speed		14400/12000/9600/7200/4800/2400bps
Scanning method		CIS (Contact Image Sensor)
Input document size		8.5 inches (216mm)
Effective scanning width		8.27 inches (210mm)
Effective recording width		8 inches (203mm)
Power consumption		Standby: 4.9 Wh Printing Mode: Maximum 15 Wh
Temperature range		50°F to 95°F (10°C to 35°C)
Humidity range		20 to 80% RH (non-condensing)
Dimension (W x D x H)		368 x 254 x 141mm (folded all trays) 368 x 557 x 256mm (extended all trays)
Weight		3.5 Kg (including handset)
Power source		See Rating Label attached on the back of the machine.
Resolution	Scan	200 x 200dpi
	PC print (SF-345TP only)	Mono: 600 x 600dpi
	Copy	Mono: 600 x 300dpi (Colour copy is not supported)
	Faxing	Standard: 203 x 98dpi Fine: 203 x 196dpi Super Fine: 203 x 392dpi
ADF		10 sheets (0.075~0.12mm thick)
ASF		50 sheets (70g/m ² ~ 90g/m ²)
ECM mode		YES
Grey scale		64 Greyscales
User memory capacity		1.25Mbytes(capable of 100 pages at 4% print duty on A4 : SF-345TP) 500 Kbytes (capable of 40 pages at 4% print duty on A4 : SF-340) 128 Kbytes (capable of 10 pages at 4% print duty on A4, This memory is used to store smart fax documents.)
Voice Recording time		About 15 Min. (SF-345TP only)
Message back up time		About 30 Min.(SF-345TP only)
Replacement Ink Cartridge Part Number		Mono: INK-M40
Ink Cartridge Life		Initial Cartridge(supplied with the machine; INK-M40S): About 265 sheets (based on ITU #1 chart — see "A sample of ITU #1 chart (reduced to 60.5%)" on page 9.3.) Replacement Cartridge(to be purchased in the market; INK-M40): About 750 sheets (based on ITU #1 chart — see "A sample of ITU #1 chart (reduced to 60.5%)" on page 9.3.)

A sample of ITU #1 chart (reduced to 60.5%)

●

THE SLEREXE COMPANY LIMITED

SAPORS LANE - BOOLE - DORSET - BH 25 8 ER

TELEPHONE BOOLE (945 13) 51617 - TELEX 123456

Our Ref. 350/PJC/EAC

18th January, 1972.

Dr. P.N. Cundall
Mining Surveys Ltd.,
Holroyd Road,
Reading,
Berks.

Dear Pete,

Permit me to introduce you to the facility of facsimile transmission.

In facsimile a photocell is caused to perform a raster scan over the subject copy. The variations of print density on the document cause the photocell to generate an analogous electrical video signal. The signal is used to modulate a carrier, which is transmitted to a remote destination over a radio or cable communications line.

At the remote terminal, demodulation reconstructs the video signal, which is used to modulate the density of print produced by a printing device. This device is scanning in a raster scan synchronised with that at the transmitting terminal. As a result, a facsimile copy of the subject document is produced.

Probably you have uses for this facility in your organisation.

Yours Sincerely,

Phil.

P.J. CROSS
Group Leader - Facsimile Research

Registered in England: No. 2038
Registered Office: 60 Vicars Lane, Ilford, Essex.

Font List for Print

NUL	☺	☹	♥	♠	♣	♠	•	◼	○	◉	♂	♀	♪	♫	€
▶	◀	↕	!!	¶	§	▬	↑	↓	→	←	└	↔	▲	▼	
space	!	"	#	\$	%	&	'	()	*	+	,	-	.	/
0	1	2	3	4	5	6	7	8	9	:	;	<	=	>	?
@	A	B	C	D	E	F	G	H	I	J	K	L	M	N	O
P	Q	R	S	T	U	V	W	X	Y	Z	[\]	^	_
`	a	b	c	d	e	f	g	h	i	j	k	l	m	n	o
p	q	r	s	t	u	v	w	x	y	z	{		}	~	△
Ç	ü	é	â	ä	à	â	ç	ê	ë	è	ï	î	ì	Ä	Å
È	æ	Æ	ô	ö	ò	û	ù	ÿ	Ö	Ü	ø	£	Ø	×	f
á	í	ó	ú	ñ	Ñ	ª	º	¿	®	¬	½	¼	¡	«	»
▒	▓	▒		†	Á	Â	À	©	¶		¶	¶	¥	₹	₹
⊥	⊥	τ	†	-	+	ã	Ã	ℓ	ℓ	≡	π		=	≠	≠
ø	Ð	Ê	Ë	È	ı	Í	Î	İ	Ј	г	■	■	ı	ı	■
Ó	β	Ô	Ò	õ	Õ	μ	þ	þ	Ú	Û	Ù	Ý	Ý	—	´
-	±	=	¾	¶	§	÷	,	°	¨	.	¹	³	²	■	space

Font List for LCD

€	0	@	P	`	p	Б	Ю	б	ю	À	Ð	à	đ
!	1	A	Q	a	q	Г	Я	г	я	Á	Ñ	á	ñ
"	2	B	R	b	r	Д	З	д	з	Â	Ò	â	ò
#	3	C	S	c	s	Ж	У	ж	у	Ã	Ó	ã	ó
\$	4	D	T	d	t	И	Ь	и	ь	Ä	Ô	ä	ô
%	5	E	U	e	u	Й		й	в	Å	Õ	å	õ
&	6	F	V	f	v	Л		л	к	Æ	Ö	æ	ö
'	7	G	W	g	w	П		п	м	Ç	Ɔ	ç	œ
(8	H	X	h	x	Ф		ф	н	È	Ø	è	o
)	9	I	Y	i	y	Ц		ц	т	É	Ù	é	ù
*	:	J	Z	j	z	Ч	Е	ч	т	Ê	Ú	ê	ú
+	;	K	[k	{	Ш	Љ	ш	ј	Ë	Û	ë	û
,	<	L	\	l		Щ	Œ	щ	œ	Ì	Ü	ì	ü
-	=	M]	m	}	Ъ	Ů	ъ	ů	Í	Ý	í	ý
.	>	N	^	n	→	Ы	Ǧ	ы	ǧ	Î	Ɔ	î	Ɔ
/	?	O	_	o	←	Э	Ş	э	ş	Ï	Ɔ	ï	Ɔ

Replacing the fitted plug (UK)

Important

The mains lead for this machine is fitted with a standard (BS 1363) 5 amp plug and has a 5 amp fuse.

When you change or examine the fuse, you must re-fit the correct 5 amp fuse. You then need to replace the fuse cover. If you have lost the fuse cover, do not use the plug until you get another fuse cover from the people from whom you bought the machine.

The 5 amp plug is the most widely used type in the UK and should be suitable.

However, some buildings (mainly old ones) do not have normal 5 amp plug sockets.

You need to buy a suitable plug adaptor. Do not remove the moulded plug.

Warning

If you cut off the moulded plug, get rid of it straight away.

You cannot rewire the plug or you may get an electric shock if you put it into a socket.

Important warning: You must earth this machine

The wires in the mains lead have the following colour code:

- Blue: Neutral
- Brown: Live

If the wires in the mains lead do not match the colours marked in your plug, do the following:

You must connect the blue wire to the pin which is marked with the letter N or coloured black.

You must connect the brown wire to the pin which is marked with the letter L or coloured red.

You must have a 5 amp fuse in the plug, adaptor, or at the distribution board.

Notes for use of this device (New Zealand)

The grant of a Telepermit for any item of terminal equipment indicates only that Telecom has accepted that the item complies with minimum conditions for connection to its network. It indicates no endorsement of the product by Telecom, nor does it provide any sort of warranty. Above all, it provides no assurance that any item will work correctly in all respects with another item of Telepermitted equipment of a different make or model, nor does it imply that any product is compatible with all of Telecom's network services.

This equipment shall not be set up to make automatic calls to the Telecom 111 Emergency Service.

This equipment may not provide for the effective hand-over of a call to another device connected to the same line.

Important Notice

Under power failure conditions, this telephone may not operate. Please ensure that a separate telephone, not dependent on local power, is available for emergency use.

Declaration of conformity (European countries)

Approvals and Certifications



The CE marking applied to this product symbolises Samsung Electronics Co., Ltd. Declaration of Conformity with the following applicable 93/68/EEC Directives of the European Union as of the dates indicated:

January 1, 1995: Council Directive 73/23/EEC Approximation of the laws of the member states related to low voltage equipment.

January 1, 1996: Council Directive 89/336/EEC (92/31/EEC), approximation of the laws of the Member States related to electromagnetic compatibility.

March 9, 1999: Council Directive 1999/5/EC on radio equipment and telecommunications terminal equipment and the mutual recognition of their conformity.

A full declaration, defining the relevant Directives and referenced standards can be obtained from your Samsung Electronics Co., Ltd. representative.

EC Certification

Certification to 1999/5/EC Radio Equipment & Telecommunications Terminal Equipment Directive (FAX)

This Samsung product has been self-certified by Samsung for pan-European single terminal connection to the analogue public switched telephone network (PSTN) in accordance with Directive 1999/5/EC. The product has been designed to work with the national PSTNs and compatible PBXs of the European countries:

In the event of problems, you should contact the Euro QA Lab of Samsung Electronics Co., Ltd. in the first instance.

The product has been tested against TBR21 and/or TBR 38. To assist in the use and application of terminal equipment which complies with this standard, the European Telecommunication Standards Institute (ETSI) has issued an advisory document (EG 201 121) which contains notes and additional requirements to ensure network compatibility of TBR21 terminals. The product has been designed against, and is fully compliant with, all of the relevant advisory notes contained in this document.



ELECTRONICS

EU Declaration of Conformity (R&TTE)

We, Samsung Electronics Co., Ltd.

of #259, Gongdan-Dong, Gumi-City, Kyung-Buk, KOREA 730-030
of Sanxing Road, Weihai Hi-Tech, IDZ Shandong Province, China 264209
of Samsung Electronics Slovakia s.r.o Hviezdoslavova 807, 924 27 Galanta, Slovakia
(factory name, address)

declare under our sole responsibility that the product
Multi-function Facsimile
model "SF-340/SF-341P/SF-345TP
HP 1040 Fax/HP 1040xi Fax,
HP 1050 Fax"

to which this declaration relates is in conformity with

R&TTE Directive 1999/5/EC (Annex II)
Low Voltage Directive 73/23/EEC
EMC Directive 89/336/EEC:92/31/EEC

By application of the following standards

R&TTE : TS 103 021, TBR 38, EG 201 121

.....
LVD : EN 60950-1:2001
.....

EMC : EN55022:1994, EN55024:1998inc A1:2001, EN61000-3-2:2000*,
.....

EN61000-3-3:1995 + A1:2001*, EN61000-4-2:1995, EN61000-4-3:1995
.....

EN61000-4-4:1995, EN61000-4-5:1995*, EN61000-4-6:1996, EN61000-4-11:1994
.....

(Manufacturer)

Samsung Electronics Co.,Ltd
#259,Gongdan-Dong,Gumi-City
KyungBuk, Korea 730-030

2004-07-22
.....

(place and date of issue)

Whan-Soon Yim / Senior Manager
.....

(name and signature of authorized person)

(Representative in the EU)

Samsung Electronics Euro QA Lab.
Blackbushe Business Park
Saxony Way, Yateley, Hampshire
GU46 6GG, UK

2004-07-23
.....

(place and date of issue)

Yong-Sang Park / Manager
.....

(name and signature of authorized person)

In case of interference (US)

In normal operation, your SAMSUNG fax machine produces and uses radio-frequency energy. In some cases, this can cause interference to other electronic equipment. Part 15 of the FCC rules establishes guidelines limiting the amount of radio-frequency energy which may be produced by electronic equipment. Tests have proven that your Samsung FAX machine meets or exceeds these guidelines, and is classified a Class B Digital Device for operation in a residential environment. When installed and operated according to instructions, your SAMSUNG fax machine should not cause interference to the types of equipment expected to be found in a normal residential environment. Unauthorized changes or modifications could void the user's authority to operate the equipment.

In the event your SAMSUNG fax machine appears to cause interference to other electronic equipment, it can often be easily remedied. First determine if the source of interference really is your FAX machine. To do this, turn its power off and on while observing the equipment experiencing the interference. If the interference disappears when you turn the FAX machine off, the following steps can be very effective in correcting interference problems:

- Connect the FAX machine to an AC outlet which is on a different circuit breaker from the equipment experiencing interference.
- Increase the distance between the FAX machine and the equipment experiencing interference.
- Cable TV amplifiers and splitters are extremely prone to interference. Be certain that they are as far as possible from the FAX machine and its AC power and telephone cords.
- Replace twin lead antenna wire with shielded coaxial cable, and use proper connectors and adaptors.
- Turn or relocate the receiving antenna. In most cases this is easily done by simply moving a radio. A TV antenna may need to be reoriented or installed in another area of the building.
- Consult your dealer, a reputable radio/TV technician, or an Amateur Radio Operator for help.

Fax branding (US)

The Telephone Consumer Protection Act of 1991 makes it unlawful for any person to use a computer or other electronic device to send any message via a telephone facsimile machine unless such message clearly contains in a margin at the top or bottom of each transmitted page or on the first page of the transmission the following information: the date and time of transmission identification of either business, business entity or individual sending the message; and telephone number of either the sending machine, business, business entity or individual.

See "Chapter 1" for instructions on how to enter this information into your Samsung FAX machine's memory.

The Telephone Company may make changes in its communications facilities, equipment operations, or procedures where such action is reasonably required in the operation of its business and is not inconsistent with the rules and regulations in FCC Part 68. If such changes can be reasonably expected to render any customer terminal equipment incompatible with telephone company communications facilities, or require modification or alteration of such terminal equipment, or otherwise materially affect its use or performance, the customer shall be given adequate notice in writing, to allow the customer an opportunity to maintain uninterrupted service.

Telephone company information (US)

FCC identification number

The Ringer Equivalence Number and FCC Registration Number for this equipment may be found on the label located on the bottom or rear of the machine. In some instances you may need to provide these numbers to the telephone company.

Ringer equivalence number

The Ringer Equivalence Number (REN) is a measure of the electrical load placed on the telephone line, and is useful for determining whether you have overloaded the line. Installing several types of equipment on the same telephone line may result in problems making and receiving telephone calls, especially ringing when your line is called. The sum of all Ringer Equivalence Numbers of the equipment on your telephone line should be less than five in order to assure proper service from the telephone company. In some cases, a sum of five may not be usable on your line. If any of your telephone equipment is not operating properly, you should immediately remove it from your telephone line, as it may cause harm to the telephone network.

Warning

FCC Regulations state that changes or modifications to this equipment not expressly approved by the manufacturer could void the user's authority to operate this equipment.

In the event that terminal equipment causes harm to the telephone network, the telephone company should notify the customer that service may be stopped. However, where prior notice is impractical, the company may temporarily cease service, providing that they:

- a) *Promptly notify the customer.*
- b) *Give the customer an opportunity to correct the equipment problem.*
- c) *Inform the customer of the right to bring a complaint to the Federal Communication Commission pursuant to procedures set out in FCC Rules and Regulations Subpart E of Part 68.*

You should also know that:

- Your Samsung FAX machine is not designed to be connected to a digital PBX system.
- Special features, such as Call Waiting, may interrupt FAX service, and we suggest that these services not be installed on the FAX line.
- If you intend to use a computer modem or fax modem on the same phone line as your FAX machine, you may experience transmission and reception problems with all the equipment. It is recommended that no other equipment, except for a regular telephone, share the line with your FAX machine.
- If your area experiences a high incidence of lightning or power surges, we recommend that you install surge protectors for both the power and the telephone lines. Surge protectors can be purchased from your dealer or telephone and electronic specialty stores.
- When programming emergency numbers and/or making test calls to emergency numbers, use a non-emergency number to advise the emergency service dispatcher of your intentions. The dispatcher will give you further instructions on how to actually test the emergency number.
- This equipment may not be used on coin service or party lines.
- This telephone provides magnetic coupling to hearing aids.
- You may safely connect this equipment to the telephone network by means of a standard modular jack, USOC RJ-11C.



INDEX

A

ADF 8.2, 9.2
alignment 8.3
appearance 1.3
ASF 1.5, 8.10, 9.2
asf 1.5, 8.10
auto journal 6.9
auto reduction 6.9

B

broadcasting 1.2, 3.3, 5.1, 5.2, 6.4, 8.7

C

call monitor 1.2, 4.2, 6.10
caller id 2.3, 2.4, 6.2, 6.4, 6.5, 6.9, 6.10, 8.8
canceling
 print 7.7
cartridge
 alignment 8.4
 cleaning 8.4, 8.5, 8.6, 8.10
 ink level 8.4
 installation 8.7, 8.8, 8.10
 life 9.2
 maintenance 8.5
 part number 9.2
 replacing 1.4, 8.3, 8.7, 8.10
contrast 1.4, 3.2, 3.3, 6.10
control panel 1.4, 2.2, 3.2, 4.2, 4.5, 8.2, 8.3, 8.5, 8.6, 8.11

D

default printer 7.5
delayed fax 1.2, 3.3, 5.1, 5.2, 6.4, 8.6, 8.7
dialling 1.2, 1.4, 2.4, 3.4, 8.8
discard size 6.9

E

ECM mode 6.9, 9.2

F

fax auto notice OGM 5.6
fax forward 5.5
feeder 1.2, 1.5, 1.6, 2.3, 3.2, 3.3, 8.8, 8.10

H

help, use 7.7
howler action 6.10

I

ICM record time 6.10
image TCR 6.9, 6.10
ink save mode 1.8
installing software
 MFP driver 7.2
ITU #1 chart 9.2, 9.3

J

junk fax 6.2, 6.4, 6.5, 6.10, 8.7, 8.8
 6.4, 6.5

K

keypad character 1.8

L

language 6.9

M

making a copy 1.6, 8.9
message forward 4.5, 5.5, 6.10
MFP driver
 install 7.2
mute 1.4, 6.3

O

one-touch
 caller ID 2.4
 dialling 1.2, 2.2, 2.3, 8.8
 junk fax 6.5
 programming 2.2, 6.2, 6.4
 sending 3.3, 5.2
on-hook dial 2.2

P

paging OGM 4.5, 5.5
paper size 1.5, 1.6, 6.9, 8.9
pause 1.4, 2.2, 6.2
phonebook 1.2, 2.2, 2.3, 6.4, 8.8, 8.9
polling 1.2, 5.4, 6.4, 8.6, 8.8, 8.9
printer driver
 install 7.2
 uninstall 7.5

R

rcv. start code 6.9
recall 6.2
receive mode
 auto mode 3.4, 3.5
 DRPD 1.2, 3.4, 3.6, 6.10
 fax mode 3.5, 5.4
 TAM mode 1.4, 3.4, 3.5, 3.6, 4.1,
 4.2, 4.5, 6.10
 tel mode 3.5, 8.9
remote command 4.5
remote commands 4.5
remote password 4.5, 6.10
remote test 6.10
report 1.2, 6.4, 6.8, 6.9, 8.5, 8.7, 8.9
resolution 1.6, 2.3, 3.2, 3.3, 6.10, 9.2
ring volume 1.8
rings to answer 3.5, 6.9, 6.10

S

save charge 6.10
scan driver
 install 7.2
scanning glass 8.2
scheduled job 5.4, 6.4, 8.6, 8.7, 8.8
search 1.4, 2.3, 2.4
send from memory 2.3, 3.3, 6.9
sending confirm 3.3, 6.4, 6.9
setting date and time 1.6
setting fax number 1.7
shading 8.4, 8.7
short message service 6.6
silence action 6.10
silent mode 6.10
smart fax 5.3
software
 install 7.2
speaker volume 1.8

specifications 9.2

speed dial

 caller ID 2.4
 dialling 2.2, 2.3
 junk fax 6.5
 programming 2.2, 6.2, 6.4, 8.7
 sending 3.3, 5.2

T

TAM message 4.2, 4.5, 5.5, 6.4

U

USB

 connect 7.2

W

wakeup sound 6.3
white roller 8.2, 8.7

Contact SAMSUNG WORLD WIDE

If you have any comments or questions regarding Samsung products, contact the SAMSUNG customer care center.

Country	Customer Care Center	Web Site
CANADA	1-800-SAMSUNG (7267864)	www.samsung.com/ca
MEXICO	01-800-SAMSUNG (7267864)	www.samsung.com/mx
U.S.A	1-800-SAMSUNG (7267864)	www.samsung.com
ARGENTINE	0800-333-3733	www.samsung.com/ar
BRAZIL	0800-124-421	www.samsung.com/br
CHILE	800-726-7864 (SAMSUNG)	www.samsung.com/cl
COSTA RICA	0-800-507-7267	www.samsung.com/latin
ECUADOR	1-800-10-7267	www.samsung.com/latin
EL SALVADOR	800-6225	www.samsung.com/latin
GUATEMALA	1-800-299-0013	www.samsung.com/latin
JAMAICA	1-800-234-7267	www.samsung.com/latin
PANAMA	800-7267	www.samsung.com/latin
PUERTO RICO	1-800-682-3180	www.samsung.com/latin
REP. DOMINICA	1-800-751-2676	www.samsung.com/latin
TRINIDAD & TOBAGO	1-800-7267-864	www.samsung.com/latin
VENEZUELA	1-800-100-5303	www.samsung.com/latin
BELGIUM	02 201 2418	www.samsung.com/be
CZECH REPUBLIC	844 000 844	www.samsung.com/cz
DENMARK	38 322 887	www.samsung.com/dk
FINLAND	09 693 79 554	www.samsung.com/fi
FRANCE	08 25 08 65 65 (€ 0,15/min)	www.samsung.com/fr
GERMANY	01805 - 121213 (€ 0,12/min)	www.samsung.de

Country	Customer Care Center	Web Site
HUNGARY	06 40 985 985	www.samsung.com/hu
ITALIA	199 153 153	www.samsung.com/it
LUXEMBURG	02 261 03 710	www.samsung.lu
NETHERLANDS	0900 20 200 88 (€ 0,10/min)	www.samsung.com/nl
NORWAY	231 627 22	www.samsung.com/no
POLAND	0 801 801 881	www.samsung.com/pl
PORTUGAL	80 8 200 128	www.samsung.com/pt
SLOVAKIA	0850 123 989	www.samsung.com/sk
SPAIN	902 10 11 30	www.samsung.com/es
SWEDEN	08 585 367 87	www.samsung.com/se
U.K	0870 242 0303	www.samsung.com/uk
RUSSIA	8-800-200-0400	www.samsung.ru
UKRAINE	8-800-502-0000	www.samsung.com/ur
AUSTRALIA	1300 362 603	www.samsung.com/au
CHINA	800-810-5858 010- 6475 1880	www.samsung.com.cn
HONG KONG	2862 6001	www.samsung.com/hk
INDIA	3030 8282 1600 1100 11	www.samsung.com/in
INDONESIA	0800-112-8888	www.samsung.com/id
JAPAN	0120-327-527	www.samsung.com/jp
MALAYSIA	1800-88-9999	www.samsung.com/my
PHILIPPINES	1800-10-SAMSUNG (7267864)	www.samsung.com/ph
SINGAPORE	1800-SAMSUNG (7267864)	www.samsung.com/sg
THAILAND	1800-29-3232 02-689-3232	www.samsung.com/th
TAIWAN	0800-329-999	www.samsung.com/tw
VIETNAM	1 800 588 889	www.samsung.com/vn
SOUTH AFRICA	0860 7267864 (SAMSUNG)	www.samsung.com/za
U.A.E	800SAMSUNG (7267864)	www.samsung.com/mea