# **60W DIN RAIL SWITCH MODE POWER SUPPLY**

## **OXIC INDUSTRIAL SERIES**

### SDRXX060 USER'S MANUAL

#### **INTRODUCTION**

This range of compact DIN mounted switching mode power supplies are designed for a wide range of control equipment which demands good quality regulated DC power source with excellent EMC immunity and electrical performance in an industrial environment.

#### **FEATURES**

- Overload Protection: The constant current circuitry is adopted to prevent from overload. The DC output ON indicator will turn off when the unit is 1. overloaded
- Over Temperature Protection: The over temperature circuitry is functioned when the unit is over a certain high temperature to prevent the unit from 2 damage by the high temperature. When the circuitry is functioned, the output voltage and current will drop down and the DC output ON indicator will turn off.

**De-rating Curve** foi

- Over Voltage Protection: The over voltage circuitry protect the unit and the loading equipment from damage by abnormal high output voltage. 3
- 4. High RFI Stability: The high protection circuitry against RFI (Radio Frequency Interference) provides a stable operation.
- The concealed trimmer (Fine tune access port) allows fine tuning of output voltage. 5.
- 6 Up to 5 units can be connected in parallel.

#### PANEL DESCRIPTION



#### **INSTALLATION**

- The SDRXX060 series power supplies are build-in units and designed for mounting on a standard DIN- rail TS35 (35x15/7.5). 1.
- 2 Make sure the correct mounting position for optimal cooling performance.
- 3. To fix the unit on the DIN rail, hook top part of clip on DIN rail, push down and inwards until you hear a clipping sound.
- To remove the unit, insert a insulated flat head screwdriver into the recess in the clip closest to bottom of the unit and then push down to remove it from 4. the recess and lift it off from DIN rail. Note: For Indoor Use Only.

#### SAFETY PRECAUTIONS

- 1. NEVER remove the metal cover of the power supply while AC power is connected.
- NEVER touch the unit when your hands are wet. 2
- 3 NEVER touch the enclosure during the unit is full load powered, touching it may burn your hands or part of your body by high temperature.
- This series are build-in power supplies and should be installed inside a main frame with at least 200 CFM air ventilation. 4
- NEVER operate the unit if foreign materials such as metallic objects, water, or other debris have fallen inside. Contact your dealer for check and repair. 5. NEVER operate the unit that was being damaged, as the voltage regulation circuitry may have been disabled. The resulting high voltage could damage 6.
- your equipment 7. NEVER allow foreign objects to touch the DC Power Output Terminals.

- 8. If you have the need to inspect the interior of the unit, let it to cool down completely, as some components may be enough to burn your hand in the event of component failure.
- 9. **NEVER** block the air intake window.

#### **CONNECTION AND OPERATION**

- 1. A protective device (fuse, MCB) and an easy accessible isolating device for disconnecting the power supply must be provided.
- 2. Ensure that the main switch is switched off and prevented from being switched on again. In case of non-observance touching at any alive components or improper dealing with this power supply can result in death or severe injury.
- 3. Connect the equipment to the unit. If flexible wires are used, the wires have to be terminated. (e.g. by using ferrules). The wire should be at least AWG#18 with 4mm peeled conductor.
- 4. To parallel the units to get higher output current, switch the parallel connection switch to "P" position before wire connection.

#### **SPECIFICATIONS**

	SDR05060	SDR12060	SDR24060	SDR48060
Voltage Range (Auto Select)	90 - 264Vac			
Frequency	47-63Hz~			
Full Load AC Current	1A@100Vac ; 0.5A@230Vac	1.1A@100Vac ; 0.55A@230Vac	1.1A@100Vac ; 0.55A@230Vac	1.1A@100Vac ; 0.55A@230Vac
No Load AC Current	40mA@100Vac ; 50mA@230Vac			
Inrush Current, cold start @25°C*	20A@100Vac ; 40A@230Vac			
Leakage Current	2mA			
Power Factor	min.60%			
Efficiency	75%@100Vac ; 76%@230Vac	82%@100Vac ; 83%@230Vac	85%@100Vac ; 86%@230Vac	85%@100Vac ; 86%@230Vac
OUTPUT	·	•	•	•
Normal DC Voltage	5V	12V	24V	48V
Voltage Adjust Range	4.2 - 5.5V	10.5 - 13V	21.5 - 25V	44.5 - 50V
Rated Current	10A	5A	2.5A	1.25A
Rated Power	60W			
Ripple & Noise (peak to peak)**	≤50mV			
Line Regulation	≤0.2%			
Load Regulation (10% - 100%)	≤0.8%	≤0.3%	≤0.3%	≤0.3%
Hold-up Time (Full Load)	>20mSec@100Vac;>120mSec@230Vac			
Parallel Operation	5 units max. user selectable			
PROTECTION	4			
Over load / Over Current	10.2 - 12A, C.C., Auto Restart	5.2 – 6.5A, C.C., Auto Restart	2.6 – 3.5A, C.C., Auto Restart	1.3 - 2A, C.C., Auto Restart
Output Cut Voltage	6.5Vdc Auto Restart	14Vdc Auto Restart	27Vdc Auto Restart	55Vdc Auto Restart
SAFETY & EMC	1			
Safety Standards	EN60950, UL508			
Withstand Voltage	I/P - O/P 3KVac ; I/P - F/G 1.5KVac ; O/P - F/G 0.5KVac			
Insulation Resistance	I/P - O/P, I/P - F/G, O/P - F/G 100Mohm and 500Vdc			
EMI Radiation & Conduction	Compliance to EN55011, EN55022 Class B, FCC part 15 level B			
Harmonics Current	Compliance to EN61000-3-2, 3 Class A & D			
	Compliance to EN61000-4-2, 3, 4, 5, 6, 8, 11			
EMC Immunity	AC Immunity ENV50204, EN55024, EN61000-6-2(EN50082-2) heavy Ind. level cr			
ENVIRONMENT				
Working Temperature	EN60950 : -10°C to +50°C (UL508 : 0 to 40°C)			
Derating above 50°C	See Derating Curve			
Working Humidity	20 - 90 RH non-condensing			
Storage Temperature Humidity	-10°C to +80°C , 20 - 90 RH non-condensing			
GENERAL				
Switching Frequency @ Full Load	60 - 80KHz			
Case Material	Electro-Galvanized steel & Aluminum Enclosure and Poly-carbonate Front Panel			
Safety Class	Degree of Protection 1 (IEC 5360)			
Case Protection	IP 20 (IEC 529)			
Mounting	Snap on type with self locking can be installed on 35 mm Din-Rails / 7.5 or 15			
Connection	Screw terminals with double terminals for output			
REMARK	*Ta=25°C Cold start **100MHz Band width scope			

\*All values are based on the Standard ambient Temperature 25°C and Pressure 0.1Mpa.\*