

# GNR-3000

## System Administrator's Manual

For V3.0.06 Version

# About This Manual

## Target Audience

---

This manual is intended for **System Administrators** who are responsible for installing and setting up ACTi NVR 3.0 surveillance system. The reader is expected to know the fundamentals of IP surveillance system integration and to own the administrative privileges to achieve all the tasks.

You may also check video management system section on ACTi corporate website:

[http://www.acti.com/product/detail/Standalone\\_NVR/GNR-3000](http://www.acti.com/product/detail/Standalone_NVR/GNR-3000) for updates or release information about this software and document.

## Content Overview

---

This manual provides information needed for planning the installation, installing, setting up the system and configuring the video streaming devices. Its main content consists of the following three sections:

- **Getting Started** provides the preparatory knowledge you should study before starting installation, such as system requirements, license registration and backup/restore procedures.
- **Log in to the System** explains how to log in to the system right after a successful installation.
- **System Setup** gives instructions on the tasks such as adding devices to the system, configuring the device settings, scheduling the recordings, managing events, managing storage, managing groups/users and setting up Live View. For each major task, you will be given a brief introduction of operation principles, step-by-step instructions, and a simple method to check if you have done it correctly.

## Related Documentation

---

Since this manual focuses on how to accomplish the tasks for system installation and configurations, there is very limited information about operation-wise directions for **End Users** who will be operating NVR server system. To obtain the instructions on use of NVR applications such as monitoring and playback, please download the latest User's Manual from ACTi Corporation website via [http://www.acti.com/product/detail/Standalone\\_NVR/GNR-3000](http://www.acti.com/product/detail/Standalone_NVR/GNR-3000)

## Technical Support

---

If you have any questions during system installation, please feel free to contact our engineers via our **Customer Help Desk** platform <http://www.acti.com/CHD>.

## Conventions Used in This Manual

---

The following are typographic conventions used in this manual:

- **Bold**: Bold typeface is used for a keyword, major functions of NVR, or a title of a section/column.
- *Italic*: Italic typeface is used for a filename or location path.
- Underlined: Underlined typeface is used for a document name or hyperlink.
- **"Bold"**: Bold interface enclosed in double quotation marks indicates the name of a button, a menu or a choice item.

Some notices are placed within the following boxes; each type of the box indicates different purposes or levels of importance for system:

### Important Notice

The content within this box is an **important notice**. This notice is important for you to get certain functions to work properly, or to prevent from certain potential problems that may damage your system. Make sure you read this notice and follow the instructions.

### Note

The content within this box is a **note**. A note is some necessary information you need to know about the action you are currently taking, like what will happen after you follow or don't follow certain procedure.

### Tip

The content within this box is a **tip**. A tip gives you an alternative method to easily or quickly achieve an objective, usually for specific conditions.

# Legal Notice

## Disclaimer

---

- The information contained in this document is intended for general information purposes. ACTi Corporation shall not be liable for errors contained herein or for incidental or consequential damages arising from the furnishing, performance, or use of this manual.
- The information contained herein is subject to change without notice.
- The English version of this document is the official one for all purposes. All the translated versions are provided as a convenience. Any discrepancies or differences created in the translations of any other languages are not legally binding.

## Copyright

---

Copyright ©2003-2013 ACTi Corporation All Rights Reserved.

## Trademarks

---

- ACTi Connecting Vision and its logo  **ACTi**  
Connecting Vision are registered trademarks of ACTi Corporation.
- Microsoft® and Windows® are registered trademarks of Microsoft Corporation.  
All other product or company names mentioned in this document may be trademarks or registered trademarks of their respective owners.

## Regulatory Compliance Information

---

### Federal Communications Commission Statement



This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

**WARNING:** Changes or modifications to the equipment that are not expressly approved by the responsible party for compliance could void the user's authority to operate the equipment.

### European Community Compliance Statement



This product has been tested and found to comply with the limits for Class B Information Technology Equipment according to European Standard EN 55022 and EN 55024. In a domestic environment, this product may cause radio interference in which cause the user be require to take adequate measures.

# Table of Contents

<b>1 About This Manual</b>	<b>2</b>
Target Audience .....	2
Content Overview .....	2
Related Documentation .....	3
Technical Support .....	3
Conventions Used in This Manual .....	4
<b>2 Legal Notice</b>	<b>5</b>
Disclaimer .....	5
Copyright .....	5
Trademarks .....	5
Regulatory Compliance Information .....	6
<b>3 Table of Contents</b>	<b>7</b>
<b>4 Overview</b>	<b>13</b>
Product Overview .....	13
Server / Client Architecture .....	14
Client PC System Requirements .....	15
<b>5 Getting Started</b>	<b>17</b>
What's in the Box .....	17
At a Glance .....	18
Hard Disk Installation .....	19
Step 1: Remove the Tray .....	19
Step 2: Mount the Disk .....	20
Step 3: Install the Tray .....	20
Connect the Devices .....	21
Start the Unit .....	22
Definitions of LED Indicators .....	23

<b>Turn Off the Unit.....</b>	<b>23</b>
<b>Enter Windows.....</b>	<b>24</b>
<b>Adjust Screen Resolution .....</b>	<b>25</b>
<b>Get the Hard Disks Ready for Recording.....</b>	<b>26</b>
Windows Volume Types.....	26
Windows Volume Types Comparison .....	28
Start Creating Disk Volumes .....	29
<b>Observe Disk Status.....</b>	<b>32</b>
Live View Screen.....	32
Disk Management .....	33
Trouble-shoot the Disk Drives .....	34
Reactivate the Disk .....	35
Check the Physical Connection.....	35
Reactivate the Volume .....	36
Volume Resynchronization.....	36
Repair the Mirrored Volume .....	36
Replace the Disk.....	37
<b>Configure the IP Address .....</b>	<b>38</b>
Find the IP Address of GNR.....	38
Assign a Static IP Address to GNR.....	39

## 6 Log In to the System

**41**

<b>Access the NVR Server via NVR3 Workstation.....</b>	<b>41</b>
Local Workstation Client Login.....	42
A. Enter Account & Password .....	42
B. Choose the Initial Page .....	42
C. Language .....	42
D. Remember Login Information and Auto Login .....	42
E. Retrieve the Forgotten Password .....	43
Remote Workstation Client Login.....	43
A. Server IP & Server Port .....	43
B. Enter Account & Password .....	43
C. Choose the Initial Page .....	43
D. Language .....	44
E. Remember Login Information and Auto Login .....	44
F. Retrieve the Forgotten Password .....	44
G. Server Name/Server Sites List .....	44

<b>Access the NVR Server via Internet Explorer .....</b>	<b>46</b>
Accept ActiveX Controls Installation Requests .....	46
<b>Log in Failure Troubleshooting .....</b>	<b>46</b>
Condition 1: Why can't I access NVR server via web browser? .....	47
Condition 2: Why can't I install Active X controls after logging in? .....	48
<b>Login .....</b>	<b>50</b>
A. Enter Account & Password .....	50
B. Change UI language .....	50
C. Remember Account/Password .....	50
D. Retrieve the Forgotten Password .....	50
<b>License and Activation .....</b>	<b>51</b>
Online Activation .....	52
Offline Activation .....	52
Step-by-step Activation Process .....	53
Online Activation SOP .....	53
Offline Activation SOP .....	54
Verify Your License .....	55

## **7 Set up the System 56**

<b>Setup Wizard.....</b>	<b>56</b>
System Settings .....	57
Storage .....	57
<b>NVR Main Screen.....</b>	<b>59</b>
Live View .....	59
Playback.....	59
Setup.....	59
<b>Add Devices.....</b>	<b>60</b>
Search Devices within Local Area Network.....	61
Add Devices on WAN or Other Local Area Networks .....	62
Basic Settings Attributes .....	63
Device Status .....	64
Status Icon Description .....	64
Add Non-ACTi Cameras .....	65
<b>Manage Multiple Devices.....</b>	<b>67</b>
Modify Basic Connection Settings.....	67
Delete Devices .....	67
Copy Settings Across Devices .....	68

Add Video Streams from a Multi-channel Device .....	69
<b>Configure Device Settings.....</b>	<b>70</b>
Configure Video Format .....	70
Video Settings Attributes .....	70
Save Storage by Setting Event Recording Frame Rate.....	71
Schedule Recording .....	71
Event Recording .....	71
Event Recording with Frame Rate Adjustment .....	72
How to Make Use of Event Recording with Frame Rate Adjustment .....	72
Fine-tune the Image: Brightness/Contrast/Saturation/Hue .....	73
Video Adjustment Attributes .....	74
Configure Motion Settings.....	74
Adjustment Attributes .....	75
Configure PTZ Device.....	76
Adjustment Attributes .....	77
How to Do Live PTZ Operation .....	78
Set PTZ Preset Points.....	80
Set PTZ Preset Tour.....	81
Configure Fisheye Cameras.....	82
<b>Schedule Recordings .....</b>	<b>85</b>
Configure the Recording File Properties .....	85
Attributes Explanation .....	85
Set the Schedule.....	87
Use Time Setting Quick Buttons to Set the Time in One Click .....	88
Lock Specific Days .....	89
Copy an Existing Schedule to Others.....	90
View the Entire Recording Schedule.....	91
<b>Event Management.....</b>	<b>92</b>
How Does NVR Handle Events.....	92
How to Edit an Event Rule .....	93
Manage the Event Rules.....	96
Delete the Event Rules .....	97
How to Setup SMTP Settings for Event Rules .....	97
How to Setup FTP Settings for Event Rules.....	98
<b>System Log .....</b>	<b>100</b>
Define Search Time .....	100
Choose Log Type .....	101
Read the Log .....	101

Export the Log .....	102
<b>Storage Management .....</b>	<b>103</b>
Change Recordings Folder Name.....	103
Set System Log Lifecycle .....	103
Set the Hard Drives and File Deletion Rule.....	103
<b>Manage User Groups/ Users .....</b>	<b>105</b>
Overview .....	105
User Groups.....	106
Add Users .....	108
Domain Users Management .....	110
<b>Customize Views .....</b>	<b>111</b>
Step 1: Create a New View .....	112
Step 2: Enter Edit Mode .....	112
Step 3: Select a Layout .....	112
Step 4: Add Video Source .....	113
Step 5: Add a Map .....	113
Step 6: Add Devices to the Map .....	115
Step 7: Adjust the Channel Size & Layout.....	116
Step 8: Save the View .....	116
Step 9: Set Default View.....	116
Step 10: Set Default Hotspot Channel (Optional) .....	117
Step 11: Set Fisheye Camera Mode .....	117
Manage the Views.....	118
Set View Link .....	119
Set View Patrol.....	119
Tips to Enhance Live View Performance .....	121
<b>Customize System Language.....</b>	<b>123</b>
System Languages List.....	123
<b>Display Configurations.....</b>	<b>126</b>
<b>Video &amp; Snapshot Export Configurations .....</b>	<b>127</b>
<b>Joystick .....</b>	<b>128</b>
Joystick Configurations .....	128
<b>NVR System Upgrade .....</b>	<b>129</b>
Install the Software.....	129
<b>Workstation Installation and Upgrade .....</b>	<b>133</b>
Install or Upgrade the Software.....	133
<b>Back Up System Data.....</b>	<b>135</b>
Step 1: Back up System Settings .....	135
Step 2: Back up Recording Files Folder (Optional) .....	136

Step 3: Back up Recording Files Index Folder (Optional).....	136
Step 4: System Log (Optional) .....	136
<b>Restore System Data .....</b>	<b>137</b>
<b>Advanced Administrative Tasks.....</b>	<b>138</b>
NVR Server Status.....	138
Change Server Port .....	138
Change Authentication Method.....	139

# Overview

## Product Overview

---

GNR-3000 is a compact and reliable multi-channel standalone NVR. It contains a pre-installed Windows operating system, and ACTi NVR 3.0 video management software along with client software.

This unit is composed of:

- **Computer**


A PC, with Microsoft ® Windows Embedded Standard 7 Professional operating system pre-installed.

- **NVR 3.0 Server System**

A video management software that allows this PC to become a server, where the system administrator performs the administrative tasks and NVR server services (event handling, schedule recording, media streaming, etc) take place.

- **NVR 3.0 Client Application**

The dedicated client application of NVR3 system - **NVR3 Workstation**, allowing the user to directly access NVR3 interface. A remote client can also access this system via network.




## Server / Client Architecture

NVR 3.0 is a typical web-based server/client system. In a video surveillance system architecture, the **Server** serves as a video management service provider, aimed to run 24/7 offering non-stop services for clients. A **Client** makes requests of monitoring video streams or playback recordings to **Server**, which can reside on the same computer with server program (as from local) or on another computer (as from remote). **Server** starts automatically as soon as the **Server computer** (where it is installed) boots up, and operates in the background without requiring login by administrator. It would provide services over the TCP/IP network to multiple **Clients** upon request through HTTP Protocol.

There are two types of **Clients** in NVR 3.0 system: **Web Client** and **Workstation Client**. A user, connecting from whether web browser or workstation, will enjoy the same user interface and NVR functions.

- **Web Client:** the web version of interface to access NVR server without need of installing any client program to become a client. Logging in the NVR server is as simple as visiting a website through IE browser.
- **Workstation Client:** the client application making accessing NVR server free from the use of browser. The workstation includes a set of programs that provide interface between users and the NVR server.



## Client PC System Requirements

The minimum **CPU Processor** spec will provide acceptable performance for systems that use mostly MPEG4 streams.

PC Spec		Remote Client PC	
Number of Live Channels (*2)		1-16	17-64
CPU Processor	Minimum	Intel Core 2 Quad 2.4GHz	Intel i5 2.4 GHz
	Recommended	Intel i5 2.4 GHz	Intel Core i7-920 2.67 GHz
RAM		4GB (*3)	
Network		Ethernet (1000 Base-T recommended)	
Operating System (*4)		Windows 8, Windows 7, Windows Server 2012, Windows Server 2008	
Display Resolution		Minimum: 1024 X 768	
Browser		Internet Explorer 9 and 10	

\*1 These specifications are based on following camera settings:

**Single stream mode** → 1280x1024, 3Mbps, 18fps, MPEG-4

**Dual stream mode** → 1280x1024, 3Mbps, 18fps, H.264 (recording);  
640x480, Quality: 100, 18fps, MJPEG (live view).

\*2 Live view for multiple channels requires good hardware for smooth performance. For more channels or heavy use of high resolution streaming, it is good to adopt computers with more advanced specifications than the requirements we suggest.

\*3 Please use 64-bit system if your computer has more than 4GB RAM. Windows operating system has limits on memory and address space regardless of the real or virtual memory available on a particular computer. Take Windows 7 Professional for example, the maximum physical memory for a 32-bit(X86) system can address is 3.5 GB even though 16 GB of RAM has been installed on this computer. Therefore, if you consider increasing the computer's multi-tasking capability by adding more RAM, you will need a 64-bit version of Windows to take advantage of it all.

Please visit the link below for more memory limitations on various Windows platforms.

[http://msdn.microsoft.com/en-us/library/aa366778%28VS.85%29.aspx#physical\\_memory\\_limits\\_windows\\_7](http://msdn.microsoft.com/en-us/library/aa366778%28VS.85%29.aspx#physical_memory_limits_windows_7)

Besides the limitation mentioned above, you may find the usable memory of your computer

displayed here:  → **Computer** → **Properties** is still less than actual installed memory.

This is a common symptoms of all Windows platforms, please find explanations and solutions in this Windows official support document

<http://support.microsoft.com/kb/978610/en-us> and

<http://windows.microsoft.com/en-us/windows7/taking-the-mystery-out-of-64-bit-windows>

**\*4** Please make sure your operating system is fully patched with the latest service packs.

# Getting Started

## What's in the Box



---

This product package includes the following items:



- ❶ GNR-3000 x 1
- ❷ Quick Installation Guide x 1
- ❸ Accessories
- ❹ Warranty Card x 1
- ❺ Power Chord x 1  
(Adapter type varies by region)
- ❻ Removable Hard Disk Bays x 5  
(Stored inside the unit)

## At a Glance




## Hard Disk Installation

For video recordings, you should install **at least ONE** certified 3.5-inch SATA hard disk. Be sure to use the hard disk models ACTi tested to be compatible with GNR-3000. You may find the certified models via <http://www.acti.com/hddselector>. It is strongly recommended that you use hard disks of the same model and capacity.

The actual necessary space depends on number of devices, recording and event rules settings. To get an approximate value, you may use the software tool **Bandwidth & Storage Calculator** - <http://www.acti.com/storagecalculator>.

You can install up to **four** disks in to **Storage Disk Bays**. During the installation, please avoid removing the **System Disk Bay**.



Repeat **Step 1~3** to finish installing all the storage disks.

### Step 1: Remove the Tray

Slide the **Lock Tab** up, the **Hinge Tab** will pop out by itself.

Pull the **Hinge Tab** to 90 degrees from the front, and then pull out the tray.



### Step 2: Mount the Disk

Mount the disk by locking it with supplied disk screws to the bottom of the tray.



### Step 3: Install the Tray


Press on **Lock Tab**, push the tray into the bay until it stops.

Press on the **Hinge Tab** until it clicks into place.



## Connect the Devices


Follow the procedures to connect the devices. These devices are supposed to get connected in the sequence shown below.



1. Connect the VGA monitor using the VGA cable supplied by the monitor manufacturer.
2. Connect the USB devices and the audio devices (e.g. microphone and speaker) to the audio output and audio input.
3. Connect the eSATA storage device (optional).
4. Attach the network cable to one of the LAN ports.
5. Plug the power adapter into GNR and electricity outlet.
6. Connect GNR with another network segment (e.g. remote client connection, SMTP service) via the other LAN port (optional).

## Start the Unit

1. On the rear panel, press down the **Power Switch** to the side with “I” mark.



2. On the front panel, press down **Power Button**, the **Power Status LED Indicator** will light up and turn solid blue.



## Definitions of LED Indicators


Indicator	LED Status	Description
<b>Power Status</b>	Solid	The unit power is on.
<b>HDD Bay Status</b>	Solid	The hard disk is installed and detected in this bay.
<b>HDD Activity</b>	Flashing	There is read or write activity.

## Turn Off the Unit

The unit can be turned off by the methods described below, and the **Power Status LED Indicator** will go off right after the device is turned off.



1. Shut down the system from **Windows Start**




2. Press down **Power Button** to turn the device off.

To completely cut off the power supply of this unit, press down the **Power Switch** to the side with "O" mark.

## Enter Windows

---


After the unit starts, key in “**123456**” to log in as Administrator to Windows Embedded 7 system.




## Adjust Screen Resolution

The native (maximum) resolution of GNR's built-in graphic card is **1920x1200**. By default, GNR will display a lower resolution which best suits a standard **4:3** screen monitor, at which you get to see larger icons and text but the edges are not so sharp. For a **wide screen** or higher resolution, please modify the settings below:

1. On **Windows Desktop**, right-click on the screen and then select **Screen Resolution**. Change **Multiple displays** setting to "**Show desktop only on 2**" and then apply this setting.



2. On **Screen Resolution** window, you may now select a desired resolution size from **Resolution** dropdown list.



## Get the Hard Disks Ready for Recording

GNR supports flexible storage system of up to four hard disks. Thanks to the built-in software RAID (Redundant Array of Independent Disks) provided by Windows Embedded 7 operating system, the installed hard disks can be configured to one or more arrays for the following benefits:

- The hard disks can appear as a one single volume of large storage size.
- User gets to define how the data is stored regarding protection against the physical failure of one or more hard disks.
- Increase the speed of writing and reading data.


The software RAID task of Windows runs on the computer's CPU, requiring no extra hardware attached to the computer, which saves you much cost and effort on installation. In addition, as Windows configures the arrays at the disk volume level, a disk is not necessary to serve only one array, and you can make full use of its unmatched disk space to make another array.




There are several types of software RAID configurations available in Windows, and it is good to know whichever RAID type is suitable for your system. After reading through this chapter, you will be able to choose suitable RAID type for your video surveillance project and get the storage disks ready for recording.

Please note that, Windows refers to a single accessible storage file system as **Volume** instead of **RAID**, and the creation of software RAIDs is carried out during the process of making volumes. When you make the volumes with **Disk Management** utility (please refer to Start Creating Disk Volumes on page 28), your selection of **Volume Type** will correspond to a specific RAID type. Please note that RAID-5 configuration is available on Windows 2003 Server, or similar operating system.

### Windows Volume Types

RAID Type	Windows Volume Type	Description
--	<b>Simple Volume</b>	It is the most basic method to make the available space on a <u>single disk</u> a volume; you can create more than one volumes on a single disk to make the most use of the disk capacity.



--	<b>Spanned Volume</b>	<p>This volume type is also called <b>JBOD</b> (Just a Bunch of Drives), <u>combing multiple disks as a single logical volume</u>. This method does not offer any advantage in terms of reading/writing speeds, parity or redundancy but sacrifices no disk space because the total storage equals to the sum of each individual disk's storage. However, since the data is written to the physical disks sequentially, any failure of a single disk is likely to fail the whole array.</p>  <p><i>In the example, a piece of information is being written to a <b>JBOD</b>. After the first disk is full, the rest of this data will then be written to the next disk.</i></p>
Raid 0	<b>Striped Volume</b>	<p>This configuration combines <u>two or more disks</u> as a single logical volume without using without any parity and redundancy. However, this method highly increases the writing/reading speeds by equally splitting the data into all the disks, which means the that the more disks you have in this RAID, the faster the data reading and writing will be.</p>  <p><i>In the example, there are two disks combined as one <b>RAID 0</b> array, a piece of information is first split into two data blocks and then written to both disk at the same time.</i></p>
RAID 1	<b>Mirrored Volume</b>	<p>This method is <b>RAID 1</b>, designed to make a mirror copy of one disk on the other disk, which requires exactly <u>two disks</u> of the same size. Since the second disk is used as a mirror, there is no improvement in writing speed or capacity compared to a single disk scenario.</p>  <p><i>In the example, a copy of the entire data is respectively written to both disks running under <b>RAID 1</b>.; a piece of information is first split into two data blocks and then written to both disk at the same time.</i></p>

For more details about the volume types and volume management, please refer to

[http://technet.microsoft.com/en-us/library/cc737098\(v=ws.10\).aspx](http://technet.microsoft.com/en-us/library/cc737098(v=ws.10).aspx)

## Windows Volume Types Comparison

- For the pursuit of data redundancy, which can still recover all the recordings after one disk fails, it is suggested that you make a **Mirrored Volume** out of two disks of large capacity.
- If there are quite a few high-megapixel live channels in your system, with one or more clients frequently accessing Live View and Playback, you may consider making a **Striped Volume** that provides the maximum possible capacity with high performance but no failure tolerance.

The table below is based on the available configurations of GNR.

Volume Type	Simple	Spanned	Striped	Mirrored
Corresponding RAID Type		JBOD	RAID 0	RAID 1
Minimum Number of Disks required	1	2	2	2
Capacity	V	$V_1 + V_2 + \dots + V_N$	$V_{\min} \times N$	$V_{\min}$
*Storage Efficiency	★★★★★	★★★★★	★★★★★	★★★
Fault Tolerance	None	None	None	★★★★
Write Speed	★★★	★★★	★★★★★	★★★
Read Speed	★★★	★★★	★★★★★	★★★


●  $N$  = the number of disks

●  $V$  = the disk capacity ( $V_{\min}$  = the capacity of the disk with the smallest storage in the array)


(\*) This result is obtained based on the assumption that the disks are of the same capacity.

## Start Creating Disk Volumes


1. Click **Windows Start**  , in **Windows Search Box**, input “**Computer Management**”, and enter this utility.




Select “**Disk Management**”, right-click on a disk title and select “**Initialize Disk**”, check all the disks you have installed and choose “**GPT**” as the partition type, then click “**OK**”.



- Right-click on a disk title again, and then select **"Convert to Dynamic Disk..."**, select all the disks you installed and click **"OK"**.




- Right-click on a disk and select the volume type to make a new volume.



A **Volume Wizard** will come up to bring you thorough the configuration process. Make sure you assign the desired **Drive Letter** and **Volume Label** to this volume via the wizard.

Repeat this step to finish creating all the volumes you need.


4. After the volume is created, this drive will be shown on **Volume list**, which is ready for recording. You may follow the instructions in [Storage Management](#) on page 103 to assign certain volumes to do the recording.




## Observe Disk Status

It may happen that one of your disks goes into **failed** status after NVR system started recording for a long period. Mostly, a disk does not fail all of a sudden but because the number of bad sectors on it has exceeded the minimum required level to maintain normal operation. On **NVR Live View** interface, the recording status and system events can help you make an initial assessment of the overall disk condition. For further inspection and disk management, please make use of Window 7 built-in utility- **Disk Management**.

### Live View Screen



●On **Device list**, if the recording is proceeding normally, the red “recording” icon  will appear next to the device icon. If all the icons are missing when NVR is supposed to perform schedule recording, your storage disk might have gone into abnormal status.

- On the **Event list** will also display two kinds of abnormal disk status
  - **Disk Full**: The storage drive is full, recording has stopped.
  - **Disk Not Found**: The storage disk drive has failed or disconnected.

If you encounter any abnormal condition stated above, take the following steps to make a simple diagnosis:

#### 1. Confirm the schedule-recording setting


Go to **Setup** page → **Schedule** tab, and modify the recording schedule if it was not set correctly.

#### 2. Check Disk Drive List

Go to **Setup** page → **Storage** tab.

● If the disk drive is missing from **Disk Drive List**, please refer to Trouble-shoot the Disk Drives on page 34 to fix this drive.

● If the disk is full, a warning icon will appear next to the **Drive**, please follow the instructions in Set the Hard Drives and File Deletion Rule on page 103 to configure the



recording rule setting. NVR will start recording again after the new setting is applied.


## Disk Management

The **Disk Management** built-in Windows 7 is the basic management utility used for performing main storage-related tasks including managing the volumes and the disks.

Go to **Windows Control Panel** → **Administrative Tools** → **Computer Management** and select "**Disk Management**". Check the **Volume list** for the status of each volume, and check **Disk list** below for detailed individual disk status. The **Volume list** represents the status of your recording drive; while the status of the disks contained in this volume is shown on the **Disk list** below. For the explanations of different Volume status, please refer to the online help document provided by *Microsoft TechNet*

[http://technet.microsoft.com/en-us/library/cc739417\(v=ws.10\).aspx](http://technet.microsoft.com/en-us/library/cc739417(v=ws.10).aspx), or refer to

<http://technet.microsoft.com/en-us/library/cc771775.aspx> for coping with different disk status.



## Trouble-shoot the Disk Drives

Normally, the status of a working volume appears “**Healthy**”.

Volume	Layout	Type	File System	Status	Capacity	Free Space	% Free	Fault Tolerant
	Spanned	Dynamic		Failed	1527.2...	1527.25...	100 %	No
INR_OS (C:)	Simple	Dynamic	NTFS	Healthy (Boot, Page File)	442.36 GB	422.53 GB	96 %	No
INR_Recovery (D:)	Simple	Dynamic	NTFS	Healthy	21.41 GB	17.21 GB	80 %	No
Mirror (E:)	Mirror	Dynamic	NTFS	Resynchronizing	931.31 GB	930.97 GB	100 %	Yes
RAID 0 (G:)	Striped	Dynamic	NTFS	Healthy	700.68 GB	700.57 GB	100 %	No
Small JBOD (H:)	Spanned	Dynamic	NTFS	Healthy	594.37 GB	594.27 GB	100 %	No
System Reserved	Simple	Dynamic	NTFS	Healthy (System)	1.99 GB	1.96 GB	99 %	No

This chapter will provide simple guidelines for dealing with most happening abnormal volume issues.

Volume Status	Possible Cause	Solution
The volume is in <b>Healthy (at Risk)</b> status	Windows has found some bad sectors on its underlying disk.	Run a diagnostic check using the disk manufacturer's software tool, back up the data on this disk, and replace it with a new one as soon as possible. → <a href="#">Replace the Disk</a>
The volume is in <b>Failed</b> status	One of the underlying disks has gone abnormal, which led to the failure of this volume; this also indicates <b>data loss</b> , meaning there is no way to recover the recordings not saved during this period,	<ol style="list-style-type: none"> <li>1. Make sure the all the disks are in <b>Online</b> status. → <a href="#">Reactivate the Disk</a> → <a href="#">Check the Physical Connection</a> → <a href="#">Replace the Disk</a></li> <li>2. After all the disks are <b>Online</b>, this volume should return <b>Healthy</b>. If not, try to reactivate it manually. → <a href="#">Reactivate the Volume</a></li> </ol>
The Volume is in <b>Failed Redundancy</b> status	One of the disks in a mirrored volume has failed; the recording is still ongoing though this volume is currently not fault tolerant.	<ol style="list-style-type: none"> <li>1. Make sure the underlying disks are all <b>Online</b>. → <a href="#">Reactivate the Disk</a> → <a href="#">Check the Physical Connection</a> → <a href="#">Repair the Mirrored Volume</a></li> <li>2. After the disk returns to <b>Online</b>, this volume should start repairing itself by resynchronizing → <a href="#">Volume Resynchronization</a></li> <li>3. If this volume is still in <b>Failed Redundancy</b> status, try to reactivate it manually. → <a href="#">Reactivate the Volume</a></li> </ol>

More instruction about trouble-shooting provided by *Microsoft TechNet*:

[http://technet.microsoft.com/en-us/library/cc787481\(v=ws.10\).aspx#BKMK\\_7](http://technet.microsoft.com/en-us/library/cc787481(v=ws.10).aspx#BKMK_7)

[http://technet.microsoft.com/en-us/library/cc737098\(v=ws.10\).aspx](http://technet.microsoft.com/en-us/library/cc737098(v=ws.10).aspx)

## Reactivate the Disk

When the disk appears **Online (Errors)**, **Offline**, **Unreadable** or **Missing**, try this step to bring this disk back to **Online** status. On **Disk list**, right-click on the underlying disk that does not appear **Online**, and select "**Reativate Disk**".



You may refer to the online help document provided by *Microsoft TechNet* for more details -

[http://technet.microsoft.com/en-us/library/cc786948\(v=ws.10\).aspx](http://technet.microsoft.com/en-us/library/cc786948(v=ws.10).aspx)

If this step failed to return the disk to **Online** status, please Check the Physical Connection.

## Check the Physical Connection

The abnormal status: **Online (Errors)**, **Offline**, **Unreadable** or **Missing**) might result from the physical disconnection from the bay. Observe the front of the disk tray, if the **HDD Status LED** is not lit, turn off the unit, install the disk again following the steps in Hard Disk Installation on page 19, and check the disk status in **Disk Management**.

**HDD Bay Status Indicator**




You may refer to the online help document provided by *Microsoft TechNet* for more details-

[http://technet.microsoft.com/en-us/library/cc785259\(v=ws.10\).aspx](http://technet.microsoft.com/en-us/library/cc785259(v=ws.10).aspx)

If this step failed to return the disk to **Online** status, please Replace the Disk.

## Reactivate the Volume

If the volume remains in **Failed** status even though all the underlying disks are **Online**, you may try manually reactivate this volume. On **Volume list**, right-click the volume and select **“Reactivate Volume”**.



## Volume Resynchronization


A mirrored volume will automatically start resynchronizing to ensure that two mirrors have the identical data. The mirrored volume's status will return to **Healthy** after the resynchronization is done. When the volume appears in **Resynching** status, please avoid making any change to this mirror and the disks.

Volume	Layout	Type	File System	Status	Capacity	Free Space	% Free	Fault Toler
INR_OS (C:)	Simple	Dynamic	NTFS	Healthy (Boot, Page File)	442.36 GB	422.39 GB	95 %	No
Mirror (E:)	Mirror	Dynamic	NTFS	Resynching : (33%)	931.39 GB	931.20 GB	100 %	Yes
NEW VOLUME (I:)	Simple	Basic	FAT32	Healthy (Primary Parti...	3.72 GB	3.68 GB	99 %	No
System Reserved	Simple	Dynamic	NTFS	Healthy (System)	1.99 GB	1.96 GB	99 %	No


## Repair the Mirrored Volume

To repair a mirrored volume, replace the failed disk with a new one.

1. On **Volume list**, right-click the volume and click **“Remove Mirror...”**, select the disk to be replaced, and then click **“Remove Mirror”**.



2. Remove the failed disk from the bay and install a new one, following the steps in [Hard Disk Installation](#) on page 19.
3. The mirrored volume has now become a simple volume. Right-click on this volume and select "**Add Mirror...**", select the new disk and then click "**Add Mirror**".



4. This volume will start Volume Resynchronization immediately. During this period, the recording will proceed normally. The status will turn **Healthy** after the **Resynching** is complete.

Volume	Layout	Type	File System	Status	Capacity	Free Space	% Free	Fault Tolerance
INR_OS (C:)	Simple	Dynamic	NTFS	Healthy (Boot, Page File)	442.36 GB	422.53 GB	96 %	No
INR_Recovery (D:)	Simple	Dynamic	NTFS	Healthy	21.41 GB	17.21 GB	80 %	No
Mirror (E:)	Mirror	Dynamic	NTFS	Resynching	931.31 GB	931.00 GB	100 %	Yes
System Reserved	Simple	Dynamic	NTFS	Healthy (System)	1.99 GB	1.96 GB	99 %	No

### Replace the Disk

To replace a failed disk:


1. On **Disk list**, right-click the failed disk and select "**Offline**".
2. Shut down this unit and install the new disk following the steps in [Hard Disk Installation](#) on page 19.
3. After restarting this unit, enter **Disk Management**, right-click on the failed volume and select "**Delete Volume**". For how to delete the volume using the command line, you may refer to [http://technet.microsoft.com/en-us/library/cc780763\(v=ws.10\).aspx](http://technet.microsoft.com/en-us/library/cc780763(v=ws.10).aspx) provided by *Microsoft TechNet* for more details.
4. After the, volume is deleted, you may now build a new volume using the available disks.


## Configure the IP Address

After GNR starts, the network interface cards in it will be assigned IP addresses with the DHCP service in the network.


### Find the IP Address of GNR

To check the current IP address assigned by DHCP service:


1. Click **Windows Start** menu  and select "**Control Panel**".
2. Enter "**Network and Sharing Center**", select the network card connection. Click your current Internet connection.




3. A Connection Status window will pop up, click "**Details...**", you will find all the connection properties of this current network adapter in the details, including you IP address – **IPv4 Address**.




## Assign a Static IP Address to GNR


1. Click **Windows Start** menu  and select "**Control Panel**".
2. Enter "**Network and Sharing Center**", select the network card connection.




3. On **Connection Status** window, click "**Properties**"



4. Select **"Internet Protocol Version 4 (TCP/IPv4)"** and then click **"Properties"**.



5. On **Properties** window, select **"Use the following IP address:"** and enter the appropriate values for the static IP address. Click **"OK"** to save the settings.




6. To change the current port number from **80** to another, please refer to [Change Server Port](#) on page 138.

# Log In to the System

## Access the NVR Server via NVR3 Workstation




NVR3 Workstation includes a set of programs that provide the interface between users and the NVR server. In GNR, this software is already installed, and will start automatically after you login to Windows. You can also install this software on the remote client computer to access the NVR server via network. You can download this software on ACTi website at [http://www.acti.com/product/detail/Standalone\\_NVR/GNR-3000](http://www.acti.com/product/detail/Standalone_NVR/GNR-3000), and it is wrapped together with the NVR 3.0 system software. For the instructions on the installation of this software on the client computer, please refer to Workstation Installation and Upgrade on page 133.



## Local Workstation Client Login

**Local Workstation Client** refers to the user who runs NVR3 Workstation on the NVR server to log in to the NVR system. The login process is described as follows.



The image shows the NVR Workstation login interface. It has a dark background with white text. The fields are labeled with callouts: A for Account and Password fields, B for Initial Page dropdown, C for Language dropdown, D for Remember Account/Password and Auto Login checkboxes, and E for the Forgot Password? link. The Login button is at the bottom.

### A. Enter Account & Password

**Account** (non case-sensitive)


**Admin** (default)

**Password** (case-sensitive)

**123456** (default)

### B. Choose the Initial Page

The user interface consists of three main module screens, **Live View**, **Playback** and **Setup**. You may choose one where you would like to enter after login. Default is **Live View** screen.




### C. Language


Choose a UI language from the dropdown list.

### D. Remember Login Information and Auto Login

To have **NVR3 Workstation** remember the **Account**, **Password**, **Initial Page** and **UI Language**, simply check “**Remember login info**”. Click “**Don’t Remember**” will clear your input text and reset to default. **If the NVR server or remote client computer may be accessed by someone else, you might consider not to use this function.**


To automatically login to the NVR system, please check both “**Remember login info**” and “**Auto Login**” to skip the Login page. **If the NVR server or remote client computer may be accessed by someone else, you might consider not to use this function.**

To cancel auto-login, on title bar, click  → “**Logout**” to return to login page, and this function will be cancelled.



## E. Retrieve the Forgotten Password


The NVR server can send the password of the User's account to the saved email address. To have users be able to use this service, please make sure (1) the SMTP settings have been configured (refer to [How to Setup SMTP Settings for Event Rules](#) on page 97) and (2) a valid email address has previously been saved in **Setup** page → **Users** tab → User list.



The email address input in **Forgot Password** window should match the one under your User account saved in the NVR server.

## Remote Workstation Client Login

**Remote Workstation Client** refers to the user who runs NVR3 Workstation on a computer rather than the NVR server, and tries to reach the NVR server via network. The login process is described as follows.



### A. Server IP & Server Port

In **Server IP** field, please input the LAN or WAN IP address of the NVR server.

In **Server Port** field, key in the port number. The default value is 80.

### B. Enter Account & Password

**Account** (non case-sensitive)


**Admin** (default)

**Password** (case-sensitive)

**123456** (default)

### C. Choose the Initial Page

The user interface consists of three main module screens, **Live View**, **Playback** and **Setup**. You may choose one where you would like to enter after login. Default is **Live View** screen.




## D. Language


Choose a UI language from the dropdown list.

## E. Remember Login Information and Auto Login

To have **NVR3 Workstation** remember the **Account**, **Password**, **Initial Page** and **UI Language**, simply check **"Remember login info"**. Click **"Don't Remember"** will clear your input text and reset to default. **If the NVR server or remote client computer may be accessed by someone else, you might consider not to use this function.**

To automatically login to the NVR system, please check both **"Remember login info"** and **"Auto Login"** to skip the Login page. **If the NVR server or remote client computer may be accessed by someone else, you might consider not using this function.**

To cancel auto-login, on title bar, click  → **"Logout"** to return to login page, and this function will be cancelled.



## F. Retrieve the Forgotten Password


Please refer to [E. Retrieve the Forgotten Password](#) on page 43


## G. Server Name/Server Sites List

**NVR3 Workstation** can remember multiple server sites and their login settings and show the site lists on **Login** window. To add a new site:



1. Click in the **Server Name** box and input the server site name.
2. Fill in the other fields. If you disable the **"Remember login info"**, then only the **Server Name**, **Server IP** and **Server Port** of this server site will be remembered.
3. Click **"Save"**.
4. After a server site is saved, it will be shown on **Server Name** dropdown list.



You may click on its name to enter its Login window or  to delete it from the list.


5. You can export the saved server sites, or import it to another Workstation client computer.  
Access the NVR server via **NVR3 Workstation**, go to **Setup** page → **System** tab → **Workstation**.

## A. Export current server sites list

Click “**Browse**” to select a folder to save the list, and then click “**Export**”. This file will be saved as an \*.xml file.

## B. Import a server site list

Click “**Browse**” to select the \*.xml file, and then click “**Import**”. The server sites will appear in **Server Name** dropdown list on **Login** window of your next login.




## Access the NVR Server via Internet Explorer

In addition to NVR3 Workstation, you can also log in to the NVR system with Internet Explorer (IE). If you open the IE browser on the NVR server, you will be directed to the NVR system Login page immediately. If you are connecting to the NVR server as a remote client, please type the NVR server's LAN or WAN IP address, or domain name in the URL box. Remember to append a colon and the port number after the hostname or IP address.

### Accept ActiveX Controls Installation Requests

NVR 3.0 system interface requires the add-on ActiveX Control components, please make sure browser's security settings allow ActiveX controls to be downloaded and installed. When your browser asks if you allow ACTi Corporation's add-on components to run, please allow them.




### Log in Failure Troubleshooting

Once you confront with problems accessing the NVR server, refer to the possible conditions below and follow the instruction to solve your issues.

## Condition 1: Why can't I access NVR server via web browser?

After typing in the correct NVR server IP, if you cannot access NVR Login page, you may get the below browser screens:





**Cause 1:** The NVR server is not ready

**Solution:** It may happen when you just start the NVR server and it is still booting up. Please wait a few seconds and connect again.


**Cause 2:** The NVR server is not able to respond to your request through current path because port 80 has been seized by another service running on server computer. This may happen when that service is executed right before the NVR server starts its services.

**Solution:** Please check if there is another service using port 80 right now, and change the setting in that program to release port 80 for the NVR server. Below are the steps to find the service:

1. Please click on "**Windows Start**" (Windows-Logo) , then enter "**cmd.exe**" in the run box and execute it.
2. Input the command "**netstat -a -o -b**". You will be provided with the ports in use and the services using them. Find the **Local Address** that has taken port **80**, and the **PID** number.




3. Press down “ctrl”+ “alt” + “Delete” keys to bring up **Windows Task Manager**. Select “**View**”, then “**Select columns**”, and enable the “**PID (Process Identifier)**” to appear on search results. Please also make sure “**Show process from all users**” is enabled.
4. On **Task Manager Process** tab, locate the PID number of the service using port 80. The service name is shown under “**Image Name**” column.



## Condition 2: Why can't I install Active X controls after logging in?

ActiveX Control components are essential for the NVR server to present user interface. The message below will show if these controls were not installed. Please try refreshing the browser first, making IE pop up the prompts again.




**Cause 1:** Your **Internet Explorer** browser version does not support NVR 3.0 system.

**Solution:** Make sure your browser is **32-bit** version.


**Cause 2:** Your browser restricts the installation of add-on components.

**Solution:** Internet Explorer security settings may restrict the installation of add-on components. To ensure the NVR server is always accessible from your web client regardless of any change in browser's overall Internet security settings, you may add the NVR server site to Internet Explorer's trusted sites. Trusted sites are the sites which you consider safe and wish to visit with low security restrictions while maintaining higher security for the rest of the Internet.

1. On IE browser, click **Tools → Safety** and make sure **ActiveX Filtering** is unchecked.
2. On IE browser, go to **Tools → Internet Options → Security** tab, select **"Trusted sites"**, set the security level to **"Medium High"**, and then click **"Sites"**.
3. Add <http://localhost> or the NVR server IP to the zone, and **clear** the box **"Require server verification (https:) for all sites in this zone"**.
4. Back on **Security** tab, click **"Apply"** to apply the changes. This will allow ActiveX and scripting to be available for the chosen sites but not for the Internet as a whole.



## Login



The login interface for NVR v3.0 features a dark background with white text. It includes fields for 'Account' and 'Password', a 'Language' dropdown menu set to 'English', checkboxes for 'Remember Account/Password' and 'Auto Login', a 'Don't Remember' link, and a 'Forgot Password?' link. A 'Login' button is at the bottom. Red boxes and letters A, B, C, and D highlight specific areas: A for Account/Password fields, B for the Language dropdown, C for the Remember/Auto Login section, and D for the Forgot Password? link.

### A. Enter Account & Password

**Account** (non case-sensitive):

**Admin** (default)

**Password** (case-sensitive):

**123456** (default)

### B. Change UI language

To change UI language, select the desired language from “**Language**” dropdown list.

### C. Remember Account/Password


To have the server remember your Login **Account** and **Password** in the future, check “**Remember Account/Password**”. Click “**Don't Remember**” will clear your input text and reset to default.

To directly enter the main page every time you log in, check “**Remember Account/Password**” then “**Auto Login**” to skip the Login page. **If your computer may be accessed by someone without proper authority, please DO NOT use either of these functions.**

To cancel auto-login, on title bar, click  → “**Logout**” to return to login page, and this function will be disabled.

### D. Retrieve the Forgotten Password

Please refer to [E. Retrieve the Forgotten Password](#) on page 43.



## License and Activation

In GNR, your required number of channels should be licensed and activated before connecting the devices. The **License Key**, provided by ACTi sales representative once your purchase of license is carried out, will be used to activate the license. After the license activation, the channels on NVR server will automatically become available.

Aside from ACTi brand devices, NVR 3.0 system is able to support other vendors' devices. ACTi brand devices and non-ACTi brand devices are licensed by different license types:

- **Standard License:** ACTi brand devices

- **CDP License:** Other vendors' devices

(For supported non-ACTi cameras list, please refer to <http://www.acti.com/3rdpartycamera> )

### Please note:

- The license is cumulative and perpetual.
- The license is not version-specific; upgrading software version will not influence the existing license you have activated on NVR 3.0 server.
- The number of CDP-licensed channels (for non-ACTi brand cameras) and that of standard-licensed channels (for ACTi devices) are counted separately.
- The maximum number of devices (ACTi brand + non-ACTi brands) that can be managed by NVR 3.0 server is **100**.
- After activating CDP license, please follow the instructions in [Add Non-ACTi Cameras](#) on page 65 to manually add those non-ACTi cameras to NVR system.

License activation is the process of unlocking the channels on NVR interface with the received **License Key**. **License Key** is a serial number delivered as a printed card or an E-mail after the purchase is carried out.

During license activation, your **License Key** is matched against the MAC address of the Network Interface Card (NIC) on NVR server computer. Once this license key is used by the computer with given MAC, it cannot be activated with another MAC. This matching record will be stored on the ACTi license data server. If your computer has more than one network cards, NVR server will detect them and provide you a dropdown list to select from.

### Note


Although certain fisheye camera view modes (e.g. **Quad** mode) display multiple regions in a view, they are still counted as one single channel in terms of licensing.

There are two ways to activate the licenses depending on your NVR server network condition:

**Online Activation** and **Offline Activation**.


## Online Activation

If your GNR has available Internet access, choose online activation.



## Offline Activation

Offline activation does not require Internet access GNR. It is used when GVR is located in network not connected to public Internet (e.g. in a military base). You will need to get an activation file from another computer and transfer it to GNR.




## Step-by-step Activation Process


Based on the network conditions of your site, follow [Online Activation SOP](#) or [Offline Activation SOP](#) to activate your license.

### Online Activation SOP

**Step 1:** Membership ID in **ACTi Member Center** is required for activation. Register one for free at <http://member.acti.com/>




**Step 2:** Log in NVR server, go to **Setup** page→**System** tab→**License**→“**Online Registration**”. Select the **MAC Address**, enter your **License Key**, ACTi member **Account** and **Password**, and then click “**Apply**”. NVR server will connect to the license data server via Internet to register the license key, and unlock the channels.




## Offline Activation SOP


**Step 1:** Membership ID in **ACTi Member Center** is required for activation. Register one for free at <http://member.acti.com/>



**Step 2:** Access [http://www.acti.com/support/LicenseMgt/NVR3\\_registration.asp](http://www.acti.com/support/LicenseMgt/NVR3_registration.asp), enter the **License Key** and the **MAC address** of NVR server computer, and click **“Submit”**. An e-mail with activation code file (.lic) will be sent to your registered E-mail account.




**Step 3:** Log in NVR server from local or via web client. Go to **Setup** page→ **System** tab → **License** → **“Offline Registration”**→ click **“Import”** and upload the license file (.lic). Click **“Apply”** to activate this license.



## Verify Your License

Once your license is successfully activated, the license information will be shown on **License** page.



### Important

The license data will be erased once NVR 3.0 server is uninstalled. Be sure to retain your license key information in a safe place because you may need to reinstall the software. After the software is uninstalled, you should contact **ACTi Customer Help Desk** <http://www.acti.com/CHD> to clear the original registration data in our data server, and then you may activate the license again.

### Tip

#### How to find MAC Address

1. Click **Windows Start**, in the run box on **Start** menu, input "**cmd**".
2. Execute the **cmd** program, and input the command "**ipconfig /all**" or "**getmac**".
3. The MAC address will be referred to as the **Physical Address**, made up of 12 characters e.g. **00-1E-65-FE-8E-98**


# Set up the System

This chapter will guide you through everything you need to know in System Setup procedure from first time connection with ACTi NVR 3.0 server to general system configuration.

## Setup Wizard

Once you connect to ACTi NVR 3.0 for the first time, **Setup Wizard** will guide you through the initial setup process. You may click “**Previous**” or “**Next**” button located on the lower right at any time. This will skip the current step so that you may come back to it later. All the settings in the **Setup Wizard** are available in the **Setup** page.

To skip this wizard, click the bubble “**Done**” on top right corner.



## System Settings

You can adjust the E-mail & SMTP settings, FTP settings for event rules now or later. For more details about the settings, please refer to [How to Setup SMTP Settings for Event Rules](#) on page 97 and [How to Setup FTP Settings for Event Rules](#) on page 98.



The screenshot shows the ACTi System Settings interface. At the top, there is a progress bar with five steps: Intro, System Settings, Storage, License, and Done. The 'System Settings' step is currently active. Below the progress bar, the interface is divided into two main sections: 'E-mail & SMTP Settings' and 'FTP Settings'.

**E-mail & SMTP Settings:**

- SMTP:**
  - Server: [Text Field]
  - SMTP Port: **25**
  - Account: [Text Field]
  - Password: [Text Field]
  - Security: ☒ None ☐ SSL ☐ TLS
- Email:**
  - Sender Name: [Text Field]
  - Sender Mail: [Text Field]

Buttons: 'Send Test Mail' (disabled), 'Test FTP Connection' (disabled).

**FTP Settings:**

- Server: [Text Field]
- Port: **21**
- Account: [Text Field]
- Password: [Text Field]
- Mode: **Passive Mode** (dropdown menu)
- Remote Folder: **/**


Buttons: 'Test FTP Connection' (disabled).

Footnote: \* You must configure mail setting to send mail when event occurs. \* Set FTP server to upload snapshot when an event occurs. This is default setting for event handling.

Navigation: 'Previous' and 'Next' buttons at the bottom right.

## Storage

On NVR server, you may choose which disk drives to store the recording files, and decide how much memory space is left for all computer applications to run. You must configure the **Drive** and **Reserve Space** for recording. **Reserve Space** is the space on the drive that will not be used to save recording files, the deletion of earliest recording files will be performed if available space has decreased to reach below **Reserve Space** configuration; you may choose one or multiple disk drives in **Disk Drive List** to save the recordings. If you skip this step, **Drive C** will be the default drive. For more details about the settings, please refer to [Storage Management](#) on page 103.



The screenshot shows the ACTi Storage Settings interface. At the top, there is a progress bar with five steps: Intro, System Settings, Storage, License, and Done. The 'Storage' step is currently active.

**Recording Settings:**


- Recording Folder Name: **Recordings**
- Keep System Log for (1-999 days): **30**

**Disk Drive List:**

Select	Drive	Free Space (GB)	Total Space (GB)	Reserve Space (GB)
<input checked="" type="checkbox"/>	C:	76.3	100	20
<input type="checkbox"/>	D:	136.4	198.1	20

Navigation: 'Previous' and 'Next' buttons at the bottom right.


## Licensing



This is the license management section. On lower right part of the screen shows number of channels allowed under your current license. Each NVR server has a license for **16** channels which is already activated. You can click “**Next**” to next setting if you do not want to add new license for now. For more details about the settings, please refer to [License and Activation](#) on page 51.

## The End of Setup Wizard


Click “**Done**” to complete **Setup Wizard**, the previous configuration steps you have gone through are available in **Setup** page.



## NVR Main Screen

You will enter the live view screen after **Setup Wizard**. On the right are link buttons to three NVR major functions: (1) **Live view**, (2) **Playback** and (3) **Setup**. You can click the orange button to enter the function page.

### Live View




In this module, you can see live view from cameras, perform PTZ operations with mouse or Joystick, view system log, receive alerts on the event panel, setup view layouts, perform manual recording or take a snapshot.

### Playback



You may search and view playback of multiple channels synchronously. Snapshots or video segments can be taken from playback files. Recorded files can also be exported to AVI format here.

### Setup




This module includes user setup, device setup, event setup, schedule setup and system-wide settings.

## Add Devices


Cameras or video encoders are the fundamental building blocks of surveillance systems. To manage cameras from NVR3, you have to add camera devices into NVR3 system first. In this section, we will guide you through how to add or delete devices on NVR system.

To start adding new devices, please follow steps as below:


1. On **Setup** page→**Home** screen, click **"Device"**.



2. On **Devices** page, the **Device List** is currently empty, and you need to add some video sources to it. Now click **"Add Device"**.




- There are two ways to add devices into the system, **Search Devices** and **Add Device Manually**. Use **Search Devices** to auto search your cameras located in the same subnet with your NVR server. If your cameras / video encoders are located outside of local subnet or over WAN, please do it by **Add Device Manually**. You need to know the IP address of the device to add it manually.



## Search Devices within Local Area Network


- Select "**Search Devices**". Once the search is completed, a list of available devices will be shown. You click on the title header to sort by that column. Click the header again to sort in the reverse order.



- Refresh
  - IP filter ( for multiple networks)
  - Available / Licensed channel
  - Search result
  - Column title
  - Available / Total Licensed Channels
- Select the row of the camera you wish to add to the system and repeat this step until you have checked all the devices you need.
- Click "**Apply**" to add selected devices into NVR system.

## Add Devices on WAN or Other Local Area Networks


1. After selecting “**Add Device Manually**”, camera setting page will appear as below. The most important settings are (1) Protocol, (2) Camera IP, (3) HTTP Port, and (4) User Name & Password. Please fill in these fields required for NVR to communicate with the device.



### Important Notice

If any of the said fields is incorrect, NVR will not be able to connect the device. When you have any device connection problem, please check these settings. However, at this point, you may skip filling in the Device Name, Brand, Model, and Stream Mode configuration.

2. Click “**Get Device Settings**” to have NVR contact the device and get the live view. Once connected to the device, NVR will get all the device properties such like **Brand**, **Model**, **Device Serial Number**, **Firmware Version**. If the device supports dual stream, **Stream Mode** selection field will reveal, you may select different streaming mode and configure relative options. You may click “**Cancel**” button on the top to abort setting this device or “**Apply**” to save it.



- To directly access the device configurator webpage, simply click "**Web Configurator**" on top right to open it. Certain detailed settings are only through the web configurator and not through NVR.

## Basic Settings Attributes

Field Name	Description
<b>Device Name</b>	Enter the name of the camera, which will be shown in the <b>Device</b> list on the left in Live View. This name should be descriptive so that you know where the camera is located.
<b>Protocol</b>	Select a streaming protocol to connect the camera with.
<b>IP address</b>	Enter the camera's IP address or host name.
<b>Brand</b>	Select the manufacturer of device.
<b>Model</b>	Select the device model of the IP cameras / video servers. In most cases, this is automatically filled in after you perform <b>Get Device Setting</b> for ACTi cameras.
<b>Stream Mode</b> <sup>*1</sup>	Select one of the streaming modes this device supports.
<b>Channel No.</b> <sup>*2</sup>	The channel ID you set for a stream of a multi-streaming device.
<b>HTTP Port</b>	Enter the HTTP port for IP cameras/ video servers. Most cameras use the default port number - 80.
<b>User Name</b>	Enter the user name to access the camera.
<b>Password</b>	Enter the password to access the camera.
<b>Default Live View Stream</b> <sup>*3</sup>	Choose the streaming id for Live View.
<b>Recording Stream</b> <sup>*3</sup>	Choose the streaming id for Recording.
<b>Connection Timeout(0~99 secs)</b>	Enter length of time allowed for a device to respond to NVR. If the response is so late as to exceed this time, NVR will consider this device "disconnected". We recommend you to set different values for different types of connection. The default setting is 5 seconds. For devices located over the WAN, you may wish to increase this value to allow for occasional Internet lags.


<sup>\*1</sup> Available when NVR is connected to a multi-streaming device.

<sup>\*2</sup> Available when NVR is connected to a device that is concurrently in multi-streaming mode (Dual Stream mode excluded).






<sup>\*3</sup> Available when NVR is connected to a multi-streaming device in Dual Stream mode.

## Device Status

To validate if you have successfully added a device to NVR system, simply check the **Device List** on the left of **Setup** → **Devices** tab to see if the device name appears in the tree. Point your mouse cursor over the device icon will bring up an information box containing the device's **IP Address**, **HTTP Port**, **Protocol** and device type.



## Status Icon Description


Icon	Status Description
	NVR server cannot retrieve video streaming. This may be that a video server is not connected with cameras, or that the streaming is blocked by the firewall between the device and NVR server. Please (1) ensure the device side is well connected and can output video normally,(2) check the firewall and port forwarding settings.
	This device's settings have been modified but not saved yet. If you leave these modifications unsaved, they will not take effect by next time the server starts. Please always remember to save upon every change.
	NVR cannot build up connection with this device. Please check the device connection settings (including IP Address, Port number, Account Name and Password); or increase the " <b>Connection Timeout</b> " to allow more time for the device to respond.
	This device is currently connected, video is being transmitted and no recording is proceeding.
	This device is currently connected, and video is being recorded either manually or according to the schedule.

## Add Non-ACTi Cameras


In this section, we will guide you through how to add devices to NVR3 system.

After the required CDP license is activated, please:


1. Use the utility provided by camera manufacturer to confirm the camera properties:  
(1) **Protocol**, (2) **IP Address**, (3) **HTTP Port**, and (4) **User Name & Password**.
2. Log in to NVR, go to **Setup** page→ **"Device"** tab, click **"Add Device"**, and select **"Add Device Manually"**.



3. After selecting **"Add Device Manually"**, camera setting page will appear as below. Please fill in the below **seven** marked fields that are required to communicate with the device - **Protocol**, **IP Address**, **Brand**, **Model**, **HTTP Port**, **User Name** and **Password**, and then click **"Apply"**.



4. By applying the settings, NVR will get the video stream, and this camera is successfully added to NVR system. You may click **Video**, **PTZ**, or **Preset Tour** (available for cameras with zoom/pan/tilt capability) tabs to configure other properties.




5. To directly access the device configurator webpage, simply click "**Web Configurator**" on top left to open it. Certain advanced settings are only available through the web configurator and not through NVR.

## Manage Multiple Devices


After adding several devices to the system, you may get an overview of all devices on **Setup** page → **Device** tab; this is where you may use certain fast and convenient approaches to manage a number of devices. In this section, we will guide you through how to quickly add or delete multiple devices.

### Modify Basic Connection Settings

Go to **Setup** page → **Devices** tab, and click **All Devices** in **Device List** to get the devices overview in right column. Each basic connection setting field including Name, IP Address, HTTP Port, User Name and Password, is editable. Simply click in the field to modify it directly.



Select	ID	Name	IP Address	HTTP Port	User Name	Password	Brand	Model	Channel
<input type="checkbox"/>	1	Front Door 1	172.16.26.81	80	admin	*****	ACTi	TCM1511	1
<input type="checkbox"/>	2	Front door 2	172.16.26.87	80	admin	*****	ACTi	TCM5311	1
<input type="checkbox"/>	3	Office	172.16.26.80	80	Admin	*****	ACTi	KCM3911	1
<input type="checkbox"/>	4	2nd Floor Hallway	172.16.26.8	80	admin	*****	ACTi	ACD2300	1
<input type="checkbox"/>	5	3rd Floor Hallway	172.16.26.8	80	Admin	*****	ACTi	ACD2300	2


Every time you modify a property without saving it, an icon  will appear next to the device in **Device List**. You may click “**Reset**” to retrieve the settings you saved last time once you want to abort current modification. After changing any field, please remember to click “**Apply**” before you leave this page.




### Tip

NVR will sync with devices upon connecting to them. To make sure the settings on NVR side are prior to and always overwrite those on device sides, please check “**Auto save NVR settings into devices upon connection**”.


### Delete Devices

You may delete a single, multiple or all devices on **All Devices List**. The logs and video files of the devices will be kept until deleted by server storage deletion rule. Select the device(s) you wish to delete, click “**Delete**” button and confirm the deletion. If you want to delete all the existing devices, simply click  on upper right to select them all at once. To validate if you have successfully deleted a device on NVR system, simply check the **Device List** on the left of **Setup** page → **Devices** tab to see if the device name is removed from the tree.




## Copy Settings Across Devices

When setting a large number of devices, many settings will resemble other ones, and it is sometimes tiresome to repeat every setting again and again. You can use the **Copy** function to save the hassle of needless repetition.



1. On **All Device List**, select the source device whose settings are to be copied from. You can select only one device to be the source.
2. Click **"Copy"** to bring up the copy setting window.
3. On the window, below the source device name are the settings you may choose to copy, including **Basic settings**, **PTZ Settings** and **Video Settings**.
4. Click **"Apply"**, the settings will be written to target devices.
5. To add a new device with the same settings, choose **"Add New Device"** in



6. There are a few differences of the copied items between two target device types:
- Each field on this page has already been filled with the source device's properties. You may continue to modify the **Device Name**, **IP Address**, get the live view by clicking **"Get Device Settings"**, and then click **"Apply"** to add this device to **Device List**.

## Settings Copied to Target Devices

Target Type Settings	New Device	Existing Device
Basic	All	All except <b>Device Name</b> , <b>IP Address</b> , <b>HTTP Port</b> , <b>RTSP Port</b> , <b>User Name</b> and <b>Password</b>
Video		All except <b>Motion Settings</b> , <b>Video Adjustment</b>
PTZ		All except <b>PTZ Preset Points</b> and <b>Commands</b>

### Note


1. You can only choose either “**Add New Device**” or existing devices as target.
2. To add new devices by copying from an existing one, the user's group should be permitted with this right. To check the access rights, please go to **Setup** page→**Users** page→**User Groups**, select the user group, and enable the “**Device Setup**” -“**Add New Device**” under **NVR Permissions**.

## Add Video Streams from a Multi-channel Device

There are devices that output more than one video streams to NVR. For example, a video encoder converts a number of analog video signals into the same amount of IP video streams; certain high megapixel cameras such as ACTi KCM-5111, supports outputting multiple VGA streams cropped from a single high-resolution video source. These multiple streams coming from a single device are managed as different cameras by NVR server.

To add these streams as multiple channels for you to view and record, please:

1. Select the desired stream mode in “**Stream Mode**” field on **Setup** page →**Devices** tab→**Basic** tab.
2. The “**Channel No.**” column will display for you to input the stream ID (the same with your setting in device's web configurator).
3. After configuration, click “**Apply**”.
4. Go to **All Devices** page, duplicate this device to a new channel, repeat this step until all the channels you need are added.
5. Individually modify the **Channel No** value of the channels.



### Tip


#### Saving CPU loading with Your Dual Streaming devices


The device supporting dual-streaming function can output two video streams of different value. You may make the live view stream smaller in size with lesser frame rate to save decoding CPU power and bandwidth. Meanwhile the recording stream can be larger and have more FPS so that you have clear images when you need to retrieve evidence. For settings in both streams of devices with dual stream functionality, please refer to section Configure Video Format on page 70

## Configure Device Settings

After adding a device to NVR, you may continue to configure its video, motion detection, PTZ or preset tour settings on **Setup** page→**Devices** tab. In this section, we will guide you through how to configure these settings and their corresponding functions.

### Configure Video Format

Go to **Setup** page →**Device** tab, select a device from **Device List**, and then go to **Video** tab to configure the video format of the stream output from this device. If the device is currently in Dual Stream mode, you may switch the stream in live view window by click on the switch below  and configure individual settings for Media 1 and Media 2.



### Video Settings Attributes

Field Name	Description
<b>TV Standard</b>	Default is <b>NTSC</b>
<b>Stream Mode</b> *1	Select one of the streaming modes this device supports
<b>Mounting Type</b> *2	Select the mounting position
<b>Installation Angle</b> *3	Input the angle for a device mounted on the wall
<b>Video encoder</b>	Select one of the codec this device supports
<b>Resolution</b>	Select one of the resolutions this device supports
<b>Video Quality</b> *4	Select your desired video quality of the image
<b>Frame Rate(fps)</b>	Select the (Frames Per Second) this device supports.
<b>Maximum Bitrate</b>	This puts a hard cap on the maximum bit rate allowed in any given second of streaming. Assigning a limited bit rate may cause a few dropped frames when the stream data overflows the allowed bit rate.

<b>Bitrate</b> <sup>*5</sup>	This is the target bitrate that the camera will attempt to provide when you have selected “ <b>Unlimited</b> ” for <b>Maximum Bitrate</b> . The actual value will fluctuate slightly based on scene changes.
------------------------------	--

<sup>\*1</sup> Available when NVR is connected to a multi-streaming device.

<sup>\*2</sup> Available when NVR is connected to a hemispheric device.

<sup>\*3</sup> Available for hemispheric devices with “**Wall**” **Mount Type**.

<sup>\*4</sup> Available when “Video Encoder” is selected as MJPEG.


<sup>\*5</sup> Available when “Maximum Bitrate” is selected as “Unlimited”.

## Save Storage by Setting Event Recording Frame Rate

Video surveillance system is aimed to preserve as much evidence as possible, and you may want to have a view be recorded 24/7 to capture every important moment; however, the general recording methods provided by most network recording systems- event and schedule recording, will either consume too much storage or have risk in missing important scenes. The “**Set Frame Rate for Event Recording Mode**” function record everything at economical storage usage by automatically adjusting video frame rate during event recording period.


### Schedule Recording

Continuous recording promises no loss of video evidence; **however, large data storage is required** because this video is always recorded at the high frame rate you set for device.




### Event Recording

This mode is storage-efficient because recording would stop during the non-event moments; while **certain vital video evidences may be missed** if the triggering device fails to take effect.




## Event Recording with Frame Rate Adjustment

Keeps recording all the way without losing any single moment; lower frame rate can be set for non-event recording, which consumes only a little storage.



## How to Make Use of Event Recording with Frame Rate Adjustment

To make use of **Event recording with Frame Rate Adjustment** function, you may configure the **Frame Rate** settings on **Setup** page → **Device** tab → **Video** tab. The **Frame Rate (fps)** you set will always be applied to live view and schedule recording. Once **Set Frame Rate for Event Recording Mode** is checked, you may configure advanced settings for event recording. If the device is in **Dual** stream mode, you will only need to configure these settings of the **Recording Stream**.



### Scenario A:

Suppose you want all the videos recorded at very high frame rate. With sufficient storage, you may not need this function. Set the video **Frame Rate** that will apply to all the recordings. In this way, NVR 3.0 will not record non-event during event recording period.

Frame Rate Setting		Event Recording
<input type="checkbox"/> Set Frame Rate for Event Recording Mode		
Frame Rate (fps)	30	Non-Event: 0 FPS
		Event: 30 FPS

## Scenario B:

Suppose you wish the system to record 24/7, the non-event recording to be kept at very low frame rate. Please set the event and schedule recordings at different frame rate, you will need to enable “**Set Frame Rate for Event Recording Mode**”, and set the “**Non-event Frame Rate**” and “**Active Event Frame Rate**”.

Frame Rate Setting		Event Recording
<input checked="" type="checkbox"/> Set Frame Rate for Event Recording Mode		
Frame Rate (fps)	30	Non-event: 1 FPS
Non-event Frame Rate (fps)	1	
Active Event Frame Rate (fps)	30	Event: 30 FPS

## Fine-tune the Image: Brightness/Contrast/Saturation/Hue

Not only details but also brightness, contrast, saturation and hue are essential factors to make images closer to real scene. For devices that support these property configurations, you may directly modify them and save to the device in NVR 3.0 system.


To start, on **Device Video** tab, click “**Video Adjustment**”. Each field is only available when the device opens this property for modification. If the device is in Dual Mode, the video you get in this window will always be **Stream 1**.

1. At first, synchronize with the device to get the current settings by clicking “**Get Video Adjustment**”.
2. After retrieving the settings from device, the fields available for modification (depends on models) will be enabled. Select the desired value for the field.
3. Click “**Apply**”.

### Video Adjustment

Get Video Adjustment

4 IP-Camera 2013-03-20 19:01:10



#### Video Adjustment Settings

Brightness: 50

Contrast: 20

Saturation: 50

Hue: 45

Reset Apply Close


## Video Adjustment Attributes

Field Name	Description
<b>Brightness(1-100)</b>	Defines how much portion of light and of dark appear in the image. As the value increases, the image appears brighter, and vice versa.
<b>Contrast(1-100)</b>	Defines the range level between light values and dark values. As the value increases, the separation between light and dark becomes more obvious.
<b>Saturation(1-100)</b>	Defines the level of the actual color intensity. As it increases, colors appear more pure; as it decreases, colors appear more gray-out.
<b>Hue(1-100)</b>	It is the term used to refer to the pure spectrum colors. Adjust this value to find the color closest to the real scene.

## Configure Motion Settings

To make use of the motion and PIR detection functions supported by your devices, you need to configure the detection regions and settings. Once a motion is detected, NVR 3.0 can trigger events and recording, bring up instant pop-up windows and show the detected area on live view.


Before configuring motion detection settings, first make sure you can connect properly to the IP camera / video server and get device settings. On **Device** tab→**Video** tab, and click "**Motion Detection**" to start.



1. Click "**Get Motion Settings**" to retrieve the live view. For Dual Mode, the video you get in this window will always be **Stream 1**
2. Click "**Motion Setup**" to enable the property fields.
3. There are three motion regions for you to set. To enable one, check it in the **MD** box, a red frame will appear in the view. You may start setting the detection area by adjusting this red frame on the view. Simply use your mouse to move and resize the frame.

## To move the entire frame

Place the mouse cursor over the **title bar**, and drag to move.



## To disable this detection region

Place the mouse cursor over the **upper right corner**, and click the "X" to close this frame.

## To adjust the region dimension

Place the mouse cursor over the **downright corner**, and drag to resize.

- When the setting is finished, click "**Apply**" to save, then "**Close**" to exit this page. To check or modify the regions you set, please go through clicking "**Get Motion Settings**", **Motion Setup**" and then "**Motion Enable**" buttons, the saved regions are already selected on the list, select one to proceed.

## Adjustment Attributes

Field Name	Description
<b>Sensitivity(1-100)</b>	Determines how sensitive the camera reacts to the movement. The higher the sensitivity level is, the smaller motion will trigger the alarm, but may give false alarms. Default is 70.
<b>Timer(0-300 secs)</b>	The interval before the next motion detection can be triggered again. Default is 1 second.
<b>Threshold (%)</b>	The threshold level of this motion detection region. The lower threshold level is, smaller portion of the region would be considered as motions, which is more easily to be triggered, but may give more false alarms.

## Note


- If you have changed the motion detection settings via the web configurator, please remember to come back to NVR and press "**Get Device Settings**", then "**Apply**" to save to NVR. This is to ensure that the settings in NVR are always in sync with the device.
- If a motion region is set, once a movement is detected in this region, in live view:
  - (1) the red region frame will blink, and
  - (2) a new alert entry will be generated in the event list.
- PIR detection is available only for models with this function.

## Configure PTZ Device

PTZ devices can do panning, tilting and zooming automatically or through manipulation. The PTZ-related applications are broadly supported by NVR 3.0. For example, you may control the movements of a PTZ camera with user interface panel controls or a joystick; the device can be programmed to execute a continuous tour or triggered by events to go to a preset position. Once an ACTi PTZ device is added to the system, NVR 3.0 will use the default settings of the device model and enable PTZ functions, so that you may immediately start PTZ operations.

If you have previously changed the communication parameters of PTZ devices, please make sure these parameters on NVR side and device side match.

Below is a list of functions supported ACTi solutions and the required settings. When you configure PTZ Protocol properties for ACTi Pan/Tilt/Zoom devices, please make sure the required settings are correct



ACTi Pan/Tilt/Zoom devices	Vendor	Protocol	Baud rate	Parity	Address ID
IP Zoom Camera/ IP PTZ Camera	V	V			V
IP Speed Dome / IP Camera mounted on Scanner/ Analog PTZ camera attached to Video Server	V	V	V	V	V

To start matching up the parameters, please follow the below procedures:

1. If the device is a speed dome camera or an analog camera attached to video server, configure the parameters on physical device according to the product's installation instructions.
2. On the device's (camera or video server)web configurator, configure the parameters to match the setting on physical device, and test the PTZ operations to make sure the device is properly set to be connected
3. In NVR 3.0 server, go to **Setup** page → **Devices** tab, select the device from **Device List**, and click **PTZ** tab. In **PTZ Protocol** section, fill in the communication parameters.

## Adjustment Attributes

Field Name	Description																																								
Vendor	Vendor is the provider of Protocol. The selectable vendors would vary depending on different device models. Available vendor types are: <b>ACTI, DYNACOLOR, PELCO and SONY.</b>																																								
Protocol	Protocol is a set of rules to define the communication format between the device and controller. Different protocols are provided for selection according to the Vendor you choose. Available protocols following their vendors are: <b>ACTI: [ACTI] / DYNACOLOR: [DYNACOLOR] / PELCO: [PELCOD] [PELCOP] SONY: [VISCA]</b>																																								
Parity	Parity is the data validation mechanism for analog devices that use serial port interface to send or receive data. When choosing parity mode other than "none", the data packets will be validated for possible data losses so that failed command could be re-sent if necessary. Please refer to the parity setting of the analog device and choose exactly the same parity setting also in NVR. <b>When setting up ACTi Zoom, PTZ or Speed Dome cameras using “ACTi” protocol, you may ignore the parity setting.</b> Available parity modes are: <table><tr><th>Parity mode name in NVR</th><th>Serial data, represented by given amount of bits</th><th>Parity mode (none, odd, even)</th><th>Number of stop bits</th></tr><tr><td>8N1</td><td>8</td><td>N</td><td>1</td></tr><tr><td>8O1</td><td>8</td><td>O</td><td>1</td></tr><tr><td>8E1</td><td>8</td><td>E</td><td>1</td></tr><tr><td>8N2</td><td>8</td><td>N</td><td>2</td></tr><tr><td>8O2</td><td>8</td><td>O</td><td>2</td></tr><tr><td>8E2</td><td>8</td><td>E</td><td>2</td></tr><tr><td>7N2</td><td>7</td><td>N</td><td>2</td></tr><tr><td>7O2</td><td>7</td><td>O</td><td>2</td></tr><tr><td>7E2</td><td>7</td><td>E</td><td>2</td></tr></table>	Parity mode name in NVR	Serial data, represented by given amount of bits	Parity mode (none, odd, even)	Number of stop bits	8N1	8	N	1	8O1	8	O	1	8E1	8	E	1	8N2	8	N	2	8O2	8	O	2	8E2	8	E	2	7N2	7	N	2	7O2	7	O	2	7E2	7	E	2
Parity mode name in NVR	Serial data, represented by given amount of bits	Parity mode (none, odd, even)	Number of stop bits																																						
8N1	8	N	1																																						
8O1	8	O	1																																						
8E1	8	E	1																																						
8N2	8	N	2																																						
8O2	8	O	2																																						
8E2	8	E	2																																						
7N2	7	N	2																																						
7O2	7	O	2																																						
7E2	7	E	2																																						
Baud rate	Baud rate defines the data speed through serial port interface – the rate value represents the number of symbols that can be transmitted within 1 second. Please refer to the baud rate setting of the analog device and choose exactly the same baud rate setting also in NVR. <b>When setting up ACTi Zoom, PTZ or Speed Dome cameras using “ACTi” protocol, you may ignore the baud rate setting.</b> Available baud rates: 2400, 4800, 9600, 19200, 38400, 57600, 115200																																								

<b>Address ID</b>	Address ID represents the identity of the device, only analog devices or speed dome cameras require this configuration. Please refer to the Address ID of the device and choose exactly the same baud rate setting also in NVR 3.0. Available value is from 1~99. By default, ACTi devices will use "1" as Address ID, it is suggested not to change it.
-------------------	--

## How to Do Live PTZ Operation


To configure PTZ settings, you need to view the live streaming while manipulating the PTZ controls simultaneously in this window.



There are two kinds of PTZ navigation:

### Optical PTZ Navigation


1. Get the live view from **Live Preview** window:

Make sure the "**Enable PTZ**" is checked, a red crosshair will appear on the **Live Preview** window, if the device is in Dual Stream mode, this window will always shows the stream set for live view. You may click on  to switch between the streams.

2. Use the mouse to do the following PTZ operations:


To execute optical **Panning** and **Tilting**, click anywhere on the live window to allow the camera to move in that direction. The length of the direction indicator is proportional to the Pan and Tilt speed. The farther you place the cursor from the center, the faster the Pan/Tilt movement.

To execute optical **Zoom in** or **Zoom out**, scroll the mouse wheel forward to zoom in; scroll the mouse wheel backward to zoom out.



### 3. Use panel controls to operate PTZ movements:

Click a button on the panel to start, the red crosshair will appear in the view.



### Note

1. The zoom buttons are only applicable for those devices supporting optical zooming.
2. The focus buttons are only applicable for devices with controllable zoom lens, e.g. KCM5211. Please remember to turn off the autofocus mode on device firmware before using these buttons.
3. The device should be equipped with DC-Iris or P-iris and has been switched to manual iris mode before you use the buttons for widening or narrowing aperture.

### Digital PTZ Navigation

Digital PTZ allows you to zoom into part of the video and enlarge it to display on screen. This PTZ function is applied to every camera model in NVR 3.0 system.

1. Get the live view from **Live Preview** window:  
Make sure the **"Enable PTZ"** is unchecked.
2. Click and drag a highlight rectangle over any channel, and the area highlighted will be displayed in the full live video window. In this mode, a picture-in-picture view will show in the lower right of live view window. A red rectangle will mark the currently enlarged view area within the full size video. You may click and drag the red rectangle to see another area.
3. To go back to the original full video view, just right-click on the minimized Picture in Picture view.



Draw Zoom area




Cancel Zoom area

## Set PTZ Preset Points

With PTZ devices, you may define a view by where to look (through panning and tilting) and how close (through zooming) to zoom. Once these views have been saved in NVR server as preset points, the device can always point to this view upon the event triggering or user's command.

1. Go to **Setup** page → **Devices** tab, select the device from **Device List**, and click **PTZ** tab.
2. By PTZ operation, control the device to point at your desired view, and adjust the zoom level (if available). In **PTZ Preset Point** section, click a preset point name field to start editing the name, then click "+" to set this point. After finishing setting your desired preset points, click **Apply**. You may review the points you set by clicking "→" to go to the point, or "X" to delete it. You may modify an existing point with following procedure: 1. Select it 2. Define a new view 3. Click the "+" to set it 4. Click **Apply** to save it.



3. After the preset points are set, they are available on **Live View** page → **PTZ control** panel.

## Set PTZ Command

If your speed dome or PTZ device has a special function not supported in the standard protocol, you may input it in **PTZ Command** list and execute it. Ex: Activate the wiper to clean the window of the PTZ.

1. To add a PTZ action command, go to **Setup** page → **Devices** tab, select the device from **Device List**, on **PTZ** tab, check the **"Enable PTZ"**.

ID	Name	PTZ Command
1	Wash	FF01000418001D
2	Wipe	A00000000A080800FFAF...

2. In **"PTZ Command"** area, click in a command entry; input the name, command and then click **"Apply"** to save it. You may also click **"→"** to execute it or **"X"** to clear it.

## Set PTZ Preset Tour


Preset Tour is a preconfigured PTZ sequence that directs the camera to cycle through multiple preset points, including where to look and how long to look at each location. With this preset tour, your PTZ device can perform an automatic patrol to scan through your cared areas.

For example, a Preset Tour should include two or more preset points. Once a tour is initiated, the device will automatically point to the preset points based on the sequence and stay at that view according to the duration you set.



Before setting up Preset Tours, please make sure you have configured PTZ settings and set PTZ Preset Points. To start setting the Preset Tour:

1. Go to **Setup** page → **Devices** tab, select the device from **Device List**, and click **Preset Tour** tab.
2. In the **"Tour List"**, as there is currently no existing tour, click **"Add New Tour"** to add one. The default tour name is **"Preset Tour 1"**.
3. In the **"Preset Points of a Tour"** area, click **"Add Preset Point"** to add the number of points for this tour. The number of points may outnumber the actual preset points you set, for the same preset point might be gone through more than one time in a single tour. For each point, click in the **"Preset Point"** field to bring up the dropdown list, and select one preset point and define the dwell time which represents the time the device would stay in a certain view. Finally, click **"Apply"** to save the tour.



4. After a tour is saved, it is available on **Live View** page→**PTZ control** panel.

## Note

The preset points and tour set in NVR 3.0 are independent from those you set on device. If you have already defined certain preset points or tour on device, they will not be brought to NVR system. On the other hand, the settings on NVR 3.0 will not write to the devices.

## Configure Fisheye Cameras

With hemispherical lenses, fisheye cameras generate images at up to 360-degree width, which can cover all four corners of a room or both sides of a long aisle. As the original image captured by wide-angle lens is much distorted, to suit most monitoring purposes, the **Dewarping** process is required to alter the uneven lines and shapes before the images are displayed. Nowadays, the fisheye cameras come in two types in terms of the image-correction capability:

- Fisheye Cameras **with** in-camera dewarping function

The dewarping takes place in camera before the video is output to NVR server. Since the image correction counts on the camera itself, NVR server will not bear much extra loading, which benefits the system requiring many of these fisheye cameras (e.g. ACTi KCM-3911, KCM-7911)

- Fisheye Cameras **without** dewarping function

These fisheye cameras output only original global images, relying on software algorithm processing provided by NVR sever to correct the images. They are suitable for a system with limited bandwidth, for NVR server processes and responds to User's ePTZ manipulation or demands for changing view modes immediately, without waiting for camera side to deliver a new frame (e.g. ACTi E96).

NVR 3.0 makes it possible to integrate both kinds of fisheye cameras into your system with the following advantages:

- Full support for all types of dewarped video stream output from fisheye cameras with in-camera dewarping capability.
- NVR's software algorithm can perfectly corrects the original fisheye images, generating **6 specific fisheye view modes** from User's usual perspective.
- Based on user's instant request for changing view mode or PTZ viewpoint, NVR server will process the original fisheye image and respond to the client individually. In this way, what a client sees on Live View will not affect playback, recording, as well as another concurrent connection.
- The virtualized **ePTZ** manipulation also allows User to dynamically explore any region of interest within the hemispheric view like operating a genuine PTZ device.


To make use of NVR's dewarping features for your fisheye cameras, please


## 1. Adjust Video Quality Settings






After the fisheye camera is successfully added, go to **Setup** page → **Devices** tab, select the device and then **Video** tab, make sure you set the **Stream Mode** as "**FISHEYE**" for a hemispheric camera ( KCM-3911, KCM-7911 ). This is to make sure this hemispheric camera is outputting fisheye original video stream as a mini fisheye dome camera does.

## 2. Adjust Fisheye Display Settings

Select your **Mounting Type**, and then **Default Fisheye Mode**. For a Fisheye Mode containing panorama view, you may want to configure the **Default Rotate X** (width of view) and **Default Rotate Y** (height of view) configurations.



Fisheye Mode	Description	PTZ Navigation
<b>Original View</b>	The very raw fisheye view 	Digital PTZ

<b>Dewarping</b>	<p>One large user-defined cropped area</p> 	ePTZ
<b>Panorama</b>	<p>360-degree panorama view for ceiling mount 180-degree panorama view for wall mount</p> 	Digital PTZ
<b>Double Panorama</b>	<p>Two 180-degree panorama views</p> 	Digital PTZ
<b>Panorama /Focus</b>	<p>One panorama view Two small user-defined cropped regions</p> 	ePTZ
<b>Quad</b>	<p>Four small user-defined cropped regions</p> 	ePTZ

- After the configuration is done, remember to click **"Apply"** to save the settings.

## Schedule Recordings


Unlike the traditional analog surveillance system, the IP surveillance system provides a target-oriented recording schedule for devices; the view of each device can be recorded based on your required time segments and event types. For example, you may have a camera installed on the office ceiling do continuous recording during work hours, and record only upon the triggers (incidents that detected by system) at night. In this way, the system does not waste disk space storing meaningless parts, and you save lots of effort browsing playback for specific events.

For the device's recording schedule, NVR 3.0 supports Schedule recording and Event recording modes, which are set up on a week-based timetable; the event-handling schedule can also be configured on it. This section describes how to setup the recording schedule for the IP cameras / video servers.

### Configure the Recording File Properties

Before setting the recording schedule, you may define (1) where the recordings are stored, (2) how long an event recording is and (3) how long a recording file will be kept in the system.

1. To set the saved recordings folder, go to **Setup** page→**Storage** tab, make sure you have assigned the disk drives to store recorded files. For related recording settings, please refer to [Storage Management](#) on page 103.
2. To define how long an event recording is and the recording's lifecycle, go to **Setup** page→**Schedule** tab, select the device from **Device List**, a week schedule will appear on the right. Configure the recording file related settings. The settings below will make an event recording as long as 5+30 seconds, which will be kept on server for 30 days.



### Attributes Explanation

Field Name	Description
<b>Pre-event Recording Buffer (sec):</b>	NVR keeps a short cache of video received from devices. If an event is triggered, NVR will automatically store the pre-event buffer along with the recording of the event itself. Available choices are <b>0, 3, 5</b> seconds.
<b>Post-event Recording Buffer (sec):</b>	This will determine how long after the event is triggered should be included in the event recording file. Available choices are <b>10, 30, 60, 120, 180, and 300</b> seconds.

## Keep Recording Files for (1-999 days):

NVR 3.0 will keep recording file of specific device for the number of days you set here. The default value is **30**, if you want to modify it, please check the box to start configuring it. Available value is among **1~999** days.

### Tip

#### How to make proper storage arrangement

In NVR 3.0 system, there are two file-deleting mechanisms you can use based on different needs. If both rules are set, the threshold reached earlier will execute the deletion first.

1. **"Keep Recording Files for (1-999 days)"** – Set this rule if you have more concern in how long the recordings are kept, especially when you don't want the old recordings to stay longer in the system than a certain period.
2. **"Reserve space"** in the **Disk Drive List** on **Setup** page → **Storage** tab - If the disk space is more critical in your system, please give an approximate value here, the system will always reserve this amount of space to store the newer recordings.

Given that you set the **Reserve space** as **30G**, while **Keeping Recording Files** setting is **5 days**, certain recording file will be deleted when it has been kept on disk for 5 days, despite that there is still plenty of available disk space.

Before setting up the rules, you can make use of a handy storage calculator provided by ACTi to find out the estimated storage your system requires on ACTi corporate website:

[http://www.acti.com/project\\_planner](http://www.acti.com/project_planner)


## Set the Schedule


Here you can configure camera's recording schedule on 7 days / 24 hours basis. The schedule is split into segments of 20-minute-length. By default, once a device is added to the system, its schedule is automatically set to full time schedule recording and event handling. You should configure it according to your system plan.

Go to **Setup-Schedule** tab, on **Schedule Setting** panel:

1. Select the recording mode from "**Recording Mode Bar**"

 **Schedule Recording** :Continuous recording that channel

 **Event Recording** : Records a period of the detected motion event. Please make sure you have configured the motion settings on **Setup** page → **Device** tab beforehand.

 **Event Handling** :Event handling is activated.


(Please refer to [How to Edit an Event Rule](#) on page 93 for **Event Rules** settings)

 **Clear** : Clear the setting

 **Schedule Recording** +  **Event Handling** : Continuous recording + event handling


 **Event Recording** +  **Event Handling** : Event recording + event handling

2. Click and drag over the "**Time Track**" to set time period.




## Use Time Setting Quick Buttons to Set the Time in One Click


Select the recording mode, then click one of these buttons to apply the mostly-used time settings.

Click  to apply schedule **for all day**.



Click  to apply schedule **from 06:00 to 18:00 every day**, with the settings for the rest of the time track being cleared.



Click  to apply schedule **from 18:00 to 06:00 every day**, with the settings for the rest of the time track being cleared.




Click  to clear all schedule setting in this device.




## Lock Specific Days

Clicking the day of the week will lock/unlock that day from schedule setting. You can shield schedule on a certain day from being changed by changes in other weekdays. You may easily set just the weekdays or the same time over the same week this way. To do this:

1. Click the days to shield them.




2. As you drag any settings over the time track, it will not apply to those shielded days.




## Copy an Existing Schedule to Others

With plenty of devices in your system, it happens that you want to apply the same schedule to multiple devices. After creating a schedule for one device, you can copy it to other cameras.

1. Go to **Setup** page → **Schedule** tab, on **Device List**, select the device you want to copy schedule settings from.
2. Click the **Copy** button.
3. On popup window, select target devices you want to copy schedule settings to.
4. Click the **Apply** button.




To check the result, go to **Schedule** tab, click **All Devices** on **Device List**.








## View the Entire Recording Schedule


On **Setup** page → **Schedule** tab, click **All Devices** on **Device List**, an overview of all device schedules will be listed on the right.



The below list explains the status of different bar patterns:


Icon	Recording Function Description
	Schedule recording. During this period, device view will be recorded continuously.
	Event handling. During this schedule, the event rules you set are active.
	Schedule recording and Event handling are both active during this period.
	Event recording. During this period, only detected events (e.g. Motion/PIR) will be recorded .
	Event recording and Event handling are both active during this period

## How to Know if the Recording is Proceeding?

As the recording is taking place, you can observe the status on the **All Device** list. There will be an icon  appearing in front of the device. In **Playback**, you can drag the playback bar to current time position to check the latest recording.

## Event Management

When something happens on camera site, such as someone walks by, the door opens or closes, a fire breaks out or the sun goes down – these are all **Events**. Events which occur in the environment or were preprogrammed in the camera may be used as **Triggers**. Triggers cause the device to react with **Responses**. The link between trigger and response is governed by **Event Rules**. Event rules become active or inactive based upon a weekly **Schedule**. Each event rule detects one specific trigger and may initiate multiple responses. An example rule would be for NVR to send e-mail to alert the supervisor (**Response 1**) and trigger alarm (**Response 2**) when motion detection from camera is triggered (**Trigger**) during the event handling active period (**Schedule**).




### How Does NVR Handle Events

In NVR 3.0, each device can be involved in several event rules. As different device models possess various capabilities, the supported event trigger types would vary. For example, a PIR built-in camera can execute a PIR-triggered event rule, while this option is not provided to other models without this feature; similarly, the supported response types would vary by device models, like Goto-preset behavior can only be executed by PTZ devices. The below chart shows NVR server supported **Trigger** types and **Response** types. Once a device is added to NVR server, the server would create empty rules with compatible trigger types for you to configure.


Trigger Type	Response Type
Video Motion Detection	Focus Channel in Live View
Digital Input	Make Device Pan/Tilt/Zoom
PIR Detection	Audio Alert
Video Loss	Trigger DO Device
Video Recovery	Execute URL Commands
Network Loss	Upload Snapshots to FTP
Network Recovery	Email Notifications/ Snapshots

## How to Edit an Event Rule




1. Go to **Setup** page → **Event** tab. All the editable event rules are listed in the device ID order.
2. Select a device from the **Device List** on the left. Based on the trigger types this device supports, the corresponding events rules are listed accordingly on the right. In this example, this selected camera model supports three motion detection regions, and hence three MD trigger event rules are available.



3. Highlight the rule you wish to edit. Click in the **“Event Name”** column to edit the event name, and then double-click the **“Response”** column to edit the response action.



You can enable multiple responses by first checking the box(es) to enable the items:

Action Items	Function Description
 <p>The screenshot shows two panels for 'Focus Channel' settings. The top panel has 'Pop-up' and 'Hot-spot' checked. 'Pop-up' has Target '08 Stroeroo...' and Duration '5'. 'Hot-spot' has Target '04 Counter' and Duration '10'. Below these is a 'Switch View' section with 'Group' set to 'New Group', 'View' set to 'All Channels', and Duration '5'. The bottom panel has 'Pop-up' and 'Switch View' checked. 'Pop-up' has Target '1 11F_Entrance' and Duration '5'. 'Switch View' has 'Group' set to '11F', 'View' set to 'Office Fisheye', and Duration '5'.</p>	<p>This kind of action will focus your attention on the channel when triggered.</p> <p><b>Pop-up:</b> Brings up event pop-up instant playback window of selected channel upon trigger. You may also define the display duration of video on the window.</p> <p><b>Hot-spot:</b> Displays video in Hot-Spot window (red flashing frame) upon event. You may also define display duration of video on the Hot-spot window.</p> <p><b>Switch View:</b> The current Live View will be switched to another one for a while. To enable this option, you will need to customize and save Views on Live View screen first. You may also define duration of the temporary View. Only <b>Public Views</b> are selectable for Switch View event rule.</p> <p><b>Hot-spot</b> and <b>Switch View</b> responses cannot be executed at the same time.</p>
 <p>The screenshot shows 'PTZ' settings with 'Goto Preset' checked. It has Target '08 Stroeroo...', Preset '01 Left row', Duration '10', and 'Then go to Preset' set to '03 Right row'.</p>	<p>Upon being triggered, specific camera can make PTZ movements like going to specific PTZ presets as responses. You may set both the start / end point and the duration. <b>This action is only available when you have set the preset points.</b></p>
 <p>The screenshot shows two panels for 'Audio Alert' settings. The top panel has 'Beep' checked with Duration '5' and Times '1'. The bottom panel has 'Audio File' checked with Path 'C:\tokyo hot .mp3' and Times '1'. There is a 'Browse' button next to the path.</p>	<p>Makes NVR play beep sound or an audio file for a number of repetitions.</p> <p>On <b>NVR3 Workstation</b> client computer, you can upload a WAV file or an MP3 file as the alert sound, and set how many times this audio file is played when the event occurs. (This NVR server has to be already on <b>Server Site list</b>, refer to <a href="#">G. Server Name/Server Sites List</a> on page 44 for how to save a server site). Please note that <b>Beep</b> and <b>Audio file</b> responses cannot be executed at the same time.</p>

Digital Output

☒

DO 1

Target

04 Counter

Value

On

Duration(secs)

5

☒

DO 2

Target

07 Office Ai...

Value

Off

Duration(secs)

5

Set the DO to become ON or OFF upon trigger, only the devices supporting DO functions can be the target devices.

Execute Command

☒

Enable

Command

C:\Program Files\Skype\Phone\Skype.exe

Enable NVR to execute a certain command upon this event. You can use it to integrate NVR's event handling with other programs. Enter the path of the command to be executed upon event.

Upload Snapshot to FTP

☒

Upload Snapshot to FTP

Server

actiftp.hosting4les

Port

21

Account

Admin

Password

••••

Mode

Passive Mode

Remote Folder

/NVR3

Enable NVR to upload snapshots to a FTP site upon this event. The default FTP settings can be set in advance in **Setup** page→**System** tab→**Settings** → **FTP Settings**. You may set another FTP destination here for this single event. Please also make sure the FTP server setting is correct and the folder access rights are properly configured.

Mail

Send Mail

☒

Send Mail

To

jeremy.lin@acti.com;jeremy

Subject

Storeroom motion detected

Content

Please see attached photo

☒

Attach Snapshot

User List

☐ Clear All

☒ Select All

Select	User Account	Email
<input type="checkbox"/>	Admin	wen.cheng@acti.com
<input checked="" type="checkbox"/>	Jeff	jeff.buckley@acti.com
<input checked="" type="checkbox"/>	Jeremy Lin	jeremy.lin@acti.com
<input type="checkbox"/>	Jimmy Hendrix	jimmy.hendrix@acti.com
<input type="checkbox"/>	Neil Young	neil.young@acti.com

Cancel

Apply

Enable NVR to send e-mail notification via SMTP server. The default SMTP and sender's e-mail settings can be set in advance in

**Setup** page →**System** tab→**Settings** → **E-mail& SMTP Settings**.

1. Type one or more recipients' e-mail addresses in "To" column (if more than one, please separate them by ";" symbol) or click the  icon to select recipients from existing NVR User list. The E-mail address should be set in advance (in **Setup** page→**Users** tab→**Users**) for an NVR User so that it can be selected in this list.
2. Edit the e-mail subject and content.
3. Choose to attach a snapshot or not. If event trigger type is **Video Recovery** or **Network Recovery**, this function is disabled.

4. After configuring the actions, click "**Apply**" to save this response.
5. Go to **Setup** page→**Schedule** tab and set the **Event Handling** schedule for this device. Event responses will only be triggered when the trigger time falls within either the **Event Handling** recording or the **Event Handling with Schedule** recording period.

- To check if this rule is successfully set, please make sure you have properly configured the involved (1) triggering side settings like **Motion Detection Regions** or **DI**, (2) response side settings like **PTZ Preset Points**, **SMTP Server** and **E-mail Recipients**, **FTP Server** or **DO**. Then set the **Event Handling** schedule for current time and trigger this rule.

## Note


- Sending e-mail, Uploading snapshot to FTP and Executing command** actions are executed on the server computer, not from the client computer.
- There must be video stream from device when the event happens for event responses to work.
- Internet Explorer browser may become unstable due to frequent pop-up instant playback windows, please avoid setting the **"Pop-up"** action as the event rule for a device which is too frequently triggered. The next server version v3.1 will improve the program efficiency with Internet Explorer browser.

## Manage the Event Rules


**Event List** panel gives an overview on event rules set on the NVR server. Go to **Setup** page → **Event** tab → select **All Devices** on the left. As the entire available rules of all devices are listed here, you may want to sort out some of them from the long list.

### View the Event Rules

To sort by **Device** name, **Trigger** type or **Event Name**, click the titles to list the entries in ascending or descending alphabetic order.




To filter out the configured events, select from the **"All Triggers"** dropdown list; or filter by the event type by selecting from the **"All Events"** dropdown list.




## Delete the Event Rules

On **Event List**, select the rules you wish to delete, and then click “**Delete**” to clear this rule.



## How to Setup SMTP Settings for Event Rules

NVR 3.0 supports e-mail notification for **Event Handling** sent through an SMTP server. You can specify the e-mail and server settings here.



1. Go to **Setup** page→**System** tab→**Settings** → **E-mail& SMTP Settings**.
2. Fill in **each** of the following fields.

Field Name	Description
<b>Server</b>	Input the sender's SMTP server address. Only alphabets, numbers, and the symbols (.), ( _), (-) are valid.
<b>SMTP Port</b>	Set the SMTP port, allowed value is from 1~65535, default is <b>25</b> .
<b>Account</b>	Input the name of the SMTP server account. Only alphabets, numbers, and the symbols (@), (.), ( _), (-) are valid.
<b>Password</b>	Input the password of the SMTP server account. Only alphabets and numbers are valid.
<b>Security</b>	Certain webmail providers provide the SSL/TLS-encrypted SMTP connections to secure your data when sending/receiving e-mails. Please check if the SMTP connection settings you use (especially the <b>SMTP Port</b> ) now require enabling either SSL or TLS.
<b>Sender Name</b>	Input the name or title of the sender. You may input a name different from the account name.
<b>Sender Mail</b>	Input the sender's e-mail address, which should be the same account you set for SMTP server.


- As all necessary information is filled in, click **"Send Test Mail"** to try sending an e-mail according to your settings, and then log in to your SMTP server to check incoming e-mails. If the test mail is sent successfully, NVR server is ready to send out e-mails.
- As the settings are confirmed, click **"Apply"** to save.

## How to Setup FTP Settings for Event Rules

NVR 3.0 supports uploading snapshots to FTP servers for Event Handling.

You can specify the e-mail and server settings here.

- Go to **Setup** page→**System** tab→**Settings** → **FTP Settings**.




2. Fill in **each** of the following fields.


Field Name	Description
<b>Server</b>	Input the FTP server address. Only alphabets, numbers, and the symbols (.), ( _), (-) are valid
<b>Port</b>	Set the FTP port, allowed value is from 1~65535, default is <b>21</b> .
<b>Account</b>	Input the name of the FTP server account. Only alphabets, numbers, and the symbols (@), (.), ( _), (-) are valid.
<b>Password</b>	Input the password of the FTP server account. Only alphabets and numbers are valid.
<b>Mode</b>	The FTP works in two very different manners, <b>Active</b> mode and <b>Passive</b> mode. If your FTP server is behind the firewall or a NAT router, you have to use " <b>Passive</b> " mode.
<b>Remote Folder</b>	Input the upload path of the file. Default will be "/" to represent the root folder.

- As all necessary information is filled in, click "**Test FTP Connection**" to test the connection. If NVR server pops up a "Testing **FTP connection was successful**" message, NVR server is ready to upload to this FTP.
- As the settings are confirmed, click "**Apply**" to save. The FTP settings here will be default for every event rule.

## System Log


The activities performed by logged-in Users are recorded on server as **System Log**. With the access permission, a user may view, search and export this record for analysis or investigation. This section will provide the instructions on how to read and search data in the system log.

“**System Log**”  is one of the resident buttons on top of NVR server user interface, click it to enter search window.




## Define Search Time

You need to first define the time of the logs you would like to search for. On **Search Time** bar, define the date and time. Default is your current client time.






## Choose Log Type

You may filter the logs by **Type**, **User Account**, and **Device** by selecting from dropdown list, then click **“Search”**. By default, all types are selected.



## Read the Log

The search result will show 1000 records before and after your query time. You may click the pagination buttons  to navigate earlier or later records. If there is an icon  on the right top corner of an entry, click it to view the full description content.



A log entry contains several kinds of information including **Date Time**, **Type**, **User Account**, **Device** and **Description**. Check **Type** and **Description** fields to know what the user has done or what happened to the whole system. In **Type** field shows what major functions user engaged in, in **Description** field narrates how the change was done (in green font color, uppercase) and the result (in white font color).

Date Time ▲	Type ▲	User Name ▲	Device ▲	SET	Description
2012/05/09 15:15:28	Setup System	Admin		UIStyle MainForm Alignment = left	

The following user behaviors are recorded in NVR server:

Type	Description
User Operation	Login, Logout, Manual Record, Trigger DO
Setup System	Recording Configure, Storage System Setting
Setup Users	User – Add, Delete, Modify User Groups – Add, Delete, Modify
Setup Schedule	Modify
Setup Event	Modify
System Status	Server start up, disk is full, disk is not found, disk is available
Request Log	Time, source ip address

## Note

If the pagination button appears to be disabled, that means no more records found on NVR server. By default, the server will keep the logs for 30 days. If you wish to adjust the period, please go to **Setup** page → **Storage** tab, in **Recording Settings** section, key in the value in this field: Keep System Log for (1-999 days) **30**

## Export the Log

Click “**Export**” button to export the log as .csv file. You can specify the time duration, engaged User Account and devices of the logs, and click “**Apply**”.

**System Log**

Search Time 2012/09/19 13 : 23

Type User Operation;Setup D... User Account Select All Device Select All Search Export

**Export System Log**

Time Duration 2012/09/18 13 : 27 ~ 2012/09/19 13 : 27

Type User Operation;Setup D...

User Account Select All

Device Select All


Cancel Apply

## Storage Management

This section describes how to manage storage space in NVR. Please note that this section only deals with the overall storage rules, and not storage of individual channels.

Please note that as NVR continuously writes and deletes file from the disk drive, using a removable disk may risk losing recording when device is removed while being accessed.

Go to **Setup** page→**Storage** tab.



### Change Recordings Folder Name

In “**Recording Settings**” section, you may change the name of video recordings folder. The video files are saved in a folder named “**Recordings**” under hard drive root directory. You may change the name here.

### Set System Log Lifecycle

System Log is the record of User activities and events that took place on the server. In “**Recording Settings**” section, you may set how long this record is kept on the server. Default is **30** days.

### Set the Hard Drives and File Deletion Rule

1. On **Disk Drive List** displays the detected hard drives in your server computer. You may select the storage location of the recording files and set the deletion threshold. By default, NVR server will select **C** drive as storage location.

Select	Drive ^	Free Space (GB) ^	Total Space (GB) ^	Reserve Space (GB)
<input checked="" type="checkbox"/>	C:	60.4	100	30
<input checked="" type="checkbox"/>	D:	136.6	198.1	20

2. After selecting the disk drive, please set the deletion rule. There are two ways to delete recordings, when both are active, NVR server will start to delete old files when any of the criteria below is met:
  - (1) Keep the recordings for a number of days, and delete files older than this period by 1 GB at a time. Please go to **Setup** page → **Schedule** tab to set it.
  - (2) Keep recordings until the disk is almost full, and then delete the earliest recording files by 1 GB at a time. NVR server will delete old files when available space is lower than **Reserve Space** you set in **Disk Drive List**.

When setting the deletion rule, please input a number in **Reserve Space** which should be smaller than your current **Free Space**.

Item	Description
<b>Free Space (GB)</b>	Currently available space of the chosen disk drive.
<b>Total Space (GB)</b>	The total volume of the chosen disk drive.
<b>Reserve Space (GB)</b>	This is the amount of space to be reserved for the whole computer system. Once the free space is used up as to reach the limit of reserve space, the system will delete the earliest recordings. <u>The “Reserve Space” should always be smaller than “Free Space”</u>

3. When finish settings, click “**Apply**”.


## Manage User Groups/ Users

The User Groups/Users page allows you to (1) manage the access permissions of different user groups, (2) add users to or delete them from user groups, (3) and assign users to specific user group. This chapter will take you through these settings.

### Access Permissions

In NVR 3.0, the access permissions are managed by **User Groups**. **User Groups** defines what functions and devices are allowed for each user. Different **User Groups** will have different access rights in terms of permitted operations with each device like **Live View**, **Playback**, and NVR server management operations like **Device Setup**, **Schedule Setup**, **Event Setup** and **System Setup**. For example, an Administrator User is allowed for all the operations in NVR, while a standard User may only be permitted to do **Live View** and **Playback** with limited devices.

The chart below displays different employees as NVR Users and their access rights in this system:



### Overview

Go to **Setup** page → **Users** tab. There are two sections to manage User Groups and Users individually.

**User Groups:** To setup user groups and its permissions for device and functionalities.

**Users:** To manage user accounts and configure user information.

ACTi NVR 3.0 has integrated **Microsoft Active Directory®** service to provide network administrators a more convenient choice for user management. Active Directory is a directory service built in Microsoft Server products to manage user identities and privileges within the

domain network. As ACTi NVR 3.0 runs on a server computer logged on to the same domain with Active Directory server, you can import a user account or a group from those concurrently existing in Active Directory into NVR server. In this way, the user identification is processed by Active Directory centrally; there is no need for NVR administrator to maintain user accounts as long as they are under management of Active Directory service.

## User Groups

You can specify access permissions to each device for a whole user group. This user grouping can save you significant amount of works if you have multiple users performing similar tasks and acting as similar roles.

There are already two default User groups


- **Administrator:** With full permissions in the NVR.
- **User:** With the permissions to watch all camera live view and playback.

You can create a new user group on NVR server or import an existing group from the Active Directory database within your domain.


1. Select  **User Groups**, click **Add** and then choose the group type:


- Add a new user group:

Insert **ID**, group **Name** and group **Description**, your input in the **Name** field will be the name of this User group. Click **Apply** to finish.



- Import a domain group as a User group:  
Choose an existing user group from your domain, and click **Apply** to finish.




The domain users within that group will all be added to NVR server at the same time. To view the whole users within this group, please select  **Users** and enable the “**Show users in domain groups.**” The account information of these domain users, unlike those user accounts you add one by one to NVR server, are not editable on Users page.


<input checked="" type="checkbox"/> Show users in domain groups.						
	User Type	User Account	User Name	Password	Email	Group Name
<input type="checkbox"/>	Customized User	admin	Admin	*****		Administrator
<input type="checkbox"/>	Domain User	Deckard Cain	Deckard Cain		Deckard.Cai@acti.com	\$Security Office
<input type="checkbox"/>	Domain User	John Bourne	John Bourne		John.Bourne@acti.com	\$Security Office
<input type="checkbox"/>	Domain User	Steve Lin	Steve Lin		Steve.Lin@acti.com	\$Security Office
<input type="checkbox"/>	Domain User	Joyce Holiday	Joyce Holiday		Joyce.Holiday@acti.com	General Service

Domain users added as a whole group


- Assign **NVR Permissions** for created group. This will define what functions this User group is allowed to access. By default, a new User group will initially be allowed to access only **Live View** page and **Playback** page, but without any permission to any device setting, so you will have to assign the device permissions later.



- Assign **Device Permissions** for created group. This will define which devices this User group is allowed to access. If this User group is allowed to access all newly-added devices, check “**New Device Default**” and edit the permissions, these default settings will be applied to any device added in the future.




You may copy the **Device Permissions Settings** to other devices. Click “**Copy**” under **Device Permissions** tab to bring up the target device menu, check the target devices, and click “**Apply**”.




Click “**Apply**” on the top to save the settings.

## Add Users

To create a user account with on NVR server.

1. Select  **Users**, and click **Add** button.
2. Select **User Type** as **Customized User** or **Domain User**.
  - **Customized User**: an account created and managed on NVR server only. You will input an account name, its password and e-mail address for this User.
  - **Domain User**: an account that already exists in Active Directory database within the domain. Since this is an existing account in your domain, you will have to select this account from **Account** dropdown list.
3. Insert user account, name, password, and the account mail (For **Customized User**).
4. Assign this created user account to a specific user group.
5. After you click “**Apply**”, this new user will be added to the list on the top.



## Note

NVR server provides a procedure to help Users who have forgotten the password retrieving the original information, which relies solely on the “e-mail address” authentication. It is strongly recommended that you input an e-mail address that this User has access to when you establish the User account. To update the e-mail address of an account, go to **Setup** page → **Users** tab → edit “**E-mail**” of an selected User account; the Users can also update the e-mail addresses themselves after logging in to NVR on **Live View** page → **Update Profile**

## Note

### Account /Password Rules


1. **Account** and **Password** fields allow alphabets, numbers, and symbols except the following: `/ \ [ ] : ; | = , + * ? < > " ' ``
2. In **Account** field, for alphabets, the input will be recognized as lowercase letters. Space is only allowed between characters; the space in the beginning or at the end will be deleted as it is saved.
3. The **Password** field is case-sensitive, and the space is allowed.

## Note

**Admin** is the default user account and belongs to “**Administrator**” user group. Hence, the user **Admin** and the group **Administrator** cannot be deleted; it possesses full permissions to all devices and NVR settings.

## Domain Users Management

As NVR server computer is logged on to a domain Active Directory, it can import a user account from Active Directory.



This type of User account is “**Domain User**”. Upon being added to NVR server, the User properties stored on Active Directory database including (1) account name (2) e-mail address will be imported to NVR server.

Home Users Devices Storage Schedule Event Language System						
Add Delete Reset Apply						
Clear All Select All						
Select	User Type	User Account	User Name	Password	Email	Group Name
<input type="checkbox"/>	Customized User	admin	Admin	*****		Administrator
<input type="checkbox"/>	Domain User	wen.cheng	Wen.Cheng		Wen.Cheng@ACTi.com	User

Whenever a domain User client tries to log in to NVR server, NVR server will first verify if this account exists in NVR server database, and then have Active Directory verify the user account and password.

As Active Directory owns the privilege to create, edit and delete domain users, **the Domain User's account and password are not editable through NVR user interface but via Active Directory Administrative Tool.**


## Customize Views


After all devices are configured, you may start customizing the views for different users and purposes. This chapter will teach you how to add video source, arrange the channels and manage live view layouts.

In NVR 3.0 system, a **View** refers to the layout where the live images of **Cameras** or **Maps** are placed in proper positions to suit the monitoring purpose. This is very similar to a camera group, which often consists of cameras in the same physical location. For example, a View named **11F Emap & Camera** may contain the 11F floor plan and the cameras actually placed on 11F.


On NVR Live View, a saved View not only remembers (1) layout style, (2) which channel to display which camera, (3) but the fisheye view mode (for fisheye cameras only).


### Live View interface overview




1. **Layout Selection Bar:** Provides 24 options for layout styles.
2. **View Toolbar:** Provides functions keys for editing.
3. **Channels:** Each channel window may display a camera view or a map. In edit mode, you can adjust the channel size at will.
4. **View List:** All the saved Views are shown here. On **Live View**, you can go to  → **View Manager** to group and manage these views (refer to [Manage the Views](#) on page 118).
5. **Device List:** In edit mode, drag camera from here to your desired channel.

## Step 1: Create a New View

On **View Tool Bar**, click the **Create View** button , input the **View Name**, add a **New Group** for this View and decide whether this group is to be **Public** or **Private**, and then click “**Apply**”.


- The views under **Private View Group**  are only available to the User who created them.
- The views under **Public View Group**  are open to every User.




## Step 2: Enter Edit Mode


On **View Tool Bar**, click the **Edit View** button , this view will turn into edit mode. In edit mode, you may add a video source to a channel, and adjust the channel size.


## Step 3: Select a Layout


On **Layout Selection Bar**, click the **Expand** button  to find all provided layout styles. Select a layout that is perfect for your required channel number and ideal arrangement.




## Step 4: Add Video Source



In edit mode, move the mouse over the channel and click . You may also directly pull a camera from the **Device** panel to your desired channel.





● **Remove the camera view:** right-click on the channel and select “Remove”.




## Step 5: Add a Map

By adding a map, you put a picture on the channel, where you may place camera icons to make it an “e-Map”.



In edit mode, move the mouse over the channel and click  to upload a map. Please input the **Map Name**, select the image location (file format must be JPG) and click “Apply”.




## ●Map brightness:





To change the map brightness, right-click on the map, select “Map Mask” and the brightness percentage level.



## ●Map size:



By default, the map will be displayed in its original size. Use the buttons on upper right to adjust the map size.

-  Enlarge to fill channel height
-  Original image size
-  Zoom in
-  Zoom out


## ●Edit map title:


The map title will be shown on channel title bar. In edit mode, right-click on a map channel and select “Edit Map Information”

## ●Remove the whole map:

Right-click on the map and select “Remove”.


## ●Manage maps:

All the uploaded images are managed under **Map Image Manager**. On **Live View** screen, you may go to  → **Map Image Manager** to view, upload or delete the maps.



## Step 6: Add Devices to the Map

Pull a device from **Device List** to the map.



●To remove this device from map:


Click 

●To move this device:

Left-click on the device icon and drag.

●To turn the pointed direction:

Mouse over the viewing angle area, left-click on the clockwise arrow to turn the direction.





●To adjust precise pointed direction:  
Right-click on the device icon, select  
“**Pointed Direction**”.

●To adjust device's viewing angle:  
Right-click on the device icon, select  
“**Vision Angle**”.


## Step 7: Adjust the Channel Size & Layout


●Adjust the channel size:

Click  on right lower corner of the channel window, drag and then release.



●Switch channel windows:


Click on a channel title until the cross arrow  appears, hold it to drag this device or map to your desired channel.





## Step 8: Save the View

Click  on **View Tool Bar** to save it.

## Step 9: Set Default View

To set a View as default, select it in the **View List** panel and then click  on **View Tool Bar**.  
By next time you log in, you will directly enter this View.

## Step 10: Set Default Hotspot Channel (Optional)

By system default, the global hotspot channel will always be the top left one. You can set any other channel on your live view screen to be the default hotspot channel. Right-click on the channel and select **“Default Hotspot”**  , then click  on **View Tool Bar** to save it.

## Step 11: Set Fisheye Camera Mode

Define a view for a fisheye camera channel by selecting its mode and using ePTZ control. Please note that the maximum number of fisheye channels on the same View is **16**.

1. On this channel, right-click to bring up channel menu, click **“Fisheye Mode”** and select one mode.




2. After the fisheye mode is selected, click the entire channel or a region of interest.

- Use **PTZ Panel** controls to operate PTZ movements:



### ePTZ Controls on PTZ Panel

8 directional buttons



Zoom in / Zoom out

- Click the mouse anywhere on the view to pan/tilt, scroll the mouse wheel to zoom in/out.



- To reset the ePTZ navigation area back to default viewing angle, right-click to bring up channel menu, and then click **"Reset"**.

3. click  on **View Tool Bar** to save the configuration.



## Note

Once a channel is changed to any of the following fisheye modes: **Dewarping, Panorama, Double Panorama, Panorama/Focus** or **Quad**, the resolution of this live stream will become 1920x1080, while NVR still records the live stream at the resolution you set on **Setup** page.

## Manage the Views


Each View belongs to a specific **View Group**. With the group management, NVR 3.0 Server makes it easy to deal with Views you created for multiple Users.


After you created and saved the Views on **Live View** screen, click  → **View Manager**.



- 1 Click on the right arrow icon in front of a group folder to reveal its **Views**.
- 2 By selecting a **View**, you may directly modify its name in **Name** field.
- 3 You may change a group's **Group Type**. Upon the change, for example, by changing a group from **"Private"** to **"Public"**, all the views belonging to it will be open to every User.
- 4 Click this icon to add a new group.  **New Group** 
- 5 Click this icon to delete a selected group.
- 6 Click this icon to copy a selected group to another group.
- 7 Click this icon to move a selected group to another group.



## Set View Link


By creating a link button on a map view, you can directly be linked to another specific view by clicking the button. On the picture below shows how to create a link button  to 7F View on 11F View.



1. Select a View, on which you will place a link button to another view.
2. Click  on **View Toolbar** to enter edit mode.
3. From **View List**, drag the target View to current View, a link button will appear.
4. Click  on **View Toolbar** to save it.

## Set View Patrol

You may have the saved Views patrol in turns. In this way, the views in different area in your site may cycle through themselves for you automatically.



On **View Toolbar**, click  then select **Create Patrol**.


1. Input the **Patrol Name**
2. Select the **Patrol Type** to be either available for all Users or to the creator's account only.
3. Define the **Global Dwell Time** between the views. If you want to set different dwell time length for individual Views, do not check this option, and configure them separately in the table below.
4. Choose the **Views** to display in patrol. If you select the **All Device** group, you will also need to select "**All Device Layout Style**" for it.
5. Click "**Apply**" to save the settings.

### Create Patrol





Patrol Name

Patrol Type Private

☒ Global Dwell Time(5-120 secs)


All Devices Layout Style 


☐ Clear All
☒ Select All

	Name	Dwell Time(5-120 secs)
<input checked="" type="checkbox"/>	 All Devices	5
<input checked="" type="checkbox"/>	 11F	
<input checked="" type="checkbox"/>	 11F Entrance	5
<input checked="" type="checkbox"/>	 7F	5

Cancel

Apply

6. The saved patrols will be shown on the patrol list after you click  on **View Tool Bar**, you may delete and edit a saved patrol or select it to start patrolling.




## Tips to Enhance Live View Performance


Live view for multiple channels requires sufficient computing power to run the performance. In certain extreme cases, like when viewing several megapixel H.264 video streams at the same time, client computer will be overloaded and hence affect browser's performance. This is a common limitation imposed upon all Windows based video management programs and web browser.

To enhance live view performance, below are several tips you may try:

1. Use dual stream mode for those devices supporting this function. Enable the dual stream mode and use the stream of lower resolution/frame rate/bit rate for live view, and megapixel resolution stream for recording.
2. Use another browser client to share these high-resolution channels. Given that there are 32 megapixel channels to be monitored, you may have Layout 1 to display channel 1~16, set Layout 2 to display channel 17~32, then open one browser client to show Layout 1 and the second browser on an extended monitor to show Layout 2.
3. Have NVR automatically lower the frame rate of live streams when system loading is high. Go to **Setup** page → **System** tab → **Settings** → **Display Performance Setting** and enable this function. Basically, this setting will lower frame rate when the CPU usage is above certain percentage. You may also enable “**Lower the frame rate when current layout is above\_**”, in this way, when the layout is displaying over certain number of channels, the frame rate of all live streams will be declined. This setting will be applied to the live display of all connected clients except for the client on GNR..



4. A **Workstation** client computer can have its own specific display configuration without being affected by NVR universal setting. Log in as **NVR3 Workstation** client, go to **Setup** page → **System** tab → **Workstation** and configure the **Display Performance Setting**.



## Note


By default, on GNR, when the number of layout on Live View or Playback screen exceeds **four**, all the channels will automatically turn in to Decode-I mode. For smooth video quality, please remember to go to **Setup** page → **System** tab → **Workstation** and configure the **Display Performance Setting**.

## Customize System Language


NVR server supports multiple languages for user interface display. There are already **10** translated language files in the server system. Each language is open to customization based on your own needs. This section will describe how to choose or customize language strings for your site.

### System Languages List

You may decide which languages to be selectable on Login screen. The chosen languages will appear on the “**Language**” dropdown list.



Go to **Setup** page → **Language** tab, click “**Active Languages**”. On popup window, check the languages you need, and click “**Apply**”. By default, all languages are selected, as the default system language, **English** and **Traditional Chinese** are not removable from this list.




## Edit User Interface Wordings


Each language file contains four editable string tables. Each table displays the default wordings in English and the translation in target language.


To view each table:


1. Select the language from “**Select Language**” dropdown list, then select a table from the “**Language List**” list on the left column.



2. Your target language will be displayed on the right column, while the default system language “**English**” appears on the left for reference. Click in any field on right column to customize your desired wordings, and click “**Apply**” to overwrite the current wordings.



The new string will be applied by next time you log in. If you log in as an **NVR3 Workstation client**, please press  button on **Login** page to synchronize with the latest modified language file, then log in to the system.



**NVR Workstation**

Server Name:


Server IP:

Server Port:

Account:

Password:

Initial Page:

Language:  

☒ Remember login info


☐ Auto Login

[Don't Remember](#)

[Forgot Password?](#)

## Export / Import Language String File


You may also click “**Export**” to export the language file as .xml format to edit in **Notepad**, or “**Import**” to import a language file to use in the system.



In general, it is suggested that you always save a modified language table with a different file name in a location other than default system language folder *C:\Program Files\ACTi Corporation\WVR3\Language*, then import it to use. In this way, you can avoid overwriting the original language file.

## Display Configurations

You can change the user interface style by arranging the main screen and **Panel/Device List** on the right or left. Go to **Setup** page→**System** tab→**Settings**, in **User Interface Style** section, select the setting style then click “**Apply**”. The change will be applied upon your next login.




## Video & Snapshot Export Configurations

The snapshots taken by Users on **Live View** and all exported video files are saved to a default file location, and you may configure the destination on NVR server. Go to **Setup** page→**System** tab→**Settings**, in **Export Video Settings** section, click **"Browse"** to choose the Export file path.

You may also define what information is printed on each snapshot by checking the items: **Date and time**, **Device ID** and **Device Name**.

These configurations will take place after you click **"Apply"**.



## Joystick

On NVR 3.0, other than user interface PTZ panel and mouse operation, you may also control the PTZ movements by physical controllers. NVR 3.0 supports two types of controllers, which both feature in a joystick and twelve buttons for users to assign specific actions.




Model: **IP Desktop**  
Manufacturer: CH Products



Model: **Extreme™ 3D Pro**  
Manufacturer: Logitech

### Joystick Configurations

1. Log out from NVR server.
2. Connect the controller device to your computer. To make sure the device is installed properly, open **Windows Start menu** and enter **Devices and Printers** to check the status.
3. Log in to NVR server, go to **Setup** page → **System** tab, enter “**Controller**” section and select your product.
4. You may assign specific commands from dropdown list to buttons 1~12 of the controller. When setting is done, click “**Apply**”. The modification you did on one controller model will be applied to the other joystick model as well.





5. To validate its function, go to **Live View** page and focus on a PTZ device channel to operate the supported PTZ operations.


## NVR System Upgrade

When a newer version of the NVR system software for GNR is released on ACTi website, you can download and install it directly to upgrade your NVR system. To download the latest version, please go to [http://www.acti.com/product/detail/Standalone\\_NVR/GNR-3000](http://www.acti.com/product/detail/Standalone_NVR/GNR-3000) to see if there is any newly released version of the NVR system. The upgrade process is as easy as 1-2-3 by following the installation wizard's instructions. The server would start its service right after installation completes, without the need to restart the server computer.


### Install the Software

1. Execute the install shield application .
2. Follow the onscreen instructions of **Install Shield Wizard**, and accept the license agreement and proceed.







When selecting **Setup Type**, the default “**Complete**” will have the program installed on default **C drive**, you may select “**Custom**” to choose another program location.



3. The **IP Port Checker** will pop up to confirm the NVR port number with you. The installation program will use **80** as default. You may enter another available port number in "**Listen Port**" field and click "**Apply**".



You may just click "**Apply**" if you are not sure whether this port has been taken or not. If the port is being used by another service, you will be asked to input another available port number.



4. As the server port is confirmed, the installation process is done, click **“Finish”**.



5. After the installation completes, connect to [http://localhost:port\\_number](http://localhost:port_number) with Internet Explorer browser, you will see NVR Login page.

#### Note


If IIS Web Server has been installed on the computer and you are asked to restart the computer during installation process, please



1. Choose ☒ Yes, I want to restart my computer now. to restart right away.
2. After the computer reboots, this install shield will continue to complete the installation.


## Workstation Installation and Upgrade

**NVR3 Workstation** program is wrapped together with the NVR system software in a zip file. When you upgrade the NVR system to a new version, please also upgrade NVR3 Workstation to the same version as the NVR system.

### Install or Upgrade the Software

1. Execute the install shield application  .
2. Follow the onscreen instructions of **Install Shield Wizard**, accept the license agreement and proceed.





3. Double-click the shortcut  on desktop to execute the application.

## Back Up System Data

Making regular system backups is always recommended in case of unexpected disasters or accidents that may damage the NVR server. Other than this, you may need to perform an on-demand backing up to migrate the whole NVR server data to another one. There are several types of data on the NVR server essential to your surveillance system, and please consider your purpose and follow the below instructions to create their backups:

### Regular Backup (system settings only)


The NVR server can create a backup file of the whole system settings within one click. The backed up settings include the following properties you set for system: (1) **Users** (2) **Device** (3) **Storage** (4) **Schedule** (5) **Event** (6) **System** → **Settings** / **User Interface Style** / **Joystick**, and (7) the saved **Views** in **Live View** page.

### Complete Backup (system settings + video files)

Besides system settings, some organizations may want to back up the video recording occasionally in case that the recording hard drives may fail. The recording files ( \*.raw) can only be played on the playback utility **Archive Player**. You may download it from <http://www.acti.com/utility>

### Step 1: Back up System Settings

1. Go to **Setup** page → **System** tab → **Backup / Restore**.
2. In **Backup** section, click “**Browse**” to select the destination for the backup file, and the file will be saved as *Backup\_YYYYMMDD.xml* file. Then click “**Backup**” to export the file.




## Important Notice

The license data is not included in the system backup file. You have to preserve the license key information provided in email or printed card after the purchase takes place.


## Step 2: Back up Recording Files Folder (Optional)

Back up the whole **Recordings** folder(s) with the recorded video files on storage hard drive(s). If you selected multiple storage hard drives via **Setup** page → **Storage** tab → “**Disk Drive List**”, the server may have generated one **Recordings** folder under each selected drive. If you have renamed the folders or change the locations, please make sure you find the correct path.



## Step 3: Back up Recording Files Index Folder (Optional)

This step is necessary for the NVR 3.0 system migration between two servers. The recording files index folder contains important video index data that the NVR server needs to process recorded video clips. Enter the server program folder **ACTi Corporation\NVR3\DataSource**, and back up the **DataBase** folder (where stores the recording files index data).




## Step 4: System Log (Optional)

The system log records the operations users perform during logging in to the NVR server. You may export the system log of latest three days as \*.csv file as backup. Please refer to the section Export the Log on page 102 for instructions.


## Restore System Data

Before starting restoring the system, make sure you already have the backup file (.xml). Please follow the below steps to restore the configuration.

1. Go to **Setup** page → **System** tab → **Backup / Restore**.
2. In **Restore** section, click “**Browse**” to select the backup file, and then click “**Restore**” to start restoring the settings.




3. The restoring process requires logging out of the NVR server. After restoring is done, you may log in using your previous user account properties.




## Advanced Administrative Tasks

To assist the NVR administrator in monitoring the server status and basic trouble-shooting, the **NVR3 Administrator Tool** is installed along with NVR server program on the server computer. This tool will start running as the server computer starts up, and resides in the system tray. You may double-click the icon to open this tool.




### NVR Server Status

You may observe the NVR services status on **Service** tab.



### Change Server Port

On **Settings** tab, input a new port and then click “**Apply**”.



## Change Authentication Method

You may enable the **Digest** authentication other than the basic way. With this method, User's credentials are encrypted using MD5 algorithm. In this way, there is more secure protection to prevent from unauthorized access.

Please also note that, with **Digest** authentication method enabled, a mobile client user or a domain user will be blocked from NVR system.

