



FR6000 Series Mobile Computer User Guide



***FR6000 Series Mobile Computer
User Guide***

72E-119052-01

Rev. C

August 2009

© 2009 by Motorola, Inc. All rights reserved.

No part of this publication may be reproduced or used in any form, or by any electrical or mechanical means, without permission in writing from Motorola. This includes electronic or mechanical means, such as photocopying, recording, or information storage and retrieval systems. The material in this manual is subject to change without notice.

The software is provided strictly on an “as is” basis. All software, including firmware, furnished to the user is on a licensed basis. Motorola grants to the user a non-transferable and non-exclusive license to use each software or firmware program delivered hereunder (licensed program). Except as noted below, such license may not be assigned, sublicensed, or otherwise transferred by the user without prior written consent of Motorola. No right to copy a licensed program in whole or in part is granted, except as permitted under copyright law. The user shall not modify, merge, or incorporate any form or portion of a licensed program with other program material, create a derivative work from a licensed program, or use a licensed program in a network without written permission from Motorola. The user agrees to maintain Motorola’s copyright notice on the licensed programs delivered hereunder, and to include the same on any authorized copies it makes, in whole or in part. The user agrees not to decompile, disassemble, decode, or reverse engineer any licensed program delivered to the user or any portion thereof.

Motorola reserves the right to make changes to any software or product to improve reliability, function, or design.

Motorola does not assume any product liability arising out of, or in connection with, the application or use of any product, circuit, or application described herein.

No license is granted, either expressly or by implication, estoppel, or otherwise under any Motorola, Inc., intellectual property rights. An implied license only exists for equipment, circuits, and subsystems contained in Motorola products.

MOTOROLA and the Stylized M Logo and Symbol and the Symbol logo are registered in the US Patent & Trademark Office. Bluetooth is a registered trademark of Bluetooth SIG. Microsoft, Windows and ActiveSync are either registered trademarks or trademarks of Microsoft Corporation. All other product or service names are the property of their respective owners.

Motorola, Inc.
One Motorola Plaza
Holtsville, New York 11742-1300
<http://www.motorola.com>

Patents

This product is covered by one or more of the patents listed on the website:
<http://www.motorola.com/enterprisemobility/patents>

Revision History

Changes to the original manual are listed below:

Change	Date	Description
01 Rev.B	2009/07/02	Initial release

Table of Contents

About This Guide	11
Introduction	11
Documentation Set.....	11
Configurations	12
Software Versions.....	12
Phone Software	12
Chapter Descriptions.....	13
Notational Conventions	13
Related Documents.....	13
Service Information	14
Chapter 1 Getting Started.....	15
Introduction	15
Unpacking	16
Accessories.....	16
Getting Started	18
Installing the SIM Card (Located Under Battery).....	18
Removing the SIM Card.....	19
Installing the Main Battery.....	19
Removing the Battery	20
Charging the Battery	20
Charging the Main Battery and Memory Backup Battery	20
Charging Spare Batteries.....	21
Charging Temperature.....	21
Powering On the FR6000 Series	21
Calibrating the Screen	22
Checking Battery Status	22
CF Card Installation	22
Micro Secure Digital (microSD) Card	22
Adjusting the Handstrap.....	24
Removing the Screen Protector	24
Replacing the Main Battery	25

Battery Management.....	25
Changing the Power Settings.....	25
Changing the Backlight Settings	25
Turning Off the Radios.....	26
Chapter 2 Using the FR6000 Series	27
Introduction	27
Today Screen.....	27
Status Icons	28
Programs	30
Settings	32
Adjusting Volume	34
Battery Status Indications	35
Power Setting.....	36
Main Battery Temperature Notifications	37
LED Indicators.....	37
Resetting the FR6000 Series	38
Performing a Cold Boot.....	38
Waking the FR6000 Series	38
Locking the FR6000 Series.....	39
Keypads	40
Numeric Keypad Configurations	41
Function Buttons	44
Stylus	44
Entering Data	45
Data Capture.....	45
Linear Scanning	45
Scanning Considerations	45
Using IrDA.....	47
Infrared Connection	47
Exchanging Files using IR Connection	47
Chapter 3 Using GPS Navigation	49
Introduction	49
Software Installation.....	49
FR6000 Series GPS Setup	49
Operation	50
GPS Maps on microSD Cards	50
Downloading GPS Data	50
Answering a Phone Call While Using GPS	51
Losing the GPS Signal While in a Vehicle	51
Assisted GPS.....	51
Chapter 4 Using Bluetooth	53
Introduction	53
Adaptive Frequency Hopping	53
Security	54
Turning the Bluetooth Radio Mode On and Off	54
Disabling Bluetooth	55
Enabling Bluetooth.....	55
Bond New Device(s)	55
File Transfer Services	57
Bluetooth Settings.....	57

Device Info Tab	57
Mode Tab	58
COM Ports Tab	58
Chapter 5 ActiveSync	61
Introduction	61
Installing ActiveSync	61
Mobile Computer Setup	61
Setting Up an ActiveSync Connection on the Host Computer	62
Synchronization with a Windows Mobile 6 Device	63
Chapter 6 Using the Phone	67
Introduction	67
Accessing the Phone Keypad	67
Audio Modes	68
Using a Wired Headset	69
Using a Bluetooth Headset	70
Adjusting Audio Volume	70
Making a Call	71
Using the Phone	71
Using Contacts	71
Using Call History	72
Making a Speed Dial Call	72
Making an Emergency Call	73
Answering a Call	73
Incoming Call Features	74
Smart Dialing	74
Muting a Call	75
Taking Notes	76
Using Speed Dial	77
Adding a Speed Dial Entry	77
Editing a Speed Dial Entry	79
Deleting a Speed Dial Entry	79
Using Call History	80
Managing Call History	80
Changing the Call History View	80
Resetting the Recent Calls Counter	81
Deleting Call History Items by Call Date	81
Deleting All Call History Items	82
Viewing Call Status	83
Using the Call History Menu	83
Swapping Calls	84
Conference Call	85
Text Messaging	86
Viewing Text Messages	86
Sending a Text Message	88
Chapter 7 GSM Configuration	91
Introduction	91
FR6074/FR6076 Service Verification	91
Ensuring Network Coverage	91
Configuring a Data Connection	92
Establishing a Data Connection	94

Ending a Data Connection	95
FR6074/FR6076 Settings.....	96
Phone	96
Sounds.....	96
Security.....	97
Services	98
Call Barring (Call Blocking)	98
Caller ID.....	99
Call Forwarding.....	99
Call Waiting.....	100
Voice Mail and Text Messages	100
Fixed Dialing	101
Network.....	101
Changing Networks Manually	101
Viewing Available Networks.....	102
Setting Preferred Networks.....	103
Phone Info.....	103
Network Time Synchronization	104
Chapter 8 Accessories	105
Introduction	105
Single Slot USB/Serial Cradle.....	105
Charging the FR6000 Series Battery	106
Charging the Spare Battery	106
Battery Charging Indicators	106
Charging Temperature.....	107
Four Slot Battery Charger	108
FR6000 Series Battery Shim Installation	108
Spare Battery Charging	108
Battery Charging Indicators	109
Charging Temperature.....	109
Headset.....	110
Cables.....	110
Battery Charging and Operating Power	110
LED Charge Indications	111
Charging Temperature.....	111
Chapter 9 Maintenance&Troubleshooting	113
Introduction	113
Maintaining the FR6000 Series.....	113
Battery Safety Guidelines.....	114
Cleaning	115
Materials Required.....	115
Cleaning the FR6000 Series	115
Housing.....	115
Display	115
Scanner Exit Window.....	115
Connector	115
Cleaning Cradle Connectors	116
Cleaning Frequency	116
Troubleshooting the FR6000 Series.....	117
Bluetooth Connection.....	119

Single Slot USB/Serial Cradle	120
Four Slot Battery Charger	121
Cables.....	122
Appendix A Technical Specification	123
FR6000 Series Technical Specifications.....	123
FR6000 Series Accessory Specifications.....	125
Single Slot USB/Serial Cradle.....	125
Four Slot Battery Charger	126
Glossary	127
Index	131



About This Guide

Introduction

This guide provides information about using the FR6000 handy terminal and accessories.

✓ **NOTE** Screens and windows pictured in this guide are samples and can differ from actual screens.

Documentation Set

The documentation set for the FR60 provides information for specific user needs, and includes:

- **FR6000 Series Quick Start Guide** - describes how to get the FR6000 Series up and running.
- **FR6000 Series User Guide** - describes how to use the FR6000 Series.

Configurations

This guide covers the following configurations:

Configuration	Radios	Display	Memory	Data Capture	Operating System	Keypads
FR6076	WLAN: 802.11b/g WPAN: Bluetooth WWAN: HSDPA GPS: A-GPS	2.8" QVGA Color	128 MB RAM/ 256 MB Flash	1D laser scanner	Windows Mobile 6.1 Professional	numeric keypad
FR6074	WLAN: 802.11b/g WPAN: Bluetooth WWAN: GSM GPS: A-GPS	2.8" QVGA Color	128 MB RAM/ 256 MB Flash	1D laser scanner	Windows Mobile 6.1 Professional	numeric keypad
FR6070	WLAN: 802.11b/g WPAN: Bluetooth	2.8" QVGA Color	128 MB RAM/ 256 MB Flash	1D laser scanner	Windows Mobile 6.1 Classic	numeric keypad

Software Versions

This guide covers various software configurations and references are made to operating system or software versions for:

- Adaptation Kit Update (AKU) version
- Phone version

AKU Version

To determine the Adaptation Kit Update (AKU) version:

Tap **Start** > **Settings** > **System** tab > **About** icon > **Version** tab.

The second line lists the operating system version and the build number. The last part of the build number represents the AKU number. For example, *Build 18552.0.7.5* indicates that the device is running AKU version 0.7.5.

Phone Software

To determine the Phone software version:

Tap **Start** > **Phone** > **Menu** > **Options** > **Phone** tab.

Chapter Descriptions

Topics covered in this guide are as follows:

- [Chapter 1, Getting Started](#) provides information on getting the FR6000 Series up and running for the first time.
- [Chapter 2, Using the FR6000 Series](#) provides basic instructions for using the FR6000 Series, including powering on and resetting the FR6000 Series, and entering and capturing data.
- [Chapter 3, Using GPS Navigation](#) provides information about GPS navigation with the FR6000 Series.
- [Chapter 4, Using Bluetooth](#) explains Bluetooth functionality on the FR6000 Series.
- [Chapter 5, ActiveSync](#) synchronizes information on the mobile computer with information on the host computer
- [Chapter 6, Using the Phone](#) provides basic instructions for using the FR6000 Series phone.
- [Chapter 7, GSM Configuration](#) provides basic GSM settings for using the FR6000 Series phone.
- [Chapter 8, Accessories](#) describes the available accessories and how to use them with the FR6000 Series.
- [Chapter 9, Maintenance & Troubleshooting](#) includes instructions on cleaning and storing the FR6000 Series, and provides troubleshooting solutions for potential problems during FR6000 Series operation.
- [Appendix A, Technical Specifications](#) provides the technical specifications for the FR6000 Series.

Notational Conventions

The following conventions are used in this document:

- “Handy” refers to the Motorola FR6000 Series of hand-held computers.
- *Italics* are used to highlight the following:
 - Chapters and sections in this and related documents
 - Icons on a screen.
- **Bold** text is used to highlight the following:
 - Dialog box, window, and screen names
 - Drop-down list and list box names
 - Check box and radio button names
 - Key names on a keypad
 - Button names on a screen.
- bullets (•) indicate:
 - Action items
 - Lists of alternatives
 - Lists of required steps that are not necessarily sequential
- Sequential lists (e.g., those that describe step-by-step procedures) appear as numbered lists.

Related Documents

- *FR6000 Series Quick Start Guide*, p/n 72-119047-01.
- *FR6000 Series Windows Mobile 6.1 Regulatory Guide*, p/n 72-119053-01.
- *Microsoft® Applications for Mobile 6.1 User Guide*, p/n 72E-108299-xx.

- Latest ActiveSync software, available at: <http://www.microsoft.com>.

For the latest version of this guide and all guides, go to:
<http://www.motorola.com/enterprisemobility/manuals>.

Service Information

If you have a problem with your equipment, contact Motorola Enterprise Mobility support for your region. Contact information is available at:

<http://www.motorola.com/enterprisemobility/contactsupport> .

When contacting Enterprise Mobility support, please have the following information available:

- Serial number of the unit
- Model number or product name
- Software type and version number

Motorola responds to calls by email, telephone or fax within the time limits set forth in support agreements.

If your problem cannot be solved by Motorola Enterprise Mobility Support, you may need to return your equipment for servicing and will be given specific directions. Motorola is not responsible for any damages incurred during shipment if the approved shipping container is not used. Shipping the units improperly can possibly void the warranty.

If you purchased your Enterprise Mobility business product from a Motorola business partner, contact that business partner for support.



Chapter 1 Getting Started

Introduction

This chapter lists the parts and accessories for the FR6000 Series and explains how to install and charge the batteries, replace the strap, and power on the FR6000 Series for the first time.




Figure 1-1 FR6000 Series View

- | | | | |
|---------------------|------------------|------------------|------------------|
| 1. IrDA Window | 2. Headset Jack | 13. Battery Door | 14. Door Latch |
| 3. Scan Button | 4. Microphone | 15. Speaker | 16. Scan Window |
| 5. I/O Connector | 6. Power button | 17. CF Card Slot | 18. SD Card Slot |
| 7. Keypad | 8. Touch Screen | 19. Reset Button | 20. Scan Button |
| 9. Radio Status LED | 10. Charging LED | 21. Handstrap | 22. Stylus |
| 11. Scan/Decode LED | 12. Receiver | | |

Unpacking

Carefully remove all protective material from the FR6000 Series and save the shipping container for later storage and shipping.

Verify that you received the following:

- FR6000 Series
- 3600 mAh Lithium-ion battery
- Battery cover/strap assembly
-
- FR6000 Series Cradle Adaptor Clip
- Tethered stylus
- Protective screen protector, installed on display window
- Regulatory Guide
- Quick Start Guide.

Inspect the equipment for damage. If any equipment is missing or damaged, contact the Motorola Enterprise Mobility Support center immediately. See [page 15](#) for contact information.

Accessories

[Table 1-1](#) lists the accessories available for the FR6000 Series.

Table 1-1 *FR6000 Series Accessories*

Part Number	Description
Cradles	
CRD7X00-1000RR	MC75 RoHS Compliant Single Slot USB Cradle with Spare Battery Charging: Must Order Power Supply (KT-14000-148R), and US AC Line Cord (23844-00-00R) separately
CRD7X00-101RR	1 Slot USB Cradle Kit, Includes: Single Slot USB Charge Cradle (w/spare battery charging), Power Supply (KT-14000-148R) & US AC line cord 7.5Ft, 3 wire (23844-00-00R)
CRD7X00-100RR	MC75 Single Slot USB cradle kit, includes: Single Slot USB Charge Cradle (w/spare battery charging), Power Supply (KT-14000-148R) & US AC line cord 7.5Ft, 3 wire (23844-00-00R)
Charging	
SAC7X00-4000CR	MC75 4 Slot Battery Charger. Can also be used with MC3000 Batteries. Requires power supply (KT-14000-148R) and 3 Wire GROUNDED AC line cord.
SAC7X00-400CR	4-Slot Battery Charger "Toaster" for MC75 and MC3000. Charges spare standard and high capacity batteries. Includes Shim for MC75, Power Supply (KT-14000-148R) and US AC Line Cord (23844-00-00R).
SAC7X00-401CR	4-Slot Battery Charger "Toaster" for MC75 and MC3000. Charges spare standard and high capacity batteries. Includes Shim for MC75 and Power Supply (KT-14000-148R). Must purchase 3 Wire AC line cord separately.
KT-14000-148R	KT-14000-148R - Provides power to the Single Slot Cradle (CRD5500-1000UR) and Four Slot Battery Charger (SAC5500-4000CR). Order country specific three wire grounded AC line cord separately.
50-14000-249R	AC power supply with barrel jack. Allows for charging of an MC55 terminal without a cradle. Requires USB (25-108022-01R) or Charge only (25-112560-02R) cable. Order country specific two wire AC power line cord separately.
BTRY-MC7XEAB00	FR6000 Li-Ion Battery, 3600 mAh

Table 1-1 *FR6000 Series Accessories (Continued)*

Part Number	Description
MN2800AAAPBL	FR6000 Series battery door
MN2800AAAPHS	FR6000 Series hand strap only
MN2800AAAPCF	FR6000 Series compact flash cover door and fastener. Pack of 10.
MN2800BAAPCF	FR6000 Series compact flash cover door and fastener. Pack of 50.
25-118707-01R	FR6000 Series Auto Charge Cable (Cigarette Lighter Adapter)
Cables	
25-68596-01R	USB ActiveSync Cable for cradle to the host system.
25-118708-01R	FR6000 Series USB Charging
25-118710-01R	FR6000 Series Charge Only Cable
Miscellaneous	
KT-76490-01R	Battery adapter (shim for 4 slot charge only; packet of 5)
MN2800AAAPCD	FR6000 Series Cradle Adaptor Clip – Adapts FR6000 Series mobile computer to the cradle. Pack of 3.
MN2800BAAPCD	FR6000 Series Cradle Adaptor Clip – Adapts FR6000 Series mobile computer to the cradle. Pack of 10.
MN2800AAAPST	FR6000 Series spare stylus with tether. Pack of 3.
MN2800AAAPSC	Screen protector for 2.8" QVGA display. Pack of 3.
90-17C28-001R	Hands free headset (earbud).

Getting Started

To start using the FR6000 Series for the first time:

- Install the SIM card (FR6074 and FR6076 only)
- Install the main battery.
- Charge the FR6000 Series.
- Power on the FR6000 Series.
- Configure the FR6000 Series.

Installing the SIM Card (Located Under Battery)

✓ **NOTE** FR6074 and FR6076 configurations only.

GSM phone service requires a Subscriber Identification Module (SIM) card, or smart card. Obtain this card from your service provider. The card fits into the FR6000 Series and can contain the following information:

- Mobile phone service provider account details.
- Information regarding service access and preferences.
- Contact information, which can be moved to **Contacts** on the FR6000 Series.
- Any additional services to which you have subscribed.

✓ **NOTE** For more information about SIM cards, refer to the service provider's documentation.

To install the SIM card(located under the battery):

Place SIM card with contacts facing down




Figure 1-2 *Install the SIM Card*

1. Install the battery. See [Installing the Main Battery on page 19](#) for more information.
2. Press the red **Power** button.
3. Tap **Start > Phone > Menu > Options > Network** tab and verify that the service provider appears in the **Current network:** field.
4. Make a call to verify connection.

Removing the SIM Card

1. Remove the battery door.
2. Remove the battery.
3. With finger, press and hold the slot lock down.
4. Using other hand, remove the SIM card from the slot.
5. Replace the battery.
6. Replace the battery door.




Figure 1-3 Removing the SIM Card

Installing the Main Battery

✓ **NOTE** The FR6000 Series ships with a 3600 mAh battery.

To install the main battery:

1. Push the latch to the unlock position.
 2. Slide the battery door downwards and remove it..
 3. Insert the battery, bottom first, into the battery compartment in the back of the FR6000 Series.
- ✓ **NOTE** Position the battery correctly, with the battery charging contacts on top of the charging contacts in the battery compartment.
4. Press the battery down into the battery compartment until the battery release latch snaps into place.
 5. Slide the battery door upwards.
 6. Push the latch to the lock position.




Figure 1-4 *Inserting the Battery*

7. With the battery cover latch open, push the cover forwards until the cover fits into the place.
8. Push the latch to the lock position to lock the cover.
9. Insert the handstrap through the handstrap slot, then tighten and press down to secure.

The FR6000 Series powers up after inserting the battery and replacing the battery cover.

Removing the Battery

1. Remove the battery door.
2. Wait for five seconds.
3. Remove the battery.

Charging the Battery



CAUTION

Ensure that you follow the guidelines for battery safety described in [Battery Safety Guidelines on page 114](#).

Charging the Main Battery and Memory Backup Battery

Before using the FR6000 Series for the first time, charge the main battery until the green Charging/Battery Status LED remains lit (See [Table 1-2 on page 21](#) for charge status indications). To charge the FR6000 Series, use a cable or a cradle with the appropriate power supply. For information about the accessories available for the FR6000 Series, see [Chapter 8, Accessories](#).

The FR6000 Series is equipped with a memory backup battery which automatically charges from the fully-charged main battery. When using the FR6000 Series for the first time, the backup battery requires approximately 36 hours to fully charge. This is also true any time the backup battery is discharged, which occurs when the main battery is removed for several hours. The backup battery retains RAM data in memory for at least 15 minutes (at room temperature) when the FR6000 Series' main battery is removed. When the FR6000 Series reaches a very low battery state, the combination of main battery and backup battery retains RAM data in memory for at least 48 hours.

To charge the main battery, use either a charging cable or a cradle.

- Single Slot USB/Serial Cradle

To charge the main battery:

1. Connect the charging accessory to the appropriate power source.
2. Insert the FR6000 Series into a cradle or attach to a cable. The FR6000 Series begins charging. The Charging/Battery Status LED blinks amber while charging, then turns solid green when fully charged. See [Table 1-2 on page 21](#) for charging indications.

The 3600 mAh battery is fully charged in approximately six hours.

Table 1-2 LED Charge Indicators

Charging/Battery Status LED	Indication
Off	FR6000 Series is not charging. FR6000 Series is not inserted correctly in the cradle or connected to a power source. Charger/cradle is not powered.
Slow blinking amber	FR6000 Series is charging.
Solid green	Charging complete. Note: When the battery is initially inserted in the FR6000 Series, the amber LED flashes once if the battery power is low or the battery is not fully inserted.
Fast blinking red	Charging error, e.g.: • Temperature is too low or too high. • Charging has gone on too long without completion (typically eight hours).
Single blink amber (when device is turned on)	Battery depleted.
Fast Blink amber	Battery over-temperature condition.

Charging Spare Batteries

See [Chapter 8, Accessories](#) for information on using accessories to charge spare batteries.

Charging Temperature

Charge batteries in temperatures from 0°C to 45°C (32°F to 113°F). Charging is intelligently controlled by the FR6000 Series.

To accomplish this, for small periods of time, the FR6000 Series or accessory alternately enables and disables battery charging to keep the battery at acceptable temperatures. The FR6000 Series or accessory indicates when charging is disabled due to abnormal temperatures via its LED. See [Table 1-2 on page 21](#).

Powering On the FR6000 Series

Press the **Power** button to turn on the FR6000 Series.

When turning the FR6000 Series on for the first time, the splash screen displays for about a minute as the FR6000 Series initializes its flash file system, then the calibration window appears. Note that these windows also appear upon cold boot.

- ✓ **NOTE** When the FR6000 Series powers up after inserting a battery for the first time, the device boots and powers on automatically.

Calibrating the Screen

To calibrate the screen so the cursor on the touch screen aligns with the tip of the stylus:

1. Remove the stylus from its holder on the back of the FR6000 Series.
2. Carefully press and briefly hold the tip of stylus on the center of each target that appears on the screen.
3. Repeat as the target moves around the screen, then tap the screen to continue.

Checking Battery Status

To check the charge status of the main battery in the FR6000 Series, tap **Start > Settings > System** tab > **Power** icon to display the **Power** window.

To save battery power, tap the **Advanced** tab and set the FR6000 Series to turn off after a specified number of minutes.

CF Card Installation




Figure 1-5 CF Card Installation

To install the CF card:

1. Remove the screws securing the cover.
2. Remove the cover.
3. Insert the CF card into the slot with the contacts facing down.
4. Replace the cover and secure the two screws.

Micro Secure Digital (microSD) Card

The microSD card slot provides secondary non-volatile storage. The slot is located on the side of the FR6000 Series (see [Figure 1-6](#)). Refer to the documentation provided with the card for more information, and follow the manufacturer's recommendations for use.



CAUTION Follow proper ESD precautions to avoid damaging the microSD card. Proper ESD precautions include, but are not limited to, working on an ESD mat and ensuring that the operator is properly grounded.

To install the microSD card:

1. Power off the FR6000 Series.
2. Open the memory card cover on the side of the FR6000 Series .




Figure 1-6 *microSD Card Installation*

3. Insert the card with the card contacts facing up and the cut corner on the left, until you feel a click.
4. Close the memory card cover .


To remove the microSD card:

1. Power off the FR6000 Series.
2. Open the memory card cover.
3. Carefully press and release the card to eject it.
4. Remove the card from the card slot.
5. Close the memory card cover.

Adjusting the Handstrap

The FR6000 Series handstrap is attached to the bottom of the battery cover. Adjust the handstrap to increase comfort when holding the FR6000 Series for extended periods of time. To adjust the handstrap:

1. Feed the handstrap through the handstrap slot in either direction, to tighten or loosen
2. Secure the handstrap by pressing the two sides together.



Removing the Screen Protector

A screen protector is applied to the FR6000 Series. Motorola recommends using this to minimize wear and tear. Screen protectors enhance the usability and durability of touch screen displays.

To remove the screen protector, lift the corner using a thin plastic card, such as a credit card, then carefully lift it off the display.




Figure 1-7 *Removing the Screen Protector*

 **CAUTION** Do not use a sharp object to remove the protector. Doing so can damage the display.

 **NOTE** Not using a screen protector can affect warranty coverage. To purchase replacement protectors, contact your local account manager or Motorola, Inc. These include screen protector installation instructions. Part number: MN2800AAPSC .

Replacing the Main Battery

1. Loosen the handstrap.
 2. Release the battery cover latch to the unlock position.
 3. Please wait for 5 seconds after the display is off.
 4. Lift the top of the battery cover and remove.
 5. Press the battery release latch on the top of the battery to unlock, and lift the battery out of the well.
 6. Insert the replacement battery, bottom first, into the battery compartment in the back of the FR6000 Series.
 7. Press the battery down into the battery compartment until the battery release latch snaps into place.
- ✓ **NOTE** Position the battery correctly, with the battery charging contacts on top of the charging contacts in the battery compartment.
8. With the battery cover latch open, push the cover forwards.
 9. Push the latch to the lock position to lock the cover.
 10. Insert the handstrap through the handstrap slot, then tighten and press down to secure.

The FR6000 Series powers up after the battery is inserted and the battery cover is replaced.

Battery Management

Observe the following battery saving tips:

- ✓ **NOTE** The FR6000 Series factory default settings for the WWAN and WLAN radios are set to ON.
- Leave the FR6000 Series connected to AC power at all times when not in use.
 - Set the FR6000 Series to turn off after a short period of non-use.
 - Set the backlight to turn off after a short period of non-use.
 - Turn off all wireless activities when not in use.
 - Power off the FR6000 Series when charging at a faster rate.

Changing the Power Settings

To set the FR6000 Series to turn off after a short period of non-use:

1. Tap **Start > Settings > System tab > Power icon > Advanced tab**.
2. Select the **On battery power: Turn off device if not used for** check box and select a value from the drop-down list.
3. Select **ok**.

Changing the Backlight Settings

To change the backlight settings in order to conserve more battery power:

1. Tap **Start > Settings > System tab > Backlight icon > Power tab**.
2. Select the **Turn off backlight if device is not used for** check box and select a value from the drop-down list.
3. Select the **Brightness** tab.
4. Use the slider to set a low value for the backlight.
5. Select **ok**.

Turning Off the Radios

Windows Mobile 6.1 devices include **Wireless Manager**, which provides a simple method of enabling, disabling, and configuring all the device's wireless capabilities in one place.

To open **Wireless Manager**, tap the **Connectivity** icon or tap **Wireless Manager** on the **Today** screen.



Figure 1-9 Opening Wireless Manager

Select **Wireless Manager**.




Figure 1-10 Selecting Wireless Manager

✓ **NOTE** Wireless connection options vary depending upon configurations.

To enable or disable a wireless connection, tap the specific button.

To enable or disable all wireless connections, tap the **All** button. To configure settings for a connection, tap **Menu**.

Chapter 2 Using the FR6000 Series

Introduction

This chapter explains the buttons, status icons, and controls on the FR6000 Series, and provides basic instructions for using the FR6000 Series, including powering on and resetting the FR6000 Series, and entering and capturing data.

The FR6000 Series factory default radio states are:

- Bluetooth - OFF
- Phone - ON
- Wireless LAN - ON

Today Screen

The Today screen displays important information, such as upcoming appointments and status indicators. Tap a section on the screen to open the associated program. Alternatively, tap **Start > Today** to display the **Today** screen.




Figure 2-1 Today Screen

To customize the **Today** screen, tap **Start > Settings > Today** icon. Use the **Appearance** tab to customize the background and the **Items** tab to change the list and order of items that appear on the screen.

Status Icons

The Navigation bar at the top of the screen can contain the status icons listed in [Table 2-1](#).

Table 2-1 *Status Icons*

Icon	Function	Description
	Notification	Backup Battery Low.
		Notification that one or more instant messages were received.
		Notification that one or more e-mail/text messages were received.
		Notification that one or more voice messages were received.
		There are more notification icons than can be displayed. Tap to display remaining icons.
		Indicates a reminder of an upcoming calendar event.
	Connectivity	Connection is active.
		Connection is not active.
		Synchronization is occurring.
		WLAN available.
		WLAN in use.
		HSDPA available. (FR6076 only)
		3G available. (FR6076 only)
		GPRS available. (FR6074 and FR6076)
		EGPRS available. (FR6074 and FR6076)

Table 2-1 Status Icons (Continued)

Icon	Function	Description
	WAN	Call missed.
		Dialing while no SIM card is installed.
		Voice call in progress.
		Calls are forwarded.
		Call on hold.
		Speakerphone is on.
		Antenna/signal icon: wireless on/good signal.
		Antenna/signal icon: wireless off.
		Antenna/signal icon: no service or searching.
		HSDPA connecting. (FR6076 only)
		HSDPA in use. (FR6076 only)
		3G connecting. (FR6076 only)
		3G in use. (FR6076 only)
		GPRS connecting. (FR6074, FR6076)
		GPRS in use. (FR6074, FR6076)
		EGPRS connecting. (FR6074, FR6076)
		EGPRS in use. (FR6074, FR6076)
		Roaming.
		SIM Card not installed. (FR6074, FR6076)
	Speaker	All sounds are on.
		All sounds are off.
		Vibrate is on.
	Battery	Main battery is charging.
		Battery power completely depleted.
		Main battery is low.
		Main battery level.
	Time and Next Appointment	Displays current time in analog or digital format.

The command bar at the bottom of the screen can contain the task tray icons listed in [Table 2-2](#).

Table 2-2 *Task Tray Icons*

Icon	Name	Description
	ActiveSync	Active serial connection between the FR6000 Series and the host computer.

Programs

[Table 2-3](#) lists the default programs in the **Start** menu.

Table 2-3 *Programs in the Start Menu*

Icon	Name	Description
	Office Mobile	Use the complete suite of Microsoft® Office applications for your mobile device. Excel Mobile - Create new workbooks or view and edit Microsoft® Excel® workbooks. OneNote Mobile - Create new notes or view existing notes. PowerPoint Mobile - View Microsoft® PowerPoint® slides and presentations Word Mobile - Create, view, and edit Microsoft® Word documents
	Calendar	Keep track of appointments and create meeting requests.
	Contacts	Keep track of friends and colleagues.
	Internet Explorer Mobile	Browse Web and WAP sites as well as download new programs and files from the Internet.
	Messaging	Send and receive e-mail and text messages.
	Phone	Make and receive calls, switch between calls, and set up Conference Call. Note: For FR6074,FR6076
	Help	See Help topics for the current screen or program.

Table 2-4 lists programs that are listed in the Programs window.

Table 2-4 *Programs in Program Window*

Icon	Name	Description
	Games	Bubble Breaker, Solitaire
	Sample AP	ScanWedgeFR, Notify, and Scanner
	ActiveSync	Synchronize information between the FR6000 Series and a host computer or the Exchange Server.
	Calculator	Perform basic arithmetic and calculations, such as addition, subtraction, multiplication, and division.
	File Explorer	Organize and manage files on your device.
	Getting Started	Display help on how to use some functions
	GPSXtra	Allow you to download GPS data to enhance GPS performance Note: For FR6074,FR6076
	Internet Sharing	Connect a notebook computer to the Internet using the FR6000 Series' data connection.
	Messenger	Use this mobile version of Windows Live Messenger.
	Notes	Create handwritten or typed notes, drawings, and voice recordings.
	Pictures & Videos	View and manage pictures, animated GIFs, and video files.
	Search	Search contacts, data, and other information on your FR6000 Series.
	Task Manager	Show and stop all the tasks on run
	Tasks	Keep track of your tasks.
	Windows Live	Use this mobile version of Windows Live™ to find information on the web.
	Windows Media	Play back audio and video files.

Settings

[Table 2-5](#) lists control applications pre installed on the FR6000 Series. Tap **Start** > **Settings** to open the **Settings** window.

Table 2-5 *Settings in the Setting Window*

Icon	Name	Description
Personal Tab		
	Buttons	Assign a program to a button.
	Input	Set options for each of the input methods.
	Lock	Set a password for the FR6000 Series.
	Menus	Set what programs appear in the Start menu.
	Owner Information	Enter personal information on the FR6000 Series.
	Phone	Make and receive calls, switch between calls, and set up Conference Call.
	Sounds & Notifications	Enable sounds for events, notifications, and more, and set the type of notification for different events.
	Today	Customize the appearance and the information to be displayed on the Today screen.

Table 2-5 Settings in the Setting Window (Continued)

Icon	Name	Description
System Tab		
	802.11d Tools	Enable or disable 802.11d
	About	View basic information such as the Windows Mobile® version and type of processor used on the FR6000 Series.
	Backlight	Set the display backlight time-out and adjust brightness.
	Certificates	See information about certificates installed on the FR6000 Series.
	Clock & Alarms	Set the device clock to the date and time of your locale or to a visiting time zone when you're traveling. Alarms can also be set at specified days and times of a week.
	Customer Feedback	Submit feedback on the Windows Mobile 6.1 software.
	Device information	Displays the FR6000 Series' software and hardware information.
	Encryption	Allow files on a storage card to be encrypted. Encrypted files are readable only on your device.
	Enroller	Allow you to get a Certificate from Certificate servers.
	Error Reporting	Enable or disable the device's error reporting function. When this function is enabled and a program error occurs, technical data about the state of the program and your computer is logged in a text file and delivered to Microsoft's technical support if you choose to send it.
	External GPS	Set the appropriate GPS communication ports, if required. You may need to do this when there are programs on your device that access GPS data or you have connected a GPS receiver to the FR6000 Series.
	Managed Programs	View installation history.
	Memory	Check the device memory allocation status and memory card information and stop currently running programs.
	Power	Check battery power and set the time-out for turning off the display to conserve battery power.

Table 2-5 *Settings in the Setting Window (Continued)*

Icon	Name	Description
	Regional Settings	Set the regional configuration to use, including the format for displaying numbers, currency, date, and time on the FR6000 Series.
	Remove Programs	Remove programs that you installed on the FR6000 Series.
	Screen	Change the screen orientation, re-calibrate the screen, and change the screen text size.
	Task Manager	Show and stop all the tasks on run
	Windows Update	Link to Microsoft's web site and update Windows Mobile® on your device with the latest security patches or fixes. Do not use. Obtain updates from Motorola.
Connection Tab		
	Beam	Set the FR6000 Series to receive incoming IrDA beams and bluetooth beam.
	Bluetooth	Search for other Bluetooth devices.
	Connections	Set up one or more types of modem connections for your device, such as phone dial-up, GPRS, Bluetooth, and more, so that your device can connect to the Internet or a private local network.
	Domain Enroll	Enroll in domain.
	USB to PC	Enables or disables the enhanced network connectivity.
	Wi-Fi	Setup wireless network connection and customize settings.
	Wireless Manager	Enables or disables the FR6000 Series' wireless radios and customizes WLAN, Bluetooth and Phone settings.

Adjusting Volume

To adjust the system volume using the **Speaker** icon in the navigation bar:

1. Tap the **Speaker** icon. The **Volume** dialog box appears.



Figure 2-2 Volume Dialog Box

2. Tap and move the slide bar to adjust the volume.
3. Select the **On** or **Off** radio button to turn the volume on or off.

You can also adjust the system volume using the **Sounds & Notifications** window, or use the **Up/Down** button on the side of the FR6000 Series.

Battery Status Indications

Battery icons appear on the navigation bar indicating the battery power level. When the main battery or backup battery power falls below a predetermined level, the icon indicates the status and a battery dialog box appears indicating the status of the main or backup battery.




Figure 2-3 Battery Status Dialog Box

The **Battery** icon always appears in the **navigation bar** when the Today screen is visible. The icon indicates the battery power level. The message displays until the **Dismiss** button is pressed.



Figure 2-4 Battery Icon on the Title Bar

Also view the battery status using the **Power** window.

Power Setting

1. Tap **Start** > **Settings** > **Power** icon > **Main** tab. A power remaining capacity bar appears.




Figure 2-5 Main Tab

2. Tick the following options to save the power, and tap **ok**.




Figure 2-6 Advanced Tab

3. Select Slow charge or Fast charge, and tap **ok**.




Figure 2-7 USB Charge Tab

Main Battery Temperature Notifications

The temperature notification system displays warnings as the following figures when the temperature within the battery exceeds specific temperature thresholds:




Figure 2-8 Main Battery Temperature Notification

✓ **NOTE** The **Temperature Warning** dialog box remains visible until you tap **Hide**.

LED Indicators

The FR6000 Series has three LED indicators. The Scan/Decode LED indicates status for bar code scanning. The Charging/Battery Status LED indicates battery charging and status. The Radio Status LED indicates radio status. [Table 2-6](#) describes the LED indications



Figure 2-9 LED Indicators

1. Scan/Decode LED
2. Charging LED
3. Radio Status LED

Table 2-6 LED Indications

LED status	Indication
Scan/Decode LED	
single blink green	Barcode was successfully decoded
Solid red	Laser enabled, scanning in process
System led (Amber blink)	The behavior of this LED controlled by Microsoft system.
Off	Not enabled
Charging/Battery Status LED	
Off	FR6000 Series is not charging. FR6000 Series is not inserted correctly in the cradle or connected to a power source. Charger/cradle is not powered.
Slow blinking amber	FR6000 Series is charging.
Solid green	Charging complete. Note: When the battery is initially inserted in the FR6000 Series, the amber LED flashes once if the battery power is low or the battery is not fully inserted.
Fast blinking amber	Battery over-temperature condition
Fast blinking red	Charging error, e.g.: • Temperature is too low or too high. • Charging has gone on too long without completion (typically eight hours).
Single blink amber (when the device is turned on)	Battery depleted
Radio Status LED	
Slow blink green	All those radio devices which are powered on are available for receiving / sending data
slow blink red	Any one of the radio devices which is powered on and not available for receiving / sending data
Off	All radio off

✓ **NOTE** For information about scanning/decoding, see [Data Capture on page 45](#). For information about WAN radio status and settings, see [Chapter 6, Using the Phone](#).

Resetting the FR6000 Series

The reset function is cold boot. A cold boot restarts the FR6000 Series, and also resets the clock. Data saved in flash memory or a memory card is not lost.

Performing a Cold Boot

Press the reset button to reboot the device.

Waking the FR6000 Series

The wake-up conditions define what actions wake up the mobile computer after it has gone into suspend mode. The mobile computer can go into suspend mode by either pressing the Power button or automatically by Control Panel time-out settings. These settings are configurable and the factory default settings shown in [Table 2-7](#) are subject to change or update.


Table 2-7 Wake-up Default Settings

Condition for Wake-up	Power Button	Automatic Time-out
AC power is applied.	No	Yes
Mobile computer is inserted into a cradle.	No	Yes
Mobile computer is removed from a cradle.	No	Yes
Mobile computer is connected to a USB device.	No	Yes
Mobile computer is disconnected from a USB device.	No	Yes
The scan triggered is pressed.	No	Yes
The screen is touched.	No	No
Audio Jack	No	No
Audio Btn	No	No
Bluetooth communication	Yes	Yes
Incoming phone call	Yes	Yes


Locking the FR6000 Series

Use the Device Lock feature to prevent use of the device. Note that when locked, the FR6000 Series does not respond to screen or keypad input.

To lock the device, tap the **Device unlocked** icon. The icon changes to locked.

**Figure 2-10** Device Locked/Unlocked Icons

To unlock the device and free it for use, tap **Unlock**.

**Figure 2-11** Unlock Device Window

Tap **Unlock** on the **Unlock** window.

✓ **NOTE** You can make emergency calls even when the FR6000 Series is locked. See [Making an Emergency Call on page 73](#) for more information.

Keypads

The FR6000 Series offers one type of modular keypad configuration: numeric.

Table 2-8 *Numeric Keypad Input Modes*

Key	Numeric Mode			Orange Key (Alpha Lowercase Mode)								
		Blue+ Key	SHIFT + Key	1st Press	2nd Press	3rd Press	4th Press	5th Press	6th Press	7th Press	8th Press	9th Press
1	1	1	!	Space	1							
2	2	2	@	a	b	c	2	A	B	C		
3	3	3	#	d	e	f	3	D	E	F		
4	4	4	\$	g	h	i	4	G	H	I		
5	5	5	%	j	k	l	5	J	K	L		
6	6	6	^	m	n	o	6	M	N	O		
7	7	7	&	p	q	r	s	7	P	Q	R	S
8	8	8	*	t	u	v	8	T	U	V		
9	9	9	(	w	x	y	z	9	W	X	Y	Z
0	0	0	)	+	0							
Note: An application can change the key functions. The keypad may not function exactly as described.												

Table 2-9 *Numeric Keypad Input Modes*

Key	Numeric Mode			Orange Key (Alpha Lowercase Mode)				Orange + Shift Keys (Alpha Uppercase Mode)			
		Blue+ Key	SHIFT + Key	1st Press	2nd Press	3rd Press	4th Press	1st Press	2nd Press	3rd Press	4th Press
Up	Up	Up	Highlight Up	Left				Left			
Down	Down	Down	Highlight Down	Right				Right			
Enter	Action	Action	Action	Action				Action			
Note: An application can change the key functions. The keypad may not function exactly as described.											

Numeric Keypad Configurations

The numeric keypad produce the 26-character alphabet (A-Z, both lowercase and uppercase), numbers (0-9), and assorted characters. The keypad is color-coded to indicate which modifier key to press to produce a particular character or action. The keypad default is alphabetic, producing lowercase letters. See [Table 2-9](#) for key and button descriptions.




Figure 2-12 FR6000 Series Numeric Keypad

Table 2-10 *Numeric Keypad Descriptions*


Key	Action
Blue Key 	Launches applications (shown on the keypad in blue). - Press the Blue key once to activate this mode temporarily, followed by another key. This displays the following icon at the bottom of the screen, until a second key is pressed:  - Press the Blue key twice to lock this mode. This displays the following icon at the bottom of the screen:  - Press the Blue key a third time to unlock. - Press and hold the Blue key while selecting a sequence of keys to activate this mode temporarily. This displays the following icon at the bottom of the screen as long as the key is pressed: 
Orange Key 	Accesses the secondary layer of characters and actions (shown on the keypad in orange). - Press the Orange key once to lock this mode. This displays the following icon at the bottom of the screen:  - Press the Orange key another time to unlock.
Talk/End 	Talk (Green Phone): press to display the phone keypad window or to dial a phone number (from the phone keypad window). End (Red Phone): press when the phone keypad window displays to stop dialing or end a call.
Scroll Up and Left 	Moves up one item. Moves left one item when pressed with the Orange key.
Scroll Down and Right 	Moves down one item. Moves right one item when pressed with the Orange key.
Soft Keys 	Accesses the command or menu above it on the screen.
Backlight 	Turns the display backlight on and off.
Backspace 	Produces a backspace.

Table 2-10 *Numeric Keypad Descriptions (continued)*

Shift 	Changes the state of the alpha characters from lowercase to uppercase. ● Press the Shift key to activate this mode temporarily, followed by another key. This displays the following icon at the bottom of the screen, until a second key is pressed:  ● Press and hold the Shift key while selecting a sequence of keys to activate this mode temporarily. This displays the following icon at the bottom of the screen as long as the key is pressed:  ● Press the Shift key twice to lock this mode. This displays the following icon at the bottom of the screen:  ● Press the Shift key a third time to unlock.
Enter 	Executes a selected item or function.
Star 	The user has to press the blue key first to get the asterisk.

Function Buttons

The FR6000 Series' buttons perform certain functions.



Figure 2-13 *Function Buttons*

1. Scan button

2. Power button

- **Power:** Press the red **Power** button to turn the FR6000 Series screen on and off. The FR6000 Series is in suspend mode when the screen is off. For more information, see [Powering On the FR6000 Series on page 21](#). Press the reset button to reboot the device performing a cold boot. See [Resetting the FR6000 Series on page 38](#).
- **Scan:** Press to scan bar codes. See [Data Capture on page 45](#).

Stylus

Use the FR6000 Series stylus to select items and enter information. The stylus functions as a mouse.


- **Tap:** Touch the screen once with the stylus to press option buttons and open menu items.
- **Tap and Hold:** Tap and hold the stylus on an item to see a list of actions available for that item. On the pop-up menu that appears, tap the action to perform.
- **Drag:** Hold the stylus on the screen and drag across the screen to select text. Drag in a list to select multiple items.



CAUTION To prevent damage to the screen, do not use any device other than the Motorola-provided stylus.

Entering Data

When entering data on the keypad, use either the single-hand method or the two-hand method as shown in [Figure 2-14](#).



Single-hand Method

Two-hand Method

Figure 2-14 *Entering Data on the Keypad*

Data Capture

The FR6000 Series offers linear scanning as data capture.

✓ **NOTE** To perform data capture a scanning enabled application must be installed on the FR6000 Series. A sample scanning application can be downloaded from the Motorola Support site at: <http://www.motorola.com/enterprisemobility/contactsupport>

Linear Scanning

FR6000 Series with an integrated linear scanner have the following features:

- Reading of a variety of bar code symbologies, including the most popular linear, postal, and 1-D code types.
- Intuitive aiming for easy point-and-shoot operation.

Scanning Considerations

Typically, scanning is a simple matter of aim, scan, and decode and a few quick trial efforts master it. However, consider the following to optimize scanning performance:

- **Range**

Any scanning device decodes well over a particular working range — minimum and maximum distances from the bar code. This range varies according to bar code density and scanning device optics.

Scanning within range brings quick and constant decodes; scanning too close or too far away prevents decodes. Move the scanner closer and further away to find the right working range for the bar codes being scanned.

- Angle

Scanning angle is important for promoting quick decodes. When laser beams reflect directly back into the scanner from the bar code, this special reflection can “blind” the scanner.

To avoid this, scan the bar code so that the beam does not bounce directly back. But don't scan at too sharp an angle; the scanner needs to collect scattered reflections from the scan to make a successful decode. Practice quickly shows what tolerances to work within.

- Hold the FR6000 Series farther away for larger symbols.
- Move the FR6000 Series closer for symbols with bars that are close together.

✓ **NOTE** Scanning procedures depend on the application and FR6000 Series configuration. An application may use different scanning procedures from the one listed above.

1. Ensure that a scan enabled application is loaded on the FR6000 Series.
2. Aim the scan window at the bar code.




Figure 2-15 *Linear Scanning*

3. Press the scan button. Ensure the red scan beam covers the entire bar code. The Scan/Decode LED lights red to indicate that scanning is in process, then lights green and a beep sounds, by default, to indicate the bar code was decoded successfully.




Figure 2-16 *Linear Scanner Aiming Pattern*

4. Release the scan button.

Using IrDA

In a Microsoft Windows Mobile program (except Messaging), and Picture & Videos, you can exchange files using either infrared or Bluetooth.

✓ **NOTE** You can also beam files (not folders) from the **File Explorer** window. Tap and hold the item you want to send, then tap **Beam File** from the pop-up menu.

First activate the beam function before exchanging files with another IrDA device.

To activate the Beam function:

1. Tap **Start > Settings > Connections** tab > **Beam** icon.
2. Tap **Receive all incoming beams** check box.




Figure 2-17 *Beam Window*

3. Tap **ok**.

Infrared Connection

Using infrared, you can enable short-range file exchange between your FR6000 Series and another IrDA device.

Exchanging Files using IR Connection

Ensure that the IrDA function on both the FR6000 Series and the other device are enabled. To send files via IrDA connection:

1. Switch to the program where you created the item you want to send and locate the item in the list.
- ✓ **NOTE** Do not cover or block the IrDA window.
2. Align the IrDA port of the FR6000 Series with that of the IrDA device so that they are unobstructed and within a close range.




Figure 2-18 Align FR6000 Series with IrDA Device

3. Tap and hold the item, then tap Beam [type of item] on the pop-up menu.
4. Tap the device that you want to send the file to.




Figure 2-19 Beam Contact

To receive files via IrDA connection:

1. Align the IrDA port of the FR6000 Series with that of the other IrDA device so that they are unobstructed and within a close range.
2. On the other device, send the file to the FR6000 Series.
3. When the **Receiving Data** dialog displays, tap **Yes**.



Figure 2-20 Receive File

Chapter 3 Using GPS Navigation

Introduction

The FR6000 Series includes Global Positioning System (GPS) technology using the Qualcomm chip. GPS technology is based on a worldwide system of GPS satellites orbiting the earth that continuously transmit digital radio signals. These radio signals contain data on the satellites' locations and their exact clock time and are used to determine your location on the earth.

✓ **NOTE:** This chapter is for FR6074 and 6076 only.



WARNING! When using the FR6000 Series in a vehicle, it is the user's responsibility to place, secure and use in a manner that will not cause accidents, personal injury or property damage or obstruct their view. It is the responsibility of the driver to operate the vehicle in a safe manner, maintain observation of all driving conditions at all times, and not become distracted by the device to the exclusion of safe driving practices. It is unsafe to operate the controls of the device while driving.

Software Installation

Third-party GPS navigation software is required. Evaluation software is available from various suppliers.

If interested in purchasing GPS navigation software, check with the GPS software vendor (before purchasing, downloading, or installing any software) to determine that the application is compatible with the FR6000 Series. Refer to the application's user guide for application installation and setup information.

FR6000 Series GPS Setup

The GPS-enabled FR6000 Series uses Microsoft Windows Mobile 6.1, so the operating system automatically manages access to the GPS receiver to allow multiple programs to simultaneously access GPS data.

Ensure that the following settings are set on the FR6000 Series:

1. Tap **Start > Settings > System > External GPS** icon.

2. In the **Programs** tab, select *GPD1* from the **GPS program port** drop-down list.
3. In the **Hardware** tab, select *COM6* in the **GPS hardware port** drop-down list.
4. Tap **ok** to close the **Setting** window.

✓ **NOTE** If an application error message appears indicating that the COM port cannot be opened, ensure that a free COM port is selected in the **GPS hardware port** drop-down list.

Operation

Acquiring satellite signals may take a few minutes. It is best to be outside and have a clear, unobstructed view of the sky. Without a clear view, acquisition takes much longer and could result in the FR6000 Series being unable to compute the initial position quickly. When operating the device indoors access to the GPS signals may be limited or unavailable.

✓ **NOTE** When using a GPS navigation application, ensure that the FR6000 Series does not go into suspend mode. If the FR6000 Series suspends then the power to the GPS radio is removed. Upon resume the GPS receiver must reacquire a valid GPS signal, resulting in a delay of positional information.

GPS Maps on microSD Cards

GPS navigation software vendors may sell maps on microSD cards. If using a microSD card with the GPS navigation software:

1. Remove the Memory Card Cover on the side of the FR6000 Series.
2. Insert the microSD card into the slot.
3. Replace the Memory Card Cover.

Downloading GPS Data

Use this function to download GPS data to enhance GPS performance. This may require additional charge for data connection.

1. Tap **Start > Program > GPSXtra** icon.
2. Enter GPSXtra to download GPS data.




Figure 3-1 Download GPS data

Answering a Phone Call While Using GPS

If you receive a phone call while using your GPS navigation software:

1. Answer the phone call by pressing the **Answer** button.
2. Once you end the phone call, press the **End Call** button to resume the audio on the GPS software.

✓ **NOTE** Anytime you are using GPS on the FR6000 Series and you receive a phone call, the audio on the GPS navigation software is muted until you finish the call.

Losing the GPS Signal While in a Vehicle

GPS performance on the FR6000 Series may be affected if the vehicle has thermal glass windows and windshields, which can block the FR6000 Series from receiving a GPS signal from satellites. To improve GPS signal strength, place the FR6000 Series where there is a clear view of the sky. A direct line of sight is required between the FR6000 Series and the GPS satellites to access information from the satellites.

The Global Positioning System (GPS) is a system that allows the user to track their position anywhere on the earth.

Assisted GPS

GPS can be used in stand-alone or Assisted GPS (A-GPS) modes. A Stand-alone GPS receiver downloads data from GPS satellites. It can take several minutes to get a fix. By using GPS Location servers, A-GPS dramatically improves the performance of the Time To First Fix (TTFF) of GPS receivers by providing them with data that they would ordinarily have to download from the GPS satellites. With the A-GPS data, GPS receivers can operate faster and more reliably.

A-GPS follows the Secure User Plane Location (SUPL) protocol which allows the FR6000 Series to communicate with a location server.

Chapter 4 Using Bluetooth

Introduction

Bluetooth-equipped devices can communicate without wires, using frequency-hopping spread spectrum (FHSS) radio frequency (RF) to transmit and receive data in the 2.4 GHz Industry Scientific and Medical (ISM) band (802.15.1). Bluetooth wireless technology is specifically designed for short-range (30 feet/10 meters) communication and low power consumption.

FR6000 Series with Bluetooth capabilities can exchange information (e.g., files, appointments, and tasks) with other Bluetooth enabled devices such as phones, and other mobile computers. To use the FR6000 Series as a modem, create a dial-up modem connection between a computer and FR6000 Series.

Adaptive Frequency Hopping

Adaptive Frequency Hopping (AFH) is a method of avoiding fixed frequency interferers, and can be used with Bluetooth voice. All devices in the piconet (Bluetooth network) must be AFH-capable in order for AFH to work. There is no AFH when connecting and discovering devices. Avoid making Bluetooth connections and discoveries during critical 802.11b communications. AFH for Bluetooth consists of four main sections:

- Channel Classification - A method of detecting an interference on a channel-by-channel basis, or pre-defined channel mask.
- Link Management - Coordinates and distributes the AFH information to the rest of the Bluetooth network.
- Hop Sequence Modification - Avoids interference by selectively reducing the number of hopping channels.
- Channel Maintenance - A method for periodically re-evaluating the channels.

When AFH is enabled, the Bluetooth radio “hops around” (instead of through) the 802.11b high-rate channels. AFH coexistence allows Motorola mobile computers to operate in any infrastructure.

The Bluetooth radio in this FR6000 Series operates as a Class 2 device power class. The maximum output power is 2.5mW and the expected range is 32.8 feet (10 meters). A definition of ranges based on power class is difficult to obtain due to power and device differences, and whether one measures open space or closed office space.

✓ **NOTE** It is not recommended to perform Bluetooth wireless technology inquiry when high rate 802.11b operation is required.

Security

The current Bluetooth specification defines security at the link level. Application-level security is not specified. This allows application developers to define security mechanisms tailored to their specific need. Link-level security occurs between devices, not users, while application-level security can be implemented on a per-user basis. The Bluetooth specification defines security algorithms and procedures needed to authenticate devices, and if needed, encrypt the data flowing on the link between the devices. Device authentication is a mandatory feature of Bluetooth while link encryption is optional.

Pairing of Bluetooth devices is accomplished by creating an initialization key that is used to authenticate the devices and create a link key for them. Entering a common PIN number in the devices being paired generates the initialization key. The PIN number is never sent over the air. By default, the Bluetooth stack responds with no key when a key is requested (it is up to user to respond to the key request event). Authentication of Bluetooth devices is based-upon a challenge-response transaction. Bluetooth allows for a PIN number or passkey that is used to create other 128-bit keys used for security and encryption. The encryption key is derived from the link key used to authenticate the pairing devices. Also worthy of note is the limited range and fast frequency hopping of the Bluetooth radios that makes long-distance eavesdropping difficult.

Recommendations are:

- Perform pairing in a secure environment
- Keep PIN codes private and don't store the PIN codes in the mobile computer
- Implement application-level security.

Turning the Bluetooth Radio Mode On and Off

Turn off the Bluetooth radio to save power or if entering an area with radio restrictions (e.g., an airplane). When the radio is off, other Bluetooth devices cannot see or connect to the FR6000 Series. Turn on the Bluetooth radio to exchange information with other Bluetooth devices (within range). Communicate only with Bluetooth radios in close proximity.

✓ **NOTE** To achieve the best battery life turn off radios not in use.

Disabling Bluetooth

To disable Bluetooth, tap **Bluetooth** icon to enter **Wireless Manager**. Tap **Bluetooth** icon to change **on** to **off**. The **Bluetooth** icon changes to indicate that Bluetooth is disabled.




Figure 4-1 *Disable Bluetooth*

Enabling Bluetooth

To enable Bluetooth, tap **Bluetooth** icon to enter **Wireless Manager**. Tap **Bluetooth** icon to change **off** to **on**. The **Bluetooth** icon changes to indicate that Bluetooth is enabled.




Figure 4-2 *Enable Bluetooth*

Bond New Device(s)

The FR6000 Series can exchange information with bonded devices.

To find Bluetooth devices in the area:

1. Ensure that Bluetooth is enabled on both devices.
2. Ensure that the Bluetooth device to discover is in discoverable and connectable modes.
3. Ensure that the two devices are within 30 feet (10 meters) of one another.
4. Tap the **Bluetooth** icon to enter **Wireless Manager**. Then tap **Menu**.




Figure 4-3 Enter Bluetooth Window

5. Tap **Bluetooth Setting** to enter **Settings** window. Then tap **Add new device** to search for bluetooth devices.




Figure 4-4 Add new device Window

6. After the device appears, you have to select it and then tap **Next**.
7. Enter a passcode to establish a secure connection with other devices. Meanwhile enter the passcode on the target device.




Figure 4-5 Discover Devices Dialog Box

File Transfer Services

To transfer files between the FR6000 Series and another Bluetooth enabled device, ensure the FR6000 Series is discoverable and connectable.

✓ **NOTE** Some devices might not require a PIN. This depends upon the device's authentication.

1. Choose one file as below, tap **Menu > Beam picture** Menu.




Figure 4-6 Select file

2. Then choose the destination device, and wait till **Done** is showed.




Figure 4-7 Transfer file Window

Bluetooth Settings

Use the **Bluetooth Settings** window to configure the operation of the application. Tap **Menu > Settings**. The **Bluetooth Settings** window appears.

Device Info Tab

Use the Device Info tab to add and bond new devices. Please refer to **Bond new device(s)**.

Mode Tab

Use the **Mode** tab to configure the FR6000 Series' Bluetooth connection modes.




Figure 4-8 Explorer Settings - Device Info Tab

1. Before bonding a new device, make sure to turn on Bluetooth.
2. If you want other devices to find FR6000 Series, select “**Make this device visible to other devices**” check box.

COM Ports Tab

Use the **COM Ports** tab set specific outgoing ports for bonded devices.

1. Tap **New Outgoing Port**.




Figure 4-9 Add COM Ports

2. Select the device you want to add. Then tap **Next**.




Figure 4-10 *Select device*

3. Select a port from drop-down list. Then tap **Finish**.




Figure 4-11 *Select a Port for Device*

Chapter 5 ActiveSync

Introduction

To communicate with various host devices, install Microsoft ActiveSync (version 4.5 or higher) on the Host computer. Use ActiveSync to synchronize information on the mobile computer with information on the host computer. Changes made on the mobile computer or host computer appear in both places after synchronization.

ActiveSync software:

- Allows working with mobile computer-compatible host applications on the host computer. ActiveSync replicates data from the mobile computer so the host application can view, enter, and modify data on the mobile computer.
- Synchronizes files between the mobile computer and host computer, converting the files to the correct format.
- Backs up the data stored on the mobile computer. Synchronization is a one-step procedure that ensures the data is always safe and up-to-date.
- Copies (rather than synchronizes) files between the mobile computer and host computer.
- Controls when synchronization occurs by selecting a synchronization mode, e.g., set to synchronize continually while the mobile computer is connected to the host computer, or set to only synchronize on command.
- Selects the types of information to synchronize and control how much data is synchronized.

Installing ActiveSync

To install ActiveSync on the host computer, download version 4.5 or higher from the Microsoft web site at <http://www.microsoft.com>. Refer to the installation included with the ActiveSync software.

Mobile Computer Setup

The mobile computer can be set up to communicate either with a USB connection. [Chapter 8, Accessories](#) provides the accessory setup and cable connection information for use with the mobile computer. The mobile computer communication settings must be set to match the communication settings used with ActiveSync.

1. On the mobile computer tap **Start > Programs > ActiveSync** icon. The **ActiveSync** window appears.




Figure 5-1 ActiveSync Window

2. Tap **Menu > Connections**.
3. Select the connection type from the drop-down list.
4. Tap **OK** to exit the **Connections** window and tap **OK** to exit the **ActiveSync** window.
5. Proceed with installing ActiveSync on the host computer and setting up a partnership.

Setting Up an ActiveSync Connection on the Host Computer

To start ActiveSync:

1. Select **Start > Programs > Microsoft ActiveSync** on the host computer. The **ActiveSync** Window displays.
- ✓ **NOTE** Microsoft recommends installing ActiveSync on the host computer before connecting the mobile computer.




Figure 5-2 ActiveSync Window

- ✓ **NOTE** Assign each mobile computer a unique device name. Do not try to synchronize more than one mobile computer to the same name.
2. In the **ActiveSync** window, select **File > Connection Settings**. The **Connection Settings** window appears.




Figure 5-3 Connection Settings Window

3. Select the appropriate check box for the type of connection used.
4. Select the **Show status icon in Taskbar** check box.
5. Select **OK** to save any changes made.

Synchronization with a Windows Mobile 6 Device

✓ **NOTE** When a mobile computer with Windows Mobile 6 is connected to a host computer and an ActiveSync connection is made, the WLAN radio (if applicable) is disabled. This is a Microsoft security feature to prevent connection to two networks at the same time.

To synchronize with a Windows Mobile 6 device:

1. If the **Get Connected** window does not appear on the host computer, select **Start > All Programs > Microsoft ActiveSync**.



Figure 5-4 Synchronization Setup Wizard Window

2. Click **Next**.




Figure 5-5 *Synchronization Directly With a Server Window*

3. Select the check box to synchronize with a server running Microsoft Exchange if applicable.

4. Click **Next**.




Figure 5-6 *Synchronization Option Window*

5. Select the appropriate settings and click **Next**.




Figure 5-7 Wizard Complete Window

6. Click Finish.




Figure 5-8 ActiveSync Connected Window

During the first synchronization, information stored on the mobile computer is copied to the host computer. When the copy is complete and all data is synchronized, the mobile computer can be disconnect from the host computer.

For more information about using ActiveSync, start ActiveSync on the host computer, then see ActiveSync Help.

✓ **NOTE** The first ActiveSync operation must be performed with a local, direct connection. Windows Mobile retains partnerships information after a cold boot.

For more information about using ActiveSync, start ActiveSync on the host computer, then see ActiveSync Help.

Chapter 6 Using the Phone

Introduction

Use the FR6000 Series to make phone calls, set up speed dials, keep track of calls, and send text messages. Your wireless service provider may also provide other services such as voice mail, call forwarding, and caller ID.

Also use the integrated phone to connect to an ISP or work network in order to browse the Web and read e-mail. Connect to the Internet or work network over High-Speed Downlink Packet Access (HSDPA) (FR6076) using Cellular Line, or using the modem specified by the mobile operator.

✓ **NOTE:** This chapter is for FR6074 and 6076 only.

Accessing the Phone Keypad

Access the keypad regardless of the program in use. Applications on the FR6000 Series can be in use during a call.



Figure 6-1 Phone Keypads

To access the phone keypad tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad.

To receive calls when the FR6000 Series is suspended, leave the phone radio turned on and ensure the FR6000 Series is set to wake with any key.

Turning the Phone On and Off

Windows Mobile 6.1 devices include **Wireless Manager**, which provides a simple method of enabling and disabling the phone.

To open **Wireless Manager**, tap the **Connectivity** icon.




Figure 6-2 Opening Wireless Manager

Select **Wireless Manager**. The **Wireless Manager** window appears. To toggle on or off the phone, tap blue Phone bar.

To configure settings for a connection, tap **Menu > Phone Settings**.

✓ **NOTE** To receive calls when your device is suspended, leave the phone turned on.

Audio Modes

The FR6000 Series offers three audio modes for use during phone calls:

- **Handset Mode:** Switches audio to the speaker at the top front of the FR6000 Series, so you can use the FR6000 Series as a handset. This is the default mode.
- **Speaker Mode:** Use the FR6000 Series as if on speaker phone. Tap the **Speaker On** button to activate this mode. Tap the **Speaker Off** button to switch back to handset mode.
- **Headset Mode:** Connect a wired or Bluetooth headset to automatically switch audio to the headset. The FR6000 Series defaults to handset mode. When a wired headset is plugged into the FR6000 Series audio connector or a Bluetooth headset is configured for use with the FR6000 Series, the earpiece and speakerphone are muted and audio is heard through the headset.

✓ **NOTE** While using a Bluetooth headset during a call, the mobile computer will not go into suspend mode.



Handset Mode
Figure 6-3 *Audio Modes*

Speaker Mode

Headset Mode

Using a Wired Headset

You can use a stereo headset for audio communication when using an audio-enabled application. To use a headset, plug the headset jack into the audio connector on the side of the FR6000 Series. Set the FR6000 Series' volume appropriately before putting the headset on. Plugging a headset into the jack mutes the speaker.

For the best audio performance, Motorola recommends a 2.5mm jack headset, see [Accessories on page 16](#).




Figure 6-4 *Using a Headset*

Using a Bluetooth Headset

You can use a Bluetooth headset for audio communication when using an audio-enabled application. See [Chapter 4, Using Bluetooth](#) for information on connecting a Bluetooth headset to the FR6000 Series. Set the FR6000 Series' volume appropriately before putting the headset on. When a Bluetooth headset is connected the speakerphone is muted.

It is recommended for phone conversations to use the Bluetooth Hands-free profile instead of the Headset profile. See [Chapter 4, Using Bluetooth](#) for more information.

✓ **NOTE** When using a Bluetooth headset during a call, the FR6000 Series power button is disabled and the FR6000 Series will not go into suspend mode. Once the call is completed, the power button functionality is enabled.

The following dialog box displays when a Bluetooth headset connection is established.



Figure 6-5 WWAN Bluetooth Audio Notification Dialog Box

Adjusting Audio Volume

Use the Volume Control Slider or the keypad keys to adjust the volume of the ringer when not in a call and the audio volume when in a call.



Phone volume slider

Figure 6-6 Phone Volume Slider

To adjust the volume tap the **Speaker** icon in the **Title** bar. Move the slider up or down to adjust the volume.

✓ **NOTE** Adjust the conversation phone volume during a call. Adjusting the volume while not in a call affects the ring and notification sound levels.

Making a Call

- ✓ **NOTE** You can make emergency calls even when the FR6000 Series is locked or when a SIM card is not installed. See [Making an Emergency Call on page 73](#) for more information.

With the FR6000 Series, you can make a call from the phone, contacts, speed dial and call history.

Using the Phone

To make a call using the phone keypad:

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad.
2. From the **Phone** keypad, tap the number to call.
3. Tap **Talk**.
4. Tap **End** to stop dialing or end the call.

- ✓ **NOTE** Alternatively, use the green and red phone keys on the FR6000 Series keypad to dial (green) and end (red) calls. If you tap a wrong number, tap Delete key to erase each subsequent digit of a number. To erase the entire number, tap and hold the Delete key.

Using Contacts

Use Contacts to make a call without looking up or entering the phone number. To make a call from Contacts:

1. Tap **Start > Contacts**.
2. From the contact list, tap and hold the contact name.




Figure 6-7 *Contacts Menu*

3. Tap **Call Work**, **Call Home** or **Call Mobile**.

- ✓ **NOTE** To make a call from an open contact, tap the number to call. See On-Device Help for more information about Contacts.

Using Call History

To make a call using Call History:

1. Tap **Start** > **Phone** or press the green phone key on the FR6000 Series' keypad.
2. From the Phone keypad, tap **Call History**.



Figure 6-8 Call History

3. Tap the phone icon next to the number to begin dialing and return to the phone keypad.
4. Tap **End** or press the red phone key on the FR6000 Series keypad to stop dialing or end the call.

Making a Speed Dial Call

Use Speed Dial to call someone saved in the speed dial directory. To make a speed dial call:

1. Tap **Start** > **Phone** or press the green phone key on the FR6000 Series' keypad.
2. From the Phone keypad, tap and hold the speed dial location number assigned to a contact. (To dial a one-digit speed dial location number, tap and hold the speed dial number. To dial a two-digit speed dial location number, tap the first digit and then tap and hold the second digit.) or from the Phone keypad, tap **Speed Dial** and tap the speed dial location number of the desired contact in the list.




Figure 6-9 Speed Dial Contact List

3. To stop dialing or end the call, tap **End** or press the red phone key on the FR6000 Series keypad.

Making an Emergency Call

Your service provider programs one or more emergency phone numbers, such as 911 or 999, that you can call under any circumstances, even when your phone is locked or the SIM card is not inserted (on FR6076/FR6074). Your service provider can program additional emergency numbers into your SIM card. However, your SIM card must be inserted in your phone in order to use the numbers stored on it. See your service provider for additional information.

When the numeric keypad phone is locked, press the Orange key twice to set the keypad to numeric mode and then enter the emergency number.

✓ **NOTE** Emergency numbers vary by country. Your phone's pre-programmed emergency number(s) may not work in all locations, and sometimes an emergency call cannot be placed due to network, environmental, or interference issues.

Answering a Call

A dialog box appears on the FR6000 Series when it receives an incoming call. If the phone is set to ring, a ring tone sounds. Answer or ignore the incoming call.

To answer an incoming call tap **Answer** on the **Phone - Incoming** dialog or press the green phone key on the FR6000 Series keypad.




Figure 6-10 Incoming Call

To ignore the incoming call tap **Ignore**. This may send the caller to voice mail, depending on the service provider. Otherwise, this presents busy signal to the calling party.

To end the call tap **End** or press the red phone key on the FR6000 Series keypad.

Incoming Call Features

- If you receive a call while in a call, tap **Wait** to place the call in call waiting.
- You can use other programs on the FR6000 Series during a call. To switch back to Phone, tap **Talk** or tap **Start >Phone**. Tap **End** to end the call.
- If a caller isn't in your contact list, create a contact during the call or from Call History by tapping **Menu >Save to Contacts**.
- To terminate a call when a second call comes in and answer the waiting call, tap **End** on the Phone keypad to disconnect the active call, then tap **Answer** or press the **Send** key to answer the waiting call.
- To hold the current call and answer a waiting call, tap **Answer** or press the **Send** key to place the current call on hold and answer the incoming call.
 - To put a call on hold to call another number or answer an incoming call, tap **Hold** on an FR6076/FR6074. To move from one call to another, tap **Swap** on an FR6076/FR6074

Smart Dialing

Smart Dialing makes it easy to dial a phone number. When you start entering numbers or characters, Smart Dialing automatically searches and sorts the contact entries on the SIM card, in Contacts, and the phone numbers in Call History (including incoming, outgoing, and missed calls). You can then select the desired number or contact from the filtered list to dial.

Open the Phone screen, then tap the keys on the Phone keypad that correspond to the phone number or contact to call. The contact panel lists contacts that match the sequence that you entered.

Smart Dialing starts looking for numbers or contacts that match the sequence entered. To find a phone number:

- Enter the first one or two digits to find a phone number in Call History.
- Enter the first three digits or more to find a phone number from the saved Contacts and SIM card.

To find a contact name:

- Enter the first letter of a contact's first name or last name. Smart Dialing searches for the letter starting from the first character of a contact name as well as from the character that appears after a space, dash, or underscore in a contact name. For example, if you tap number "2" which is associated with [a, b, c] on the Phone keypad, contact names such as the following will be considered matches: "Smith, Bernard", "Adams, John", "Carlson, Eileen", "Dillon, Albert", "Childs, Larry", "Cooper, Robert" and "Parks, Celine".
- If the matching list is long narrow down the search further by entering another letter. Using the same example above, tap "3" which is associated with (d, e, f), the matching list is narrowed down to the following names: "Smith, Bernard", "Adams, John", and "Parks, Celine".




Figure 6-11 *Finding a Contact*

To make a call or send a text message using Smart Dialing:

1. Begin entering the first few numbers or characters.
2. In the Smart Dialing panel, use the up and down arrows on the keypad to navigate to the desired contact or phone number.
3. When the correct contact is selected, press **TALK** to make a voice call.
4. To send a text message to the selected contact, tap **Menu > Send Text Message**.
5. To call a different phone number associated with the selected contact, tap the contact name and select the phone number to call.

Muting a Call

During a call, you can mute the microphone so you can hear the person on the line but he or she cannot hear conversation from the microphone. This is useful when there is conversation or background noise on your end.

To mute or unmute a call:

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad.
2. Make a call.
3. Tap **Mute** on the display to mute the audio. The **Mute** icon appears.



Figure 6-12 *Mute Button and Icon*

Taking Notes

To create a note during a call, tap **Note** on the display, then enter the note. For more information about creating notes see the Windows On-Device Help.

To access a note created during a call:

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad.
2. From the Phone keypad, tap **Call History**.
3. Tap and hold the number or the **Note** icon for the phone call entry containing the note.




Figure 6-13 Call History - Notes Menu

4. Tap **View Note**.




Figure 6-14 Call History - Notes

5. Tap **ok** to exit.

✓ **NOTE** Also access notes directly from the Notes application by tapping **Start > Notes**.

Using Speed Dial

Create speed dial numbers to dial frequently called numbers with a single tap. Before creating a speed dial entry, ensure the phone number exists in Contacts.

Adding a Speed Dial Entry

To add a speed dial entry from the phone keypad:

1. Ensure the contact and phone number are in the Contacts list.
2. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad.
3. Tap **Menu > Speed Dial > Menu > New**.



Figure 6-15 *Contacts*

4. Tap the desired contact name and number in the list.



Figure 6-16 *Speed Dial Contact Location*

5. In the **Location** field, tap the up/down arrows to select an available location to assign as the new speed dial entry. The first speed dial location is reserved for voice mail.
6. Tap **ok** to add the contact to the speed dial list.



Figure 6-17 Speed Dial Contact List

7. Tap **ok** to exit the **Speed Dial Contact List**.

To add a speed dial entry from the **Contacts** window:

1. Tap **Start > Contacts**.




Figure 6-18 Contacts

2. Tap a contact name.
3. Tap **Menu > Add to Speed Dial**.




Figure 6-19 Speed Dial Contact Location

4. Tap the up/down arrows to select an available location to assign as the new speed dial entry. The first speed dial location is reserved for voice mail.
5. Tap **ok**.

Editing a Speed Dial Entry

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad.
2. Tap **Menu > Speed Dial**.




Figure 6-20 Speed Dial Contact List

3. Tap and hold the contact name.
4. Tap **Edit...**
5. Change the name, phone number, or location information.
6. Tap **ok**.

✓ **NOTE** Editing names and phone numbers in **Speed Dial** does not alter contact information in **Contacts** (**Start > Contacts**).

Deleting a Speed Dial Entry

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad.
2. Tap **Menu > Speed Dial**.
3. Tap and hold the contact name.




Figure 6-21 Speed Dial Delete Menu

4. Tap **Delete**.
5. Tap **Yes** to confirm permanently deleting the speed dial entry.

✓ **NOTE** Deleting names and phone numbers in *Speed Dial* does not delete the contact information in **Contacts** (**Start > Contacts**).

Using Call History

Use Call History to call someone who was recently called, or recently called in. Call History provides the time and duration of all incoming, outgoing, and missed calls. It also provides a summary of total calls and easy access to notes taken during a call. [Table 6-1](#) lists the call history icons that appear in the **Call History** window.

Table 6-1 *Call History Icons*

Icon	Description
	This icon appears next to the contact information for all outgoing calls.
	This icon appears next to the contact information for all incoming calls.
	This icon appears next to the contact information for all missed calls.

Managing Call History

Change views, reset the call timer, and delete calls to manage the calls stored in Call History.

Changing the Call History View

1. Tap **Start** > **Phone** or press the green phone key on the FR6000 Series' keypad to display the Phone keypad.
2. From the Phone keypad, tap **Call History**.
3. Tap **Menu** > **Filter** to show the menu.




Figure 6-22 *Call History - All Calls/Show Menu*

4. Select a view type from the menu to display only missed calls, outgoing calls, incoming calls, or calls listed alphabetically by caller name.
5. Tap **ok** to exit the **Call History** window.

Resetting the Recent Calls Counter

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad to display the Phone keypad.
2. From the Phone keypad, tap **Call History**.
3. Tap **Menu**.




Figure 6-23 Call History - Tools Menu

4. Select **Call Timers...**




Figure 6-24 Call History - Call Timers

5. Tap **Reset**. (The **All Calls:** counter cannot be reset.)
6. Tap **ok** to exit the **Call Timers** window.

Deleting Call History Items by Call Date

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad to display the Phone keypad.
2. From the Phone keypad, tap **Call History**.
3. Tap **Menu > Call Timers...**




Figure 6-25 Call History - Call Timers

4. In the **Delete call history items older than:** drop-down list select a time period on which to base deletion of stored items.
5. Tap **ok** to exit the **Call Timers** window.

Deleting All Call History Items

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad to display the Phone keypad.
2. From the Phone keypad, tap **Call History**.
3. Tap **Menu**.




Figure 6-26 Call History - Tools Menu

4. Select *Delete all calls*.




Figure 6-27 Call History - Delete All Dialog

5. Tap **Yes**.
6. Tap **ok** to exit the **Call History** window.

Viewing Call Status

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad to display the Phone keypad.
2. From the Phone keypad, tap **Call History**.
3. Tap an entry. The Call Status window appears.




Figure 6-28 Call History - Detail

✓ **NOTE** When more than one call is on the phone line, only the duration of the first call is recorded.

4. Tap **ok** and then **ok** to exit.

Using the Call History Menu

Use the Call History menu to dial voice mail, access the Activation Wizard, save to contacts, view a note, delete a listing, send an SMS, and make a call.

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad to display the Phone keypad.
2. From the Phone keypad, tap **Call History**.
3. Tap and hold an item in the list.




Figure 6-29 Call History - Menu

4. Select an applicable item from the menu, as needed.

5. Depending on the item selected, the appropriate window displays. For example, select **Send SMS** to display the **Inbox** window.
6. Tap **ok** to exit the **Call History** window.

Swapping Calls

To move between two or more phone calls:

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad to display the phone keypad.
2. Enter the first phone number and press **Talk**. When the call connects, **Hold** appears on the keypad.



Figure 6-30 *Call Swapping - Hold*

3. Tap **Hold** on to place the first number on hold.
4. Enter the second number and tap **Talk**.



Figure 6-31 *Call Conferencing - Conferencing*

5. Tap **Swap** to move from one call to the other.
6. Tap **End** or press the red phone key on the FR6000 Series keypad to end each call.

Conference Call

- ✓ **NOTE** Conference Call and the number of conference calls allowed may not be available on all services. Please check with your service provider for Conference Call availability.

To create a conference phone session with multiple people:

1. Tap **Start > Phone** or press the green phone key on the FR6000 Series' keypad to display the Phone keypad.
2. Enter the first phone number and press **Talk**. When the call connects, **Hold** appears on the keypad.



Figure 6-34 Conference Call - Hold

3. Tap **Hold** to place the first call on hold.
4. Enter the second phone number and tap **Talk**.
5. After the call is answered, tap **Menu > Conference** to place the calls in conference mode.




Figure 6-35 Creating a Conference Call

6. Tap **Hold** to place the conference on hold.
7. Enter another phone number and tap **Talk**.
8. After the call is answered, tap **Menu > Conference** to place all the calls in conference mode.
9. Repeat steps 6 through 8 for up to six phone numbers.

10. Tap **End** or press the red phone key on the FR6000 Series keypad to end the conference call.

✓ **NOTE** To speak privately with one party during a conference call, tap **Menu > Private**. To include all parties again, tap **Menu > Conference**.




Figure 6-36 Creating a Private Call

Text Messaging

Use the **Text Messages** window to send and receive text messages to and from mobile phones. The text can contain words, numbers, or an numeric combination no longer than 160 characters.

Short text messages delivered over mobile networks transmit from the sending FR6000 Series, are stored in a central short message center, then forwarded to the destination mobile device. If the recipient is not available, the message is stored and can be sent later.

Viewing Text Messages

To view a text message:

You can view a text message whether the phone is on or off. When the phone is on, you can view a text message from its notification callout. Tap the **text message notification** icon on the navigation bar to display the message.



Figure 6-38 New Text Message Notification

The Caller Identification feature matches incoming text message numbers with those stored in **Contacts** so you know who is sending you a message. Furthermore, the **New Text Message** dialog box gives you the option to call the sender or save, dismiss, or delete the message.



Figure 6-39 New Text Message Options

When the phone function is off, you can still view received text message in Messaging:

1. Tap **Start > Messaging > Text Messages**, or on the Today screen, tap **Text Messages**.

Tap Text Messages.




Figure 6-40 Text Messaging on Today Screen

The **Messaging** window appears.




Figure 6-41 Messaging Window

2. In the message list, tap a **Text Messages**.




Figure 6-42 Text Messages List

3. Tap **Reply** to reply the message.

If the phone is turned off and you tried to call the sender, send a reply, or forward the message, you are prompted to turn the phone function on.

Sending a Text Message

To create a text message:

1. On the **Phone** screen, select a contact name that you want to send a message to.
2. Tap **Menu > Send Text Message**.



Figure 6-43 Phone Screen Contact List

3. Compose your message.



Figure 6-44 Create Text Message

- The auto-correct feature automatically fixes common spelling errors as you type so your messages are more accurate.
- The character counter lets you see and control the size of the message as you compose.
- If you want to know if your text message was received, tap **Menu > Message Options**, then select the **Request SMS** text message delivery notification check box.




Figure 6-45 *Message Options Window*

4. Tap **Send** when you've finished the message.

If the phone is turned on, your text message is sent. If it's off, you are prompted to turn on the phone.

If you do so, the message is sent; otherwise when you tap **ok**, the message is saved in the **Drafts** folder and sent when the phone is turned on.

If you are out of coverage area, the message is saved in the **Drafts** folder and sent when you return to a coverage area.

- ✓ **NOTE** On FR6076 and FR6074 devices, the message remains in the **Drafts** folder and has to be manually re-sent when you return to a coverage area.

Chapter 7 GSM Configuration

Introduction

This chapter explains how to verify FR6074 and FR6076 service on an Global System for Mobile communications (GSM) wireless network and establish settings. GSM networks deliver mobile voice and data services, such as Short Message Service (SMS)/Text Messaging, with full roaming capabilities across the world. High-speed Downlink Packet Access (HSDPA) enabled networks offer Internet-based content and packet-based data services. This enables services such as internet browsing, e-mail on the move, powerful visual communications, multimedia messages, and location-based services. When using the FR6074, FR6076 as a phone, services can include speed dialing, call tracking, voice mail, call forwarding, conference calling, and caller ID, depending on the type of service. Also use the integrated phone as a modem to connect the FR6074/FR6076 to an ISP or work network. The GSM enabled FR6074, FR6076 can connect to the Internet or work network using Cellular Line, or using the modem specified by the mobile phone service provider.

✓ **NOTE** Before using an FR6074/FR6076 on a wireless network, first select a provider, establish a voice and data-enabled service plan, and configure the FR6074/FR6076 (where applicable). Refer to the *FR6074/FR6076 User Guide* for information on how to use the phone and services.

FR6074/FR6076 Service Verification

FR6074/FR6076 phone and data services require a live SIM card, obtained from a service provider, installed in the FR6074/FR6076. The SIM card has embedded circuitry on one side of its surface which, when inserted into an FR6074/FR6076 phone, provides phone service. The SIM card provides a phone number, determines the features or services available to the subscriber, and identifies the subscriber to the network.

In addition to SIM card installation, the FR6074/FR6076 may require various settings to operate as a phone with data connection features.

Ensuring Network Coverage

1. Ensure an activated SIM card, from the phone service provider, is installed in the

FR6074/FR6076.

✓ **NOTE** The SIM card must be enabled to connect to the network.

2. Verify active phone and data services by tapping  to display the **Phone** dialog. The Carrier name appears in the dialog box.



Figure 7-1 Connectivity Dialog

3. Verify SIM card functionality:
 - a. Tap **Start > Settings > Personal tab > Phone icon > Network tab**.




Figure 7-2 Phone Settings Window - Network Tab

- b. Ensure the service provider's network appears in the **Current network:** field.
 - c. If the network does not appear, tap **Find Network**. If the network still does not appear, verify that the SIM card was installed correctly. If it was, and no network appears, contact the service provider.

Configuring a Data Connection

A data connection allows Internet access across a wireless network.

To set up a new data connection:

1. Acquire an Access Point Name (APN) from the service provider.
2. Tap **Start > Settings > Connections tab > Connections icon > Tasks tab**.



Figure 7-3 Connections Window

3. Under **My ISP** select **Add a new modem connection**.




Figure 7-4 Connections Window - Make New Connection

4. Enter a connection name in the *Enter a name for the connection:* text box.
5. Select **Cellular Line (GPRS)** from the **Select a modem:** drop-down list.
6. Tap **Next**.




Figure 7-5 Connections Window - Access Point Name

7. Enter the APN from the service provider in the **Access point name:** text box.

8. Tap Next.




Figure 7-6 Connections Window - User Name & Password

9. Enter a username in the User name text box, if required by the service provider.
10. Enter a password in the Password text box, if required by the service provider.
11. Enter a domain name in the Domain text box, if required by the service provider.
12. Tap Finish.
13. Tap ok to exit Connections.

Establishing a Data Connection

1. Ensure a SIM card is installed in the FR6074/FR6076.
2. Configure a GPRS data connection. See [Configuring a Data Connection on page 92](#).
3. Tap the connectivity icon , , or  at the top of the screen.




Figure 7-7 Connectivity Dialog Box

4. Tap Settings.
5. Tap Connections icon.
6. Tap Managing existing connections.

7. Tap and hold on the data connection until a menu appears.




Figure 7-8 Data Connection

8. Select Connect.



Figure 7-9 Connecting Using GPRS

9. If the SIM card is protected with a Personal Identification Number (PIN), a dialog box pops up requesting the appropriate PIN to unlock the SIM card. In this case, enter the PIN and tap **ok**.
- ✓ **NOTE** Place emergency calls at any time, without entering a PIN or a SIM card.
10. When a connection is established, launch **Internet Explorer** to browse the Internet or launch an applicable application.

Ending a Data Connection

To cancel a data connection in progress, tap **Cancel** in the **Connecting...** dialog window.

To end an established data connection:

1. Tap **G**, **E**, or **H** to display the **Connectivity** dialog box.



Figure 7-10 Connectivity Dialog Box

2. Tap Disconnect.

- ✓ **NOTE** Tapping **Disconnect** during an active data transfer (e.g., downloading a web page) automatically reconnects the connection. You cannot disconnect the connection until the data transfer is complete.

FR6074/FR6076 Settings

Use the **Phone Settings** window to customize settings, such as the ring type and ring tone for incoming calls, security options, and other options depending on the type of service.

Phone

Use the **Phone** tab to customize ring type, ring tone, keypad tone, and security options.

Tap **Start > Settings > Personal tab > Phone icon > Phone tab** or **Start > Phone > Menu > Options > Phone tab**.



Figure 7-11 FR6074/FR6076 Phone Window - Phone Tab

Sounds

1. **Phone Number** automatically displays on the **Phone** tab when a live SIM card is installed.

2. Select a ring type from the **Ring type:** drop-down list. The ring type changes the way the FR6074/FR6076 rings when you receive an incoming call. Regardless of the ring type selected, a dialog box appears on the FR6074/FR6076's display for incoming calls.
3. Select a ring tone for incoming calls from the **Ring tone:** drop-down list. To hear a sample of the selected ring tone, tap . Tap  to end the ring tone.
 - ✓ **NOTE** To use custom .wav, .mid, or .wma files as ring tones, use ActiveSync on the host computer to copy the file to the /Windows/Rings folder on the FR6074/FR6076. Then select the sound from the ring tone list.
4. Select a keypad tone from the **Keypad:** drop-down list. This selection determines the tone that sounds when entering a phone number on the keypad. Select **Short tones** or **Long tones** to specify the duration of the sound when you press a number on the keypad. Select **Off** to disable tones.
 - ✓ **NOTE** Turning off sounds saves power and prolongs battery life.

Security

Enabling a PIN

- ✓ **NOTE** Place emergency calls at any time, without requiring a PIN or a SIM card.

To require a PIN when using the phone:

1. From the **Phone** tab ([Figure 7-11](#)), select the **Require PIN when phone is used** check box under **Security**.




Figure 7-12 Enter PIN

2. Use the touch keypad to enter a four to eight digit PIN.
3. Tap **Enter** to enable the PIN and return to the **Phone** tab.

Changing a PIN



CAUTION If you enter an incorrect PIN, the message "SIM PIN incorrect: Try again" appears. After three consecutive incorrect attempts, the SIM card is blocked. The phone does not allow you to attempt to enter your PIN again and you must obtain a PIN Unblock Key from your service provider.

1. From the **Phone** tab ([Figure 7-11](#)), tap **Change PIN**.

2. Use the touch keypad to enter the current PIN.
3. Tap **Enter**.
4. Use the touch keypad to enter a new four to eight digit PIN.
5. Tap **Enter**.
6. Reenter the new PIN for confirmation and tap **Enter**.
7. Tap **ok** to confirm the change.

Disabling a PIN

1. From the **Phone** tab ([Figure 7-11](#)), deselect the **Require PIN when phone is used** check box.
2. Use the touch keypad to enter the current PIN.
3. Tap **Enter**.
4. Tap **ok** to confirm the change.
5. Tap **ok** to exit settings.

Services

Use the **Services** tab to configure settings for subscribed phone services. For example, block certain types of incoming and/or outgoing calls ([page 95](#)), disclose the caller's identity when making outgoing calls ([page 95](#)), forward incoming calls to a different phone number ([page 95](#)), receive notification of incoming calls when a phone session is in use, and set up voice mail and short message service ([page 88](#)).

1. Tap **Start > Settings > Personal tab > Phone icon > Services** tab.




Figure 7-13 FR6074/FR6076 Phone Window - Services Tab

2. Select a service from the list and tap **Get Settings...**
3. Change services settings as follows.

Call Barring (Call Blocking)

Use call barring to block certain types of incoming and/or outgoing calls. Select the type of incoming and/or outgoing calls to block.




Figure 7-14 Call Barring/Call Blocking

Caller ID

Enable caller ID to reveal the identity of the person making an outgoing call. Select the **Everyone** radio button to always display the caller ID. Select the **No one** radio button to prevent the caller's identity from appearing to others.




Figure 7-15 Caller ID

Call Forwarding

✓ **NOTE** Call Forwarding may not be available on all networks. Check with your service provider for availability.

Use call forwarding to forward incoming calls to a different phone number.

- To forward all calls to a different phone number:
 - select the **Forward all incoming phone calls** check box.
 - enter the phone number to receive forwarded calls in the **To:** text box.
- To forward incoming calls to a different phone number based on a specific situation, select one or more of the check boxes under **Forward phone calls only if:**.
 - **No answer:** enter the phone number to receive forwarded calls only when the phone cannot be answered. Then select a time period from the **Forward after:** drop-down list. Options are 5, 10, 15, 20, 25, and 30 seconds.
 - **Unavailable:** enter the phone number to receive forwarded calls only when the phone is turned off or the user is unreachable.
 - **Busy:** enter the phone number to receive forwarded calls only when the line is busy.




Figure 7-16 Call Forwarding

Call Waiting

✓ **NOTE** Call Waiting may not be available on all networks. Check with your service provider for availability.

Call waiting notifies you of an incoming call when the phone is in a phone session. Select the **Notify me** radio button to enable call waiting. Select the **Do not notify me** radio button to disable call waiting.




Figure 7-17 Call Waiting

Voice Mail and Text Messages

To use voice mail and send short messages, enter the voice mail and/or text message phone number in the appropriate text boxes.




Figure 7-18 Voice Mail and Text Messages

Fixed Dialing

Use Fixed Dialing to restrict the phone to dial only the phone number(s) or area code(s) specified in a Fixed Dialing list.

1. Select **Fixed Dialing** and tap **Get Settings**.




Figure 7-19 Fixed Dialing Window

2. Select the **Enable fixed dialing** check box.
3. To add a number to the list, tap **Menu > Add**.
4. Enter the phone number or area code to restrict and tap **Done**.
5. Repeat steps 3 and 4 to add more numbers, and tap **Done** twice when complete.
6. Enter **PIN2** and tap **Done**.

Network

Use the **Network** tab to view available networks, determine the order in which the phone accesses another network if the current network is unavailable, and specify whether to change networks manually or automatically. The current network remains active until it's changed, the signal is lost, or the SIM card is changed.

The network the FR6074/FR6076 currently uses appears in the **Current network:** field at the top of the window.

Changing Networks Manually

1. Tap **Start > Settings > Personal tab > Phone icon > Network tab** or **Start > Phone > Menu > Options > Network tab**.




Figure 7-20 FR6074/FR6076 Phone Window - Network Tab

- 2 From the **Network selection** drop-down list, select **Manual**.




Figure 7-21 Choose Network

3. From the **Choose Network** window, select the network to use.
4. Tap **OK**.

Viewing Available Networks

To view all wireless networks available:

1. Tap **Start > Settings > Personal tab > Phone icon > Network tab** or **Start > Phone > Options > Network tab**.




Figure 7-22 FR6074/FR6076 Phone Window - Network Tab

2. Tap **Find Network**.




Figure 7-23 Choose Network

3. From the **Choose Network** window, select the network to use.
4. Tap **OK**.

Setting Preferred Networks

Set networks in a preferred order of access. Setting preferred networks allows the FR6074/FR6076 to access a second preferred network if the first is unavailable.

1. Tap **Start > Settings > Personal tab > Phone icon > Network tab** or **Start > Phone > Menu > Options > Network tab**.




Figure 7-24 FR6074/FR6076 Phone Window - Network Tab

2. Tap **Set Networks** to view all available networks.




Figure 7-25 Preferred Networks

3. Select the preferred networks by tapping one or more check boxes.
4. Tap **Move Up** and **Move Down**, as necessary, to place the selected networks in the preferred order.
5. Tap **ok** to send the new settings to the network.
6. From the **Network** tab, select **Automatic** from the **Network selection** drop-down list.
7. Tap **ok** to exit settings.

Phone Info

Use the *Phone Info* tab to view hardware and software information about the phone.

1. Tap **Start > Settings > Personal tab > Phone icon > Phone Info tab** or **Start > Phone > Menu > Options > Phone Info tab**.




Figure 7-26 FR6074/FR6076 Phone Window - Phone Info Tab

2. Tap **ok** to exit settings.

Network Time Synchronization

The FR6074/FR6076 can support NITZ (Network Identity and Time Zone) feature, and this feature depends on network carrier.

Chapter 8 Accessories

Introduction

FR6000 Series accessories, listed below, provide a variety of product support capabilities.

- Single Slot USB/Serial Cradle - Charges the FR6000 Series main battery and a spare battery. Synchronizes the FR6000 Series with a host computer through a USB connection.
- Four Slot Battery Charger - Charges spare standard capacity battery.
- Auto Charge Cable - Plugs into a vehicle cigarette lighter to charge the FR6000 Series while on the road.
- Charge Only Cable - Provides power to the FR6000 Series.
- USB Charging Cable - Provides power to the FR6000 Series and USB communication with a host computer.
- Headset - Used in noisy environments.

Single Slot USB/Serial Cradle

This section describes how to use a Single Slot USB/Serial cradle with the FR6000 Series.

The Single Slot USB/Serial Cradle:

- Provides 5.4 VDC power for operating the FR6000 Series.
- Synchronizes information between the FR6000 Series and a host computer.
- Charges the FR6000 Series' battery.
- Charges a spare battery.

Charging the FR6000 Series Battery

Connect the cradle to power. Insert the FR6000 Series into the slot to begin charging.

✓ **NOTE** Insert the adaptor module into the cradle before inserting the FR6000 into the cradle.

* It is recommended that this product be charged for 24 hours before the first use to ensure that the internal battery is fully charged.





Figure 8-1 *FR6000 Series Battery Charging*

Charging the Spare Battery



Spare Battery

Figure 8-2 *Spare Battery Charging*

Battery Charging Indicators

The Single Slot USB/Serial Cradle charges the FR6000 Series' main battery and a spare battery simultaneously.

The FR6000 Series' charge LED indicates the status of the battery charging in the FR6000 Series. See [Table 1-2 on page 21](#) for charging status indications.

The spare battery charging LED on the cradle indicates the status of the spare battery charging in the cradle. See [Table 6-1](#) for charging status indications.

The 3600 mAh battery is fully charged in approximately six hours.

Charging Temperature

Charge batteries in temperatures from 0°C to 45°C (32°F to 113°F). Charging is intelligently controlled by the FR6000 Series.

To accomplish this, for small periods of time, the FR6000 Series or accessory alternately enables and disables battery charging to keep the battery at acceptable temperatures. The FR6000 Series or accessory indicates when charging is disabled due to abnormal temperatures via its LED. See [Table 1-2 on page 21](#) and [Table 8-1](#).

Table 8-1 Spare Battery LED Charging Indicators

Spare Battery LED (on cradle)	Indication
Off	Battery is not charging; battery is not inserted correctly in the cradle; cradle is not powered
Slow Blinking Amber	Spare battery is charging.
Solid Amber	Charging complete.
Fast Blinking Red	Charging Error

Four Slot Battery Charger

This section describes how to use the Four Slot Battery Charger to charge up to four FR6000 Series batteries.

FR6000 Series Battery Shim Installation




Figure 8-3 *FR6000 Series Battery Shim Installation*

✓ **NOTE** To purchase additional shims, contact your local account manager or Motorola, Inc. Part number: KT-76490-01R.

Spare Battery Charging

1. Connect the charger to a power source.
2. Insert the spare battery into a spare battery charging well and gently press down on the battery to ensure proper contact.




Figure 8-4 *Four Slot Battery Charger*

Battery Charging Indicators

The charger has an amber LED for each battery charging well. See [Table 8-1](#) for charging status indications. The 3600 mAh battery is fully charged in approximately six hours.

Charging Temperature

Charge batteries in temperatures from 0°C to 45°C (32°F to 113°F). Charging is intelligently controlled by the FR6000 Series.

To accomplish this, for small periods of time, the charger alternately enables and disables battery charging to keep the battery at acceptable temperatures. The charger indicates when charging is disabled due to abnormal temperatures via its LED. See [Table 8-1](#).

Table 8-2 *Spare Battery LED Charging Indicators*

LED	Indication
Off	No spare battery in slot; battery is not charging; battery is not inserted correctly in the charger; charger is not powered.
Slow Blinking Amber	Spare battery is charging.
Solid Amber	Charging complete.

Headset

Use the headset to communicate via Voice-Over-IP (VOIP) or for audio playback and telephony applications. To connect the headset, remove the plug from the headset jack at the top of the FR6000 Series and insert the headset connector. Contact a Motorola representative for compatible headsets.

For best performance, Motorola recommends a 2.5mm jack headset, p/n 90-17C28-001R.




Figure 8-5 *Headset Connection*

Cables

This section describes how to set up and use the cables. The cables are available with a variety of connection capabilities.

The following communication/charge cables are available:

- USB Client Charge cable (standard-A connector and a barrel receptacle for power)
- Auto charge cable
- Charge only cable.

Communication/charge cables:

- Provide the FR6000 Series with operating and charging power when used with the Motorola approved power supply.
- Synchronize information between the FR6000 Series and a host computer.
- Provide USB connection through the USB pass-through port for communication with a USB device, such as a host computer.

Battery Charging and Operating Power

The communication/charge cables can charge the FR6000 Series battery and supply operating power. To charge the FR6000 Series battery:

1. Connect the communication/charge cable power input connector to the Motorola approved power source.
2. Slide the bottom of the FR6000 Series into the connector end of the communication/charge

cable and gently press in until it latches into the FR6000 Series. The FR6000 Series amber Charge LED indicates the FR6000 Series battery charging status. The 3600 mAh standard battery is fully charged in approximately six hours. See [Table 1-2 on page 21](#) for charging status indications.

3. When charging is complete, remove the cable by gently pulling the FR6000 Series and the cable apart.

LED Charge Indications

The amber Charge LED on the FR6000 Series indicates battery charging status. See [Table 1-2 on page 21](#) for charging status indications.

Charging Temperature

Charge batteries in temperatures from 0°C to 45°C (32°F to 113°F). Charging is intelligently controlled by the FR6000.

To accomplish this, for small periods of time, the FR6000 Series or accessory alternately enables and disables battery charging to keep the battery at acceptable temperatures. The FR6000 Series or accessory indicates when charging is disabled due to abnormal temperatures via its LED. See [Table 1-2 on page 21](#).

Chapter 9 Maintenance&Troubleshooting

Introduction

This chapter includes instructions on cleaning and storing the FR6000 Series, and provides troubleshooting solutions for potential problems during FR6000 Series operation.

Maintaining the FR6000 Series

For trouble-free service, observe the following tips when using the FR6000 Series:

- Do not scratch the screen of the FR6000 Series. When working with the FR6000 Series, use the supplied stylus or plastic-tipped pens intended for use with a touch-sensitive screen. Never use an actual pen or pencil or other sharp object on the surface of the FR6000 Series screen.

Motorola recommends using a screen protector, p/n MN2800AAPSC.

- The touch-sensitive screen of the FR6000 Series is glass. Do not drop the FR6000 Series or subject it to strong impact.
- Protect the FR6000 Series from temperature extremes. Do not leave it on the dashboard of a car on a hot day, and keep it away from heat sources.
- Do not store or use the FR6000 Series in any location that is dusty, damp, or wet.
- Use a soft lens cloth to clean the FR6000 Series. If the surface of the FR6000 Series screen becomes soiled, clean it with a soft cloth moistened with a diluted window-cleaning solution.
- Periodically replace the rechargeable battery to ensure maximum battery life and product performance. Battery life depends on individual usage patterns.
- A screen protector is applied to the FR6000 Series. Motorola recommends using this to minimize wear and tear. Screen protectors enhance the usability and durability of touch screen displays. Benefits include:
 - Protection from scratches and gouges
 - Durable writing and touch surface with tactile feel
 - Abrasion and chemical resistance
 - Glare reduction

- Keeping the device's screen looking new
- Quick and easy installation.

Battery Safety Guidelines

- The area in which the units are charged should be clear of debris and combustible materials or chemicals. Particular care should be taken where the device is charged in a non commercial environment.
- Follow battery usage, storage, and charging guidelines found in the user's guide.
- Improper battery use may result in a fire, explosion, or other hazard.
- To charge the mobile device battery, the battery and charger temperatures must be between +32 °F and +113 °F (0 °C and +45 °C)
- Do not use incompatible batteries and chargers. Use of an incompatible battery or charger may present a risk of fire, explosion, leakage, or other hazard. If you have any questions about the compatibility of a battery or a charger, contact Motorola Enterprise Mobility support.
- For devices that utilize a USB port as a charging source, the device shall only be connected to products that bear the USB-IF logo or have completed the USB-IF compliance program.
To enable authentication of an approved battery, as required by IEEE1725 clause 10.2.1, all batteries will carry a Motorola hologram. Do not fit any battery without checking it has the Motorola authentication hologram.
- Do not disassemble or open, crush, bend or deform, puncture, or shred.
- Severe impact from dropping any battery-operated device on a hard surface could cause the battery to overheat.
- Do not short circuit a battery or allow metallic or conductive objects to contact the battery terminals.
- Do not modify or remanufacture, attempt to insert foreign objects into the battery, immerse or expose to water or other liquids, or expose to fire, explosion, or other hazard.
- Do not leave or store the equipment in or near areas that might get very hot, such as in a parked vehicle or near a radiator or other heat source. Do not place battery into a microwave oven or dryer.
- Battery usage by children should be supervised.
- Please follow local regulations to promptly dispose of used re-chargeable batteries.
- Do not dispose of batteries in fire.
- Seek medical advice immediately if a battery has been swallowed.
- In the event of a battery leak, do not allow the liquid to come in contact with the skin or eyes. If contact has been made, wash the affected area with large amounts of water and seek medical advice.
- If you suspect damage to your equipment or battery, contact Motorola Enterprise Mobility support to arrange for inspection.

Cleaning



CAUTION Always wear eye protection.

Read warning label on compressed air and alcohol product before using.

If you have to use any other solution for medical reasons please contact Motorola for more information.



WARNING! Avoid exposing this product to contact with hot oil or other flammable liquids. If such exposure occurs, unplug the device and clean the product immediately in accordance with these guidelines.

Materials Required

- Alcohol wipes
- Lens tissue
- Cotton tipped applicators
- Isopropyl alcohol
- Can of compressed air with a tube.

Cleaning the FR6000 Series

Housing

Using the alcohol wipes, wipe the housing including keys and in-between keys.

Display

The display can be wiped down with the alcohol wipes, but care should be taken not to allow any pooling of liquid around the edges of the display. Immediately dried the display with a soft, non-abrasive cloth to prevent streaking.

Scanner Exit Window

Wipe the scanner exit window periodically with a lens tissue or other material suitable for cleaning optical material such as eyeglasses.

Connector

1. Remove the main battery from mobile computer. See [Replacing the Main Battery on page 25](#).
2. Close battery door.
3. Dip the cotton portion of the cotton tipped applicator in isopropyl alcohol.
4. Rub the cotton portion of the cotton tipped applicator back-and-forth across the connector on the bottom of the FR6000 Series. Do not leave any cotton residue on the connector.
5. Repeat at least three times.
6. Use the cotton tipped applicator dipped in alcohol to remove any grease and dirt near the connector area.

7. Use a dry cotton tipped applicator and repeat steps 4 through 6.
8. Spray compressed air on the connector area by pointing the tube/nozzle about ½ inch away from the surface.



CAUTION Do not point nozzle at yourself and others, ensure the nozzle or tube is away from your face.

9. Inspect the area for any grease or dirt, repeat if required.

Cleaning Cradle Connectors

To clean the connectors on a cradle:

1. Remove the DC power cable from the cradle.
2. Dip the cotton portion of the cotton tipped applicator in isopropyl alcohol.
3. Rub the cotton portion of the cotton tipped applicator along the pins of the connector. Slowly move the applicator back-and-forth from one side of the connector to the other. Do not let any cotton residue on the connector.
4. All sides of the connector should also be rubbed with the cotton tipped applicator.
5. Spray compressed air in the connector area by pointing the tube/nozzle about ½ inch away from the surface.



CAUTION Do not point nozzle at yourself and others, ensure the nozzle or tube is pointed away from your face.

6. Ensure that there is no lint left by the cotton tipped applicator, remove lint if found.
7. If grease and other dirt can be found on other areas of the cradle, use lint free cloth and alcohol to remove.
8. Allow at least 10 to 30 minutes (depending on ambient temperature and humidity) for the alcohol to air dry before applying power to cradle.

If the temperature is low and humidity is high, longer drying time is required. Warm temperature and dry humidity requires less drying time.

Cleaning Frequency

The cleaning frequency is up to the customer's discretion due to the varied environments in which the mobile devices are used. They may be cleaned as frequently as required. However when used in dirty environments it may be advisable to periodically clean the scanner exit window to ensure optimum scanning performance.

Troubleshooting the FR6000 Series

Table 9-1 *Troubleshooting the FR6000 Series*

Problem	Cause	Solution
FR6000 Series does not turn on.	Lithium-ion battery not charged.	Charge or replace the lithium-ion battery in the FR6000 Series.
	Lithium-ion battery not installed properly.	Install the battery properly. See Installing the Main Battery on page 19 .
	System crash.	Perform a cold boot. See Resetting the FR6000 Series on page 38 .
Rechargeable lithium-ion battery did not charge.	Battery failed.	Replace battery. If the FR6000 Series does not operate, perform a cold boot. See Resetting the FR6000 Series on page 38 .
	FR6000 Series removed from cradle while battery was charging.	Insert FR6000 Series in cradle. The 3600 mAh battery is fully charged in approximately six hours.
	Extreme battery temperature.	Battery does not charge if ambient temperature is below 0°C (32°F) or above 45°C (113°F).
Cannot see characters on display.	FR6000 Series not powered on.	Press the reset button.
During data communication, no data transmitted, or transmitted data was incomplete.	FR6000 Series removed from cradle or disconnected from host computer during communication.	Replace the FR6000 Series in the cradle, or reattach the communication cable and re-transmit.
	Incorrect cable configuration.	See the system administrator.
	Communication software was incorrectly installed or configured.	Perform setup.
No sound.	Volume setting is low or turned off.	Adjust the volume. See Adjusting Volume on page 34 .

Table 9-1 Troubleshooting the FR6000 Series (Continued)

Problem	Cause	Solution
FR6000 Series shuts off.	FR6000 Series is inactive.	The FR6000 Series turns off after a period of inactivity. If the FR6000 Series is running on battery power, set this period from 1 to 5 minutes, in one-minute intervals. If the FR6000 Series is running on external power, set this period to 1, 2, 5, 10, 15, or 30 minutes. Check the <i>Power</i> window by selecting Start > Settings > System tab and tapping the Power icon. Select the Advanced tab and change the setting for a longer delay before the automatic shutoff feature activates.
	Battery is depleted.	Replace the battery.
	Battery is not inserted properly.	Insert the battery properly. See Installing the Main Battery on page 19 .
	Battery is over-temperature.	Battery temperature >40°C (104°F) or <-10°C (14°F)
Tapping the window buttons or icons does not activate the corresponding feature.	Screen is not calibrated correctly.	Re-calibrate the screen. See Calibrating the Screen on page 22 .
A message appears stating that the FR6000 Series memory is full.	Too many files stored on the FR6000 Series.	Delete unused memos and records. If necessary, save these records on the host computer (or use an SD card for additional memory).
	Too many applications installed on the FR6000 Series.	Remove user-installed applications on the FR6000 Series to recover memory. Select Start > Settings > System tab and tap the Remove Programs icon. Select the unused program and tap Remove .
FR6000 Series keeps powering down to protect memory contents.	The FR6000 Series' battery is low.	Recharge the battery.
	The internal Bluetooth radio is powered on for a long time.	Because this mode requires battery power, power it off when not needed.

Table 9-1 *Troubleshooting the FR6000 Series (Continued)*

Problem	Cause	Solution
The FR6000 Series does not accept scan input.	Scanning application is not loaded.	Load a scanning application on the FR6000 Series. See the system administrator.
	Unreadable bar code.	Ensure the symbol is not defaced.
	Distance between exit window and bar code is incorrect.	Place the FR6000 Series within proper scanning range.
	FR6000 Series is not programmed for the bar code.	Program the FR6000 Series to accept the type of bar code being scanned.
	FR6000 Series is not programmed to generate a beep.	If the FR6000 Series does not beep on a good decode, set the application to generate a beep on good decode.
	Battery is low.	If the scanner stops emitting a laser beam upon a trigger press, check the battery level. When the battery is low, the scanner shuts off before the FR6000 Series low battery condition notification. Note: If the scanner is still not reading symbols, contact the distributor or Motorola.

Bluetooth Connection

Table 9-2 *Troubleshooting Bluetooth Connection*

Problem	Cause	Solution
FR6000 Series cannot find any Bluetooth devices nearby.	Too far from other Bluetooth devices.	Move closer to the other Bluetooth device(s), within a range of 10 meters.
	The Bluetooth device(s) nearby are not turned on.	Turn on the Bluetooth device(s).
	The Bluetooth device(s) are not in discoverable mode.	Set the Bluetooth device(s) to discoverable mode. If needed, refer to the device's user documentation for help.
When trying to connect a Bluetooth phone and FR6000 Series, the phone thinks a previously paired FR6000 Series is used.	The phone remembers the name and address of the FR6000 Series it last paired with via the Bluetooth radio.	Manually delete the pairing device and name from the phone. Refer to the phone's user documentation for instructions.

Single Slot USB/Serial Cradle

Table 9-3 *Troubleshooting the Single Slot USB/Serial Cradle*

Symptom	Possible Cause	Action
LEDs do not light when FR6000 Series or spare battery is inserted.	Cradle is not receiving power.	Ensure the power cable is connected securely to both the cradle and to AC power.
	FR6000 Series is not seated firmly in the cradle.	Remove and re-insert the FR6000 Series into the cradle, ensuring it is firmly seated.
	Spare battery is not seated firmly in the cradle.	Remove and re-insert the spare battery into the charging slot, ensuring it is firmly seated.
FR6000 Series battery is not charging.	FR6000 Series was removed from cradle or cradle was unplugged from AC power too soon.	Ensure cradle is receiving power. Ensure FR6000 Series is seated correctly. Confirm main battery is charging under Start > Settings > System > Power . The 3600 mAh battery is fully charged in approximately six hours.
	Battery is faulty.	Verify that other batteries charge properly. If so, replace the faulty battery.
	The FR6000 Series is not fully seated in the cradle.	Remove and re-insert the FR6000 Series into the cradle, ensuring it is firmly seated.
	Ambient temperature of the cradle is too warm.	Move the cradle to an area where the ambient temperature is between 0°C (32°F) and 35°C (95°F).
	Extreme battery temperature.	Battery does not charge if ambient temperature is below 0°C (32°F) or above 45°C (113°F).
Spare battery is not charging.	Battery not fully seated in charging slot.	Remove and re-insert the spare battery in the cradle, ensuring it is firmly seated.
	Battery inserted incorrectly.	Re-insert the battery so the charging contacts on the battery align with the contacts on the cradle.
	Battery is faulty.	Verify that other batteries charge properly. If so, replace the faulty battery.
	Ambient temperature of the cradle is too warm.	Move the cradle to an area where the ambient temperature is between 0°C (32°F) and 35°C (95°F).

Table 9-3 *Troubleshooting the Single Slot USB/Serial Cradle (Continued)*

Symptom	Possible Cause	Action
During data communication, no data transmits, or transmitted data was incomplete.	FR6000 Series removed from cradle during communications.	Replace FR6000 Series in cradle and retransmit.
	Incorrect cable configuration.	See the system administrator.
	Communication software is not installed or configured properly.	Perform setup.

Four Slot Battery Charger

Table 9-4 *Troubleshooting The Four Slot Battery Charger*

Symptom	Possible Cause	Action
Battery not charging.	Battery was removed from the charger or charger was unplugged from AC power too soon.	Re-insert the battery in the charger or re-connect the charger's power supply. The 3600 mAh battery is fully charged in approximately six hours.
	Battery is faulty.	Verify that other batteries charge properly. If so, replace the faulty battery.
	Battery contacts not connected to charger.	Verify that the battery is seated in the battery well correctly with the contacts facing down.
	Ambient temperature of the cradle is too warm.	Move the cradle to an area where the ambient temperature is between 0°C and 35°C.

Cables

Table 9-5 *Troubleshooting the Cables*

Symptom	Possible Cause	Action
FR6000 Series battery is not charging.	FR6000 Series was disconnected from AC power too soon.	Connect the power cable correctly. Confirm main battery is charging under Start > Settings > System > Power . The 3600 mAh battery is fully charged in approximately six hours.
	Battery is faulty.	Verify that other batteries charge properly. If so, replace the faulty battery.
	The FR6000 Series is not fully attached	Detach and re-attach the power cable to the FR6000 Series, ensuring it is firmly connected.
During data communication, no data transmits, or transmitted data was incomplete.	Cable was disconnected from FR6000 Series during communications.	Re-attach the cable and retransmit.
	Incorrect cable configuration	See the system administrator.
	Communication software is not installed or configured properly.	Perform setup.

Appendix A Technical Specification

FR6000 Series Technical Specifications

The following tables summarize the FR6000 Series' intended operating environment and technical hardware specifications.

Table A-1 *FR6000 Series Technical Specifications*

Item	Description
Physical Characteristics	
Dimensions	Length: 188 mm (7.4 in.) Width: 72 mm (2.8 in.) Depth: 45.3 mm (1.8in.)
Weight	345g (12.16 oz) with standard battery
Display	2.8" QVGA with backlight, TFT-LCD, 240x320(QVGA)
Touch Panel	Glass analog resistive touch
Backlight	LED backlight
Main Battery	Rechargeable Lithium Ion 3.7V, 3600 mAh Smart Battery
Backup Battery	Lithium battery 25mA 3.0V
Expansion Slot	User accessible microSD slot (with secure cover). CompactFlash (only for FR6000 Series)
Network Connections	High-speed client USB
Notification	Vibrator and LED
Keypad Options	34 key
Audio	Speaker, receiver, microphone, headset jack, software support for full duplex record and playback (stereo)
Performance Characteristics	
CPU	Marvel PXA312 624 MHz
Operating System	Microsoft® Windows Mobile™ 6.1
Memory	128MB RAM/256MB FLASH
Interface/Communications	USB 2.0; IrDA
Output Power	USB: 5 VDC @ 500 mAh

Table A-1 FR6000 Series Technical Specifications (Continued)

Item	Description
User Environment	
Operating Temperature	-10°C to 40°C (14°F to 104°F)
Storage Temperature	-30°C to 60°C (-22°F to 140°F) - without battery
Charging Temperature	0° C to 45° C(32°F to 113°F)
Humidity	90% non-condensing
Drop Specification	1.2m (4 ft) 26 drops per MIL STD 810G
Electrostatic Discharge (ESD)	±15kV air discharge,±8kV contact
Sealing	IP54
Wireless WAN Data and Voice Communications	
Wireless Wide Area Network (WWAN) radios	FR6074 and FR6076: GSM: 3G HSDPA (850, 900, 1800, 1900 and 2100 MHz)
GPS	Integrated Assisted-GPS (A-GPS)
Wireless LAN Data	
Wireless Local Area Network (WLAN) radio	Dual-mode IEEE® 802.11b/g
Data Rates Supported	1, 2, 5.5, 6, 9, 11, 12, 24, 36, 48, and 54 Mbps
Operating Channels	Chan 1-13 (2412-2472 MHz) Chan 14 (2484 MHz) Japan only Actual operating frequencies depend on regulatory rules and certification agency
Security	Open, Shared Key, WPA, WPA2, WEP, TKIP, AES, EAP (EAP-MD5 CHAP, EAP-TLS, PEAP, EAP-SIM)
Spreading Technique	Direct Sequence Spread Spectrum (DSSS) and Orthogonal Frequency Division Multiplexing (OFDM)
Antenna	Internal for WLAN, Bluetooth, GPS, WWAN
Wireless PAN Data and Voice Communications	
Bluetooth	Class II, v 2.0 EDR; on-board chip antenna
Data Capture Specifications	
Options	1D linear
Linear 1D Scanner (SE955 Specifications)	
Optical Resolution	0.004 in. minimum element width
Roll	+/- 35 from vertical
Pitch Angle	+/- 65° from normal
Skew Tolerance	+/- 50 from normal
Ambient Light	Sunlight: 10,000 ft.(107640 Lux), Artificial Light: 450 ft.(4844 Lux)
Shock	2,000 +/- 5% G
Scan Rate	50 (+/- 6) scans/sec (bidirectional)
Scan Angle	Wide: 47° (+/- 3 typical), Narrow: 35(+/-3)
Laser Power	1.7mW(+/-0.2mW) scan mode; 0.5mW(+/-0.05mW) aim mode

Table A-2 *Data Capture Options*

Item	Description		
Laser Decode Capability	Code 39 Codabar Interleaved 2 of 5 supplementals	Code 128 Code 11 EAN-8 UPCA Chinese 2 of 5	Code 93 Discrete 2 of 5 EAN-13 UPCE UPC/EAN Trioptic 39

FR6000 Series Accessory Specifications

Single Slot USB/Serial Cradle

Table A-3 *Single Slot USB/Serial Cradle Technical Specifications*

Item	Description
Dimensions	Length: 145.4 mm (5.72 in.) Width: 110.5 mm (4.35 in.) Height: 91.0 mm (3.58 in.)
Weight	196 g (6.9 oz)
Input Power	12 VDC
Power Consumption	30 watts
Interface	USB, Serial
Operating Temperature	0°C to 50°C (32°F to 122°F)
Storage Temperature	-40°C to 70°C (-40°F to 158°F)
Charging Temperature	0°C to 40°C (32°F to 104°F)
Humidity	5% to 95% non-condensing
Drop	76.2 cm (30.0 in.) drops to vinyl tiled concrete at room temperature
Electrostatic Discharge (ESD)	+/- 15 kV air +/- 8 kV contact

Four Slot Battery Charger

Table A-4 *Four Slot Battery Charger Technical Specifications*

Item	Description
Dimensions	Length: 210 mm (8.27 in.) Width: 155 mm (6.10 in.) Height: 34.7 mm (1.37 in.)
Weight	386 g (13.6 oz)
Input Power	12 VDC
Power Consumption	30 watts
Operating Temperature	0°C to 50°C (32°F to 122°F)
Storage Temperature	-40°C to 70°C (-40°F to 158°F)
Charging Temperature	0°C to 40°C (32°F to 104°F)
Humidity	5% to 95% non-condensing
Drop	76.2 cm (30.0 in.) drops to vinyl tiled concrete at room temperature
Electrostatic Discharge (ESD)	+/- 15 kV air +/- 8 kV contact

Glossary

B

Bar. The dark element in a printed bar code symbol.

Bit. Binary digit. One bit is the basic unit of binary information. Generally, eight consecutive bits compose one byte of data. The pattern of 0 and 1 values within the byte determines its meaning.

Bits per Second (bps). Bits transmitted or received.

boot or boot-up The process a computer goes through when it starts. During boot-up, the computer can run self-diagnostic tests and configure hardware and software.

bps. See **Bits Per Second**.

C

Character. A pattern of bars and spaces which either directly represents data or indicates a control function, such as a number, letter, punctuation mark, or communications control contained in a message.

Cold Boot. A cold boot restarts the mobile computer and erases all user stored records and entries.

COM port. Communication port; ports are identified by number, e.g., COM1, COM2.

Cradle. A cradle is used for charging the terminal battery and for communicating with a host computer, and provides a storage place for the terminal when not in use.

D

Decode. To recognize a bar code symbology (e.g., UPC/EAN) and then analyze the content of the specific bar code scanned.

E

ESD. Electro-Static Discharge

F
Flash Memory

Flash memory is nonvolatile, semi-permanent storage that can be electronically erased in the circuit and reprogrammed. FR6000 Series mobile computers use Flash memory to store the operating system (ROM-DOS), the terminal emulators, and the Citrix ICA Client for DOS.

H

Hz. Hertz; A unit of frequency equal to one cycle per second.

Host Computer. A computer that serves other terminals in a network, providing such services as computation, database access, supervisory programs and network control.

High-Speed Downlink Packet Access (HSDPA). A 3G (third generation) mobile telephony communications protocol in the High-Speed Packet Access (HSPA) family, which allows networks based on Universal Mobile Telecommunications System (UMTS) to have higher data transfer speeds and capacity.

I

IEC. International Electrotechnical Commission. This international agency regulates laser safety by specifying various laser operation classes based on power output during operation.

IP. Internet Protocol. The IP part of the TCP/IP communications protocol. IP implements the network layer (layer 3) of the protocol, which contains a network address and is used to route a message to a different network or sub-network. IP accepts "packets" from the layer 4 transport protocol (TCP or UDP), adds its own header to it and delivers a "datagram" to the layer 2 data link protocol. It may also break the packet into fragments to support the maximum transmission unit (MTU) of the network.

IPX/SPX. Internet Package Exchange/Sequential Packet Exchange. A communications protocol for Novell. IPX is Novell's Layer 3 protocol, similar to XNS and IP, and used in NetWare networks. SPX is Novell's version of the Xerox SPP protocol.

K

Key. A key is the specific code used by the algorithm to encrypt or decrypt the data. Also see, **Encryption** and **Decryption**.

L

LASER. Light Amplification by Stimulated Emission of Radiation. The laser is an intense light source. Light from a laser is all the same frequency, unlike the output of an incandescent bulb. Laser light is typically coherent and has a high energy density.

laser scanner. A type of bar code reader that uses a beam of laser light.

LED Indicator. A semiconductor diode (LED - Light Emitting Diode) used as an indicator, often in digital displays. The semiconductor uses applied voltage to produce light of a certain frequency determined by the semiconductor's particular chemical composition.

M

MC. Mobile Computer

Mobile Computer. In this text, *mobile computer* refers to the FR6000 series. It can be set up to run as a stand-alone device, or it can be set up to communicate with a network, using wireless radio technology.

R

RAM. Random Access Memory. Data in RAM can be accessed in random order, and quickly written and read.

RF. Radio Frequency.

S

Scanner. An electronic device used to scan bar code symbols and produce a digitized pattern that corresponds to the bars and spaces of the symbol. Its three main components are: 1) Light source (laser or photoelectric cell) - illuminates a bar code;; 2) Photodetector - registers the difference in reflected light (more light reflected from spaces); 3) Signal conditioning circuit - transforms optical detector output into a digitized bar pattern.

Space. The lighter element of a bar code formed by the background between bars

Symbol. A scannable unit that encodes data within the conventions of a certain symbology, usually including start/stop characters, quiet zones, data characters and check characters.

Symbology. The structural rules and conventions for representing data within a particular bar code type (e.g. UPC/EAN, Code 39, PDF417, etc.).

T

Terminal. See **Mobile Computer**.

Tolerance. Allowable deviation from the nominal bar or space width.

Index

Accessing the Phone Keypad.....	67	Changing the Backlight Settings.....	25
Accessories	16	Changing the Power Settings	25
ActiveSync	13, 14, 61	Chapter Descriptions	13
Adaptive Frequency Hopping	53	charge cable.....	110
Adding a Speed Dial Entry.....	77	Charging Temperature.....	21, 107
Adjusting the Handstrap.....	24	Charging the Main Battery and Memory	
AFH	53	Backup Battery.....	20
Alpha-numeric Keypad.....	40, 41, 42, 43	Cleaning	115
Answering a Call	73	Clock & Alarms	33
Assisted GPS	51	Cold Boot	38
Audio Modes	68	Communication/charge cables	110
Audio Volume.....	70	Conference Calling	85
Auto Charge Cable	105	Configurations.....	12
Backlight.....	33	Connector.....	115
backup battery.....	22	contact.....	74
bar codes.....	44, 45	Contacts	30, 71
Battery Charging Indicators	106	Cradle Connectors	116
Battery Management.....	25	Customer Feedback.....	33
Battery Safety Guidelines	114	Data Capture.....	45
Blue key.....	42	decode	45
Bluetooth	53	Deleting a Speed Dial Entry	79
Bluetooth Connection.....	119	Display	115
Bluetooth headset	68	Editing a Speed Dial Entry.....	79
Bond	55	Emergency Call.....	73
Buttons	44	Entering Data	45
Cables	110, 122	File Explorer	31
Calendar.....	30	Four Slot Battery Charger.....	105, 108, 121
Calibrating the Screen	22	Frequency	116
Call History	72	Games.....	31
Call History menu.....	83	Getting Started.....	31

Global Positioning System	49	Phone	30
GPS	49	Phone Software	12
GPSXtra	31	Pictures & Videos	31
Handset Mode	68	Power	44
Headset	70, 110	Radio Status	37
Headset Mode	68	Removing the Screen Protector	24
Help	30	Replacing the Main Battery	25
High-Speed Downlink Packet Access	67	Scan	44
Housing	115	Scanner Exit Window	115
HSDPA	67	Screen Protector	24
Incoming Call	74	Search	31
Infrared Connection	47	Security	54
Input Modes	40	Sending a Text Message	88
Installing ActiveSync	61	Shim Installation	108
Installing the Main Battery	19	Single Slot USB/Serial Cradle	105
Installing the SIM Card	19	Smart Dialing	74
Internet Explorer Mobile	30	Software Versions	12
Internet Sharing	31	Spare Battery	106
IrDA	47	Spare Battery Charging	108
Keypad Descriptions	42, 43	Speaker Mode	68
Keypads	40	Specifications	13
LED Indicators	37	Speed Dial	77
Linear Scanning	45	Speed Dial Call	72
Lithium-ion battery	16	Stylus	44
Locking	39	Swapping Calls	84
Maintaining	113	Task Manager	31, 34
Materials	115	task tray	30
memory card	23	Tasks	31
Messaging	30	text messages	86
Messenger	31	Troubleshooting	117
microSD	22	Turning Off the Radios	26
Mobile Computer Setup	61	Unpacking	16
modem	34, 53	Vehicle Cradle	21
Muting	75	view a text message	86
Muting a Call	75	Waking	38
Notational Conventions	13	Windows Live	31
Notes	31	Windows Media Player	31
notification icons	28	Wired Headset	69
operating system	12	Wireless Manager	26



MOTOROLA

Motorola, Inc.
One Motorola Plaza
Holtsville, New York 11742, USA
1-800-927-9626
<http://www.motorola.com>

MOTOROLA and the Stylized M Logo and Symbol and the Symbol logo are registered in the U.S. Patent and Trademark Office. All other product or service names are the property of their registered owners.
© Motorola, Inc. 2009

72E-119052-01 Revision C– August 2009