

**Sommario**

**INTRODUCTION:**.....2

**DESCRIPTION OF THE DEVICE**.....2

Features..... 2

**OVERVIEW** .....3

**SAFETY INSTRUCTIONS**.....3

**GENERAL GUIDELINES**.....4

**INSTALLATION INSTRUCTIONS**.....5

Mounting the device..... 5

Overhead rigging..... 6

DMX-512 control connection..... **Errore. Il segnalibro non è definito.**

Control Board ..... 8

Main functions: ..... 9

**INSTRUCTIONS ON USE:** .....15

**INSTRUCTIONS FOR INSTALLING THE BARN-DOOR AND FROST FILTER**.....17



**CLEANING AND MAINTENANCE** .....17

**TECHNICAL SPECIFICATIONS** .....18



## KEEP THIS MANUAL FOR FUTURE NEEDS

Thank you for your patronage. We are confident that our excellent products and service can satisfy you. For your own safety, please read this user manual carefully before installing the device.

<b>CAUTION</b>	
	Keep this device away from rain and moisture!
	Unplug mains lead before opening the housing

Every person involved with the installation, operation and maintenance of this device has to

- be qualified
- follow the instructions of this manual
- consider this manual to be part of the total product
- keep this manual for the entire service life of the product
- pass this manual on to every further owner or user of the product
- download the latest version of the user manual from the Internet

## INTRODUCTION:

Thank you for having chosen this professional LED lighting. You will see you have acquired a powerful and versatile device.

Unpack the device. Inside the box you should find:

1. The fixture device
2. One power cables
3. One XLR connection cable
4. One safety rope and this manual

Belows are the optional accessories, please purchase from your local dealer if needed

1. Barn-door
2. Frost filter


Please check carefully that there is no damage caused by transportation. Should there be any, consult your dealer and don't install this device.

## DESCRIPTION OF THE DEVICE

### Features

- Equipped with 36 x3 W LEDs: 10 x red, 10 x blue, 16 x green
- 50,0 000 hours LED life
- DMX channel: 8 channels
- Strobe-effect with 1-18 flashes per second
- Zoom: 13°~55° linear zoom
- Stepless RGB colour changing
- Programmable color-change speed and strobe effect
- 4digit LED display
- Software-upload by optional accessory via DMX line

**OVERVIEW**



- 1. Housing
- 2. LEDs
- 3. Floor-stand
- 4. Menu-button
- 5. Up-button
- 6. Down-button
- 7. Enter-button
- 8. Power input
- 9. DMX output
- 10. DMX-input

**SAFETY INSTRUCTIONS**

**CAUTION!**



Be careful with your operations. With a dangerous voltage you can suffer a dangerous electric shock when touching wires!

This device has left the factory in perfect condition. In order to maintain this condition and to ensure a safe operation, it is absolutely necessary for the user to follow the safety instructions and warning notes written in this user manual.



**Important:**

*Damages caused by the disregard of this user manual are not subject to warranty. The dealer will not accept liability for any resulting defects or problems.*

If the device has been exposed to temperature changes due to environmental changes, do not switch it on immediately. The arising condensation could damage the device. Leave the device switched off until it has reached room temperature.

This device falls under protection-class I. Therefore it is essential that the device be earthed. The electric connection must carry out by qualified person. The device shall only be used with rate voltage and frequency. Make sure that the available voltage is not higher than stated at the end of this manual.

Make sure the power cord is never crimped or damaged by sharp edges. If this would be the case, replacement of the cable must be done by an authorized dealer.



Always disconnect from the mains, when the device is not in use or before cleaning it. Only handle the power cord by the plug. Never pull out the plug by tugging the power cord.

During initial start-up some smoke or smell may arise. This is a normal process and does not necessarily mean that the device is defective, it should decrease gradually.

Please don't project the beam onto combustible substances.

Fixtures cannot be installed on combustible substances, keep more than 30cm distance with wall for smooth air flow, so there should be no shelter for fans and ventilation for heat radiation.

If the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or his service agent or a similar qualified person in order to avoid a hazard.

<b>CAUTION!</b>	
	Never touch device during operation! The housing may heat up
	Never look directly into the light source, as sensitive persons may suffer an epileptic shock.

Please be aware that damages caused by manual modifications to the device are not subject to warranty. Keep away from children and non-professionals.

## **GENERAL GUIDELINES**



This device is a lighting effect for professional use on stages, in discotheques, theatres, etc. This fixture is only allowed to be operated with the max alternating current which stated in the technical specifications in the last page of this manual, the device was designed for indoor use only. Lighting effects are not designed for permanent operation. Consistent operation breaks may ensure that the device will serve you for a long time without defects. Do not shake the device. Avoid brute force when installing or operating the device. The device shall only be used complete with its protective shield. While choosing the installation-spot, please make sure that the device is not exposed to extreme heat, moisture or dust. The minimum distance between light-output from the projector and the illuminated surface must be more than 0.1 meter.

Operate the device only after having familiarized with its functions. Do not permit operation by persons not qualified for operating the device. Most damages are the result of unprofessional operation.


Please use the original packaging if the device is to be transported. For safety reasons, please be aware that all modifications on the device are forbidden.

If this device will be operated in any way different to the one described in this manual, the product may suffer damages and the guarantee becomes void. Furthermore, any other operation may lead to short-circuit, burns, electric shock, lamp explosion, crash, etc.

## INSTALLATION INSTRUCTIONS

<b>CAUTION!</b>	
	Do not operate this device with open cover.
	Only install the lamp with the device unplugged from the mains.

### Mounting the device

<b>CAUTION</b>	
	Please consider the EN 60598-2-17 and the other respective national norms during the installation. The installation must only be carried out by a qualified person.


The applicable temperature for the lighting is between -25°C to 45°C. Do not use the lighting under or above the temperature.

The installation of the effect has to be built and constructed in a way that it can hold 10 times the weight for 1 hour without any harming deformation.

**The installation must always be secured with a secondary safety attachment, e.g. an appropriate safety rope.**


Never stand directly below the device when mounting, removing or servicing the fixture.

The operator has to make sure the safety relating and machine technical installations are approved by an expert before taking the device into operation for the first time. These installations have to be approved by a skilled person once a year.


<b>CAUTION</b>	
	Before taking into operation for the first time, the installation has to be approved by an expert.

#### **Cautions:**

**The effect should be installed outside areas where persons may reach it, walk by or be seated.**

<b>CAUTION</b>	
	When installing the device, make sure there is no highly inflammable material within a distance of min. 0,5m


Overhead mounting requires extensive experience, including amongst others calculating working load limits, installation material being used, and periodic safety inspection of all installation material and the device. If you lack these qualifications, do not attempt the installation yourself. Improper installation can result in bodily injury.

<b>CAUTION</b>	
	The electric connection must only be carried out by a qualified electrician.

Before mounting make sure that the installation area can hold a minimum point load of 10 times the device's weight.

Connect the fixture to the mains with the power plug.

## Overhead rigging




Screw the bolt of the clamp into the hold of the bracket, and tighten the screw underneath. Pull the safety-rope through the holes on the bracket of the base and over the trussing system or a safe fixation spot. Insert the end in the carabine and tighten the safety screw.

## DMX-512 control connection


The product has a DMX 512 input fitted with standard 5-pin XLR connectors. Screened cables in compliance with EIA RS-485 specifications and the following characteristics must be used for connections:

- 2 conductors plus screen
- 120Ohm impedance
- low capacitance
- max. transmission rate 250kbaud.

### Cable connections:



see illustration, taking care with the screen, which must be connected to Pin 1




**Please note:** to ensure maximal stability, when the voltage is 120V, only six devices may be connected

**GB**

**Please note:** to ensure maximal stability, when the voltage is 120V, only five devices may be connected together in this manner! From the sixth device, please connect to power supply to get power for the second link; when the voltage is over 220V, only ten devices may be connected together in this manner! From the eleventh device, please connect to power supply to get power for the second link.

**DMX-512 connection with DMX terminator**

For installations where the DMX cable has to run a long distance or is in an electrically noisy environment, such as in a discotheque, it is recommended to use a DMX terminator. This helps in preventing corruption of the digital control signal by electrical noise. The DMX terminator is simply an XLR plug with a 120 Ω resistor connected between pins 2 and 3, which is then plugged into the output XLR socket of the last fixture in the chain. Please see illustrations below.



**Projector DMX starting address selection**

All fixtures should be given a DMX starting address when using a DMX signal, so that the correct fixture responds to the correct control signals. This digital starting address is the channel number from which the fixture starts to “listen” to the digital control information sent out from the DMX controller. The allocation of this starting address is achieved by setting the correct number on the display located on the base of the device.

You can set the same starting address for all fixtures or a group of fixtures, or make different address for each fixture individually.

If you set the same address, all the units will start to “listen” to the same control signal from the same channel number. In other words, changing the settings of one channel will affect all the fixtures simultaneously.

If you set a different address, each unit will start to “listen” to the channel number you have set, based on the quantity of control channels of the unit. That means changing the settings of one channel will affect only the selected fixture.

In the case of the led lighting, which is 8 channels fixture when you select the standard channel mode, you should set the starting address of the first unit to 1, the second unit to 9(8 + 1), the third unit to 17 (8+ 9), and so on.

## Control Board

Default settings shaded.

0	MODE	ADDR	VALU	A001~XXX (AXXX)	DMX address setting
			SLAV	ON/OFF (SLAV)	Slave setting
			RDMX	ON/OFF	Change DMX address via external controller
		RUN	AUTO	ALON (AU-A)	Automatic Run in Stand Alone
				MAST (AU-M)	Automatic Run as Master
			SOUN	ALON (SO-A)	Sound-controlled Run in Stand Alone
				MAST (SO-M)	Sound-controlled Run as Master
		DISP	VALU	D-XX (DXXX) <b>D-00</b>	Display the DMX 512 value of each channel
			FLIP	ON/OFF	Reverse display
			D ON	ON/OFF	Shut off LED display
			LOCK	ON/ <b>OFF</b>	Key lock (Press the MENU button for 3 seconds to activate)
		1	SET	MIC	M-XX
FAIL	OFF/HOLD/ AUTO/SOUN			No DMX Status	
REST				Reset	
DFSE	ON/OFF			Restore factory settings	
POHO	ON/ <b>OFF</b>			Power on to preserve the MANL settings	
VER	V-1.0~V-9.9			Software version	
2	MANL	<RED	R XXX(000~255)	Test function of each channel	
		GREN	G XXX(000~255)		
		BLUE	B XXX(000~255)		
		MACO	M XXX(000~255)		
		PROG	P XXX(000~255)		
		STRB	S XXX(000~255)		
		DIMM	D XXX(000~255)		
		ZOOM>	Z XXX(000~255)		
3	TIME	LIFE	0000~9999(hours)	Fixture running time	
		CLFE	ON/OFF	Clear fixture time *code is "838"	
4	EDIT	STEP	S-01 ~S-48	Steps of Program Run	
		REC.	RE.XX	Auto Save Scene	
		SC01 ~ SC48	<RED	R XXX(000~255)	Edit the channels of each scene
			GREN	G XXX(000~255)	
			BLUE	B XXX(000~255)	
			MACO	M XXX(000~255)	
PROG	P XXX(000~255)				
STRB	S XXX(000~255)				
DIMM	D XXX(000~255)				
ZOOM>	Z XXX(000~255)				
FADE	XXX	Adjust fade speed			
CEDT	ON/OFF	Edit program via controller			



**Main functions:**

MODE - SET - MAIN - LINE - EDIT

**MODE - Main menu 0**

1. Press **[MENU]** to enter the main menu "MODE" (display flashing)
2. Press **[ENTER]** and select "ADDR", "RUN" or "DISP" by pressing **[UP]** or **[DOWN]** button.
3. Press **[ENTER]** for selecting the desired sub menu.

MODE - ADDR  
 RUN  
 DISP

**ADDR - DMX address setting, Slave setting**

MODE - ADDR - VALU - ADDR - A11111  
 SLAV - ON/OFF  
 RDMX - ON/OFF

**VALU - DMX address setting**

With this function, you can adjust the desired DMX-address via the Control Board.

1. Select "VALU" by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, adjust the DMX address by pressing **[UP]** or **[DOWN]** button.
3. Press **[ENTER]** to confirm or pressing **[MENU]** to return to main menu.

**SLAV - Slave setting**

With this function, you can define the device as slave.

1. Select "SLAV" by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, the display shows "ON" or "OFF".
3. Press **[UP]** to select "ON" if you wish to enable this function or press **[DOWN]** to select "OFF" if you don't.
4. Press **[ENTER]** to confirm or press **[MENU]** to return to main menu.

**RDMX - DMX address setting via controller**


With this function, you can adjust the desired DMX-address via an external controller.

This function can only be activated when the DMX-value of all other channels is set to "0" on the controller.

1. Select "RDMX" by pressing **[UP]** or **[DOWN]**.
2. Press **[ENTER]**, the display shows "ON" or "OFF".
3. Press **[UP]** to select "ON" if you wish to enable this function or **[DOWN]** to select "OFF" if you don't.
4. Press **[MENU]** to confirm.
5. Press **[ENTER]** in order to return to the main menu.


## **run** - Program Run, Master setting

With the function "RUN", you can run the internal program. You can set the number of steps under Step. You can edit the individual scenes under Edit. You can run the individual scenes either automatically (AUTO), i.e. with the adjusted Step-Time or sound-controlled (SOUN). The selection "ALON" means Stand Alone-mode and "MAST" that the device is defined as master.



1. Select "AUTO" or "SOUN" by pressing [UP] or [DOWN] button.
2. Press [ENTER] for selecting the desired extension menu.
3. Select "ALON" or "MAST" by pressing [UP] or [DOWN] button.
4. Press [ENTER] to confirm or Press [MENU] to return to the main menu.

## **disp** - Display the DMX-value, Reverse display, Shut off LED display



### **VALU** - Display the DMX 512 value of each channel

With this function you can display the DMX 512 value of each channel.

1. Select "VALU" by pressing [UP] or [DOWN] button.
2. Press [ENTER] to confirm; the display shows "D-00". In this setting, the DMX-adjustment of every channel will be displayed.
3. Press [UP] or [DOWN] button in order to select the desired channel. If you select "D-12" the display will only show the DMX-value of the 12<sup>th</sup> channel.
4. Press [ENTER] to confirm or Press [MENU] to return to the main menu.
5. The display shows "D- XX", "X" stands for the DMX-value of the selected channel.

### **FLIP** - Reverse display

With this function you can rotate the display by 180°.

1. Select "FLIP" by pressing [UP] or [DOWN] button.
2. Press [ENTER], the display shows "ON" or "OFF".
3. Press [UP] to select "ON" if you wish to enable this function or press [DOWN] button to "OFF" if you don't; the display will rotate by 180°.
4. Press [ENTER] to confirm or Press [MENU] to return to the main menu.

### **d on** - Shut off LED display

With this function you can shut off the LED display after 2 minutes.


1. Select "D ON" by pressing [UP] or [DOWN] button.
2. Press [ENTER], the display shows "ON" or "OFF".
3. Press [UP] to select "ON" if you wish to enable this function or press [DOWN] button to "OFF" if you don't.
4. Press [ENTER] to confirm or Press [MENU] to return to the main menu.

## **LOCK** - Locked keys the display

With this function you can activate the automatic keylock status. If this function is activated, the keys will be locked automatically after exiting the edit mode for 15 seconds. Keeping press the **[MENU]** key for 3 seconds if you do not need this function.

1. Tap the **[UP]** button until **"LOCK"** is displayed and tap the **[ENTER]** button.
2. Press the **[UP]** button to select **"ON"** to activate this function, or **"OFF"** to deactivate this function. Press **[ENTER]** to confirm.
3. Press **[MENU]** to return to the main menu.

## **SEt** - Main menu 1



1. Press **[MENU]** to enter the main menu (display flashing).
2. Press **[UP]** or **[DOWN]** button. to select **"SET"**.

## **MIC** - Mic sensitivity

With this function you can adjust the sensitivity of the microphone.

1. Select **"MIC"** by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, the display shows **"M-XX"**, **"XX"** stands for the number from 0 to 99.
3. Press **[ENTER]** to confirm or Press **[MENU]** to return to the main menu.

## **FAIL** - Automatic Run by no DMX

With this function you can automatic run the device by no DMX.

1. Select **"FAIL"** by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, the display shows **"OFF"**, **"HOLD"**, **"AUTO"** or **"SOUN"**.
3. Press **[UP]** or **[DOWN]** button to select **"OFF"**, **"HOLD"**, **"AUTO"** or **"SOUN"**, the default is **"HOLD"**.
4. Press **[ENTER]** to confirm or Press **[MENU]** to return to the main menu.

## **rESE** - Reset

With this function you can reset the device via the Control Board.

1. Select **"REST"** by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]** to reset or Press **[MENU]** to return to the main menu.

## **dFSE** - Restore factory settings

With this function you can restore the factory settings of the device. All settings will be set back to the default values (shaded). Any edited scenes will be lost.

1. Select **"DFSE"** by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, the display shows **"ON"** or **"OFF"**.
3. Press **[UP]** to select **"ON"** if you wish to enable this function or press **[DOWN]** button to **"OFF"** if you don't.
4. Press **[ENTER]** to confirm or Press **[MENU]** to return to the main menu.

## **POHO** — Power on to preserve the MANL settings

With this function you can activate. The fixture will return to the scene manual set before automatically after re-power on.

1. Tap the **[UP]** button until **"POHO"** is displayed and tap the **[ENTER]** button.
2. Press the **[UP]** button to select **"ON"** to activate this function, or **"OFF"** to deactivate this function. Press **[ENTER]** to confirm.
3. Press **[MENU]** to return to the main menu.

## **VER** - Software version

With this function you can display the software version of the device.

1. Select **"VER"** by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, The display will show "V-XX", "XX" stands for the version number, such as the display may also show,"V-1.0","V-9.9"etc.
3. Press **[ENTER]** to confirm or Press **[MENU]** to return to the main menu.

## **MANL** - Main menu 2

With this function you can Manual adjust intensity

1. Select "MANL" by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, the display shows "RED", "GREN", "BLUE", "MACO", "PROG", "STRB", "DIMM", "ZOOM".
3. Press **[UP]** or **[DOWN]** button to select "RED", "GREN", "BLUE", "MACO", "PROG", "STRB", "DIMM", "ZOOM".
4. Press **[ENTER]** to confirm or Press **[MENU]** to return to the main menu.

## **TIME** - Main menu 3

**TIME** - **LIFE** - 0000-9999  
**CLFE** - ON/OFF

1. Press **[MENU]** to enter the main menu (display flashing).
2. Press **[UP]** or **[DOWN]** button to select **"TIME"**.

## **LIFE** - Fixture running time


With this function you can display the running time of the device.

1. Select **"LIFE"** by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, the display shows **"XXXX"**, "X" stands for the number of hours.
3. Press **[ENTER]** to confirm or Press **[MENU]** to return to the main menu.

## **CLFE** - Clear fixture time

With this function you can clear the running time of the device.

1. Select **"CLFE"** by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, the display shows **"ON"** or **"OFF"**.
3. Press **[UP]** to select **"ON"** if you wish to enable this function or press **[DOWN]** button to **"OFF"** if you don't.
4. Press **[ENTER]** to confirm or Press **[MENU]** to return to the main menu.



## Edit - Main menu 4

1. Press **[MENU]** to enter the main menu (display flashing).
2. Press **[UP]** or **[DOWN]** button to select "EDIT".

## STEP - Define the number of steps in Run

With this function you can define the number of steps in the Program Run.

1. Select "STEP" by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, the display shows "S-XX", "X" stands for the total amount of steps you want to save, so you can call up to 48 scenes in "RUN". For example if the "XX" is 05, it means that "RUN" will run the first 5 scenes you saved in "EDIT".
3. Press **[ENTER]** to confirm or Press **[MENU]** to return to the main menu.

## REC - Auto Save

With this function you can automatic save the number of steps in the Program Run.

1. Select "REC" by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, the display shows "RE.XX", "XX" stands for the number from 1 to 400.
3. Press **[ENTER]** to confirm or Press **[MENU]** to return to the main menu.

## SC01 - Editing the channels of the individual scenes

With this function you can edit the program to be called up in Run.

### a) Editing via the Control Board

1. Select "SC01" by pressing **[UP]** or **[DOWN]** button.
2. Press **[ENTER]**, the display shows "SCXX", "X" stands for the scene no. to be edited.
3. Select the channel no. you would like to edit by pressing **[UP]** or **[DOWN]** button.
4. Adjust the desired DMX value by pressing **[UP]** or **[DOWN]** button.
5. Press **[ENTER]** in order to edit other channels of this scene.
6. Repeat steps 3-5 until you finish setting all the DMX values for all channels of this scene.
7. Once all the channels completed, the display will flash "TIME"
8. Press **[ENTER]** to edit the time needed, the display shows "TXXX", "XXX" stands for the time needed to run the current scene, value "001-999". E.g., "002" means you need 0.4ms (002\*0.2ms) to run the current scene. Adjust the desired time by pressing **[UP]** or **[DOWN]** button.
9. Press **[ENTER]** to save the settings for the scene you are editing, the display will change to the next scene automatically.
10. Repeat step 3-8 to edit and other scenes, you can edit and save a maximum of 48 scenes.
11. Press **[MENU]** to exit. The number of steps can be defined under "STEP" and the scenes can be called up under "RUN".

**b) Editing via the external controller****Call up the first scene in your controller now.**

1. Press **[ENTER]**, the display to be edited.
2. Select "**SC01**" by pressing **[UP]** or **[DOWN]** button.
3. Select the channel no. you would like to edit by pressing **[UP]** or **[DOWN]** button.
4. Press **[ENTER]**, the display shows "**C-01**".
5. Press **[UP]** or **[DOWN]** button .the display shows "**FADE**". (Adjust fade speed)
6. Press **[ENTER]**, the display to be adjust fade speed.
7. Select "**CEDT**" by pressing **[UP]** or **[DOWN]** button.
8. Press **[ENTER]**, the display shows "**OFF**".
9. Press **[UP]** or **[DOWN]** button .the display shows "**ON**".
10. Press **[ENTER]**, the display shows "**SC02**". You successfully downloaded the first scene.
11. Adjust the Step-time as described above under point 12.
12. Call up the second scene in your controller now.
13. Repeat steps 5-11 until all desired scenes are downloaded.
14. Press **[MENU]** to exit. The number of steps can be defined under "**STEP**" and the scenes can be called up under "**RUN**"

**INSTRUCTIONS ON USE:**

<b>DMX channel´s functions and their values (8 DMX channels):</b>		
<b>Channel</b>	<b>Value</b>	<b>Function</b>
1		<b>Red :</b>
	0-255	Red ( 0-Black , 255-100% Red )
2		<b>Green:</b>
	0-255	Green ( 0-Black , 255-100% Green )
3		<b>Blue:</b>
	0-255	Blue ( 0-Black , 255- 100% Blue )
4		<b>Color macros:</b>
	0	No function
	1-7	Color macro 1
	8-15	Color macro 2
	16-23	Color macro 3
	24-31	Color macro 4
	32-39	Color macro 5
	40-47	Color macro 6
	48-55	Color macro 7
	56-63	Color macro 8
	64-71	Color macro 9
	72-79	Color macro 10
	80-87	Color macro 11
	88-95	Color macro 12
	96-103	Color macro 13
	104-111	Color macro 14
	112-119	Color macro 15
	120-127	Color macro 16
	128-135	Color macro 17
	136-143	Color macro 18
	144-151	Color macro 19
	152-159	Color macro 20
	160-167	Color macro 21
	168-175	Color macro 22
	176-183	Color macro 23
	184-191	Color macro 24
	192-199	Color macro 25
	200-207	Color macro 26
	208-215	Color macro 27
	216-223	Color macro 28
	224-231	Color macro 29
	232-239	Color macro 30
240-247	Color macro 31	
248-255	Color macro 32	


5		<b><u>Internal programs:</u></b>
	0-10	Without internal program
	11-40	Internal program 1
	41-70	Internal program 2
	71-100	Internal program 3
	101-130	Internal program 4
	131-160	Internal program 5
	161-190	Internal program 6
	191-220	Internal program 7
	221-255	Gradient effect
6		<b><u>Shutter, strobe:</u></b>
	0-31	Led turn off
	32-63	Led turn on
	64-95	Strobe effect slow to fast
	96-127	Led turn on
	128-159	Pulse-effect in sequences
	160-191	Led turn on
	192-223	Random strobe effect slow to fast
	224-255	Led turn on
7		<b><u>General dimming/speed:</u></b>
	0-255	Dimming( 0-Black , 255- 100% )
		Speed from slow to fast /when running internal programs
		Speed from slow to fast /when running gradient effect
8		<b><u>Zoom:</u></b>
	0-255	Continuous adjustment from far to near



## INSTRUCTIONS FOR INSTALLING THE BARN-DOOR AND FROST FILTER

For this device, the barn door and the frost filter can be installed separately or together.

1. When only install the frost filter, use the rotating clips on the lens cover to fix it.
2. When only install the bar door, loose the 2 M4 screws on the lens cover, put on the bar door and tighten the screws.
3. When install the bar door and frost filter together, loose the 2 M4 screws, put on the frost filter and the bar door one by one, then tighten the screws.



## CLEANING AND MAINTENANCE

The following points have to be considered during the inspection:

- 1) All screws for installing the devices or parts of the device have to be tightly connected and must not be corroded.
- 2) There must not be any deformations on the housing, fixations and installation spots (ceiling, suspension, trussing).
- 3) Mechanically moved parts must not show any traces of wearing and must not rotate with unbalances.
- 4) The electric power supply cables must not show any damage, material fatigue or sediments.

Further instructions depending on the installation spot and usage have to be adhered by a skilled installer and any safety problems have to be removed.

### CAUTION!



Disconnect from mains before starting maintenance operation.

In order to make the lights in good condition and extend the life time, we suggest a regular cleaning to the lights.

- 1) Clean the inside and outside lens each week to avoid the weakness of the lights due to accumulation of dust.
- 2) Clean the fan each week.
- 3) A detailed electric check by approved electrical engineer each three month, make sure that the circuit contacts are in good condition, prevent the poor contact of circuit from overheating.

**Should you need any spare parts, please order genuine parts from your local dealer.**

## TECHNICAL SPECIFICATIONS

**Power supply:** AC 100V-240V~, 50 Hz / 60Hz

**Power consumption:** max. 120 W

**Packing dimensions:** 40 x 30 x 48 CM

**Flight case dimensions:** 79x76.5x60 cm

**Net weight:** 7 KGS

**Gross weight:** 10KGS (carton packing) 75.5 KGS(flight case packing/6pcs)

**Remark:** errors and omissions for every information given in this manual except. All information is subject to change without prior notice.