



User's Manual

Line Scan Camera

Type : XCM8060SA/8040SA/6040SA



NIPPON ELECTRO-SENSORY DEVICES CORPORATION

For Customers in U.S.A.

This equipment has been tested and found to comply with the limits for a Class A digital device, in accordance with Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference, in which case the user will be required to correct the interference at his or her own expense.

For Customers in the EU

This equipment has been tested and found to comply with the essential requirements of the EMC Directive 2004/108/EC, based on the following specifications applied:

EU Harmonized Standards

EN55011: 1998+A1: 1999+A2: 2002 Group1 Class A

EN61000-6-2: 2005

*Group 1 contains all ISM (Industrial, Scientific and medical) equipment in which there is intentionally generated and/or used conductively coupled radio-frequency energy which is necessary for the internal functioning of the Equipment itself.

*Class A equipment is equipment suitable for use in all establishments other than domestic and those directly connected to a low voltage power supply network which supplies buildings used for domestic purposes.

Directive on Waste Electrical and Electronic Equipment (WEEE)



Please return all End of Life NED products to the distributor from whom the product was purchased for adequate recycling and / or disposal. All costs of returning the Product to NED are borne by the shipper.

Introduction

Thank you for purchasing NED's XCM80 Line Scan Camera. We look forward to your continued custom in the future.

For safety use

- ◆ For your protection, please read these safety instructions completely before operating the product and keep this manual for future reference.
- ◆ The following symbols appear next to important information regarding safe product handling.

 Warning	If the product is not handled properly, this may result in serious injury or possible death.
 Caution	If the product is not handled properly, this may result in physical injury or cause property damage.

Safety precaution



Warning

- ◆ Never disassemble or modify this product, unless otherwise specified to do so in this manual.
- ◆ When hands are wet, avoid handling this product and do not touch any of the connection cable pins or other metallic components.
- ◆ Do not operate this product in an environment that is exposed to rain or other severe external elements, hazardous gases or chemicals.
- ◆ If the product is not to be used for an extended period of time, as a safety precaution, always unplug the connection cable from the camera unit.
- ◆ If the product installation or inspection must be executed in an overhead location, please take the necessary measures to prevent the camera unit and its components from accidentally falling to the ground.
- ◆ If smoke, an abnormal odor or strange noise is emitted from the camera unit, first turn OFF power, then unplug the cable from the camera unit.
- ◆ This product is not intended for use in a system configuration built for critical applications.

Instructions before use

- ◆ Only operate this product within the recommended environmental temperature range.
- ◆ Use only the specified power source and voltage rating.
- ◆ Do not drop this product. Avoid exposure to strong impact and vibrations.
- ◆ Install the camera unit in a well-ventilated environment, in order to prevent the camera from overheating.
- ◆ If the camera must be installed in an environment containing dust or other particles, take required measures to protect the camera unit from dust adhesion.
- ◆ Do not unplug the cable while power is being supplied to the camera unit. To prevent product damage, always shut down the power supply before unplugging the power cable.
- ◆ When the surface of the camera window becomes dirty due to dust or grime, black smudges appear in the displayed image. Use an air blower to remove the dust particles. Dip a cotton swab into ethanol alcohol and clean the camera window. Be careful not to scratch the glass.
- ◆ Use of non-infrared lighting such as a daylight fluorescent lamp is recommended. If halogen lighting is employed, always install an infrared filter into your system configuration.
- ◆ Please note that exposure to long wavelength light outside of the sensors visible optical range can affect the image.
- ◆ Sensitivity may fluctuate depending on the spectral response level of the light source. In cases like this, changing the light source to one with a different spectral response level may reduce this problem.
- ◆ For stabilized image capturing, turn ON the power supply and execute aging for ten to twenty minutes before actually using the camera unit.
- ◆ Do not share the power supply with motor units or other devices that generate noise interference.
- ◆ Do not disconnect the camera while rewriting the embedded memory.
- ◆ When you change the exposure mode that is set at the NED factory, input control signal (CC1) from the capture board.

Exclusion Clause

- ◆ The manufacturer assumes no responsibility for damages resulting from natural disasters, earthquakes, or acts executed by a third party. Warranty excludes any accidents resulting from improper handling or misuse of this product, whether intentional or not, and any camera operations conducted under abnormal conditions.
- ◆ The manufacturer assumes no responsibility for any incidental damages (loss of corporate profits, interruption of business, etc.) resulting from use or non-use of this product.
- ◆ The manufacturer assumes no responsibility for damages resulting from failure to follow the instructions and procedures indicated in this User's Manual.
- ◆ The manufacturer assumes no responsibility for any damages resulting from malfunctions caused by combined use of this product with other peripheral equipment.
- ◆ The manufacturer assumes no responsibility for damages resulting from malfunctions caused by non-authorized repair or modifications made to this product.

Table of Contents

1 Product Outline	9
1.1 Features (XCM8060SA/8040SA/6040SA)	9
1.2 Applications	9
1.3 Image Sensor	11
1.4 Performance Specifications	11
2 Camera Setting and Optical Interface	14
2.1 Setting Camera	14
2.2 Fixing Camera	14
2.3 Optical Interface	17
3 Hardware	18
3.1 Camera Connection	18
3.2 Input / Output Connectors and Indicator	20
3.3 Connectors• Pin Assignments• Cables	21
3.4 Power Supply	24
4 Camera Control	25
4.1 Flow of Camera Control	25
4.1.1 Command Overview	25
4.1.2 Command Format (PC to Camera Transmission)	25
4.1.3 Reply Format (Camera to PC Transmission)	26
4.1.4 Camera Control Commands	27
4.1.5 Memory Setup Values (Factory Settings)	28
4.2 Details on Commands	28
4.2.1 Setting Analog Gain	28
4.2.2 Setting Digital Gain	29
4.2.3 Setting Digital Offset	29
4.2.4 Setting Exposure Mode	29
4.2.5 Setting Exposure Time	30
4.2.6 Setting Output Signals 1 (Setting Data Format)	30
4.2.7 Setting Output Signals 2 (Setting Linear / Log)	30
4.2.8 Memory Initializing (Initializing Camera Settings)	31
4.2.9 Memory Load	31

4.2.10 Memory Save	32
4.2.11 Generating Test Pattern	32
4.2.12 Saving Pixel Correction Data.....	33
4.2.13 Setting Pixel Correction.....	33
4.2.14 Setting Exposure Time - Readout Time	34
4.2.15 Returning the Current Camera Settings.....	34
4.2.16 Setting Pixel Readout Direction.....	35
4.3 Digital Processing flow in FPGA.....	36
4.4 Startup.....	36
4.5 Saving and Loading Camera Settings.....	37
4.6 Serial Communication Settings	38
4.7 Video Output Format	38
4.8 Exposure Mode and Timing Chart	43
4.8.1 Free Run Exposure Mode	43
4.8.2 External Trigger Exposure Mode (Trigger Edge).....	44
4.8.3 External Trigger Exposure Mode (Trigger Level).....	45
4.9 Setting Offset.....	46
4.10 Setting Gain	47
4.11 Pixel Correction	49
4.11.1 Command Settings.....	50
4.11.2 How to correct	50
4.12 Test Pattern	51
5 Confirming Camera Settings	53
5.1 Before Power-on	53
5.2 After Power-on	54
5.3 During Operation.....	57
6 Sensor Handling Instructions.....	58
6.1 Electrostatic Discharge and the Sensor.....	58
6.2 Protecting Against Dust, Oil and Scratches.....	58
6.3 Cleaning the Sensor Window.....	58
7 Troubleshooting	59
7.1 No Image	59
7.2 Noise on Image	61

7.3 Camera becomes hot.....	63
8 CLISBeeCtrl.....	64
8.1 Overview	64
8.2 System Requirements	64
8.3 Install	64
8.4 Uninstall	64
8.5 Operation	65
8.5.1 Start Program	65
8.5.2 Selecting interface and Timeout setting	66
8.5.3.Connect.....	70
8.5.4.Disconnect and end program.....	70
8.5.5.Check of the contents of communication	70
8.5.6.Export Parameters to text file	71
8.5.7.Import Parameters from text file.....	71
8.6 Control.....	72
8.6.1 Gains and Offsets.....	72
8.6.2 Clock & Integration.....	73
8.6.3 Trigger & Video.....	74
8.6.4 Intelligence	75
8.6.5 Memory in camera.....	76
8.7 Upgrade	77
8.8 How to Program.....	77
8.9 Other Points of Note	77
9 Others	78
9.1 Notice	78
9.2 Contact for support	78
9.3 Product Support	79
Revision History.....	80

1 Product Outline

1.1 Features (XCM8060SA/8040SA/6040SA)

- High speed readout (240/160/160MHz)
- High resolution (8192/8192/6144 pixels)
- On-chip AD (8-or 10-bit) conversion
- Easy control of gain / offset / video output (8-/10-bit) with external software.
- Easy connection with a variety of frame grabber boards via Camera Link interface
- Single power source DC12V to 15V for operation
- Flat-field correction - minimizes lens vignetting, non-uniform lighting and sensor FPN and PRNU

1.2 Applications

- Inspection of Transparent panels and PCBs
 - Wide dynamic range prevents saturation caused by direct rays and specular reflection rays.
 - High speed inspection is possible because of the cameras high data output speed.
 - Using random access reading, High speed inspection becomes possible because only the required data is being transferred.
- Inspection of high speed moving objects
- Flat panel display inspection
- Inspection of glass and sheet-like objects
- Printed circuit board inspection
- This camera utilizes an Intelligent Transportation System
- Outdoor surveillance

An example of Visual Inspection of PCBs is shown below.




Figure 1-2-1 Visual Inspection of PCBs

Applicable Work

COB, BGA and MCM printed circuit boards

Performance

1. Maximum board size: 100mm×200mm
2. Resolution: 10μm
3. Inspection time: less than 30 seconds

Unit Configuration

1. Camera: Line scan camera (8192/6144pixels)
2. Controller: Dedicated software for PC system
3. Size: L930 x D500 x H500 (mm)

Applicable Fields

Inspection of patterns on film PCBs

1.3 Image Sensor

The camera uses a CMOS sensor with a maximum data rate of 240MHz (8060SA)・160MHz(8040SA, 6040SA) to acquire high responsivity and superior quality images.

The pixel size is 7μm×7μm.

8060SA outputs 8192 pixel data through 60MHz-4Tap,

8040SA outputs 8192 pixel data through 40MHz-4Tap,

6040SA outputs 6144 pixel data through 40MHz-4Tap.

1.4 Performance Specifications

The Performance Specifications are shown below. Unless otherwise specified, the data shown is when the camera is operating at the maximum scan rate.

Table 1-4-1 Performance Specifications

Items	Specifications		
	XCM8060SA	XCM8040SA	XCM6040SA
Number of Pixels	8192		6144
Pixel Size H x V (μm)	7 x 7		
Sensor Length (mm)	57.344		43.008
Spectral Responsivity (nm)	400 -1000 (Peak : 625)		
Data Rate (MHz)	240 (60 x 4)	160 (40 x 4)	160 (40 x 4)
Maximum Scan Rate (μs) / [kHz]	35.73 / [27.99]	53.6 / [18.65]	40.2 / [24.88]
Saturation Exposure (lx・s) (typically)	0.071[Minimum Gain, Pixel Correction Initial Value, Daylight Fluorescent Light]		
Responsivity (typically) [Minimum Gain, Pixel Correction Initial Value, Daylight Fluorescent Light] Visible Area (400 ~ 700nm)	70(V/[lx・s]) Analog 5V Conversion Sensitivity 40.7(V/[μJ/cm ²])		
Gain Adjustable Range *Analog Amplifier +Digital	Analog Amplifier : x 1 to x 11.2 (21 Steps) Digital : x 1 to x 2 (512 Steps)		

Offset Adjustable Range *Digital		Digital : -15 to 15DN (31 Steps) 8 bit -60 to 60DN (31 Steps) 10 bit	
FPN (Fixed Pattern Noise)		Typically 5DN (without correction, at minimum gain) 2DN (with correction, at minimum gain)	
PRNU (Photo Response Non Uniformity)		Typically 20DN (without correction, at minimum gain) 4DN (with correction, at minimum gain)	
Random Noise		Typically 20DN (peak value at minimum gain)	
Video output		Camera Link Medium Configuration (8 or 10 bit / 4tap)	
Control Input		CC1: External Trigger Signal, CC2-4: Not in use	
Connectors	Data/Controller	3M : MDR26[Camera Link] x 2	
	Power Supply	Hirose: HR10A (4Pin)	
Lens Mount		M72 x 0.75 Screw	Nikon F Mount
Operating Temperature (°C) No Condensation		0 to 50	
Power Supply Voltage (V)		DC12 to 15 [+/-5%]	
Consumption Current (mA) (typically)		500	
Size W x H x D (mm)		80 x 120 x 65	80 x 120 x 79.7
Mass (g) (Camera only)		Approx. 600	Approx. 730
Additional Functions		1 Shading Correction 2 Gain/Offset Control, 8 or 10 bit Video Output 3 Test Pattern Selection 4 Programmable Exposure Control 5 Scan Direction Switching	

*1) DN : Digital Number (10bit : 0 -1023)

*2) Measurements were made at room temperature.

The spectral Responsivity is shown below.




Figure 1-4-1 Spectral Responsivity

2 Camera Setting and Optical Interface

2.1 Setting Camera

Use the M4 screw holes or the screw hole for a tripod to set the camera.

An optional mounting base (sold separately) is available.

2.2 Fixing Camera

- Use the M4 screw holes (4 places at the front, 8 places at the side) to fix the camera.
- Or use the 1/4"-20UNC screw hole for a tripod (1 place at the side).
- ◆ If using the front panel M4 mounting holes, the screw length for fixing the camera should be less than 8mm at the front, and less than 6mm at the side.
- ◆ No X-, Y-axis orientation and tilt adjustment mechanism is available. Please provide an adjustment mechanism yourself as necessary.

The dimensions for 72 x 0.75 screw mount cameras are shown below.

72x0.75 Screw Mount

Unit : mm




Figure 2-2-1 Dimensions (72x0.75 Screw Mount)

The dimensions for Nikon F mount cameras are shown below.




Figure 2-2-2 Dimensions (Nikon F Mount)

2.3 Optical Interface

The lens mount depends on the type of camera.

For 8060/8040SA, M72 × 0.75 screw mount is used.

For 6040SA, Nikon F mount is used.

The amount and wavelengths of light required to capture useful images depend on the intended use. Factors include the property, speed, the object's spectral characteristics, exposure time, the light source characteristics, the specifications of the acquisition system and so on.

The exposure amount (exposure time x light amount) is the most important factor in getting desirable images. Please determine the exposure amount after studying what is most important to your system.

Keep these guidelines in mind when setting up your light source:

- LED light sources are relatively inexpensive, provide a uniform field and longer life span compared to other light sources. However, they also require a camera with excellent sensitivity.
- Halogen light sources generally provide very little blue relative to infrared light (IR).
- Fiber-optic light distribution systems generally transmit very little blue light relative to IR.
- Metal halide light sources are very bright but have a shorter life span compared to other light sources.

Generally speaking, the brighter light sources, the shorter life span.

CMOS image sensors are sensitive to infrared (IR). We recommend using daylight color fluorescent lamps that have low R emissions. If you use a halogen light source, to prevent infrared from distorting the images use an IR cutoff filter that does not transmit IR wavelengths.

3 Hardware

3.1 Camera Connection

(1) Camera Link cables shall be used to connect the camera unit with the frame grabber board.

- ◆ Use two cables of the same length and the same manufacturer. If you use asymmetric Camera Link cables, connect the camera with the connector labeled as "Camera side".

(2) Connect with a power supply.

Use a power cable to connect the camera with the power source for the camera. Insert the plug end of the cable into the camera. Attach the opposite end (loose wires) to the power unit.

- ◆ Other than the above, a personal computer, a frame grabber board, a photographic lens, a photographic lens mount, a light source and an encoder are necessary, depending on the situation.




Figure 3-1-1 Connections between Camera and Frame Grabber Board and Power Supply

- ◆ There are two connectors available for the Camera Link Medium Configuration board. Always check the frame grabber board specifications before making connections.

<Note: Choosing the appropriate Camera Link cable length >

According to the Camera Link Specification, the maximum cable length is 10m. But the maximum cable length to be able to transfer data depends on the type of cable performance and clock speed. The actual maximum transmission distance becomes less than 10m at faster clock speeds, though the transmission distance of 10m is feasible at slower clock speeds.

The following table shows values being calculated in accordance with the Camera Link Specification 2007.Version1.2., using a typical cable (14B26-SZLB-xxx-0LC from 3M) and frame grabber board (Solios from Matrox). Please choose the appropriate Camera Link cable type and length for your application. We recommend you perform a connection test in advance.

Table 3-1-1 calculated value of maximum cable length

Solios model	clock speed (MHz)	maximum cable length (m)
SOL 6M CL E* (20 ~ 66MHz)	40	9.8
	66	8.0
SOL 6M FC E* (20 ~ 85MHz)	75	7.6
	85	5.8

3.2 Input / Output Connectors and Indicator

The layout of input /output connectors and the indicator lamp are as follows.




Figure 3-2-1 Input/Output Connectors and Indicator

3.3 Connectors• Pin Assignments• Cables

This camera uses the Medium Configuration of Camera Link interface standards. The figure shown below shows the interface for the camera and a typical implementation for the frame grabber interface.




Figure 3-3-1 Camera / Frame Grabber Interface

- ◆ Set the LVDS, Channel Link receiver side to 100-ohm termination.
- ◆ With the driver side of LVDS, even if not used, do not make it open but set the logic to H or L.




Figure 3-3-2 Circuit of LVDS

The camera has 26-pin MDR connectors for control signals of Camera Link, data signals and serial communications. The camera also has a 4-pin HIROSE connector for power supply.




Figure 3-3-3 Camera Link Connector

- Half pitch (miniature half ribbon) shape
- Locking screw (UNC #4-40) type

Table 3-3-1 Camera Link Connector (26-pin MDR Connector) pin assignments

CL1(Base Configuration)					CL2(Medium Configuration)				
No	NAME	No	NAME	I/O	No	NAME	No	NAME	I/O
1	Inner Shield	14	Inner Shield		1	Inner Shield	14	Inner Shield	
2	X0-	15	X0+	Out	2	Y0-	15	Y0+	Out
3	X1-	16	X1+	Out	3	Y1-	16	Y1+	Out
4	X2-	17	X2+	Out	4	Y2-	17	Y2+	Out
5	Xclk-	18	Xclk+	Out	5	Yclk-	18	Yclk+	Out
6	X3-	19	X3+	Out	6	Y3-	19	Y3+	Out
7	SerTC+	20	SerTC-	In	7	100 terminated	20	100 terminated	
8	SerTFG-	21	SerTFG+	Out	8	Open	21	Open	
9	CC1-	22	CC1+	In	9	100 terminated	22	100 terminated	
10	CC2+	23	CC2-	In	10	100 terminated	23	100 terminated	
11	CC3-	24	CC3+	In	11	100 terminated	24	100 terminated	
12	CC4+	25	CC4-	In	12	100 terminated	25	100 terminated	
13	Inner Shield	26	Inner Shield		13	Inner Shield	26	Inner Shield	

- Explanation of Signals

Inner Shield : Shield cable (GND)

X0+,X0-...X3+,X3- : Data output (Channel Link)

Xclk+,Xclk- : Clock output for above data output synchronization (Channel Link)

Y0+,Y0-...Y3+,Y3- : Data output (Channel Link)

Yclk+,Yclk- : Clock output for above data output synchronization (Channel Link)

SerTC+, SerTC- : Serial data input (LVDS)

SerTFG+, SerTFG- : Serial data output (LVDS)

CC1+,CC1- : External synchronous signal input (LVDS)

CC2+,CC2- : Not in use (LVDS)

CC3+,CC3- : Not in use (LVDS)

CC4+,CC4- : Not in use (LVDS)

- Camera Link compatible cable

14B26 - SZLB - xxx - 0LC by 3M (or equivalent)

- ◆ To avoid uncoupling of cable connectors during power on, make sure to clamp them with locking screws.
- ◆ Do not unplug the cable while power is being supplied to the camera.

The pin assignment of the power supply connector is shown below.




Figure 3-3-4 Power Supply Connector (HIROSE : HR10G -7R- 4PB)

- Round shape push-pull lock type

Table 3-3-2 Pin Assignment of Power Supply Connector

No	NAME	Color of Cable
1	12 -15V	White
2	12 -15V	Red
3	GND	Green
4	GND	Black

3.4 Power Supply

The camera requires a single power supply (DC+12 to +15V).

- ◆ When selecting a power source, choose one with the capacity to allow for inrush current. (15W or more recommended)
- ◆ Insert the cable plug securely until it locks into position. This is to prevent the connector from coming loose during power transmission.
- Compatible Cable (Compatible plug): DGPS -10 (HIROSE : HR10A -7P - 4S)
- Power supply voltage: DC+12 -15V (+/-5%)
- Consumption Current (rated): DC+12V : 500mA
- The LED lamp illuminates when +12V to +15V power is being supplied to the camera.
- ◆ If the lamp fails to illuminate even after power is supplied, turn OFF power immediately. Inspect wiring. Check the voltage and capacity of the supplied power source.

4 Camera Control

The camera can be controlled through serial communication. Two methods can be used to change the camera's parameters. The first approach is to change parameters using CLISBeeCtrl (Camera control software). (See "8 CLISBeeCtrl".) Or you can also change the parameters directly from your application by using binary read/write commands to set values in the camera register.

The camera can be used without the serial interface after it has been set up correctly.

4.1 Flow of Camera Control

4.1.1 Command Overview

The serial interface uses a simple ASCII-based command.

- Communication begins when the computer sends control commands to the camera.
- The camera receives and interprets the computer commands and then executes control operation accordingly.
- Transmission ends when the camera returns the analyzed results of control commands to the computer.
- ◆ Always allow the previous transmission to end before starting the next transmission. (Only one command can be sent per transmission.)

4.1.2 Command Format (PC to Camera Transmission)

- Format 1 CMD CR
- Format 2 CMD VAL1 CR
- Format 3 CMD VAL1 VAL2 CR

CMD: Control text (3 Bytes) Use 3 lowercase letters only. No numerals allowed.

CR: Carriage Return (0x0D)

: Space (0x20) or Comma (0x2C)

VAL: Setting value (decimal, maximum 5 digits)

<Example>

gax 0 CR

4.1.3 Reply Format (Camera to PC Transmission)

- Format 1 >R CR >[SB] CR EOT
- Format 2 (for “sta” command) >OK CR >[MEM] CR >sta CR EOT

> : Results start text (0x3E)
 R: Camera receive command analyzed results
 [SB] : Camera receive command send back
 [MEM] : Memory data readout value
 CR: Separated text (0x0D)
 EOT: Send command all text End text (0x04)

<Example>

>OK CR >gax 0 CR EOT

Table 4-1-3-1 Error Messages

Camera Response	Meaning
OK	Camera executed command
CMD ERR!	Command is not valid
CMD OVR ERR!	Command text line is too long
VAL ERR!	Parameter accepted was outside of specified
MEM ERR!	Memory error

4.1.4 Camera Control Commands

The table below shows the list of Camera Control Commands.

Table 4-1-4-1 List of Camera Control Commands

Control Item	CMD	VAL1	VAL2	Control Description
Analog Gain	gax	0 to 20		x1.00...x11.22(1.06dB/step)
Digital Gain	gdx	0 to 511		x1...x2(x0.003906/step)
Digital Offset	odx	-15 to 15		-15...15(1DN/step at8bit)-60...60(4DN/step at10bit)
Exposure Mode	inm	0 /1/2		Free Run / Ext Edge / Ext Level
Programmable Exposure Time	int	0 to 11	61 to 1023	32.5 ~ 117388.8 μs (XCM8060SA) 48.8 ~ 1676083.2 μs (XCM8040SA) 36.6 ~ 1257062.4 μs (XCM6040SA) (VAL1: Dividing, VAL2: Counter)
Output Signal Setting 1	voa	0 /1	0 to 9	8bit /10bit、 Output block selection
Output Signal Setting 2	voc	0 /1		Linear /log
Memory Initializing	rst			Reset to factory settings
Memory Load	rfd			Readout setup data in memory
Memory Save	sav			Store present setup data in memory
Test Pattern	tpn	0 /1		OFF/ON
Pixel Correction Data Save	wht			Store pixel correction data in memory
Pixel Correction Setting	shc	0/1/2	0 to 1023	0:Correction OFF /1:Factory white correction /2:User white correction, Correction level (10-bit)
Exposure-Readout Time	pad	0 to 50		0 - 54613μs (XCM8060SA) 0 - 81920μs (XCM8040SA) 0 - 61440μs (XCM6040SA)
Operation Status Readout	sta			Returns the current camera settings.
Scanning Direction	rev	0 /1		0 : Forward / 1 : Reverse

Programmable Exposure Time = $VAL2 \div \{[X] \div (16 \times 2^{\wedge} VAL1)\}$

Exposure-Readout Time = $VAL1 \div \{[X] \div (16 \times 2^{\wedge} VAL1^*)\}$ The VAL1* is VAL1 of Programmable Exposure Time item.

XCM8060SA : [X]=30000000,

XCM8040SA : [X]=20000000,

XCM6040SA : [X]=26666667

4.1.5 Memory Setup Values (Factory Settings)

The memory setup values (factory settings) are shown below.

Table 4-1-5-1 Memory Setup Values (Factory Settings)

Control Item	CMD	VAL1	VAL2	Control Description
Analog Gain	gax	0		x1(0dB)
Digital Gain	gdx	0		x1
Digital Offset	odx	0		0DN(8 bit)
Exposure Mode	inm	0		Free Run
Programmable Exposure Time	int	0	61	32.5μs (XCM8060SA) 48.8μs (XCM8040SA) 36.6μs (XCM6040SA) (Dividing=16、Counter=61)
Output Signal Setting 1	voa	0	0	8 bit, 8192 pixel
Output Signal Setting 2	voc	0		linear
Test Pattern	tpn	0		OFF
Pixel Correction Setting	shc	1	600	Factory White Correction Correction Level 600DN(10 bit) (XCM8040SA) 900DN(10 bit) (XCM8060SA/ XCM6040SA)
Exposure-Readout Time	pad	0		0μs
Scanning Direction	rev	0		Forward : 0

4.2 Details on Commands

4.2.1 Setting Analog Gain

Sets analog gain in 21 steps between x1 and x11.2. (See Table 4-9)

- Format 2 CMD VAL1 CR
- CMD gax
- VAL 0 (x1) –20 (x11.2)

<Example>

gax 5 CR (Setting analog gain 5(x1.84))

>OK

>gax 5

4.2.2 Setting Digital Gain

Sets digital gain in 512 steps between x1 and x2.

- Format 2 CMD VAL1 CR
- CMD gdx
- VAL 0(x1) - 511(x2)

<Example>

```
gdx 255 CR (Setting digital gain 255(1023/(1023-255)=x1.33))
>OK
>gdx 5
```

4.2.3 Setting Digital Offset

Sets digital offset -15 to +15(8 bit:1DN/Step), -60 to +60(10 bit:4DN/step)

- Format 2 CMD VAL1 CR
- CMD odx
- VAL -15 to +15

<Example>

```
odx 5 CR (Setting digital offset 5(8-bit) or 20(10-bit))
>OK
>odx 5
```

4.2.4 Setting Exposure Mode

Sets the exposure mode.

- Format 2 CMD VAL1 CR
- CMD inm
- VAL 0,1,2

<Example>

```
inm 0 CR (Setting the exposure mode free run)
>OK
>inm 0
```

4.2.5 Setting Exposure Time

Sets the exposure time.

- Format 3 CMD VAL1 VAL2 CR
- CMD int
- VAL1 0 -11 (Setting Dividing)
- VAL2 0 -1023 (Setting Counter value)

<Example>

```
int 0 120 CR (Setting exposure time 96μs:in case of 8040SA)
>OK
>int 0,120
```

4.2.6 Setting Output Signals 1 (Setting Data Format)

Sets the data format of output signals.

- Format 3 CMD VAL1 VAL2 CR
- CMD voa
- VAL1 0,1 (0: 8bit /1: 10bit)
- VAL2 0- 9 (Selecting output block)

<Example>

```
voa 0 0 CR (8bit /8k pixel output)
>OK
>voa 0,0
```

4.2.7 Setting Output Signals 2 (Setting Linear / Log)

Sets the data format of output signals.

- Format 2 CMD VAL1 CR
- CMD voc
- VAL 0,1 (0:linear output / 1:log output)

<Example>

```
voc 0 CR (linear output)
>OK
>voc 0
```

4.2.8 Memory Initializing (Initializing Camera Settings)

Reset the flash memory to the factory default.

- Format 1 CMD CR
- CMD rst

<Example>

```
rst CR
>OK
>Type=XCM8040SA
>Ver.=2.06_0x4063
>Serial=0
>check_code = 20070615
>gax 0
>gdx 0
>odx 0
>inm 0
>int 0,61
>cka 0
>voa 0,0
>voc 0
>tpn 0
>shc 1,600
>pad 0
>rev 0
>rst
```

4.2.9 Memory Load

Reads out the camera settings from the flash memory.

- Format 1 CMD CR
- CMD rfd

<Example>

```
rfd CR
>OK
>Type=XCM8040SA
>Ver.=2.06_0x4063
>Serial=0
>check_code = 20070615
```

```

>gax 0
>gdx 0
>odx 0
>inm 0
>int 0,61
>cka 0
>voa 0,0
>voc 0
>tpn 0
>shc 1,600
>pad 0
>rev 0
>rfd

```

4.2.10 Memory Save

Stores current camera settings in the flash memory.

- Format 1 CMD CR
- CMD sav

<Example>

```

sav CR
>OK
>sav

```

4.2.11 Generating Test Pattern

Generates test pattern.

- Format 2 CMD VAL1 CR
- CMD tpn
- VAL 0,1 (0:Image data, 1: Test pattern)

<Example>

```

tpn 1 CR (Generating test pattern)
>OK
>tpn 1

```


4.2.12 Saving Pixel Correction Data

Acquires current pixel correction data and saves it in the flash memory. One set of correction data can be saved for each step of analog gain.

- Format 1 CMD CR
- CMD wht

<Example>

```
wht CR
>OK
>wht
```

4.2.13 Setting Pixel Correction

Sets pixel correction.

- Format 3 CMD VAL1 VAL2 CR
- CMD shc
- VAL1 0,1,2 (0:Correction OFF /1:Factory white correction /2:User white correction, Correction level (10bit))
- VAL2 0-1023 (Setting correction level:10bit)

<Example>

```
shc 1 600 CR (for Factory white correction, Correction level
600DN(10bit))
>OK
>shc 1,600
```

4.2.14 Setting Exposure Time - Readout Time

Prolongs the line period without changing the exposure time.

- Format 2 CMD VAL1 CR
- CMD pad
- VAL 1 0 -50 (XCM8060: 0 - 54613 μ s, XCM8040SA:0-81920 μ s
6040SA:0-61440 μ s)

<Example>

```
pad 10 CR
>OK
>pad 10
```

The increment of the line period depends on the exposure time setting command "int". For XCM8060SA, if VAL1 (in "int")=0 and VAL1 (in "pad")=1, the increment is $16.7\text{ns} \times 2 \times 16 \times 2 = 1.07\mu\text{s}$. If VAL1 (in "int") = 3 and VAL1 (in "pad")=1, the increment is $16.7\text{ns} \times 2 \times 16 \times (2 \times 2 \times 2) = 4.27\mu\text{s}$. For XCM8040SA or XCM6040SA, change the above 16.7ns into 25ns or 18.8ns respectively.

4.2.15 Returning the Current Camera Settings

Returns the current camera settings.

- Format 1 CMD CR
- CMD sta

<Example>

```
sta CR
>OK
>Type=XCM8040SA
>Ver.=2.06_0x4063
>Serial=0
>check_code = 20070615
>gax 0
>gdx 0
>odx 0
>inm 0
>int 0,61
>cka 0
>voa 0,0
>voc 0
```

```
>tpn 0
>shc 1,600
>pad 0
>rev 0
>sta
```

4.2.16 Setting Pixel Readout Direction

Sets the pixel readout direction.

- Format 2 : CMD VAL1 CR
- CMD : rev
- VAL1 : 0,1 (0:Forward, 1:Reverse)


<Example>

```
rev 1 CR (Reverse)
>OK
>rev 1
```

4.3 Digital Processing flow in FPGA

The figure below shows the digital processing flow in the FPGA.

FPGA Processing block diagram



In Test Pattern mode, Black / White reference and Digital Gain /Offset will be skipped.

Figure 4-3-1 FPGA Processing Block Diagram

4.4 Startup

After turning on, the camera runs a startup procedure before it starts getting images and outputting data. It takes about four seconds.

The startup procedure is as follows.

- (1) The camera initializes the hardware.
- (2) Reads out the latest camera settings from the flash memory. (User settings if any or factory default settings)
- (3) Sets up the camera with the setting values from the flash memory.

After this sequence, the camera is ready to get images and output data.

4.5 Saving and Loading Camera Settings

The camera setting data is saved in the internal memory (flash memory) and is loaded from the memory when turning on the power supply or loading (sending the “rfd” command).

- The number of times the flash memory can be rewritten will vary depending on actual operational conditions. After turning on the power supply, the camera always checks the memory status. If the data is not within the designated range due to a malfunction or other type of trouble, the memory will be automatically rewritten with the factory settings.

- ◆ If disconnecting camera power while rewriting the memory, all data saved in the memory will be deleted.

As it takes several seconds to rewrite the memory, do not disconnect the power supply before receiving the response from the camera.

Commands for rewriting the memory are as follows.

- Reset to factory settings (rst)
- Store present setup data in memory (sav)
- Store pixel correction data in memory (wht)
- ◆ When changing the factory setting exposure mode, be sure to send the control input signal (CC1) from the frame grabber board. If you do not send CC1 or sending control input signals are out of the designated range, you cannot get images and can not change the setting. See 4.8.2 and 4.8.3.

Table 4-5-1 Camera Operation Mode and Control Input

Camera operation mode (Exposure mode)	Control input (from frame grabber board)
Free Run (Programmable time setting) (Factory Setting)	Not in use
Ext Edge (External trigger edge+ Programmable time setting)	External trigger (CC1) is required
Ext Level (External trigger level time setting)	External trigger (CC1) is required

4.6 Serial Communication Settings

Serial communication is performed through the Camera Link Interface.
The table below shows the serial communication settings.

Table 4-6-1 Serial Communication Settings

Parameter Items	Setup Value
Communication Speed (Baud rate)	9600bps
Data Length	8bit
Parity Bit	None
Stop bit	1bit
Flow Control	None

4.7 Video Output Format

The camera outputs 8-bit or 10-bit digital data through 4 taps.




Figure 4-7-1 Pin Assignments of Digital Data

- ◆ The A/D converter of the camera has a 10-bit resolution. For 8-bit output, the upper 8-bit signal can be output as a video data.

Following output block patterns of 8060/8040SA are available.




Figure 4-7-2 Output Block Patterns of 8060/8040SA

- Pattern1: Medium Configuration
- Pattern2 and 3 in 10-bit mode: Medium Configuration
- Pattern2 and 3 in 8-bit mode: Base Configuration
- Pattern4-10: Base Configuration

Following output block patterns of 6040SA are available.





Figure 4-7-3 Output Block Patterns of 6040SA

- Pattern1: Medium Configuration
- Pattern2 and 3 in 10-bit mode: Medium Configuration
- Pattern2 and 3 in 8-bit mode: Base Configuration
- Pattern4-10: Base Configuration


The video output phase of XCM8060SA, XCM8040SA is shown below.



◆ FVAL = 0 (low level) fixed

Figure 4-7-4 Video Output Phase of XCM8060SA, XCM8040SA

The video output phase of 6040SA is shown below.



◆ FVAL = 0 (low level) fixed

Figure 4-7-5 Video Output Phase of XCM6040SA

4.8 Exposure Mode and Timing Chart

The camera has three exposure modes. The overview of each mode and the timing are as follows.

4.8.1 Free Run Exposure Mode

In free-run exposure mode, the camera generates its own internal control signal based on two programmable parameters, exposure time and readout time.

Table 4-8-1-1 Programmable Exposure Time

		XCM8060SA	XCM8040SA	XCM6040SA
p	Programmable exposure time	32.5 - 1,117,389	48.8 - 1,676,083	36.6 - 1,257,062
r	Readout time	34.2	51.2	38.4




Figure 4-8-1-1 Free Run Exposure Mode

- ◆ The data of Exposure (1) is read out at Readout (1)

4.8.2 External Trigger Exposure Mode (Trigger Edge)

In external trigger exposure mode (Trigger Edge), the exposure time is determined by the setting made through serial communication. Each exposure starts with the rising edge and the line period is determined by the time from rising edge to rising edge of the trigger pulse. The range of programmable exposure time and the timing chart of the exposure and the readout are shown below.

Table 4-8-2-1 Programmable Exposure Time

		XCM8060SA	XCM8040SA	XCM6040DSA
p	Programmable exposure time	32.5 - 1,117,389	48.8 - 1,676,083	36.6 - 1,257,062
r	Readout time	34.2	51.2	38.4
a	Trigger pulse H time	1.6		
b	Trigger pulse L time	3.2	4.8	3.6
c	Trigger pulse cycle	35.7	53.6	40.2




Figure 4-8-2-1 External Trigger (Trigger Edge) Exposure Mode

- ◆ The data of Exposure (1) is read out at Readout (1)

4.8.3 External Trigger Exposure Mode (Trigger Level)

In external trigger exposure mode (Trigger Level), the exposure time is determined by the high trigger pulse time. Each exposure starts with the rising edge and the line period is determined by the time from rising edge to rising edge of trigger pulse. The range of programmable exposure time, the timing chart of the exposure and the readout are shown below.

Table 4-8-3-1 Programmable Exposure Time

		XCM8060SA	XCM8040SA	XCM6040SA
r	Readout time	34.2	51.2	38.4
a	Trigger pulse H time	32.5	48.8	36.6
b	Trigger pulse L time	3.2	4.8	3.6
c	Trigger pulse cycle	35.7	53.6	40.2




Figure 4-8-3-1 External Trigger (Trigger Level) Exposure Mode

- ◆ The data of Exposure (1) is read out at Readout (1)

4.9 Setting Offset

In the figure below, the horizontal axis indicates the amount of incident light and the vertical axis indicates the output.

F_s shows the output at saturation. D_d shows the output at darkness. (Both F_s and D_d are digital.) S_e shows the saturation current, or the amount of exposure when the output saturates.




Figure 4-9-1 Saturation Exposure and Dark Current Output

By setting the offset, you can set the Yintercept arbitrarily. D_F shows the digital offset value. The gradient of the line does not change.




Figure 4-9-2 Offset Adjustment

- ◆ Adjust amount of offset in accordance with the requirements of your camera system.

4.10 Setting Gain

The camera can adjust the analog gain (x1 to x11.2 in 21 steps) and the digital gain. As shown in the figure below, increasing the gain setting increases the gradient of the camera's response curve and results in a higher camera output for a given amount of light. Analog gain can be changed by sending the "gax" command. Digital gain can be changed by sending the "gdx" command.




Figure 4-10-1 PGA Gain Adjustment

- ◆ Gain and noise values are proportionally related.
- ◆ Adjust the amount of gain in accordance with the requirements of your camera system.

Gain-Sensitivity is shown below.

Table 4-10-1 Gain-Sensitivity

	Analog Amplifier		Sensitivity (V/lx·s)
1	x1.00	0.00dB	70
2	x1.13	1.06dB	79
3	x1.28	2.12dB	89
4	x1.44	3.18dB	101
5	x1.63	4.24dB	114
6	x1.84	5.30dB	129
7	x2.08	6.36dB	146
8	x2.29	7.20dB	160
9	x2.59	8.26dB	181
10	x2.92	9.32dB	205
11	x3.31	10.40dB	232

	Analog Amplifier		Sensitivity (V/lx·s)
12	x3.74	11.46dB	262
13	x4.23	12.52dB	296
14	x4.78	13.58dB	334
15	x5.40	14.64dB	378
16	x6.10	15.70dB	427
17	x6.89	16.76dB	482
18	x7.78	17.82dB	545
19	x8.79	18.88dB	615
20	x9.93	19.94dB	695
21	x11.22	20.64dB	785

Digital gain x1, Pixel correction: default, (Factory white correction data, Correction level 600DN)

You can choose the A/D Characteristics of the camera's output by sending the "voc" command to switch between Linear mode or Log mode. The characteristics are shown in Figure 4-10-2.




Figure 4-10-2 A/D Characteristics

4.11 Pixel Correction

As a rule, image sensors (CCD, CMOS and so on) have fixed pattern noise and photo response non-uniformity. Lens shading and light sources can also cause non-uniformity. The camera is set to the optimal correction before shipping in order to provide images of the highest grade.

The camera also has a user white correction function to cope with lens shading and non-uniform illumination, or to be able to completely clear the uneven brightness generated by changing the spectral response level of the light source. Cal_bl: Output data of each pixel at perfectly dark (digital) Cal_wh: Output data of each pixel in uniform illumination (digital) Target_Val : Target value for correction (10bit digital) Vin :Input data (digital) Vout :Output data (digital) The corrected data is expressed in the following equation.
$$Vout = (Vin - Cal_bl) \times Target_val / (Cal_wh - Cal_bl)$$




Figure 4-11-1 Waveform before and after bit correction

4.11.1 Command Settings

Set the correction on or off, acquire user white correction data by sending commands through serial communication.

Examples of command settings

shc 0,600:	No correction
shc 1,600:	Factory white correction
shc 2,600:	User white correction
wht:	Acquisition of user white correction data

4.11.2 How to correct

(1) Remove the lens cap and place a white object. Then you can acquire user white correction data. With a lens, the shading by both the lens and the light source will be simultaneously corrected. At this time, please defocus a little to avoid being affected by the non-uniformity of the object.

(2) Send the “wht CR” command through serial communication.

(3) Confirm that the camera returns “>OK” and “>wht”. Thus user white correction data is saved and loaded to the camera.

(4) Send the “shc 2 VAL2 CR” command through serial communication. Then the user white correction will be on and set the correction level as “VAL2”.

4.12 Test Pattern

This camera can generate a test pattern. Use the test pattern to verify the proper timing and connections between the camera and the frame grabber board.

The test pattern of XCM8060SA, XCM8040SA is as follows.




Figure 4-12-1 Test Pattern of XCM8060SA, XCM8040SA



Figure 4-12-2 Test Image of XCM8060SA, XCM8040SA

The test pattern is a ramp from 0 to 1023DN in 10-bit mode, and then starts at 0 again.

The test pattern of XCM6040SA is as follows.



Figure 4-12-3 Test Pattern of XCM6040SA




Figure 4-12-4 Test Image of XCM6040SA

The test pattern is a ramp from 0 to 1023DN, and then from 0 to 511DN in 10-bit mode, then starts at 0 again.

5 Confirming Camera Settings

5.1 Before Power-on

(1) Confirm the pin assignment of the power cable.



No	NAME	Color of Cable
1	12 -15V	White
2	12 -15V	Red
3	GND	Green
4	GND	Black

Figure 5-1-1 Pin Assignment of Power Cable

(2) Confirm the direction and the channel of the cables. Some Camera Link cables are directional.

If one of the connectors says “Camera side”, connect this to the camera.




Figure 5-1-2 Connection Direction of Camera Cable

The connection channel of in the case of using a “Solios” board:

CL1 = CHANNEL #0

CL2 = CHANNEL #1




Figure 5-1-3 Channel of Camera Link Cables

5.2 After Power-on

(1) Confirm sent and received commands using the camera control utility. Launch CLISBeeCtrl, set COM port and connect. Click “Memory Dump” and wait for the response.




Figure 5-2-1 Confirmation of Connection

(2) Set a trigger mode and a video output mode with the camera control utility.

Trigger mode = Free run

Video output mode = 8bit




Figure 5-2-2 Exposure Mode, Video Output Mode Setting

- ◆ If you have your own application to check the images, select suitable settings.

(3) Capture images using a camera interface board utility. In the case of Matrox's Solios, it is convenient to use Intellicam.




Figure 5-2-3 Solios Window

5.3 During Operation

(1) Does an acquisition time out error occur?

<Cause>

<1> Captured images are too large.

If there are many filtering processes, the assignments to the driver may be insufficient.

<2> The cable is detached from the connector

Ensure that the power cable and Camera Link cables are connected to the camera firmly.

<3> Camera Link cables are susceptible to noise when the cables are laid near a light source inverter line or a power line. The personal computer in use may be freeze and need to be reset.

(2) Are there dark lines in the direction of vertical scanning on the image?

<Cause>

<1> Dust on the sensor window

Dust may get onto the sensor window from the inside or the outside of the camera. Remove the dust with air or a lens cleaner.

6 Sensor Handling Instructions

6.1 Electrostatic Discharge and the Sensor

CMOS sensors are susceptible to damage from electrostatic discharge and can deteriorate as a result. Take care when handling the sensor.

6.2 Protecting Against Dust, Oil and Scratches

The CMOS sensor window is part of the optical path and should be handled like other optical components with care. If you use the camera in a dusty area, prepare a dust-proof enclosure. Dust can obscure pixels, producing dark lines on the image.

6.3 Cleaning the Sensor Window

Dust: Can usually be removed by blowing the window surface using a compressed air blower.


Oil: Wipe the window with a lint-free cloth wiper moistened with ethyl alcohol carefully and slowly.


When there is dust or smudges on the sensor window, it appears in the same way as noise on the image. Please remove it appropriately.

7 Troubleshooting


The following pages contain several troubleshooting charts that can help you find the cause of problems users sometimes encounter.


7.1 No Image






7.2 Noise on Image





7.3 Camera becomes hot



8 CLISBeeCtrl

8.1 Overview

CLISBeeCtrl is the remote control software for “CLISBee” series cameras using the “**NED Camera Control Protocol**”(NCCP) from a PC.

Connectable interfaces are as follows.

- 1) Camera Link API
- 2) Communication Port (COM port, RS232C)

8.2 System Requirements

PC : PC/AT compatible

Operating System: Microsoft Windows 2000 or XP. (Windows Vista: not confirmed)

Free disk space: 1-2MB (Depending on the number of camera parameter files.)

Connection: Camera Link grabber board, Camera Link cables

8.3 Install

Copy the CLISBeeCtrl folder from the media (CD-ROM, etc) provided to your hard disk.



8.4 Uninstall

Remove the CLISBeeCtrl folder and all files in CLISBeeCtrl folder.

8.5 Operation

8.5.1 Start Program

Open Windows Explorer and Double-click the “CLISBeeCtrl.exe”.




Buttons in the tool-bar have the following functions.

- A: Export parameters in text file format.
- B: Connection with the camera.
- C: Disconnection.
- D: Communication Settings.
- E: Version Information.


8.5.2 Selecting interface and Timeout setting

8.5.2.1. Selecting interface

1) Click button D.



2) Select the interface from the Drop-down-list.




3) Click "Setting" button to set the interface. (See 8.5.2.2. and 8.5.2.3.)

4) Click "OK" button.

Click "Cancel" button to abort setup.

Note: The camera can be used without repeating this operation after it has been set up correctly.

8.5.2.2 Setting Communication port



1) Set up each item as follows;

- (1) Port: Select connecting port.
- (2) Bits per Second: 9600
- (3) Data bits: 8
- (4) Parity: None
- (5) Stop bits: 1
- (6) Flow control: None


Note: Other parameters are not used.

2) Click "OK" button.


Click "Cancel" button to abort setup.

Note: The camera can be used without repeating this operation after it has been set up correctly.

8.5.2.3 Setting Camera Link



- 1) Input the DLL file name for Camera Link API to the edit-box,
Or click “Browse” button and select the file.



- 2) Input value corresponding to the position of Camera Link cable to connect, into “Serial Index” column.

- 3) Click “OK” button.


Click “Cancel” button to abort setup.

Note: The camera can be used without repeating this operation after it has been set up correctly.

Note: DLL for Camera Link API is provided by the manufacturer of the grabber board.

The grabber board can also connect through the COM port of the PC (DLL is not provided). In this case, set the interface to the COM Port(RS232C). Please contact the board manufacturer for details. .

8.5.2.4 Setting Timeout



1) Input each timeout value in the edit-box (unit :ms)

Click “Default” to initialize the values in the edit-box.

The meanings of each timeout are as follows.

First Receive: The maximum time from sending a command to receiving the first data.

Next Receive: The maximum time between a letter and the next one.

Send: The maximum time until finishing sending a command.

2) Click “OK” button.


Click “Cancel” button to abort setup.

Note: The camera can be used without repeating this operation after it has been set up correctly.

8.5.3.Connect

Click button B, and you can control the camera. (See “8.6.Control”)

Then click “Memory Dump”.




8.5.4.Disconnect and end program

Click button C. Then click “X” button in the upper right of the window.




8.5.5.Check of the contents of communication

Click "Console" tag at the lower of a window.



8.5.6.Export Parameters to text file


- 1) Click button A.



- 2) Input file name and click “Save” button. The present setting value of each control is saved in text format.

8.5.7.Import Parameters from text file

- 1) Select menu “File” – “Text Load”



- 2) Input file name and click “Open” button.
Each command saved in the text file is issued one by one.

8.6 Control

8.6.1 Gains and Offsets

The screenshot shows a control interface with two main sections: Gain and Offset. The Gain section contains three controls: Analog 1 (a dropdown menu showing 'x1.0'), Analog 2 (a dropdown menu showing 'x1.000(0dB)'), and Digital (a slider between 'x1' and 'x2' with a numeric input box showing '0'). The Offset section contains a Digital control with a slider and a numeric input box showing '5'. Both sections have a 'Send' button next to their respective numeric inputs.

< Gain >

Analog 1 / Analog 2 :

The command will be sent to the camera every time you select from the menu in the drop-down-list.

Note: XCMx0x0SA does not use 'Analog 2'. (Included in 'Analog 1')

Digital :

Set the value with the slider, the edit-box or the spin-button. Then, click "Send" button.

< Offset >

Digital :

Set the value with the slider, the edit-box or the spin-button. Then, click "Send" button.

8.6.2 Clock & Integration

Clock : MHz
 Exposure time :
 Dividing
 Counter
 Integration Time = Counter / (Clock / 2 / Dividing) = 32.00 usec
 Padding
 Padding Time = Padding / (Clock / 2 / Dividing) = 0.00 usec
 Scanrate = 35.20 usec (Range : 3.20 - 684.80)
 usec

Clock :

Shows the camera internal clock frequency.

(Read Only)

Dividing / Counter :

Setting integration time.

First, choose the dividing clock from the drop-down-list.

Next, set the counter value with the slider, edit-box or the spin-button. Then, click "Send" button.

Integration Time :

Shows the calculated value of the integration time. (unit : μs)

Padding :

Set a value with the slider, the edit-box or the spin-button. Then, click "Send" button.

Padding Time :

Shows the calculated value of the padding time. (unit : μs)

Scanrate :


Shows the calculated value of the scan rate. (unit : μs)

Scanrate -> Counter Calculating :

Set the value in the edit-box. Then, click this button.

Input the desired scan rate value, then the counter value will be calculated automatically with the present values of clock, dividing and padding.

8.6.3 Trigger & Video



The screenshot shows a configuration window with four rows of controls:

- Trigger Mode :** A dropdown menu with "Free Run" selected.
- Video output :** Two dropdown menus. The first has "8bit" selected. The second has "**** 8192pixels" selected.
- ADC Characteristic :** A dropdown menu with "linear" selected.
- Direction of scanning :** A dropdown menu with "forward" selected.

The signal will be sent to the camera every time you select from the menu in the drop-down-list.

Trigger Mode :

The selection of Free Run Exposure mode and External Trigger Exposure mode.

Video output :

The selection of the number of the output bits and the output block.

ADC Characteristic :

The selection of the A/D characteristics.

Direction of scanning :

The selection of the scan direction.

8.6.4 Intelligence



< Calibration >

Calib White :

Acquisition of white data and saving the calibration data to camera's flash memory.

Mode / Level :


First, choose the mode from the drop-down-list.

Next, set a value with the slider, the edit-box or the spin-button. Then, click "Send" button.

Test Pattern :

The signal will be sent to the camera every time you choose the menu in the drop-down-list.

8.6.5 Memory in camera

**Memory Dump :**

Read the data from the camera's working memory.

Flash Load :

Load the data from the camera's flash memory.

Flash Save :

Save the data to the camera's flash memory.

Flash Initialize :

Initialize the camera's flash memory with the factory default data.

8.7 Upgrade

When a new software version becomes available, please follow the below procedure.

- 1) Check that CLISBeeCtrl has not started.
- 2) Uninstall the old version of the software. (See “8.4.Uninstall”)
- 3) Install new version of the software. (See “8.3.Install”)

8.8 How to Program

Please refer to the sample programs in the CLISBeeCtrl¥SampleProgram folder.

8.9 Other Points of Note

- 1) Unauthorised reproduction of part or all of this software is strictly prohibited.
- 2) Unauthorised reverse engineering, decompiling, disassembling and modifying part or all of this software is strictly prohibited.
- 3) The contents of this software may change in the future without notice.

9 Others

9.1 Notice

- No part of this document may be reproduced in any form, in whole or in part, without the express written consent of NED.
- The contents of this document are subject to change without prior notice.
- Every care has been taken in the preparation of this User's Manual. If you should discover any errors or omissions, please notify your nearest NED representative.

9.2 Contact for support

Nippon Electro-Sensory Devices Corporation

Head Office

2-5-12, Itachibori, Nishi-ku, Osaka 550-0012, Japan

Phone +81-6-6534-5300

Fax +81-6-6534-6080

Tokyo Branch

Jiburaruta Seimei Oi BLDG., Room No.402

1-45-2, Oi, Shinagawa-ku, Tokyo 140-0014, Japan

Phone +81-3-5718-3181

Fax +81-3-5718-0331

Nishi-Nippon Branch

Twin Square 1-8-28 Enokida, Hakata-ku, Fukuoka, 812-0004, Japan

Phone +81-92-451-9333

Fax +81-92-451-9335

URL

<http://ned-sensor.co.jp/en>

E-Mail

sales@ned-sensor.com

9.3 Product Support

If there is a problem with your camera after checking it in accordance to the troubleshooting, turn off the power and call your NED representative.

When contacting us with a problem, please inform us of the status of the camera. You can get the status by

- (1) executing the “sta” command, or
- (2) clicking “Memory Dump” button when using CLISBeeCtrl.

The example of the camera status.

```
sta
>OK
>Type=XCM8060SAT4
>Ver.=1.10
>Serial=517
>gaa 1
>gab 0
>gdx 0
>odx 0
>inm 0
>int 0,120
>cka 0
>voa 1,0
>voc 0
>tpn 0
>shc 3,600
>pad 0
>sta
```

Revision History

Revision Number	Date	Changes
01	28 Nov. 2008	Initial release
02	1 Nov. 2009	Changed Trigger pulse L time of Table 4-8-2-1, 4-8-3-1 Programmable Exposure Time.
03	14 Jan. 2010	Cancel the Figure 1-3-1 Block Diagrams of Image Sensors
04	30 Apr. 2010	Nishi-Nippon Branch address change etc.
05	7 Jul. 2010	Add directive on WEEE etc.
06	20 Oct. 2010	Regarding the choice of Camera Link cable etc.
07	10 Jun. 2011	Add calculated value of maximum cable length.
08	20 Sep. 2011	Correct a sentence.