

Discrete Output Modules

IC697MDL341

GFK-0382J
August 1997

120/240 Volt AC, 2 Amp Isolated 12-Point Output Module

Features

- 12 individually isolated points
- 2 amp capacity per point
- High inrush capacity (10x rated current)

Functions

The 120/240 Volt AC 2 Amp Isolated Output Module for use with a Programmable Logic Controller (PLC) provides 12 isolated output points. This allows each point to be used on different phases of the AC supply. Each output point is individually fused with a 3.15 amp replaceable fuse.


The module provides a high degree of inrush current which makes the outputs suitable for a wide range of inductive and incandescent loads. The module will operate most size 4 contactors.

LED indicators which give the ON - OFF status of each point on the logic (PLC) side of the circuit as well as an LED to indicate the status of the fuses are located at the top of the module. If one or more of the fuses should blow, this LED will turn ON.

The module is mechanically keyed to ensure correct replacement with a similar module type in the field. I/O references are user configurable without the use of jumpers or DIP switches on the module.

Configuration is done using the configuration function of the MS-DOS® or Windows® programming software running on Windows® 95 or Windows NT® over Ethernet TCP/IP or through the SNP port. The Programming Software configuration function is installed on the programming device. The programming device can be an IBM® XT, AT, PS/2® or compatible Personal Computer.

Although this module is configured as a 16 point output, only outputs 1 through 12 are available to be referenced in your program. For example, if the starting reference is Q0017, then valid references are Q0017 through Q0028.



© IBM and PS/2 are registered trademarks of International Business Machines Corporation.

© MS-DOS, Windows, Windows 95, and Windows NT are registered trademarks of Microsoft Corporation.

GFK-0382J
August 1997

120/240 Volt AC, 2 Amp Isolated 12-Point Output Module

Operation - 120/240 Volt AC 2 Amp Isolated Output Module




Figure 1. Block Diagram for IC697MDL341

Output Characteristics

The 120/240 Volt AC 2 Amp Isolated Output Module is compatible with a wide variety of load devices, such as:

- Solenoids
- Motor starters
- Indicators

The rating of 2 amps per point applies to the long-term current capacity of each point. Because of overall heat dissipation within the module, the maximum current for the module is limited to 16 amperes.

Each output on this module is capable of transiently conducting a surge current which is much greater than its long-term current rating. The rate at which such surges can be repeated depends on the current rating of the device and the duty cycle (percent of time the device is ON).

For typical incandescent devices operating at a 50% duty cycle, the following repetition rates apply to this module.

Steady-State Current (mA)	Repetition Rate (Hz)
0.5	5
1	1
2	0.1

Fault Mode Selection

This output module can be configured from the programmer so that output points assume one of two states in response to certain operating or default conditions. These states are:

- Maintain existing output state
- Turn outputs OFF

For more detailed information on module configuration, refer to the Programming Software User's Manual for IC641 software products.

Fusing

Each output is fused with a replaceable 3.15 amp fuse. Replace with the following type:

- Metric 5 x 20 mm - 3.15 amp, 250V, Slo-blo

Module Mechanical Keying

This module includes a mechanical key that prevents inadvertent substitution of one module type for another in a given slot. The key fits a uniquely shaped area on the board below the connector. Each module has a key packaged with it.

When the module is first installed, the key latches onto the backplane center rail. When the module is extracted, the key remains in the center rail, configuring the slot to accept only identical module types.

If it is necessary to change the module location in the rack after the key has been latched onto the center rail of the rack, the key can be removed by pushing it upward to unhook the latch while pulling it off the rail. It may then be reinserted onto the module and the module inserted into the rack in the desired location.

Note that only a power supply can be placed in the left-most rack position, and slot 1 (adjacent to the power supply) must always contain a CPU (in rack 0 - the CPU rack), or a Bus Receiver Module (in an expansion rack).

120/240 Volt AC, 2 Amp Isolated 12-Point Output Module

GFK-0382J
August 1997

Field Wiring

The module is wired as shown in Figure 2. Since each output is isolated from the other outputs, a wire from the power source to the power input terminal for each output is required (power input terminals for each output are not connected inside the module).

The detachable field wiring terminal board will accept wire sizes from #22 (0.36 mm²) through #14 (2.10 mm²). Two wires may be terminated on a given lug if both wires are the same size. There is room for a bundle of forty #14 (2.10 mm²) wires to be routed out through the terminal board cavity.

The wire bundle can be secured to the terminal board by passing a cable tie through a cleat located at the lower corner of the terminal board.




Figure 2. Field Wiring Connections

GFK-0382J
August 1997

120/240 Volt AC, 2 Amp Isolated 12-Point Output Module

Recommended Field Wiring Procedures

The following procedures are recommended when connecting field wiring to the detachable terminal board on this input

module. Module features referenced in the following procedures which are common to all IC697 I/O modules are illustrated in the following figure.




Figure 3. I/O Module Features

1. Turn off power before removing or installing terminal boards. Open the hinged door on the module to access a jackscrew which holds the terminal board securely in place. The detachable field wiring terminal board can now be removed from the module by turning the jackscrew counter-clockwise until it is fully disengaged.
2. To remove the terminal board, grasp the top of the terminal board and swing it outward as shown in Figure 4.
3. The terminal board is designed to accept wire sizes from AWG #22 (0.36 mm) through AWG #14 (2.10 mm²). It is important that when using AWG #14 (2.10 mm²) wire for wiring all points, that a maximum insulation diameter of .135 inch (3.43) not be exceeded. To ensure proper connection, two wires may be terminated on any one terminal only if both wires are the same size.
4. The terminal board is designed to accept a maximum of (40) AWG #14 (2.10 mm²) wires. If AWG #14 (2.10 mm²) wires are to be used, then wire markers should be placed at least 8 inches (203 mm) from termination end to provide sufficient space for the hinged door to close.

Caution

Do not use the hinged door to remove the terminal board. The hinged door could be damaged if this is done.

120/240 Volt AC, 2 Amp Isolated 12-Point Output Module


GFK-0382J
August 1997

Figure 4. Removal of I/O Terminal Board

5. After completing connections to all modules in a rack, the wire bundle must be secured. To ensure that the wire bundle is secured properly, it is recommended that a cable tie be wrapped around the wire bundle and tightly secured through the cable tie cleat located at the lower right corner of the terminal board. For extremely large wire bundles, additional cable ties should be used.
6. A door label insert is included with each module to indicate circuit wiring information and provide space to record user circuit wiring identification. A slot is provided on the hinged door to allow for insertion of this label. If the label is difficult to insert, crease the scored edge before insertion. The outside label has a color coded stripe to allow quick identification of the module voltage type (blue: low voltage; red: high voltage).
7. After field wiring is completed, the terminal board should be securely fastened to the rack by inserting the terminal board strap (attached to each module) into the small rectangular slots in the bottom card guide grill on the rack. This strap not

only secures the terminal board to the rack, it also provides a way of identifying the wired terminal board with its correct mating rack slot location.

8. For adequate module ventilation, it is recommended that at least a 6 inch (152mm) clearance be allowed above and below the rack grill. Wire bundles should not obstruct the rack grill work.

Removing an I/O Module

The instructions below should be followed when removing an I/O module from its slot in a rack.

- Grasp the board firmly at the top and bottom of the board cover with your thumbs on the front of the cover and your fingers on the plastic clips on the back of the cover.
- Squeeze the rack clips on the back of the cover with your fingers to disengage the clip from the rack rail and pull the board firmly to remove it from the backplane connector.
- Slide the board along the card guide and remove it from the rack.

GFK-0382J
August 1997

120/240 Volt AC, 2 Amp Isolated 12-Point Output Module

Table 1. Specifications for IC697MDL341 †

Rated Voltage:	120/240 volts AC
Outputs per Module:	12 individually isolated
Isolation:	1500 volts - any output to backplane 500 volts between points
Output Voltage Range:	85 to 264 volts AC, 47-63 Hz
Output Current:	2 amps maximum per point 16 amps maximum per module
Output Characteristics	
Inrush Current:	20 amps maximum for one cycle (20 ms)
Output Voltage Drop:	1.5 volts maximum
Response Time-On:	1 ms maximum
Response Time-Off:	1/2 cycle maximum
Output Leakage:	3 mA maximum at 120 volts AC 6 mA maximum at 240 volts AC
Current Required from 5 V Bus:	.25 amp
VME	System designed to support the VME standard C.1

† Refer to GFK-0867B, or later for product standards and general specifications. For installations requiring compliance to more stringent requirements (for example, FCC or European Union Directives), refer to *Installation Requirements for Conformance to Standards*.

Table 2. Ordering Information

Description	Catalog Number
OutputModule, 120/240VAC, 2 Amp Isolated, 12 Points	IC697MDL341

Note: For Conformal Coat option, or Low Temperature Testing option please consult the factory for price and availability.