SyncMaster P42HP,P50HP

# **PDP Monitor**

## **User Manual**

## **Safety Instructions**

## Notational

🖉 Note

These safety instructions must be followed to ensure your safety and prevent property damage.

Make sure to read the instructions carefully and use the product in the correct manner. UWarning / Caution



Failure to follow directions noted by this symbol could result in bodily harm or damage to the equipment.

## Notational Conventions



## Power

When not used for extended period of time, set your computer to DPM.

If using screen saver, set it to active screen mode.

The images here are for reference only, and are not applicable in all cases (or countries).

Shortcut to Anti-Afterimage Instructions



•

Do not use a damaged power cord or plug or a damaged or loose power outlet.

Otherwise, this may result in electric shock or fire.

Otherwise, this may result in electric shock.



Do not touch the power plug with wet hands when removing or plugging the plug into the outlet.



Make sure to connect the power cord to a grounded power outlet.



Otherwise, it may result in electric shock or personal injury.



Ensure that the power plug is plugged into the power outlet firmly and correctly.

• Otherwise, this may result in fire.

Do not forcefully bend or pull the power plug and do not place any heavy material on it.

• Otherwise, this may result in fire.

Do not connect multiple appliances to the same power outlet.

• Otherwise, this may cause fire due to overheating.



Do not disconnect the power cord while using the product.

• Otherwise, this may result in damage to the product due to electric shock.



■ To disconnect the apparatus from the mains, the plug must be pulled out from the mains socket, therefore the mains plug shall be readily operable.

This may cause electric shock or fire.

Use only the power cord provided by our company. Do not use the provided power cord of another product.

• Otherwise, this may result in fire or electric shock.

## Installation



 $\bigcirc$ 

Be sure to contact an authorized Service Center when installing your monitor in a location with heavy dust, high or low temperatures, high humidity, and exposed to chemical substances and where it operates for 24 hours such as at airports, train stations etc.

Failure to do so may cause serious damage to your monitor.



Ensure that at least two persons lift and move the product.

• Otherwise, it may be dropped and cause personal injury, and/ or damage the product.



When installing the product in a cabinet or rack, make sure that the front end of the bottom of the product does not project out.

- Otherwise, it may fall or cause personal injury.
- Use a cabinet or rack of a size appropriate to the product.



DO NOT PLACE CANDLES, MOSQUITO REPELLANT, CIG-ARETTES AND ANY HEATING APPLIANCES NEAR THE PRODUCT.

Otherwise, this may result in fire.



### Clean



When cleaning the monitor case or the surface of the PDP screen, wipe with a slightly moistened, soft fabric.



Do not spray cleaner directly onto the surface of the product.





Clean the product using a soft cloth with a monitor cleaner only. If you must use a cleaner other than the monitor cleaner, dilute it with water at a ratio of 1:10.



When cleaning the power plug pins or dusting the power outlet, clean it with a dry cloth.

• Otherwise, it may result in fire.

When cleaning the product, make sure to disconnect the power cord.

cle

Otherwise, it may result in electric shock or fire.

When cleaning the product, disconnect the power cord and clean it softly with a dry cloth.

 (Do not use chemicals such as wax, benzene, alcohol, thinner, mosquito repellant, lubricant, or cleaner.) These may change the appearance of the product surface and peel off the indication labels on the product.

Since the product housing is easily scratched, make sure to use the specified cloth only.

 Use the specified cloth adding only a little water. As the product may be scratched if there is any foreign material on the cloth, make sure to shake it thoroughly before using it.



When cleaning the product, do not spray water directly onto the main body of the product.

- Ensure that water does not enter the product and that it is not wet.
- Otherwise, this may result in electric shock, fire or a malfunction.

## Others



The product is a high voltage product. Ensure that users do not disassemble, repair or modify the product themselves.

• Otherwise, this may result in electric shock or fire. If the product needs to be repaired, contact a Service Center.



If there is a strange smell or a strange sound or smoke is coming from the product, disconnect the power plug immediately and contact a Service Center.



• Otherwise, this may result in electric shock or fire.

Do not place this product in a location exposed to moisture, dust, smoke, water, or in a car.

• Otherwise, this may result in electric shock or fire.



When you drop the product or the case is broken, turn the power off and disconnect the power cord. Contact a Service Center.

Otherwise, this may result in electric shock or fire.



If thunder or lightening is occurring, do not touch the power cord or antenna cable.

Otherwise, this may result in electric shock or fire.



Do not try to move the monitor by pulling only the wire or the signal cable.

Otherwise, it may fall and result in electric shock, damage to the product or fire due to damage to the cable.



Do not lift or move the product back and forwards or right and left while only holding the power cord or signal cables.

Otherwise, it may fall and result in electric shock, damage to the product or fire due to damage to the cable.



Make sure that the ventilating opening is not blocked by a table or curtain.

Otherwise, it may result in fire due to an increase in the internal temperature.



Do not place any containers containing water, vases, flowerpots, medicines as well as any metal on the product.

- If water or a foreign material enters the product, disconnect the power cord and contact a Service Center.
- This may result in a product malfunction, electric shock, or fire.



Do not use or keep combustible spray or flammable material near the product.

• Otherwise, this may result in an explosion or fire.



Do not insert any metal, such as chopsticks, coins, pins and steel, or flammable objects, such as matches or paper, inside the product (through the ventilating openings, input and output terminals, etc).

- If water or foreign material enters the product, disconnect the power cord and contact a Service Center.
- Otherwise, this may result in electric shock or fire.

0	
U	

When using a fixed screen for a long time, an afterimage or stain may occur.

If you are not using your product for a long period of time, put it into sleep mode or use a moving screen saver.

Set a resolution and frequency appropriate to the product.



Otherwise, your eyesight may be damaged.



When using headphones or earphones, do not turn the volume too high.

Having the sound too loud may damage your hearing.



If you continually move closer to the product screen, your eyesight may be failing.



Take a rest for at least five (5) minutes after using the monitor for one (1) hour.

(()))

This reduces the weariness of your eyes.

Do not install it in an unstable location such as an unstable rack or uneven surface or a location exposed to vibrations.

- Otherwise, it may fall and cause personal injury and/or damage the product.
- If you use the product in a location exposed to vibrations, it may damage the product and result in fire.



When moving the product, turn the power off and disconnect the power plug, antenna cable, and all the cables connected to the product.

Otherwise, it may result in electric shock or fire.



Ensure that children do not hang onto the product or climb up onto the product.

• The product may fall and cause personal injury or death.



▶ If you do not use the product for a long period of time, disconnect the power cord from the power outlet.

• Otherwise, this may result in overheating or fire due to dust, and may result in fire due to electric shock or leakage.



Do not place any heavy items or toys or confectionery, such as cookies etc. that may attract the attention of children and to the product.

• Your children may hang onto the product causing it to fall and this may result in personal injury or death.



Be careful that children do not place the battery in their mouths when removed from the remote control. Place the battery in a location that children or infants cannot reach.

• If children have had the battery in their mouths, consult your doctor immediately.

When replacing the battery, insert it with right polarity (+, -).





Use only the specified standardized batteries, and do not use a new battery and a used battery at the same time.

• Otherwise, the batteries may be damaged or cause fire, personal injury or damage due to a leakage of the internal liquid.



■ The batteries (and rechargeable batteries) are not ordinary refuse and must be returned for recycling purposes. The customer is responsible for returning the used or rechargeable batteries for recycling.

The customer can return used or rechargeable batteries to a nearby public recycling center or to a store selling the same type of the battery or rechargeable battery.



Do not place the product in a location exposed to direct sunlight or near any heat such as a fire or heater.

This may reduce the lifetime of the product, and may result in fire.



- Do not drop any objects onto the product or cause any impact to the product.
- Otherwise, this may result in electric shock or fire.



- Do not use a humidifier or kitchen table near the product.
- Otherwise, this may result in electric shock or fire.



When there is a gas leak, do not touch the product or the power plug but ventilate immediately.

If a spark occurs, it may cause an explosion or fire.



If the product has been turned on for a long time, the display panel becomes hot. Do not touch it.

- Keep the small accessories in a location out of the reach of children.
  - Be careful when adjusting the angle of the product or the height of the stand.
    - This may result in personal injury as your hand or fingers may become caught.
  - Also, if you tilt the product too far, it may fall and cause personal injury.



Do not install the product in a location low enough for children to reach.

- Otherwise, it may fall and result in personal injury.
- Since the front part of the product is heavy, install the product on a level and stable surface.



- Do not put any heavy objects on the product.
- This may result in personal injury and/or damage to the product.

## Introduction

## **Package Contents**

🖉 Note

Please make sure the following items are included with your PDP Display.

If any items are missing, contact your dealer.

Contact a local dealer to buy optional items.

## Unpacking



PDP Display





Quick Setup Guide





User's Guide

Cables



**D-Sub Cable** 



Warranty Card

(Not available in all locations)

Others



**Remote Control** 

Power Cord







Ferrite Core for Power Cord



- You can purchase and connect a separate network box or TV tuner box. For information on how to use these, refer to their respective user manuals.
- You can only connect one external box.

#### Ferrite Core (Power Cord)



- The ferrite cores are used to shield the cables from interference.
- When connecting a cable, open the ferrite core and clip it around the cable near the plug.

## Your PDP Display

#### Front



SOURCE button [SOURCE]

Switches from PC mode to Video mode. Changing the source is only allowed for external devices that are connected to the PDP Display at the time.

 $[PC] \rightarrow [DVI] \rightarrow [AV] \rightarrow [HDMI] \rightarrow [MagicInfo] \rightarrow [TV] \rightarrow [BNC] \rightarrow [Component] \\ \hline \bigcirc \\ Note \\ \label{eq:product}$ 

• The **TV** menu is available when a TV tuner box is installed.

• The MagicInfo menu is available when a network box is installed.

Enter button [@]

Activates a highlighted menu item.

MENU button [MENU]

Opens the on-screen menu and exits from the menu. Also use to exit the OSD menu or return to the previous menu.

3 - VOL+

Moves from one menu item to another horizontally or adjusts selected menu values. When OSD is not on the screen, push the button to adjust volume.

🕘 🛛 A SEL V

Moves from one menu item to another vertically or adjusts selected menu values.

/ When OSD is not on the screen, push the button to adjust channel.

Power button [🖒 ]

Use this button for turning the PDP Display on and off.

6	Power indicator
	Shows PowerSaver mode by blinking green
	See PowerSaver described in the manual for further information regarding power saving functions. For energy conservation, turn your PDP Display OFF when it is not needed or when leaving it unattended for long periods.
7	Remote Control Sensor
	Aim the remote control towards this spot on the PDP Display.

#### Rear

## 🖉 Note

For detailed information concerning cable connections, refer to Connecting Cables under Setup. The PDP Display 's configuration at the back may vary slightly depending on the PDP Display model.





B



## 🕑 POWER

The power cord plugs into the PDP Display and the wall plug.



BNC/COMPONENT OUT [R/P<sub>R</sub>, G/Y, B/P<sub>B</sub>, H, V] (BNC/Component Connection Terminal (Output))

BNC (Analog PC) Connection: connecting the R, G, B, H, V ports

Component Connection: connecting the  $P_{R}$ , Y,  $P_B$  ports

<sup>3</sup> BNC/COMPONENT IN [R/P<sub>R</sub>, G/Y, B/ P<sub>B</sub>, H, V] (BNC/Component Connection Terminal (Input))

С



RS232C OUT/IN (RS232C Serial PORT)

MDC(Multiple Display Control) Program Port

5 DVI / PC / HDMI IN [DVI/PC/HDMI AU-DIO IN] (PC/DVI/HDMI Audio Connection Terminal (Input))

## 🏮 DVI / PC / HDMI IN [HDMI]

Connect the HDMI terminal at the back of your PDP Display to the HDMI terminal of your digital output device using a HDMI cable.

*VI / PC / HDMI IN [RGB](PC Video Connection Terminal)* 

Using a D-Sub Cable (15 pin D-Sub) - PC mode (Analog PC)

<sup>8</sup> DVI / PC / HDMI IN [DVI] (PC Video Connection Terminal)

Using a DVI Cable (DVI-D to DVI-D) - DVI mode (Digital PC)



9DC OUT [5V/1.5A]

Connect this to the POWER connector of a TV tuner box or network box.

🕕 AV IN [VIDEO]

Connect the [VIDEO] terminal of your monitor to the video output terminal of the external device using a VIDEO cable.

U AV/COMPONENT AUDIO IN [L- AUDIO - R]

Connect the port of the DVD, VCR (DVD / DTV Set-Top Box) to the [L-AUDIO - R] port of the PDP Display.

但 AUDIO OUT [L- AUDIO - R]

Headphone output terminal.

#### Kensington Lock

The Kensington Lock is a device used to physically fix the system when using it in a public place. The locking device has to be purchased separately. The appearance and locking method may differ from the illustration depending on the manufacturer. Refer to the manual provided with the Kensington Lock for proper use. The locking device has to be purchased separately.

## 🖉 Note

The location of the Kensington Lock may be different depending on its model.

## Using the Anti-Theft Kensington Lock

- Insert the locking device into the Kensington slot on the Monitor <sup>B</sup>and turn it in the locking direction <sup>A</sup>.
- 2. Connect the Kensington Lock cable.
- 3. Fix the Kensington Lock to a desk or a heavy stationary object.



See Connecting Cables for further information regarding cable connections.



## **Remote Control**



The performance of the remote control may be affected by a TV or other electronic device operating near the PDP Display , causing a malfunction due to interference with the frequency.



1. Ü POWER	Turns the product On.
2. 🗆 Off	Turns the product Off.
3. Number Buttons	Press to change the channel.
4. DEL button	The "-" button operates only for DTV. It is used to select MMS (multi-channel) for a DTV.
5. + VOL -	Adjusts the audio volume.
6. 🕸 MUTE	Pauses (mutes) the audio output temporarily. This is dis- played on the lower left corner of the screen. The audio resumes if MUTE or - VOL + is pressed in the Mute mode.
7. TV/DTV	Selects the TV and DTV mode directly.
8. 🎵 MENU	Opens the on-screen menu and exits from the menu or closes the adjustment menu.
9. 🕒	Activates a highlighted menu item.
10. <i>i</i> INFO	Current picture information is displayed on the upper left corner of the screen.
11. Color Buttons	Press to add or delete channels and to store channels to the favorite channel list in the "Channel List" menu.
12. 12. 12. 12. 12. 12. 12. 12. 12. 12.	TV channels provide written information services via tele- text.
	- Teletext Buttons
8	$\exists , 10 \boxdot , 18 \boxdot , 18 \blacksquare , 19 \blacksquare , 29 \boxminus / 19 , 29 \blacksquare , 29 \blacksquare , 23 \blacksquare , 25 \blacksquare ,$
	For more information > TTX / MIX
13. STILL	Press the button once to freeze the screen. Press it again to unfreeze.
14. AUTO	Adjusts the screen display automatically in <b>PC</b> mode. By changing the resolution in the control panel, auto function is performed.
15. S.MODE	When pressing this button, the current mode is displayed at the bottom centre of the screen. The PDP Display has a built-in high fidelity stereo amplifier. Then press the button again to circle through available preconfigured modes. (Standard $\rightarrow$ Music $\rightarrow$ Movie $\rightarrow$ Speech $\rightarrow$ Custom )
16. MDC	MDC Quick Launch Button.
17. LOCK	Activates or deactivates all function keys on both the remote control and the PDP Display except for the Power and LOCK buttons.
18. 🖅 SOURCE	Press the button to change the input signal SOURCE.
	Changing the SOURCE is only allowed for external devices that are connected to the monitor at the time.

19. 🖭 ENTER/PRE-CH	This button is used to return to the immediately previous channel.				
20. <b>∨</b> CH/P <b>∧</b>	In <b>TV</b> mode, selects TV channels.				
21. D.MENU	DTV menu display				
22. GUIDE	Electronic Program Guide (EPG) display.				
23. 🖱 RETURN	Returns to the previous menu.				
24. Up-Down Left-Right but- tons	Moves from one menu item to another horizontally, vertically or adjusts selected menu values.				
25. 🗝 🗭 EXIT	Exits from the menu screen.				
26. (●) SRS	Selects SRS TruSurround XT mode.				
27. MagicInfo	MagicInfo Quick Launch Button.				
28. P.MODE	When you press this button, current picture mode is displayed on the lower center of the screen.				
	AV / HDMI / TV / Component : P.MODE				
	The PDP Display has four automatic picture settings that are preset at the factory. Then push button again to circle through available preconfigured modes. ( <b>Dynamic</b> $\rightarrow$ <b>Standard</b> $\rightarrow$ <b>Movie</b> $\rightarrow$ <b>Custom</b> )				
	through available preconfigured modes. ( Dynamic $\rightarrow$				
	through available preconfigured modes. ( Dynamic $\rightarrow$				
	through available preconfigured modes. ( <b>Dynamic</b> $\rightarrow$ <b>Standard</b> $\rightarrow$ <b>Movie</b> $\rightarrow$ <b>Custom</b> )				
29. <sup>H</sup> DUAL/MTS	through available preconfigured modes. ( <b>Dynamic</b> $\rightarrow$ <b>Standard</b> $\rightarrow$ <b>Movie</b> $\rightarrow$ <b>Custom</b> ) <b>PC / BNC / DVI / MagicInfo</b> <b>MagicBright</b> is a feature providing the optimum viewing environment depending on the contents of the image you are watching. Then push button again to circle through available preconfigured modes. (Entertain $\rightarrow$ Internet $\rightarrow$ Text $\rightarrow$				
29. HI DUAL/MTS	through available preconfigured modes. ( <b>Dynamic</b> $\rightarrow$ <b>Standard</b> $\rightarrow$ <b>Movie</b> $\rightarrow$ <b>Custom</b> ) <b>PC / BNC / DVI / MagicInfo</b> <b>MagicBright</b> is a feature providing the optimum viewing environment depending on the contents of the image you are watching. Then push button again to circle through available preconfigured modes. (Entertain $\rightarrow$ Internet $\rightarrow$ Text $\rightarrow$ <b>Custom</b> )				
29. <sup>H</sup> I DUAL/MTS	through available preconfigured modes. ( Dynamic → Standard → Movie → Custom ) <i>PC / BNC / DVI / MagicInfo</i> MagicBright is a feature providing the optimum viewing en- vironment depending on the contents of the image you are watching. Then push button again to circle through available preconfigured modes. (Entertain → Internet → Text → Custom ) <i>DUAL</i> - STEREO/MONO, DUAL I / DUAL II and MONO/NICAM MONO/NICAM STEREO can be operated depending on the broadcasting type by using the DUAL button on the remote				
29. <sup>HI</sup> DUAL/MTS	through available preconfigured modes. ( <b>Dynamic</b> $\rightarrow$ <b>Standard</b> $\rightarrow$ <b>Movie</b> $\rightarrow$ <b>Custom</b> ) <b>PC / BNC / DVI / MagicInfo</b> <b>MagicBright</b> is a feature providing the optimum viewing environment depending on the contents of the image you are watching. Then push button again to circle through available preconfigured modes. (Entertain $\rightarrow$ Internet $\rightarrow$ Text $\rightarrow$ <b>Custom</b> ) <b>DUAL</b> - STEREO/MONO, DUAL I / DUAL II and MONO/NICAM MONO/NICAM STEREO can be operated depending on the broadcasting type by using the DUAL button on the remote control while watching TV.				
29. H DUAL/MTS	through available preconfigured modes. ( <b>Dynamic</b> $\rightarrow$ <b>Standard</b> $\rightarrow$ <b>Movie</b> $\rightarrow$ <b>Custom</b> ) <b>PC / BNC / DVI / MagicInfo</b> <b>MagicBright</b> is a feature providing the optimum viewing environment depending on the contents of the image you are watching. Then push button again to circle through available preconfigured modes. (Entertain $\rightarrow$ Internet $\rightarrow$ Text $\rightarrow$ <b>Custom</b> ) <b>DUAL</b> - STEREO/MONO, DUAL I / DUAL II and MONO/NICAM MONO/NICAM STEREO can be operated depending on the broadcasting type by using the DUAL button on the remote control while watching TV. <i>MTS</i> -				
29. HI DUAL/MTS	through available preconfigured modes. ( $Dynamic \rightarrow Standard \rightarrow Movie \rightarrow Custom$ ) <i>PC / BNC / DVI / MagicInfo</i> MagicBright is a feature providing the optimum viewing environment depending on the contents of the image you are watching. Then push button again to circle through available preconfigured modes. (Entertain $\rightarrow$ Internet $\rightarrow$ Text $\rightarrow$ Custom ) <i>DUAL</i> - STEREO/MONO, DUAL 1 / DUAL II and MONO/NICAM MONO/NICAM STEREO can be operated depending on the broadcasting type by using the DUAL button on the remote control while watching TV. <i>MTS</i> - You can select MTS (Multichannel Television Stereo) mode. FM Stereo Mono Mono Manual Stereo Mono $\leftrightarrow$ Stereo Change				

31. SWAP

Swaps the contents of the PIP and main image. The image in the PIP window will appear on the main screen, and the main screen image will appear in the PIP window.

- This fuction does not work for this PDP Display.

Mechanical Layout (P42HP)

**Mechanical Layout** 

## **NETWORK MODEL SIZE**







## **PDP Display Head**

## **NETWORK MODEL SIZE**



## Installation VESA Bracket

- When installing VESA, make sure to comply with the international VESA standards.
- Purchasing VESA Bracket and Installation Information : Please contact your nearest SAMSUNG Distributor to place an order. After your order is placed, installation professionals will visit you and install the bracket.
- At least 2 persons are needed in order to move the PDP Display.
- SAMSUNG is not responsible for any product damage or any injury caused by installation at customer's discretion.

## **Dimensions**



## 

For securing the bracket on a wall, use only machine screws of 6 mm diameter and 8 to 12 mm length.

## Wall Bracket Installation

- Contact a technician for installing the wall bracket.
- SAMSUNG Electronics is not responsible for any damages to the product or harm to customers when the installation is done by the customer.
- This product is for installing on cement walls. The product may not stay in place when installed on plaster or wood.

## Components

Only use the components and accessories shipped with the product.



## Wall Bracket Assembly

🖉 Note

There are two hinges(left and right). Use the correct one.

1. Insert and tighten the Captive Screw in the direction of the arrow.

When done, mount the wall bracket on the wall.



There are two hinges(left and right). Use the correct one.

- A Captive Screw
- B Wall Bracket
- C Hinge (Left)
- D Hinge (Right)
- 2. Before drilling into the wall, check if the length between the two locking holes at the back of the product is correct.

If the length is too short or long, loosen all or some of the 4screws on the wall bracket to adjust the length.



- A Length between the two locking holes
- 3. Check the installation diagram and mark the drill points on the wall. Use the 5.0 mm bit to drill holes deeper than 35 mm. Fix each anchor in the corresponding hole. Match each of the brackets and hinge holes to the corresponding anchor holes and insert and tighten the 11 screws A.



## To mount the product on the wall bracket

The shape of the product may vary depending on the model. (The assemblies of the plastic hanger and the screw are the same)

1. Remove the 4 screws on the back of the product.



2. Insert the screw B into the plastic hanger.



## 

- Mount the product on the wall bracket and make sure it is properly fixed to the left and right plastic hangers.
- Be careful when installing the product on the bracket as fingers can be caught in the holes.
- Make sure the wall bracket is securely fixed to the wall, or the product may not stay in place after installation.
- 3. Tighten the 4 screws in step 2 (plastic hanger + screw B)to the rear holes of the product.



4. Remove safety pin (3) and insert the 4 product holders into the corresponding bracket holes (1). Then place the product(2) so that it is firmly fixed to the bracket. Make sure to re-insert and tighten the safety pin (3) to securely hold the product to the bracket.



- A PDP Display
- B Wall Bracket
- C Wall

## Wall Bracket Angle Adjustment

Adjust the bracket angle to -2° before installing it on the wall.



- 1. Fix the product to the wall bracket.
- 2. Hold the product at the top in the center and pull it forward (direction of the arrow) to adjust the angle.



You can adjust the bracket angle between -2° and 15°.



Make sure to use the top center, and not the leftor the right side of the product to adjust the angle.

## **Mechanical Layout (P50HP)**

### **Mechanical Layout**

## **NETWORK MODEL SIZE**



## **PDP Display Head**

## **NETWORK MODEL SIZE**



## **Installation VESA Bracket**

- When installing VESA, make sure to comply with the international VESA standards.
- Purchasing VESA Bracket and Installation Information : Please contact your nearest SAMSUNG Distributor to place an order. After your order is placed, installation professionals will visit you and install the bracket.
- At least 2 persons are needed in order to move the PDP Display.

• SAMSUNG is not responsible for any product damage or any injury caused by installation at customer's discretion.

## Dimensions



## 

For securing the bracket on a wall, use only machine screws of 6 mm diameter and 8 to 12 mm length.

### Wall Bracket Installation

- Contact a technician for installing the wall bracket.
- SAMSUNG Electronics is not responsible for any damages to the product or harm to customers when the installation is done by the customer.
- This product is for installing on cement walls. The product may not stay in place when installed on plaster or wood.

### Components

Only use the components and accessories shipped with the product.



Wall Bracket(1)	Hinge(Left 1, Rigl	nt Plastic	Screw	Screw	Anchor
	1)	Hanger	(A)(11)	(B)(4)	(11)
		(4)			

## Wall Bracket Assembly

Note

There are two hinges(left and right). Use the correct one.

1. Insert and tighten the Captive Screw in the direction of the arrow.

When done, mount the wall bracket on the wall.



There are two hinges(left and right). Use the correct one.

- A Captive Screw
- B Wall Bracket
- C Hinge (Left)
- D Hinge (Right)
- 2. Before drilling into the wall, check if the length between the two locking holes at the back of the product is correct.

If the length is too short or long, loosen all or some of the 4screws on the wall bracket to adjust the length.



- A Length between the two locking holes
- 3. Check the installation diagram and mark the drill points on the wall. Use the 5.0 mm bit to drill holes deeper than 35 mm. Fix each anchor in the corresponding hole. Match each of the brackets and hinge holes to the corresponding anchor holes and insert and tighten the 11 screws A.



### To mount the product on the wall bracket

The shape of the product may vary depending on the model. (The assemblies of the plastic hanger and the screw are the same)

1. Remove the 4 screws on the back of the product.



2. Insert the screw B into the plastic hanger.



## 

- Mount the product on the wall bracket and make sure it is properly fixed to the left and right plastic hangers.
- Be careful when installing the product on the bracket as fingers can be caught in the holes.

- Make sure the wall bracket is securely fixed to the wall, or the product may not stay in place after installation.
- 3. Tighten the 4 screws in step 2 (plastic hanger + screw B)to the rear holes of the product.



4. Remove safety pin (3) and insert the 4 product holders into the corresponding bracket holes (1). Then place the product(2) so that it is firmly fixed to the bracket. Make sure to re-insert and tighten the safety pin (3) to securely hold the product to the bracket.



- A PDP Display
- B Wall Bracket
- C Wall

## Wall Bracket Angle Adjustment

Adjust the bracket angle to -2° before installing it on the wall.



- 1. Fix the product to the wall bracket.
- 2. Hold the product at the top in the center and pull it forward (direction of the arrow) to adjust the angle.

🖉 Note

You can adjust the bracket angle between -2° and 15°.



Make sure to use the top center, and not the left or the right side of the product to adjust the angle.

## Connections

## **Connecting a Computer**



## Using a Power cord with Earth

In the event of failure, the earth lead may cause electric shock. Make sure to wire the earth lead in correctly, before connecting the AC power. When un-wiring the earth lead, make sure to disconnect the AC power in advance.

## 🖉 Note

AV input devices such as DVD players, VCRs or camcorders as well as your computer can be connected to the PDP Display. For detailed information on connecting AV input devices, refer to the contents under Adjusting Your PDP Display.



- Connect the power cord for your PDP Display to the power port on the back of the PDP Display. Turn on the power switch.
- 2 There are 3 ways to connect the D-sub to your PDP Display. Choose one of the following:

<sup>2-1</sup>Using the D-sub (Analog) connector on the video card.

• Connect the D-sub to the 15-pin, RGB port on the back of your PDP Display and the 15 pin D-sub Port on the computer.



Using the DVI (Digital) connector on the video card.

• Connect the DVI Cable to the DVI port on the back of your PDP Display and the DVI port on the computer.



2-3 Using the BNC (Analog) connector on the video card.

 Connect the BNC Cable to the BNC/COMPONENT IN - R, G, B, H, V ports on the back of your PDP Display and the 15 pin D-sub Port on the computer.



Onnect the audio cable for your PDP Display to the audio port on the back of your computer.

## Ø Note

- Turn on both your computer and the PDP Display.
- The DVI cable or BNC cable is optional.
- Contact a local SAMSUNG Electronics Service Center to buy optional items.

## **Connecting to Other devices**



## Using a Power cord with Earth

In the event of failure, the earth lead may cause electric shock. Make sure to wire the earth lead in correctly, before connecting the AC power. When un-wiring the earth lead, make sure to disconnect the AC power in advance.

## 🖉 Note

AV input devices such as DVD players, VCRs or camcorders as well as your computer can be connected to the PDP Display. For detailed information on connecting AV input devices, refer to the contents under Adjusting Your PDP Display.

### **Connecting AV Devices**



- 1. Connect the port of the DVD, VCR (DVD / DTV Set-Top Box) to the [R-AUDIO-L] port of the PDP Display.
- 2. Then, start the DVD, VCR or Camcorders with a DVD disc or tape inserted.
- 3. Select AV using the SOURCE .

## Note

The PDP Display has AV connection terminals to connect AV input devices like DVDs, VCRs or Camcorders. You may enjoy AV signals as long as the PDP Display is turned on.

## **Connecting to a Camcorder**



- Locate the AV output jacks on the camcorder. They are usually found on the side or back of the camcorder. Connect a set of audio cables between the AUDIO OUTPUT jacks on the camcorder and the AV/COMPONENT AUDIO IN [L-AUDIO-R] on the PDP Display.
- 2. Connect a video cable between the VIDEO OUTPUT jack on the camcorder and the AV IN [VIDEO] on the PDP Display.
- 3. Select **AV** for the Camcorder connection using the Source button on the front of the PDP Display or on the remote control.
- 4. Then, start the Camcorders with a tape inserted.



The audio-video cables shown here are usually included with a Camcorder. (If not, check your local electronics store.) If your camcorder is stereo, you need to connect a set of two cables.

### **Connecting a DVD Player**



- 1. Connect a set of audio cables between the AV/COMPONENT AUDIO IN [L-AUDIO-R] on the PDP Display and the AUDIO OUT jacks on the DVD player.
- 2. Connect a Component cable between the BNC / COMPONENT IN  $P_R$ , Y,  $P_B$  port on the PDP Display and the  $P_R$ , Y,  $P_B$  jacks on the DVD player.



- Select Component for the connection to a DVD player using the SOURCE button on the front of the PDP Display or on the remote control.
- Then, start the DVD Player with a DVD disc inserted.

🖉 Note

• A component cable is optional.

For an explanation of Component video, consult your DVD manual.

### **Connecting a DTV Set Top Box**

🖉 Note

• The connections for a typical Set Top Box are shown below.



- 1. Connect a Component cable between the BNC / COMPONENT IN  $P_R$ , Y,  $P_B$  port on the PDP Display and the  $P_R$ , Y,  $P_B$  jacks on the Set Top Box.
- 2. Connect a set of audio cables between the AV/COMPONENT AUDIO IN [L-AUDIO-R] on the PDP Display and the AUDIO OUT jacks on the Set Top Box.



• Select **Component** for the connection to a DTV Set Top Box using the SOURCE button on the front of the PDP Display or on the remote control.

## 🖉 Note

• For an explanation of Component video, see your Set Top Box owner's manual.

## **Connecting Using a HDMI Cable**



## Note

- Input devices such as digital DVD are connected to the HDMI IN terminal of the PDP Display using the HDMI cable.
- You cannot connect a PC to the HDMI IN terminal.

## **Connecting Using a DVI to HDMI Cable**



## Ø Note

- Connect the DVI output terminal of a digital output device to the HDMI IN terminal of the PDP Display using a DVI to HDMI cable.
- Connect the red and white jacks of an RCA to stereo (for PC) cable to the same colored audio output terminals of the digital output device, and connect the opposite jack to the HDMI / PC / DVI AUDIO IN terminal of the PDP Display.

## **Connecting to an Audio System**





 Connect a set of audio cables between the AUX L, R jacks on the AUDIO SYSTEM and AUDIO OUT [L-AUDIO-R] on PDP Display.

## **Using the Software**

## **Installation MagicInfo Pro**

## Installation

- 1. Insert CD into the CD-ROM drive.
- 2. Click the MagicInfo Pro installation file.
- 3. When the Install Shield Wizard window appears, click "Next."

Magicinfo Pro - InstallShield Wizard		
	Welcome to the InstallShield Wizard for MagicInfo Pro The InstallShield® Wizard will install MagicInfo Pro on your computer. To continue, click Next.	
	< <u>B</u> ack Next> Cancel	

4. Select "I agree to the terms of the license agreement" to accept the terms of use.

Magicinfo Pro – InstallShield Wizard	$\otimes$
License Agreement Please read the following license agreement carefully.	
END-USER LICENSE AGREEMENT FOR SAMSUNG ELECTRONICS MagicInfo SOFTWARE PRODUCT IMPORTANT-READ CAREFULLY: This Samsung Electronics End-User License Agreement ("EULA") is a legal agreement between you (either an individual or a single entity) and Samsung Electronics Co., Ltd. ("SAMSUNG ELECTRONICS") with respect to the SAMSUNG ELECTRONICS product identified above. The SAMSUNG ELECTRONICS software product may include associated software components, media, printed materials and "online" or electronic documentation ("SOFTWARE PRODUCT"). By installing, copying or using the SOFTWARE PRODUCT, you agree to be bound by the terms of this EULA. If you do not agree to the terms of this EULA, you accept the terms of the license agreement InstallShield < <a href="mailto:seal"></a>	

5. You are required to log in to the MagicInfo Pro Server program. Please enter the password to login. The password cannot be changed when you are logged in.
| Magicinfo Pro – InstallShield Wizard |  |  |  |  |  |  |  |
|--------------------------------------|--|--|--|--|--|--|--|
| Password is need<br>login MagicInfo. | ed to use MagicInfo program. This password will be used to |  |  |  |  |  |  |
| Password                             |  |  |  |  |  |  |  |
| Confirm Password                     |  |  |  |  |  |  |  |
|                                      |  |  |  |  |  |  |  |
|                                      |  |  |  |  |  |  |  |
|                                      |  |  |  |  |  |  |  |
|                                      |  |  |  |  |  |  |  |
|                                      | < <u>B</u> ack <u>N</u> ext > Cancel                       |  |  |  |  |  |  |

6. Choose a folder to install the MagicInfo Pro program.

MagicInf	o Pro – InstallShield Wizard		$\otimes$
	Destination Location Ider where setup will install files.		No.
	Install MagicInfo Pro to: C:\Program Files\SEC\MagicInfo Pro		Change
InstallShield -	(	< <u>B</u> ack <u>N</u> ext >	Cancel

7. Click "Install."

Magicinfo Pro – InstallShield Wizard 🛛 🕅
Ready to Install the Program The wizard is ready to begin installation.
Click Install to begin the installation.
If you want to review or change any of your installation settings, click Back. Click Cancel to exit the wizard.
InstallShield
< <u>B</u> ack Install Cancel

8. The "Installation Status" window appears.

MagicInfo Pro – InstallShield Wizard	$\otimes$
Setup Status	
MagicInfo Pro is configuring your new software installation.	
Installing	
C:\Program Files\SEC\MagicInfo Pro\MagicInfoPro.exe	
111111111111111111111111111111111111111	
InstallShield	
ייינויטיינויטייי	Cancel

9. It is recommended restarting the system for the normal operation of the MagicInfo Pro Server program. Click "Finish".

Magicinfo Pro – InstaliSi	Magicinfo Pro – InstallShield Wizard								
	InstallShield Wizard Complete The InstallShield Wizard has successfully installed MagicInfo Pro. Click Finish to exit the wizard.								
	< Back Finish Cancel								

10. When the installation is complete, the MagicInfo Pro executable icon appears on your desktop.



11. Double-click the icon to start the program.

## **System Requirements**

	CPU	RAM	Ethernet	OS	Application	1
Minimum Recom- mended	P1.8 P3,0GHz	256M 512M	100M/1G	dows 2000 (Service	WMP 9 c later	۶r
				Pack 4)		



#### Introduction



A Multiple Display Control (MDC) is an application allowing various displays to be easily and simultaneously operated on a PC. RS-232C, a standard of serial communication, is used for the communication between a PC and a display. Therefore, a serial cable should be connected between the serial port on a PC and the serial port on a display.

#### **Main Screen**

Click Start > Program > Samsung > MDC System to start the program.

Select a set to see the volume of the selected set within the slider.

Multiple DCCC	ntrol 3 4 Safety Lock Port Selection Help Select All Clear All 5 le	SÁMSUNG DIGIT-
Power Control	Øl         mpox         mage size           0         PC         16:9           1         1         1           2         1         1           3         1         1           1         1         1           1         1         1           1         1         1           1         1         1           1         1         1           1         1         1           1         1         1           1         1         1           1         1         1	CurrentTemp. 43 6
1		
2 Remo	Icons con y Lock	<ul> <li>5 Select Button</li> <li>6 Info Grid</li> <li>7 Display Selection</li> </ul>
-	Selection	8 Control Tools

- 1. Use the main icons to switch into each screen.
- 2. Allows you to enable or disable the remote control signal receiving function of the display unit.
- 3. Set the Safety Lock function.

When setting the Lock function, you can only operate power and lock buttons on the remote control and set.

- 4. The setting for the PC Serial Port can change. The original value is COM1.
- 5. Click Select all or Clear to select or clear all displays.
- 6. Use Grid to view brief information on selected display.
- 7. Select a display from Display Selection.
- 8. Use Control Tools to control displays.
  - <Note> The remote control Enable/Disable function operates whether or not the power is On/Off, and this applies to all displays connected to the MDC. However, regardless of the status at the time the MDC is shut down, the remote control signal receiving function of all displays is initialized to Enable when the MDC is closed.

#### **Port Selection**

隨 Multiple Display Cor	ntrol	- 233							
File Remocon	Safe	ety Lo		Port Selection	n Help	-			SAMSUNG DIGIT-
		elect		COM2	🧿 E	211011	_	_	
	2	alect	AIL	COM3		buay			
Power Control	$\mathbf{V}$	ID	<u></u>	COM4	Image S	ire C	ho Timer	Off Timer	
	H	0	0	PC	16:9	-	0		Power On Power Off
Input Source	H	0		r.v.	10.5	-	<u> </u>		
	ш				_				
									Volume 10 🔫
Image Size									
								-	
	_					_			
Time	ID	Ö	Lamp	Temp.Status	B/R Senser	Fan	Curre	ntTemp.	
	0	$\odot$	0	0	0	1	49		
PIP								-	
No.							-		
CO CO						_	-	_	
Settings									
								•	
Maintenance									
0									~
L L									

- 1. The Multiple Display Control is originally set to COM1.
- 2. If any port other than COM1 is used, COM1 through COM4 can be selected in the Port Selection Menu.
- 3. If the exact port name that is connected to the PDP Display using a serial cable is not selected, communication will be unavailable.
- 4. The selected port is stored in the program and used for the next program as well.



1. Click Power Control of the main icons and the Power Control screen appears.

	Sel	lect /	MI	Clear All	🧧 🧿 E	Busy				
Power Control	V	ID		Input	Image S	Size O	n Timer Off Tir		Power On	Danuar Off
and the second s		0	0	PC	16:9	}	0 0	- L ·	ower Un	Power Off
Input Source			1	)-2-	-3	_	)-5			
			<u> </u>		9			Volun	ne 10 <u> </u>	
Image Size										
$\bigcirc$										3
Time										
		CL L	.amp	Temp.Status	B/R Senser	Fan	CurrentTerr	np.		
<b>1</b>	0	0	0	0	0	1	49	<b>^</b>		
PIP								-		
10										
Settings										
_								-		
Maintenance										

\* Info Grid shows some basic information necessary to Power Control.

- 1) 🚺 (Power Status)
- 2) Input
- 3) Image Size
- 4) On Timer
- 5) Off Timer
- 2. Use the Select All button or Check Box to choose a display to control.



 $\star$  I power Control allows controlling some of the functions of the selected display.

- Turns the power of the selected display On/Off.
- 2) Volume
  - Controls the volume level of the selected display.
  - It receives the volume value of the selected display from the sets and displays it in the slider. (When you cancel the selection or choose Select All, the value returns to the default value 10)
- 3) 🕥 (Mute On/Off)
  - Turns on/off the Mute function of the selected display.
    When selecting one set at a time, turn on the Mute function for the selected set.
    The Mute function is disabled automatically when you adjust the volume level.
    (The values return to the default settings when you undo the selections or choose "Select All".)

\* The Power Control feature is available for all displays.

\* The Volume Control and Mute features are available only for the displays whose power status is ON.



- 1. Click Input Source of the main icons and the Input Source control screen appears. Click Select All or use Check Box to select a display to control.
- TV Mode



• PC Mode

Multiple Display Co File Remocon		Lock F	Port Selection Help			SAMSUNG DIGITA
Power Control	Sete	ct All	Clear All 🥹 Busy	_		
		D 🕅	Input PC		Choose Ing	out Source
Input Source					РС	AV 6
Image Size				$\overline{2}$	BNC	S-Video 7
S				<u> </u>	DVI	
				4		Magfieluito 9
PIP				5	DTV	
Settings						
2				<u>_</u>		
Maintenance					_	
						(!)

- \* Info Grid shows some basic information necessary to Input Source Control.
- 1) PC
  - Changes the Input Source of the selected display to PC.
- 2) BNC
  - Changes the Input Source of the selected display to BNC.
- 3) DVI
  - Changes the Input Source of the selected display to DVI.
- 4) TV

- Changes the Input Source of the selected display to TV.

5) DTV

- Changes the Input Source of the selected display to DTV.

- 6) AV
- Changes the Input Source of the selected display to AV.
- 7) S-Video

- Changes the Input Source of the selected display to S-Video.

8) Component

- Changes the Input Source of the selected display to Component.

- 9) MagicInfo
  - The Input source of MagicInfo works only on MagicInfo model.
- 10) HDMI
  - Changes the Input Source of the selected display to HDMI.
- 11) Channel
  - Channel arrow appears when the Input Source is TV.

TV Source can be selected only in products with TV and controlling channels is allowed only when Input Source is TV.

 $\star$  The Input Source Control feature is available only for the displays whose power status is ON.



### PC, BNC, DVI

1. Click Image Size of the main icons and the Image Size control screen appears.

📑 Multiple Display Co					
File Remocon	Safety	y Lock F	Port Selection Hel	p	SAMSUNG DIGITAL
	Set	ect All	Clear All	Busy	
Power Control		ID 🔯	Image Size	Input	PC Source Video Source
		0	16:9	PC 🔺	
Input Source					PC, BNC, DVI
		-1	)	3	
Image Size				-4-	16 : 9
0				4	
Time					4:3
PIP					
0					
Settings					
				<u></u>	
Maintenance					

- \* Info Grid shows some basic information necessary to Image Size Control.
- 1) 🚺 ( Power Status)
  - Shows the power status of the current display.
- 2) Image Size
  - Shows the current Image Size of the display in use.
- 3) Input
- Shows the current Input Source of the display in use.
- 4) Info Grid displays only the displays whose Input Source is PC, BNC, DVI.
- 5) PC Source When you click Image Size, the PC Source tab first appear.
   The Image Size Control button controls Image Size available for PC, BNC, DVI.
- 6) Video Source
  - Click the Video Source tab to control Image Size for respective Input Source.
- \* The Input source of MagicInfo works only on MagicInfo model.
- \* The Input source of TV works only on TV model.
- \* Image Size Control is available only for the displays for which power status is ON.



## TV, AV, S-Video, Component, DVI (HDCP), HDMI, DTV

1. Click Image Size of the main icons and the Image Size control screen appears.

Multiple Display Co	Contraction of the second s	ck Po	rt Selection Hel	p	SAMSUNG DIGITALI)
Power Control Input Source Input Source Inge Size Time PIP Sottings	Setect 7		Clear All Image Size 16:9	Busy	PC Source Video Source TV,AV,S-Video,Component,HDMI,DTV AutoWide 16 : 9 Zoom 1 Zoom 2 4 : 3

\* Info Grid shows some basic information necessary to Image Size Control.

- 1) Click the Video Source tab to adjust Image Size for TV, AV, S-Video, Component, DVI(HDCP), HDMI, DTV. Click Select All or use Check Box to select a display to control.
- 2) Info Grid displays only the display having TV, AV, S-Video, Component or DVI(HDCP) as input source.
- 3) Switch Image Size of the selected display randomly.

Note: Auto Wide, Zoom1 and Zoom2 are not available for selection when the input signal type for Component and DVI (HDCP) is 720p or 1080i.

- ( The Auto Wide mode is available only for TV, AV, and S-Video. )
- \* The Input source of MagicInfo works only on MagicInfo model.
- \* The Input source of TV works only on TV model.
- \* The Image Size Control feature is available only for the displays whose power status is ON.



1. Click Time of the main icons and the Time Control screen appears.

C	Select All	Clear All	Busy	
Power Control	🗹 ID 🚺	1 4 On Time	5 Off Time	Current Time
Contraction of the second seco	0		🗩 03:00 AM 🔘 📤	05:23
	1	MA : AM	: AM O	Apply
Image Size				On Time Setup
$\bigcirc$				1 00 AM Off AM Hour Minute AM/PM Status
Time				PC V 10 V
				Source Volume
				Apply
PIP				Off Time Setup 3
10				1 V 00 V AM V Off V
Settings				Hour Minute AM/PM Status
				Apply

\* Info Grid shows some basic information necessary to Time Control.

- 1) Current Time
  - Set the current time for the selected display (PC Time).
  - To change the current time, first change the PC Time.
- 2) On Time Setup
  - Set the Hour, Minute, AM/PM of On Time Setup, Status, Source, Volume of the selected display.
- 3) Off Time Setup
  - Set the Hour, Minute, and AM/PM, Status for Off Time Setup of the selected display.
- 4) Shows the On Time settings.
- 5) Shows the Off Time settings.
- \* The Input source of MagicInfo works only on MagicInfo model.
- \* The Input source of TV works only on TV model.
- **\*** Time Control is available only for the displays for which the power status is ON.
- \* At On Time Setup, TV Source functions only for TV Model.
- \* At On Time Setup, MagicInfo Source functions only for MagicInfo Model.



#### **PIP Size**

1. Click PIP of the main icons and the PIP control screen appears. Click Select All or use Check Box to select a display to control.

Multiple Display Co File Remocon		aalk De	ort Selection Hel	- 1		
Plie Remocon	Salety L	JCK PC	It Selection Hei	p		SAMSUNG DIGIT
	Select	All	Clear All	Busy	_	
Power Control	D ID		PIP Size	PIP Source	1 PIP Size	PIP Source
	0	•	Double 1	AV 🔺		
Input Source				-		All Inputs
Image Size					(2)	OFF
Time					3	Large
					(4)	Small
PIP					5	Double 1
R (D)					6	Double 2
Settings				-		Dauble 2
	· · · · ·	_				Double 3
Maintenance						
						~
						$(\mathbf{D})$

\* Info Grid shows some basic information necessary to PIP Size Control.

1) PIP Size

- Shows the current PIP Size of the display in use.
- 2) OFF
  - Turns off the PIP of the selected display.
- 3) Large
  - Turns on the PIP of the selected display and changes the size to Large.
- 4) Small
  - Turns on the PIP of the selected display and changes the size to Small.
- 5) Double 1
- Turns on the PIP of the selected display and changes the size to Double 1.6) Double 2
- Turns on the PIP of the selected display and changes the size to Double 2.7) Double 3 (Picture By Picture)
- Turns on the PBP of the selected display and changes the size to Double 3.
- \* The Input source of MagicInfo works only on MagicInfo model.
- **\*** The Input source of TV works only on TV model.
- **\*** PIP Size can be controlled with turning on the PDP Display power.



#### **PIP Source**

1. Click PIP of the main icons and the PIP control screen appears.

Multiple Display Constraints File Remocon	and the second second	y Loc	k P	ort Selection Hel	p		
Power Control Power Control Input Source Power Size Time Pip Pip Settings Settings				Clear All PIP Size Double 1	Busy PIP Source S-Video	2 PC 3 BNC 4 DVI	PIP Source 1 I Inputs AV 5 S-Video 6 Component 7 HDMI 8

 $\star$  Info Grid shows some basic information necessary to PIP Source Control.

1) PIP Source

- PIP Source can be controlled with turning on the PDP Display power.
- 2) PC
- Changes the source of the PIP of the selected display to PC.
- 3) BNC
   Changes the source of the PIP of the selected display to BNC.
  4) DVI
- Changes the source of the PIP of the selected display to DVI.5) AV
- Changes the source of the PIP of the selected display to AV.
- 6) S-Video
- Changes the source of the PIP of the selected display to S-Video.
- 7) Component
- Changes the source of the PIP of the selected display to Component.

8) HDMI

- Changes the source of the PIP of the selected display to HDMI.

Note: Some of the PIP Sources may not be available for selection, depending on the input source type of the Main Screen.

\* The Input source of MagicInfo works only on MagicInfo model.

The PIP Control feature is available only for the displays whose power status is ON and the PIP function is set to ON.



#### Picture

1. Click Settings of the main icons and the Settings Control screen appears.

Power Control	Sele	ect All	Clear All Busy	
ower condor		ID 🚺	input	Picture Picture PC Audio Image Lo
See.		0 😐	AV	TV,AV,S-Video,Component,HDMI,DTV
Input Source				2 Contrast 67
			5	Brightness 68
Image S			6	
				Color 60
Titte			8	6 Tint G50
				Color Tone Off Cool Normal Warm
PIP				
No				Color Temp 10000K
Settings				Brightness Sensor ON OFF
				UDynamic Contrast
Maintenance				

\* Info Grid shows some basic information necessary to Settings Control.

When each function is selected, the set value of the selected function is displayed in the slide. When selected, each function fetches the value for the set and displays it on the slide bar. When "Select All" is chosen, the default value is displayed. Changing a value in this screen will automatically change the mode to "CUSTOM."

- 1) Picture
  - Available only for TV, AV, S-Video, Component, HDMI, DTV.
- 2) Contrast
- Adjusts Contrast of the selected display.
- 3) Brightness

- Adjusts Brightness of the selected display.

4) Sharpness

- Adjusts Sharpness of the selected display.

5) Color

- Adjusts Color of the selected display.

- 6) Tint
  - Adjusts Tint of the selected display.

- Available only for NT.

- 7) Color Tone
  - Adjusts the Color Tone for the selected display.
- 8) Color Temp
  - Adjusts the Color Temp for the selected display.
- 9) Brightness Sensor
  - Adjusts the Brightness Sensor for the selected display.
- 10) Dynamic Contrast
  - Adjusts the Dynamic Contrast for the selected display.
- \* The Input source of MagicInfo works only on MagicInfo model.
- \* Color Temp is only enabled if the Color Tone is set to Off.
- \* The Input source of TV works only on TV model.
- \* This feature is available only for the displays whose power status is ON and if no selection is made, the factory default is displayed.



1. Click Settings of the main icons and the Settings Control screen appears.

📑 Multiple Display C									
File Remocon	Safe	ty Lo	ck f	Port Selection Help					SAMSUNG DIGITAL
	Se	lecta	All	Clear All 😑 Busy					
Power Control		ID		Input		Pictur	Picture PC	Audio	Image Lock
		0	•	PC	-				
Input Source							PC,	BNC, DVI	
					(2	Contrast	56 🚥		
Image Size						Brightness	50 📖		<u> </u>
					4	Red	100 📼		$\sim$
Time						Green	100 💳		(5
									~0
					6	Blue	100 💳		<u> </u>
PIP						Color Tone	011	Normal	Custom 7
1 Dec					8	Color Temp 1	10000K 🚃	-	
Settings					9	·		-	
						Brightness Se	ensor	ON	
Maintenance					_				
									(n)

- Info Grid shows some basic information necessary to Settings Control. When each function is selected, the set value of the selected function is displayed in the slide. When selected, each function fetches the value for the set and displays it on the slide bar. When "Select All" is chosen, the default value is displayed. Changing a value in this screen will automatically change the mode to "CUSTOM."
- 1) Picture PC
  - Available only for PC, BNC, DVI.
- 2) Contrast
  - Adjusts Contrast of the selected display.
- 3) Brightness
  - Adjusts Brightness for the selected display.
- 4) Red
  - Adjusts red Color of the selected display.
  - Available only for NT.
- 5) Green
  - Adjusts green Color of the selected display.
  - Available only for NT.
- 6) Blue
  - Adjusts blue Color of the selected display.
  - Available only for NT.
- 7) Color Tone
  - Adjusts the Color Tone for the selected display.
- 8) Color Temp
  - Adjusts the Color Temp for the selected display.
- 9) Brightness Sensor
  - Adjusts the Brightness Sensor for the selected display.
- **\*** The Input source of MagicInfo works only on MagicInfo model.
- 🜟 The Input source of TV works only on TV model.
- \* Color Temp is only enabled if the Color Tone is set to Off.
- This feature is available only for the displays whose power status is ON and if no selection is made, the factory default is displayed.



## Audio

1. Click Settings of the main icons and the Settings Control screen appears.



- Info Grid shows some basic information necessary to Settings Control. When each function is selected, the set value of the selected function is displayed in the slide. When selected, each function fetches the value for the set and displays it on the slide bar. When "Select All" is chosen, the default value is displayed. Changing a value in this screen will automatically change the mode to "CUSTOM."
- 1) Audio
  - Controls audio settings for all input sources.
- 2) Bass
- Adjusts Bass of the selected display.
- 3) Treble
  - Adjusts Treble of the selected display.
- 4) Balance
  - Adjusts Balance of the selected display.
- 5) SRS TS XT
  - SRS TS XT Sound ON/OFF of the selected display.
- 6) Sound Select
  - Select either Main or Sub when PIP is On.
- \* The Input source of MagicInfo works only on MagicInfo model.
- 📩 The Input source of TV works only on TV model.
- This feature is available only for the displays whose power status is ON and if no selection is made, the factory default is displayed.



## Image Lock

1. Click Settings of the main icons and the Settings Control screen appears.

🐚 Multiple Display C						
File Remocon	Safety L	ock Po	rt Selection Help			SAMSUNG DIGITAD
(0	Selec	CAIL	Clear All 🔋 😑 Busy			
Power Control						
			Input PC	Picture	Picture PC Audio	Image Lock
Input Source			FU	-		
					PC, BNC	
		+++			I	<b>&gt;</b>
Image Size						_
$\odot$				Fine		
Time						
				Position	🖻	1
PIP						
New						
R C						
Settings						
				5 Auto Adjusti	ment OK	
Maintenance						
						(1)
						C.

- \* Info Grid shows some basic information necessary to Settings Control.
- 1) Image Lock
- Available only for PC, BNC.
- 2) Coarse
  - Adjusts Coarse of the selected display.
- 3) Fine
  - Adjusts Fine of the selected display.
- 4) Position
  - Adjusts Position of the selected display.
- 5) Auto Adjustment
  - Self-Adjust to the incoming PC signal.
- \* The Input source of MagicInfo works only on MagicInfo model.
- \* The Input source of TV works only on TV model.
- $\star$  Settings Control is available only for the displays for which the power status is ON.

🥪 Maintenance

#### Lamp Control

1. Click on the "Maintenance" icon in the Main Icon column to display the Maintenance screen.

📑 Multiple Display Co	ntrol		200 - C					×
File Remocon	Safe	ty Lo	ck F	Port Selection	He	p		SAMSUNG DIGITAL
	Se	lect /	All	Clear All	•	) Busy		
Power Control		ID		Max Statu	5	Min Status		Lamp Control Scroll Video Wall
See.		0	•	05:04 PM	60	03 : 02 AM	80 🔺	
Input Source								- Auto Lamp Control
Image Size								Max. 1 💟 00 💟 AM 💟 50 💟
								Hour Minute AM.PM Value Min. 1 V 00 AM V 50 V
Time								
Inne								Apply
PIP								$\frown$
10								Manual Lamp Control
Settings								50
Maintenance								

\* An "Info Grid" showing several basic data items appears.

- 1) Maintenance
- Allows the Maintenance Control function for all input sources.
- 2) Auto Lamp Control

  - Automatically adjusts the backlight of the selected display at a specified time. The Manual Lamp Control automatically turns off if you adjust using the Auto Lamp Control.
- 3) Manual Lamp Control
  - Allows you to adjust the backlight of the selected display regardless of the time. The Auto Lamp Control automatically turns off if you adjust using the Manual Lamp Control.
- ★ The Maintenance Control feature is available only for the displays whose power status is ON.
- \* The Input source of MagicInfo works only on MagicInfo model.
- \* The Input source of TV works only on TV model.



#### Scroll

1. Click on the "Maintenance" icon in the Main Icon column to display the Maintenance screen.

💽 Multiple Display Co							
File Remocon	Safe	ty Lock	P	ort Selection	Help		SAMSUNG DIGITION
	Se	lect Al		Clear All	🔒 Idle		
Power Control		ID	8	Interval	Second	Туре	Lamp Control Scroll Video Wall
1 mm						<u>^</u>	
Input Source							Safety Screen
Image Size							
							Off V Off V Scroll V Interval Second Type
9_							
Time							Apply
1							
PIP			-				
1.6							
Settings							
			-			-	
		_				<u>×</u>	
Maintenance							

- 1) Safety Screen
  - Eliminates the afterimages that can result when the selected display stays in Pause mode for an extended period of time. You can set the repeat cycle timer by selecting the "Interval" by hour and "Second" by second. It can be set to Scroll, Pixel, Bar and Eraser by Screen Type.
- \* The Input source of MagicInfo works only on MagicInfo model.
- \* The Input source of TV works only on TV model.
- \* Setting Second, you can set to 1, 2, 3, 4, 5 for Scroll Type and to 10, 20, 30, 40, 50 for Pixel, Bar, and Eraser Type.
- ★ The Maintenance Control feature is available only for the displays whose power status is ON.



#### Video Wall

1. Click on the "Maintenance" icon in the Main Icon column to display the Maintenance screen.



#### 1) Video Wall

- A Video Wall is a set of video screens that are connected together, so that each screen shows a part of the whole picture or so that the same picture is repeated on each screen.

#### 2) Video Wall (Screen divider)

- The screen can be divided into.
- You can select a number of screens with a different layout when dividing.
- Select a mode from Screen divider.
- Select a display from Display Selection.
- The place will be set up by pressing a number in the selected mode.
- The MDC program supplied by Samsung supports up to 5x5 PDP Displayes.
- 3) On / Off
  - Turns on/off the Video Wall function of the selected display.
- 4) Format
  - The format can be selected to see a divided screen.



- \* You may not operate this function in MagicInfo.
- \* The Input source of TV works only on TV model.
- $\star$  The Maintenance Control function is available only for the displays where the power status is ON.

## Troubleshooting

The display you wish to control does not appear on the Power Control Info Grid

 Check the connection of RS232C. (Check if it is properly connected to the Com1 port)

- Check the displays to see if any of the other displays connected have the same ID. If more than one displays have the same ID, those displays are not properly detected by the program due to data conflict.
- Check if the Display Set ID is a number between 0 and 25. (Adjust using the Display menu)
- Note : A Display Set ID must be a value between 0 and  ${\bf 25}$  .
- 2. The display you wish to control does not appear on the other Control Info Grids
- Check to see if the display power is ON. (You can check this in Power Control Info Grid)
  - Check if you can change the input source of the display.
- 3. The dialogue box appears repeatedly.
  - Check to see if the display you wish to control is selected.
- 4. Both On Timer and Off Timer have been set but different time is showing.Apply current time to synchronize the display clocks.
- The remote may not function properly when you turn off the remote Function, disconnect the RS-232C cable, or exit the program in an Irregular manner. Rerun the program and turn the remote function again to Restore normal functions.
  - <Note> This program may malfunction due to problems in communication circuits or interference from electronic appliances nearby.

🛜 Notice	×
Please make selection in the information grid before controlling.	example
ок	☑ 10

## Settings Value Display In Multiple Display Mode

- \* When there are more than one displays connected, the settings values are displayed as follows.
- 1. No selection: Displays the Factory Default Value.
- 2. Selected one display: Fetches and displays the settings value for the selected display.
- 3. Selected one display (ID1) and add another display (ID3): The program, which was displaying the settings value of ID 1, fetches and displays the value of ID3.
- 4. Selected all sets using Select All: Returns to the Factory Default Value.

Copyright© 2003-2008 Samsung Electronics Co. Ltd. All rights reserved.

# Adjusting the PDP Display

Input

## **Available Modes**

- 📴 PC / BNC / DVI
- 🔼 AV
- 🖸 HDMI
- MagicInfo
- 🚺 тv
- Component

🖉 Note

- The **TV** menu is available when a TV tuner box is installed.
- The MagicInfo menu is available when a network box is installed.

## Source List PAHMTC

```
\mathsf{MENU} \to \mathsf{ENTER} \to [\mathsf{Input}] \to \mathsf{ENTER} \to [\mathsf{Source \ List}] \to \blacktriangle, \forall \to \mathsf{ENTER}
```



Use to select **PC**, **DVI** or other external input sources connected to the PDP Display. Use to select the screen of your choice.

- 1. **PC**
- 2. **DVI**
- 3. **AV**
- 4. **HDMI**

This is deactivated when a TV tuner box is installed.

#### 5. MagicInfo

This is activated when a network box is installed.

#### 6. **TV**

This is activated when a TV tuner box is installed.

- 7. BNC
- 8. Component

Note

• The direct button on the remote control is the 'SOURCE' button.

## Edit Name

 $\mathsf{MENU} \to \mathsf{ENTER} \to [\mathsf{Input}] \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Edit} \ \mathsf{Name}] \to \blacktriangle \ , \ \blacktriangledown \to \mathsf{ENTER}$ 



Name the input device connected to the input jacks to make your input source selection easier.

# VCR / DVD / Cable STB / HD STB / Satellite STB / AV Receiver / DVD Receiver / Game / Camcorder / DVD Combo / DHR / PC

🖉 Note

- When connecting a PC to the HDMI or DVI terminal, set Edit Name to PC.
- In other cases, set Edit Name to AV.
- However, since 640x480, 720P (1280x720), and 1080p (1920x1080) are common signals for AV and PC, make sure to set the Edit Name in accordance with the input signal.
- The Picture menu changes depending on the input signal and Edit Name.

## Picture [PC / BNC / DVI / HDMI / MagicInfo Mode]

## **Available Modes**

- PC / BNC / DVI / HDMI
- 🔼 AV
- MagicInfo
- 🚺 тv
- Component

Ø Note

- The **TV** menu is available when a TV tuner box is installed.
- The MagicInfo menu is available when a network box is installed.

## MagicBright PM

```
\mathsf{MENU} \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{Picture}] \to \mathsf{ENTER} \to [\textbf{MagicBright}] \to \blacktriangle, \blacktriangledown \to \mathsf{ENTER}
```

1	Entertain		
•	Internet Text		] ]
۲	Custom		]
Ø			

**MagicBright** is a feature providing the optimum viewing environment depending on the contents of the image you are watching. Currently four different modes are available: **Entertain**, **Internet**, **Text** and **Custom**. Each mode has its own pre-configured brightness value. You can easily select one of the four settings by simply pressing the **MagicBright** control button.

#### 1. Entertain

High brightness

For documents or works involving heavy text.

#### 2. Internet

Medium brightness

For working with a mixture of images such as texts and graphics.

3. Text

Normal brightness

For documents or works involving heavy text.

4. Custom

Although the values are carefully chosen by our engineers, the pre-configured values may not be comfortable to your eyes depending on your taste.

If this is the case, adjust the brightness and contrast by using the OSD menu.

#### Custom **PM**

By using the on-screen menus, the contrast and brightness can be changed to your personal preference.

```
MENU \rightarrow \P \rightarrow ENTER \rightarrow [Picture] \rightarrow \P \rightarrow ENTER \rightarrow [Custom]
Mote
```

By adjusting the **picture** using the **Custom** function, **MagicBright** will change to **Custom** mode.

#### Contrast

 $\begin{array}{l} \mathsf{MENU} \rightarrow \blacktriangledown \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Picture}] \rightarrow \blacktriangledown \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Custom}] \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Contrast}] \rightarrow \oiint \rightarrow \mathsf{ENTER} \end{array}$ 



Adjusts the Contrast.

#### **Brightness**

```
\begin{array}{l} \mathsf{MENU} \rightarrow \blacktriangledown \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Picture}] \rightarrow \blacktriangledown \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Custom}] \rightarrow \blacktriangledown \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Brightness}] \rightarrow \blacktriangleleft, \blacktriangleright \rightarrow \mathsf{ENTER} \end{array}
```

Brigthtness		100	
🗢 Move	🔁 Adjust	O Return	

Adjusts the Brightness.

#### Sharpness

```
\begin{array}{l} \mathsf{MENU} \to \P \to \mathsf{ENTER} \to [\textbf{Picture}] \to \P \to \mathsf{ENTER} \to [\textbf{Custom}] \to \P \to \P \to \mathsf{ENTER} \to [\textbf{Sharpness}] \to \P, \blacktriangleright \to \mathsf{ENTER} \end{array}
```

Sharpness		40	
Move	🗗 Adjust	O Return	

Adjusts the Sharpness.

#### Color Tone **PM**

```
MENU \rightarrow \checkmark \rightarrow ENTER \rightarrow [Picture] \rightarrow \checkmark \rightarrow \checkmark \rightarrow ENTER \rightarrow [Color Tone] \rightarrow \blacktriangle, \checkmark \rightarrow ENTER
```

The color tones can be changed.

- 1. **Off**
- 2. **Cool**
- 3. Normal
- 4. Warm
- 5. Custom

🖉 Note

If you set the **Color Tone** to **Cool**, **Normal**, **Warm**, or **Custom**, the **Color Temp** function is disabled.

If you set the Color Tone to Off, the Color Control function is disabled

#### Color Control

Adjusts individual Red, Green, Blue color balance.

 $MENU \rightarrow \Psi \rightarrow ENTER \rightarrow [Picture] \rightarrow \Psi \rightarrow \Psi \rightarrow \Psi \rightarrow ENTER \rightarrow [Color Control]$  WNote

If you adjust the picture by using the **Color Control** function, **Color Tone** will turn to the **Custom** mode.

#### Red

 $\begin{array}{l} \mathsf{MENU} \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{Picture}] \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{Color Control}] \to \mathsf{ENTER} \\ \to [\textbf{Red}] \to \blacktriangleleft, \blacktriangleright \to \mathsf{ENTER} \end{array}$ 



#### Green

 $\begin{array}{l} \mathsf{MENU} \to \P \to \mathsf{ENTER} \to [\textbf{Picture}] \to \P \to \P \to \P \to \mathsf{ENTER} \to [\textbf{Color Control}] \to \P \to \mathsf{ENTER} \to [\textbf{Green}] \to \P, \blacktriangleright \to \mathsf{ENTER} \end{array}$ 

Green \_\_\_\_\_\_ 25 ♦ Move 庄 Adjust € Return

#### Blue

 $\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Picture}] \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Color Control}] \rightarrow \P \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow \mathsf{[Blue]} \rightarrow \P, \blacktriangleright \rightarrow \mathsf{ENTER} \end{array}$ 



## Color Temp PM

 $MENU \rightarrow \P \rightarrow ENTER \rightarrow [Picture] \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow ENTER \rightarrow [Color Temp] \rightarrow \P, \blacktriangleright \rightarrow ENTER$  Color Temp. S000K

**Color Temp** is a measure of the 'warmth' of the image colors.



This function is only enabled if the Color Tone is set to Off.

## Image Lock 📔

**Image Lock** is used to fine-tune and get the best image by removing noise that creates unstable images with jitters and shakiness. If satisfactory results are not obtained using the Fine adjustment, use the Coarse adjustment and then use Fine again.

(Available in **PC** mode only)

 $\mathsf{MENU} \to \mathbf{v} \to \mathsf{ENTER} \to [\mathbf{Picture}] \to \mathbf{v} \to \mathbf{v} \to \mathbf{v} \to \mathbf{v} \to \mathbf{ENTER} \to [\mathbf{Image \ Lock}]$ 

#### Coarse



Removes noise such as vertical stripes. Coarse adjustment may move the screen image area. You may relocate it to the center using the horizontal control menu.

### Fine



Removes noise such as horizontal stripes. If the noise persists even after Fine tuning, repeat it after adjusting the frequency (clock speed).

## **H-Position**

```
\begin{array}{l} \mathsf{MENU} \to \P \to \mathsf{ENTER} \to [\textbf{Picture}] \to \P \to \P \to \P \to \P \to \P \to \mathsf{ENTER} \to [\textbf{Image Lock}] \to \P \to \P \to \mathsf{ENTER} \to [\textbf{H-Position}] \to \P, \blacktriangleright \to \mathsf{ENTER} \end{array}
```



Adjusts the screen location horizontally.

## **V-Position**

```
\begin{array}{l} \mathsf{MENU} \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{Picture}] \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacksquare \to \mathsf{ENTER} \to [\textbf{Image Lock}] \to \blacktriangledown \to \blacksquare \to \blacksquare \to \blacksquare \to \mathsf{ENTER} \to [\textbf{V-Position}] \to \blacktriangleleft, \blacktriangleright \to \mathsf{ENTER} \end{array}
```

V-Position		40	
🔶 Movi	) 🗗 Adjust	O Return	

Adjusts the screen location vertically.

## Auto Adjustment 📔

```
\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Picture}] \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \blacksquare \rightarrow \blacksquare \mathsf{ENTER} \rightarrow [\textbf{Auto Adjust-ment}] \end{array}
```

Auto Adjustment 30%

The values of **Fine**, **Coarse**, **Position** are adjusted automatically. By changing the resolution in the control panel, the auto function is performed.

(Available in PC mode only)

The direct button on the remote control is the 'AUTO' button.

#### Signal Balance P

This is used to make up for the weak RGB signal transmitted by a long signal cable.

```
\mathsf{MENU} \to \mathbf{v} \to \mathsf{ENTER} \to [\mathbf{Picture}] \to \mathbf{v} \to
```

(Available in PC mode only)

## **Signal Balance**

```
\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Picture}] \rightarrow \P \rightarrow \blacksquare \mathsf{ENTER} \rightarrow [\textbf{Signal Balance}] \rightarrow \blacktriangle, \P \rightarrow \mathsf{ENTER} \end{array}
```



Selects either **On** or **Off** with the signal control.

#### Signal Control

```
\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Picture}] \rightarrow \P \rightarrow \mathsf{F} \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Signal Balance}] \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Signal Control}] \end{array}
```

1. R-Gain

 $\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Picture}] \rightarrow \P \rightarrow \mathsf{F} \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Signal Balance}] \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Signal Control}] \rightarrow \mathsf{ENTER} \rightarrow [\textbf{R-Gain}] \rightarrow \P, \blacktriangleright \rightarrow \mathsf{ENTER} \end{array}$ 



2. G-Gain

 $\begin{array}{l} \mathsf{MENU} \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{Picture}] \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacksquare \to \mathsf{ENTER} \to [\textbf{Signal Balance}] \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{Signal Control}] \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{G-Gain}] \to \blacktriangleleft, \blacktriangleright \to \mathsf{ENTER} \end{array}$ 



3. B-Gain

 $\begin{array}{l} \mathsf{MENU} \to \overline{\mathtt{v}} \to \mathsf{ENTER} \to [\mathbf{Picture}] \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \mathbb{ENTER} \to [\mathbf{Signal} \ \mathbf{Balance}] \to \overline{\mathtt{v}} \to \mathbb{ENTER} \to [\mathbf{Signal} \ \mathbf{Control}] \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \mathbb{ENTER} \to [\mathbf{B}\text{-}\mathbf{Gain}] \to \overline{\mathtt{s}}, \mathbf{F} \to \mathbb{ENTER} \end{array}$ 



4. R-Offset

 $\begin{array}{l} \mathsf{MENU} \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{Picture}] \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacksquare \to \mathsf{ENTER} \to [\textbf{Signal Balance}] \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{Signal Control}] \to \blacktriangledown \to \blacktriangledown \to \blacksquare \to \mathsf{ENTER} \to [\textbf{R-Offset}] \to \blacktriangle \to \mathsf{ENTER} \end{array}$ 



5. G-Offset

 $\begin{array}{l} \mathsf{MENU} \to \P \to \mathsf{ENTER} \to [\textbf{Picture}] \to \P \to \mathsf{ENTER} \to [\textbf{Signal Balance}] \to \P \to \mathsf{ENTER} \to [\textbf{Signal Control}] \to \P \to \P \to \P \to \P \to \mathsf{ENTER} \to [\textbf{G-Offset}] \to \P, \blacktriangleright \to \mathsf{ENTER} \end{array}$ 

G Offset				5
🗢 Move	🗗 Adjust	Э	Return	

6. B-Offset

```
\begin{array}{l} \mathsf{MENU} \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Picture}] \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacksquare \to \mathsf{ENTER} \to [\mathsf{Signal} \ \mathsf{Balance}] \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Signal} \ \mathsf{Control}] \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacksquare \to \mathsf{ENTER} \to [\mathsf{B-Offset}] \to \blacktriangleleft, \blacktriangleright \to \mathsf{ENTER} \end{array}
```

G Offset			5
🗢 Move	🔁 Adjust	🖸 Return	

Size P

Size			
1	🖌 16: 9		
	4:3		
0			
Ø			
	🗢 Move	🕑 Enter	🕤 Return

The Size can be switched.

- 1. **16:9**
- 2. **4:3**

### Picture [ AV / HDMI / DVI / TV / Component Mode]

#### **Available Modes**

• 📔 PC / BNC

- 🔼 AV
- 🚺 HDMI / DVI
- MagicInfo
- 🚺 т
- Component

🖉 Note

- The **TV** menu is available when a TV tuner box is installed.
- The MagicInfo menu is available when a network box is installed.

#### Mode Alle

```
\mathsf{MENU} \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Picture}] \to \mathsf{ENTER} \to [\mathsf{Mode}] \to \blacktriangle, \blacktriangledown \to \mathsf{ENTER}
```

Node	
1	🗾 Dynamic
	Standard
	Movie
۲	Custom
õ	
	🕈 Move 🕞 Enter 🏷 Return

The PDP Display has four automatic picture settings ("**Dynamic**", "**Standard**", "**Movie**" and "**Custom**") that are preset at the factory.

Dynamic, Standard, Movie, or Custom can be activated.

- 1. Dynamic
- 2. Standard
- 3. Movie
- 4. Custom

Ø Note

The direct button on the remote control is the 'P.MODE' button.

## Custom

By using the on-screen menus, the contrast and brightness can be changed to your personal preference.

 $\mathsf{MENU} \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{Picture}] \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{Custom}]$ 

#### Contrast

 $\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Picture}] \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Custom}] \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Contrast}] \rightarrow \P, \blacktriangleright \rightarrow \mathsf{ENTER} \end{array}$ 

Contrast [\_\_\_\_\_] 100

Adjusts the Contrast.

## Brightness

```
MENU \rightarrow \P \rightarrow ENTER \rightarrow [Picture] \rightarrow \P \rightarrow ENTER \rightarrow [Custom] \rightarrow \P \rightarrow ENTER \rightarrow [Brightness] \rightarrow \P, \blacktriangleright \rightarrow ENTER
Brightness 100
```

Adjusts the Brightness.

## Sharpness

```
\begin{array}{c} \mathsf{MENU} \to \P \to \mathsf{ENTER} \to [\mathsf{Picture}] \to \P \to \mathsf{ENTER} \to [\mathsf{Custom}] \to \P \to \P \to \mathsf{ENTER} \to [\mathsf{Sharpness}] \to \P, \Vdash \to \mathsf{ENTER} \end{array}
```

Sharpness 40

Adjusts the picture Sharpness.

## Color





Adjusts the picture Color.

## Tint

 $\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Picture}] \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Custom}] \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \mathsf{F} \rightarrow \mathsf{ENTER} \\ \rightarrow [\textbf{Tint}] \rightarrow \P, \blacktriangleright \rightarrow \mathsf{ENTER} \end{array}$ 



Adds a natural tone to the display.

Tint function can be available just in NTSC system.

## Color Tone

 $\mathsf{MENU} \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Picture}] \to \blacktriangledown \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Color} \ \mathsf{Tone}] \to \blacktriangle, \ \blacktriangledown \to \mathsf{ENTER}$ 



The color tones can be changed. The individual Color components are also user adjustable.

- 1. Off
- 2. Cool2
- 3. Cool1
- 4. Normal
- 5. Warm1
- 6. Warm2

# 🖉 Note

If you set the **Color Tone** to **Cool2**, **Cool1**, **Normal**, **Warm1**, or **Warm2**, the **Color Temp** function is disabled.

## Color Temp.

```
MENU \rightarrow \mathbf{v} \rightarrow ENTER \rightarrow [\mathbf{Picture}] \rightarrow \mathbf{v} \rightarrow \mathbf{v} \rightarrow \mathbf{v} \rightarrow \mathbf{v} \rightarrow ENTER \rightarrow [\mathbf{Color Temp.}] \rightarrow \mathbf{v}, \mathbf{v} \rightarrow ENTER
Color Temp.
\mathbf{v} \text{ Adjust} \qquad \bigcirc \text{ Return}
```

Color temp is a measure of the 'warmth' of the image colors.  $\bigcirc$  Note

This function is only enabled if the Color Tone is set to Off.

## Size AHC

```
\mathsf{MENU} \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Picture}] \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Size}] \to \blacktriangle, \blacktriangledown \to \mathsf{ENTER}
```

1	16:9
	Zoom1
_	Zoom2
۲	4:3
ø	Just Scan
	🗢 Move 🕞 Enter 🏷 Return

The Size can be switched.

- 1. **16:9** Sets the picture to 16:9 wide mode.
- 2. Zoom 1 Magnifies the size of the picture on the screen.
- 3. Zoom 2 Magnifies the size of the picture more than "Zoom 1".
- 4. **4:3** Sets the picture to 4:3 normal mode.
- 5. **Just Scan** Displays the input scenes as they are without any cutoff when HDMI 720p, 1080i, 1080p signals are input.

## 🖉 Note

Certain external devices may feed the display an out of spec signal that may cause cutoff even when using the **Just Scan** feature.

ZOOM1, ZOOM2 will be unavailabel in HDMI mode.

The **Position** and **Reset** functions are available when **Zoom1** or **Zoom2** is run.

## Digital NR (Digital Noise Reduction)

 $\begin{array}{l} \mathsf{MENU} \to \P \to \mathsf{ENTER} \to [\textbf{Picture}] \to \P \to \P \to \P \to \P \to \P \to \P \to \mathsf{ENTER} \to [\textbf{Digital NR}] \to \blacktriangle \, , \\ \P \to \mathsf{ENTER} \end{array}$ 



Turns the Digital Noise Reduction feature **Off/On**. The Digital Noise Reduction feature allows you to enjoy clearer and crisper images.

- 1. **Off**
- 2. **On**

## Film Mode 🔼 🚺 🖸

 $\begin{array}{c} \mathsf{MENU} \to \P \to \mathsf{ENTER} \to [\mathsf{Picture}] \to \P \to \mathsf{Finn} \mathsf{Mode} ] \\ \to \blacktriangle, \P \to \mathsf{ENTER} \end{array}$ 

1	V Off
•	On
0	
0	
	🗢 Move 🕞 Enter 🏷 Return

Turns Film Mode Off/On.

The Film Mode feature offers you a theater-quality viewing experience.

(In **HDMI** mode, this function can be available when the input signal is interlaced scan; it cannot be available with progressive scan signal.)

- 1. Off
- 2. **On**

#### Sound

#### **Available Modes**

- 📔 PC / BNC / DVI
- 🔼 AV

- 🖸 HDMI
- MagicInfo
- 🚺 тv
- Component

🖉 Note

- The **TV** menu is available when a TV tuner box is installed.
- The MagicInfo menu is available when a network box is installed.

#### Mode PAHMTC

 $\mathsf{MENU} \to \blacktriangledown \to \blacktriangledown \to \mathsf{ENTER} \to [\textbf{Sound}] \to \mathsf{ENTER} \to [\textbf{Mode}] \to \blacktriangle, \blacktriangledown \to \mathsf{ENTER}$ 

Mode	
1	Standard
•	Music
	Speech
Ø	Custom
	🗢 Move 🛛 Enter 🏷 Return

The PDP Display has a built-in high fidelity stereo amplifier.

1. Standard

Selects Standard for the standard factory settings.

2. Music

Selects Music when watching music videos or concerts.

3. Movie

Selects Movie when viewing movies.

4. Speech

Selects **Speech** when watching a show that is mostly dialogue (i.e., news).

5. Custom

Selects **Custom** if you want to adjust the settings according to your personal preferences.

## Custom PAHMTC

The sound settings can be adjusted to suit your personal preferences.

 $MENU \rightarrow \forall \rightarrow \forall \rightarrow \forall \rightarrow ENTER \rightarrow [Sound] \rightarrow \forall \rightarrow ENTER \rightarrow [Custom]$  With Note = 0

• You can hear the sound even when sound value is set to 0.

• If you adjust sound using Custom function, Mode will turn to Custom mode.

#### Bass

```
MENU \rightarrow \Psi \rightarrow \Psi \rightarrow ENTER \rightarrow [Sound] \rightarrow \Psi \rightarrow ENTER \rightarrow [Custom] \rightarrow ENTER \rightarrow [Bass] \rightarrow \P,
\blacktriangleright \rightarrow ENTER
```

Emphasizes low frequency audio.

#### Treble

```
\begin{array}{c} \mathsf{MENU} \to \P \to \P \to \mathsf{ENTER} \to [\mathbf{Sound}] \to \P \to \mathsf{ENTER} \to [\mathbf{Custom}] \to \P \to \mathsf{ENTER} \to [\mathbf{Treble}] \\ \to \P, \Vdash \to \mathsf{ENTER} \end{array}
```

Emphasizes high frequency audio.

#### Balance

```
\begin{array}{c} \mathsf{MENU} \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \mathsf{ENTER} \to [\mathbf{Sound}] \to \overline{\mathbf{v}} \to \mathsf{ENTER} \to [\mathbf{Custom}] \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \mathsf{ENTER} \to [\mathbf{Bal-ance}] \to \overline{\mathbf{v}}, \ \mathbf{v} \to \mathsf{ENTER} \end{array}
```

Allows you to Adjusts the sound balance between the left and right speakers.

## Auto Volume

```
\mathsf{MENU} \to \P \to \P \to \mathsf{ENTER} \to [\mathbf{Sound}] \to \P \to \P \to \mathsf{ENTER} \to [\mathbf{Auto Volume}] \to \blacktriangle, \P \to \mathsf{ENTER}
```

1	Off	
•	On	
٩		
Ø		
	🗢 Move 🛛 🔂 E	inter 🏷 Return

Reduces the difference in volume control between broadcasters.

- 1. **Off**
- 2. **On**

## SRS TS XT PAHMTC

 $\begin{array}{l} \mathsf{MENU} \to \P \to \P \to \mathsf{ENTER} \to [\textbf{Sound}] \to \P \to \P \to \P \to \P \to \mathsf{ENTER} \to [\textbf{SRS TS XT}] \to \blacktriangle \ , \ \P \to \mathsf{ENTER} \end{array}$
#### Adjusting the PDP Display

SRS TS	(T
TA .	✓ Off
	On
٩	
ø	
	🗢 Move 🔄 Enter 🏷 Return

**SRS TS XT** is a patented SRS technology that solves the problem of playing 5.1 multichannel content over two speakers. TruSurround delivers a compelling, virtual surround sound experience through any two-speaker playback system, including internal television speakers. It is fully compatible with all multichannel formats.

1. **Off** 



🖉 Note

The direct button on the remote control is the 'SRS' button.

### Setup

### **Available Modes**

- PC / BNC / DVI
- 🔼 AV
- 🖸 HDMI
- MagicInfo
- 🚺 тv
- Component

Note

- The **TV** menu is available when a TV tuner box is installed.
- The MagicInfo menu is available when a network box is installed.

### Language PAHMTC



You can choose one of 11 languages.

English,Deutsch,Español,Français,Italiano,Svenska,Русский Português,中国语,日本語,한국어

Note 🖉

The language chosen affects only the language of the OSD. It has no effect on any software running on the computer.

#### Time **PAHMTC**

Selects from one of 4 time settings, Clock Set, Sleep Timer, On Timer, and Off Timer.

 $\mathsf{MENU} \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Setup}] \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Time}]$ 

### **Clock Set**

 $\begin{array}{l} \mathsf{MENU} \to \blacktriangledown \to \blacktriangledown \to \blacksquare \to \mathsf{ENTER} \to [\texttt{Setup}] \to \blacktriangledown \to \mathsf{ENTER} \to [\texttt{Time}] \to \mathsf{ENTER} \to [\texttt{Clock} \\ \texttt{Set}] \to \blacktriangle, \blacktriangledown \to \dashv, \blacktriangleright \to \mathsf{ENTER} \end{array}$ 



Current Time Setting.

### **Sleep Timer**

```
\begin{array}{l} \mathsf{MENU} \to \P \to \P \to \mathsf{ENTER} \to [\texttt{Setup}] \to \P \to \mathsf{ENTER} \to [\texttt{Time}] \to \P \to \mathsf{ENTER} \to [\texttt{Sleep Timer}] \to \blacktriangle \to \mathsf{ENTER} \end{array}
```

Sleep Tim	er
1	V Off
•	<b>3</b> 0
۲	90
ø	120
	180
	🗢 Move 🖃 Enter 🏷 Return

Turns the PDP Display off automatically at certain times.

- 1. **Off**
- 2. **30**
- 3. **60**
- 4. **90**
- 5. **120**
- 6. **150**

7. **180** 

### **On Timer**

 $\begin{array}{l} \mathsf{MENU} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \rightarrow [\mathbf{Setup}] \rightarrow \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \rightarrow [\mathbf{Time} \ ] \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \rightarrow [\mathbf{On \ Timer}] \rightarrow \underline{\mathtt{v}} , \overline{\mathtt{v}} / \underline{\mathtt{v}} \rightarrow \mathsf{ENTER} \end{array}$ 



Turns the PDP Display on automatically at a preset time. Controls the mode and the volume level at the time the PDP Display turns on automatically.

### **Off Timer**

 $\begin{array}{l} \mathsf{MENU} \rightarrow \forall \rightarrow \forall \rightarrow \forall \rightarrow \forall \rightarrow \mathsf{ENTER} \rightarrow [\texttt{Setup}] \rightarrow \forall \rightarrow \mathsf{ENTER} \rightarrow [\texttt{Time}] \rightarrow \forall \rightarrow \forall \rightarrow \forall \rightarrow \forall \rightarrow \mathsf{ENTER} \\ \rightarrow [\texttt{Off Timer}] \rightarrow \blacktriangle, \forall / \blacktriangleleft, \blacktriangleright \rightarrow \mathsf{ENTER} \end{array}$ 



Turns the PDP Display off automatically at a preset time.

### Menu Transparency PAHMTC



Change the transparency of the background of the OSD.

- 1. High
- 2. Medium
- 3. Low

4. Opaque

### Safety Lock PIN PAHMTC

 $\begin{array}{l} \mathsf{MENU} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \rightarrow [\mathbf{Setup}] \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \rightarrow [\mathbf{Safety} \ \mathbf{Lock} \ \mathbf{PIN} \ ] \rightarrow \\ [0 \square 9] \rightarrow [0 \square 9] \rightarrow [0 \square 9] \rightarrow [0 \square 9] \end{array}$ 

Safety Loo	
10	
•	Enter Pin
۲	
Ø	
	09 Adjust 🔁 Enter 🕤 Return

The password can be changed.

Z	Note
	11010

The preset password for the PDP Display is "0000"

### Energy Saving PAHMTC



This feature adjusts the power consumption of the unit in order to save energy.

- 1. Off
- 2. **On**

## Note

If you want to reduce the standby power consumption, set **Energy Saving** to **On**. However, when **Energy Saving** is **On**, you cannot use the remote Power On function of the MDC and the WOL (Wake On LAN) function of MagicInfo.

### HDMI Black Level 🗓

 $\begin{array}{l} \mathsf{MENU} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \rightarrow [\textbf{Setup}] \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \rightarrow [\textbf{HDMI Black Level }] \rightarrow \underline{\mathtt{a}}, \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \end{array}$ 

#### Adjusting the PDP Display

HDMI Blac	ck Level
1	V Normal
	Low
٥	
ø	
	🗢 Move 🖼 Enter 🏷 Return

When a DVD or set-top box is connected to your TV via HDMI, it may cause a degradation in the screen quality, such as an increase in the black level, a low contrast, or discoloration, etc., depending on the external device connected. In this case, adjust the screen quality of your TV by configuring the **HDMI black level**.

- 1. Normal
- 2. Low

### Video Wall

A **Video Wall** is a set of video screens connected together, so that each screen shows a part of the whole picture or where the same picture is repeated on each screen.

When the Video Wall is on, you can adjust the Video Wall screen setting.

```
\begin{array}{l} \mathsf{MENU} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \mathsf{ENTER} \to [\mathbf{Setup}] \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \mathsf{ENTER} \to [\mathbf{Video} \ \mathbf{Wall} \ ] \\ \hline & \swarrow \mathbf{Note} \end{array}
```

When Video Wall is running, the Auto Adjustment, Image Lock, and Size functions are not available. Video Wall does not operate in MagicInfo mode.

#### Video Wall

 $\begin{array}{l} \mathsf{MENU} \to \P \to \P \to \mathsf{ENTER} \to [\texttt{Setup}] \to \P \to \P \to \P \to \P \to \P \to \P \to \mathsf{F} \to \mathsf{ENTER} \to [\texttt{Video Wall}] \to \mathsf{ENTER} \to [\texttt{Video Wall}] \to \blacktriangle, \P \to \mathsf{ENTER} \end{array}$ 

1	V Off		
•	On		
۲			
Ô			

Turns Off/On the Video Wall function of the selected display Off/On.

- 1. Off
- 2. **On**

#### Format

```
\begin{array}{l} \mathsf{MENU} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \rightarrow [\mathbf{Setup}] \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \rightarrow [\mathbf{Video} \ \mathbf{Wall} \ ] \rightarrow \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \rightarrow [\mathbf{Format}] \rightarrow \underline{\mathtt{a}}, \ \overline{\mathtt{v}} \rightarrow \mathsf{ENTER} \end{array}
```

Format				
1	🗹 Full			
	Natural			
۲				
ø				
	🗢 Move	🛃 Enter	🏷 Return	

The Format can be selected to see a divided screen.

1. **Full** 

Provides a full screen without any margins.

2. Natural

Displays a natural image with the original aspect ratio intact.

### Horizontal

 $\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\texttt{Setup}] \rightarrow \P \rightarrow \mathsf{FNTER} \rightarrow [\texttt{Video} \\ \texttt{Wall} \\ ] \rightarrow \P \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\texttt{Horizontal}] \rightarrow \blacktriangle, \P \rightarrow \mathsf{ENTER} \end{array}$ 

nunzunta			
1	<mark>1</mark> 1		
	2		
۲	4		
Ø	5		
	🗢 Move 🛛	🗗 Enter 🛛 🕤 R	eturn

Sets how many parts the screen should be divided horizontally.

Five adjustment levels: 1, 2, 3, 4, and 5.

### Vertical

```
\begin{array}{l} \mathsf{MENU} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \mathsf{ENTER} \to [\mathbf{Setup}] \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \mathsf{ENTER} \to [\mathbf{Video} \ \mathbf{Wall} \ ] \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \overline{\mathtt{v}} \to \mathbf{ENTER} \to [\mathbf{Vertical}] \to \underline{\mathtt{k}} \ , \ \overline{\mathtt{v}} \to \mathsf{ENTER} \end{array}
```



Sets how many parts the screen should be divided vertically.

Five adjustment levels: 1, 2, 3, 4, and 5.

### **Screen Divider**



The screen can be divided into several images. A number of screens can be selected with a different layout when dividing.

- Select a mode in Screen Divider.
- Select a display in Display Selection.
- The selection will be set up by pressing a number in the selected mode.

### Safety Screen PASCHMC

The **Safety Screen** function is used to prevent afterimages that may appear when a still picture is displayed on the screen over a long time.

- The Safety Screen function scrolls the screen for the specified period of time.
- This function is not available when the power is turned off.

 $\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\texttt{Setup}] \rightarrow \P \rightarrow \mathsf{FNTER} \rightarrow [\texttt{Safety Screen}] \end{array}$ 

### **Pixel Shift**

### **Pixel Shift**

```
\begin{array}{l} \mathsf{MENU} \to \P \to \P \to \P \to \mathsf{ENTER} \to [\mathsf{Setup}] \to \P \to \mathsf{ENTER} \to \\ [\mathsf{Safety Screen}] \to \mathsf{ENTER} \to [\mathsf{Pixel Shift}] \to \mathsf{ENTER} \to [\mathsf{Pixel Shift}] \to \blacktriangle, \P \to \mathsf{ENTER} \end{array}
```

INELOTIN				
1	Off			
	V On			
۲				
Ø				
	🗢 Move	🚭 Enter	🏷 Return	

To prevent after-images on the screen you can use this function, so that every minute pixels on the PDP are moved in horizontal or vertical direction.

- 1. **Off**
- 2. **On**

🖉 Note

The **Pixel Shift** is not available when **Video Wall** is On.

### **Horizontal Dot**

```
\begin{array}{l} \mathsf{MENU} \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \overline{\mathbf{ENTER}} \to [\mathbf{Setup}] \to \overline{\mathbf{v}} \to \overline{
```



Sets how many pixels the screen moves horizontally.

Five adjustment levels: 0, 1, 2, 3 and 4.

### **Vertical Line**

```
\begin{array}{l} \mathsf{MENU} \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Setup}] \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \blacksquare \to \mathsf{ENTER} \to [\mathsf{Safety Screen}] \to \mathsf{ENTER} \to [\mathsf{Pixel Shift}] \to \blacktriangledown \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Vertical Line}] \to \blacktriangle , \blacktriangledown \to \mathsf{ENTER} \end{array}
```

Vertical Li	ne
1	v 0
•	2
۲	3
Ô	4

Sets how many pixels the screen moves vertically.

Five adjustment levels: 0, 1, 2, 3 and 4.

### Time

```
\begin{array}{l} \mathsf{MENU} \to \P \to \P \to \P \to \mathsf{ENTER} \to [\mathsf{Setup}] \to \P \to \mathsf{ENTER} \to [\mathsf{Safety Screen}] \to \mathsf{ENTER} \to [\mathsf{Pixel Shift}] \to \P \to \P \to \P \to \mathsf{ENTER} \to [\mathsf{Time}] \to \blacktriangle, \P \to \mathsf{ENTER} \to \mathsf{ENTER}
```



Set the time interval for performing the horizontal or vertical movement, respectively.

### Timer

### Timer

 $\begin{array}{c} \mathsf{MENU} \to \mathbf{v} \to \mathbf{v} \to \mathbf{v} \to \mathsf{ENTER} \to [\mathbf{Setup}] \to \mathbf{v} \to \mathbf{v$ 

You can set the timer for Screen Burn Protection.

ø

If you start the operation to erase any residual image, the operation will be performed for the set period of time and then automatically finish.

- 1. Off
- 2. **On**

#### Mode

 $\begin{array}{l} \mathsf{MENU} \rightarrow \texttt{V} \rightarrow \texttt{V} \rightarrow \texttt{V} \rightarrow \texttt{ENTER} \rightarrow [\texttt{Setup}] \rightarrow \texttt{V} \rightarrow \texttt{ENTER} \rightarrow [\texttt{Safety Screen}] \rightarrow \texttt{V} \rightarrow \texttt{ENTER} \rightarrow [\texttt{Timer}] \rightarrow \texttt{V} \rightarrow \texttt{ENTER} \rightarrow [\texttt{Mode}] \rightarrow \texttt{L}, \texttt{V} \rightarrow \texttt{ENTER} \end{array}$ 

Mode	
1	V Scroll
	Bar Eraser
۲	All White
٢	Pattern
	🗢 Move 🛛 Enter 🕤 Return

You can change the Safety Screen Type.

- 1. Scroll
- 2. Bar
- 3. Eraser
- 4. All White
- 5. Pattern

### Period

```
\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\mathsf{Setup}] \rightarrow \P \rightarrow \mathsf{P} \rightarrow \mathsf{ENTER} \rightarrow [\mathsf{Safety Screen}] \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\mathsf{Timer}] \rightarrow \P \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\mathsf{Period}] \rightarrow \blacktriangle, \P \rightarrow \mathsf{ENTER} \end{array}
```



Use this function to set the execution period for each mode set in the timer.

### Time

```
\begin{array}{l} \mathsf{MENU} \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \mathsf{ENTER} \to [\mathbf{Setup}] \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \mathbf{v} \to \mathsf{ENTER} \to [\mathbf{Safety Screen}] \to \overline{\mathbf{v}} \to \mathsf{ENTER} \to [\mathbf{Timer}] \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \overline{\mathbf{v}} \to \mathsf{ENTER} \to [\mathbf{Time}] \to \underline{\mathbf{k}} , \overline{\mathbf{v}} \to \mathsf{ENTER} \to [\mathbf{Time}] \to \underline{\mathbf{k}} , \overline{\mathbf{v}} \to \mathsf{ENTER} \end{array}
```

1	<u>v</u> 1
•	3
۲	4
Ô	5
۵	

Within the set period of time specify a time for execution.

- Mode-Scroll : 1~5 sec
- Mode-Bar, Eraser : 10~50 sec
- Mode-All White, Pattern : 1, 5, 10, 20 30 min

### Scroll

 $\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\mathsf{Setup}] \rightarrow \P \rightarrow \mathsf{F} \rightarrow \mathsf{ENTER} \rightarrow [\mathsf{Safety Screen}] \rightarrow \P \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\mathsf{Scroll}] \end{array}$ 

1	Pixel Shift
	Timer Scroll
۲	Bar
ø	Eraser
	Pattern
	🗢 Move 🛛 Enter 🏷 Return

This function prevents after-images on the screen by moving all the pixels on the PDP according to a pattern.

Use this function when there are remaining after-images or symbols on the screen, especially when you displayed a still image on the screen for a long time.

### Bar

```
\begin{array}{l} \mathsf{MENU} \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\mathsf{Setup}] \rightarrow \P \rightarrow \mathsf{F} \rightarrow \mathsf{ENTER} \rightarrow [\mathsf{Safety Screen}] \rightarrow \P \rightarrow \P \rightarrow \P \rightarrow \mathsf{ENTER} \rightarrow [\mathsf{Bar}] \end{array}
```

Safety Sci	reen
1	Pixel Shift
	Timer
	Scroll
۲	v Bar
~	Eraser
(O)	All White
	Pattern
	🗢 Move 🛛 🔂 Enter 🏷 Return

This function prevents after-images on the screen by moving long black and white vertical lines.

#### Eraser

This function prevents after-images on the screen by moving a rectangular pattern.

### All White

This function prevents after-images on the screen by changing the color of pixels to white.

Use this function when there are remaining after-images or symbols on the screen, especially when you displayed a still image on the screen for a long time.

#### Pattern

Safety Sci	een
1	Pixel Shift
	Timer Scroll
۲	
Ô	Eraser All White
	v Pattern

This function prevents after-images on the screen by moving a diagonal pattern stored in the panel repeatedly.

### Resolution Select

1	V Off
•	1024 x 768 1280 x 768
۲	1360 x 768
ø	1366 x 768

When the picture is not displayed properly on the screen when setting the graphics card resolution of the computer to 1024 x 768 @ 60Hz, 1280 x 768 @ 60Hz, 1360 x 768 @ 60Hz or 1366 x768 @ 60Hz, by using this function(Resolution Select), you can have the picture displayed on the screen in the specified resolution.

## 🖉 Note

Available in PC mode only

- 1. Off
- 2. 1024 X 768
- 3. 1280 X 768
- 4. 1360 x 768
- 5. 1366 X 768

### Ø Note

Selecting the menu is only allowed when the graphics resolution is set to 1024 x 768 @ 60Hz, 1280 x 768 @ 60Hz, 1360 x 768 @ 60Hz or 1366 x768 @ 60Hz.

### Power On Adjustment



Adjusts the Power On time for the screen.

 $\triangle$ 

Caution: Set the Power On time to be longer to avoid overvoltage.

### Side Gray PAHMTC



Select the brightness of the grey for the screen background.

- 1. **Off**
- 2. Light
- 3. Dark

#### Reset

Reverts the product settings to factory defaults. The Reset function is only available when PC / DVI is being used.

### Image Reset 📔

Image	Ok	Cancel
🗢 Move	Adjust	🖸 Return

🖉 Note

Available in **PC** mode only

## 🖉 Note

The Reset function is not available when Video Wall is On.

### Color Reset PAHMTC

### **Multi Control**

### **Available Modes**

- P PC / BNC / DVI
- 🔼 AV
- 🚺 HDMI
- MagicInfo
- 🚺 т и
- Component

### Multi Control

Assigns an individual ID to the SET.

 $\mathsf{MENU} \to \blacktriangledown \to \blacktriangledown \to \blacktriangledown \to \mathsf{ENTER} \to [\mathsf{Multi}\ \mathsf{Control}\ ] \to \mathsf{ENTER} \to \bot, \blacktriangledown \to [0{\sim}9]$ 



ID Setup

Assigns distinctive IDs to the SET.

• ID Input

Use to select the transmitter functions of the individual SET. Only a SET where the ID corresponds to the transmitter setting becomes activated.

### MagicInfo

### **Available Modes**

PC / BNC / DVI

- 🔼 AV
- 🖸 HDMI
- MagicInfo
- 🚺 тv
- Component

## 🖉 Note

- The operating system for this set only supports English so the other languages might be corrupted on the screen.
- For **MagicInfo**, a remote control is available for **MagicInfo**. However, it is recommended using a separate USB keyboard.
- For **MagicInfo** in Device mode, moving external devices while booting may cause errors. Set up external devices only if the PDP Display turns on.
- Do not unplug the LAN cable used for the network (ex: video display). Otherwise, the program (MagicInfo) may stop. If you do unplug the cable, restart the system.
- Do not unplug the LAN cable used by an USB device (ex: video display). Otherwise, the program (MagicInfo) may stop.
- To access other sources, press the SOURCE button in MagicInfo.
- The preset password for the PDP Display is "000000".
- The server program's Power-On option works only if the PDP Display's power is completely shut off.

Please make sure not to use the Power-On option when the PDP Display is in the process of shutting down since this may cause system errors on the PDP Display.

- In the OSD image of MagicInfo, Network mode is the same as Device.
- When using MagicInfo with the MagicInfo Pro Server Program: perform Network mode.
- When using **MagicInfo** with the device directly connected to PDP Display : execute Device mode.
- Press ALT + F12 to directly go to the MagicInfo Window screen.
- To setup MagicInfo on a Windows screen, a keyboard and mouse are required.
- To setup MagicInfo on a Windows screen, refer to the MagicInfo Server Help.

It is highly recommended not to turn off the AC power during an operation.

- For pivoted PDP Displays, ticker transparency is not supported.
- For pivoted PDP Displays, a screen resolution of up to 720\*480(SD) is supported for movies.
- For drive D:, **EWF** is not applied.

- When the contents of Setup have been changed when **EWF** is in the **Enable** state, to save the changes in the disk, you must **Commit** them.
- By selecting **Disable**, **Enable** or **Commit**, the system is restarted.

### Magicinfo

🕄 MUISetup	×
Install languages   TCP/IP	
Select the language you want to install on the system for menus and dialogs.	
Current Language : English	-
Chinese (Traditional) German French	
Italian Japanese	
Korean Swedish Chinese (Simplified)	
Spanish	
Install	
	1
Cancel Cancel	

- 1. Select Magicinfo in the Source List menu.
- 2. The MUTSetup screen appears.

Select the language you want to use.

3. Press the Install button.

If you select Do not show again and click the Install button, the Scheduler screen is displayed after rebooting.



4. Connect your keyboard and mouse and press the "ALT + F12" keys on your keyboard.

5. The Windows Desktop is displayed and the Magicinfo pro icon (the image will be inserted) appears. Move the cursor over the icon.

🖉 Note

If the **Magicinfo** icon is not displayed on the notification area, double click the **Magicinfo** icon on the window desktop. The icon will appear.



6. Right-click on the Magicinfo pro icon (the image will be inserted) and select 'Program' --> 'player' from the displayed menu.

About	
EWF	
Password	
Setup	
Rotation )	
Program )	Vone
Exit	Nayer Scheduler

7. The Player screen of Magicinfo pro is displayed.



## 🖉 Note

To finish the MagicInfo, press ALT + F12.

### Photo M

The JPEG, BMP file format are supported.

### Auto



Automatically fits the image to the window.

### Original

Shows the properties of the original file.

### **Slide Show**



Displays the properties of the original file as they are.

### Interval



Controls the time intervals between image files for a slide show. (5 Sec, 10 Sec, 20 Sec, 30 Sec, 60 Sec)

### Rotation



Displays an image file by turning it clockwise by 90 degrees.

### Zoom



Displays a reduced picture.

### Close



Closes the image control Menu.

### Music M



The MP3 file format is supported.

### MovieM

The MPEG1, WMV file format are supported.

### Play



Plays a movie file.

### Full Size



Plays a movie file in full screen.

### OFFICE / HTMLM

MagicInfo XX				
		e	<b>@</b> @	France
	Device		Setup	
			G	
Photo	Music	Movie	Office / HTML	•
¢ Mo	V 8		🕞 Enter	0 0 0 0
				Billion Mag
				1998 C

PPT(Power Point), DOC(MS Word), XLS(MS Excel), PDF, HTML, HTM files are displayed.

• Install the proper viewer(freeware) program to see the MS Office(Word, Excel, Power Point) or PDF doucuments.

### InternetM



Connects to the Internet

### Setup<sup>M</sup>

Sets various functions in **MagicInfo** mode. A password must be entered to access **Setup** mode.

### **Schedule View**



Displays a schedule.

### TCP/IP



Changes the TCP/IP settings.

### Connection

MagicInfo 🔊				
		e	<b>Ø</b> 0	
Network	Device		Setup	
Photo	Music	Movie	Office / HTML	
¢ Mov			🕞 Enter	
				6000 G 6000 G 6000 G

Modifies the network settings.

### Password



The password can be changed.

• The password should be between 6 and 12 characters in numeric format.

(You should enter a password between 6 and 12 characters in numeric format)

- If you enter the wrong password three times, the setup configuration is reset and a warning message appears from the server.
- If you forget the password, enter Info, 8, 2 and 4 on the remote control to initialize the password. This will reset the previous settings of Setup mode.



#### Local : You can delete or copy files on both local and removable disks.

#### File

### **Play Option**



You can set the repeat play and screen settings.

### Repeat : Determines the repeat option for playing movies and music.

- None Select No Repeat to play a movie or tune in the list only once.
- File Repeat Select Repeat File to play a movie or tune in the list repeatedly.
- List Repeat Select Repeat List to play movies or tunes in the list in sequence repeatedly.

### Rotation - Sets the picture orientation.

- Landscape Sets the screen resolution to 1366x768 pixels.
- Portrait Sets the screen resolution to 768x1366 pixels.

# EWF(Enhanced Write Filter) : Prevents change to and loss of the data saved on the disk.

- **Disable** Disables **EWF** to allow saved data to be changed data on the protected disk (drive C:). When switching from the **Enable** to the **Disable** state, you can select **Commit**.
- Enable Enables EWF to prevent saved data to be changed on the protected disk (drive C:).
- Commit Commit the changed data to the protected disk (drive C:) when EWF is in the Enable state. Commit is not available when EWF is in the Disable state.

## Troubleshooting

### **Self-Test Feature Check**

Ø Note

Check the following items yourself before calling for assistance. Contact a Service Center for problems that you cannot solve by yourself.

### Self-Test Feature Check

- 1. Turn off both your computer and the PDP Display.
- 2. Unplug the video cable from the back of the computer.
- 3. Turn on the PDP Display.

The figure shown below ("**Check Signal Cable**") appears on a black background when the PDP Display is working normally even though no video signal is detected: While in the Self-Test mode, the LED power indicator remains green and the figure moves around on the screen.



4. Turn off your PDP Display and reconnect the video cable; then turn on both your computer and the PDP Display

If your PDP Display screen remains blank after using the previous procedure, check your video controller and computer system; your PDP Display is functioning properly.

### Warning Messages

You can even view the screen at a resolution of 1360 x 768. However, you will receive the following message for a minute; You can choose to change the screen resolution or stay in the current mode during that time. And if the resolution is more than 85Hz, you will see the black screen because the PDP Display does not support over 85Hz.

Not Optimum Mode
Recommended Mode ****



Refer to Specifications > Preset Timing Modes for the resolutions or frequencies supported by the PDP Display.

### **Maintenance and Cleaning**

1) Maintaining the PDP Display Case.

Clean with a soft cloth after disconnecting the power cord.



- Do not use benzene, thinner or other flammable substances, or a wet cloth.
- We recommend that a SAMSUNG cleansing agent is used to prevent damage to the screen.

2) Maintaining the Flat Panel Display Screen.

Clean with a soft cloth (cotton flannel) smoothly.

• Never use acetone, benzene or thinner.

57	ê ô
	86

(They may cause flaws or deformation of the screen surface.)

• The user will be required to pay costs and related expenses for repairing damages caused.

### Symptoms and Recommended Actions

Ø Note

A PDP Display recreates visual signals received from the computer. Therefore, if there is a problem with the computer or the video card, this can cause the PDP Display to become blank, have poor coloring, become noisy, and video mode not supported, etc. In this case, first check the source of the problem, and then contact a Service Center or your dealer.

- 1. Check if the power cord and the video cables are properly connected to the computer.
- 2. Check if the computer beeps more than 3 times when booting.

(If it does, request an a service for the main board of the computer.)

- 3. If you installed a new video card or if you assembled the PC, check if you installed the Adaptor(video).
- 4. Check if the scanning ratio of the video screen is set to between 50 Hz ~ 85 Hz.

(Do not exceed 60Hz when using the maximum resolution.)

5. If you have problems in installing the Adaptor (video) driver, boot the computer in Safe Mode, remove the Display Adaptor in the "Control Panel -> System -> Device Administrator" and then reboot the computer to reinstall the Adaptor (video) driver.

### **Check List**

🖉 Note

- The following table lists possible problems and their solutions. Before calling for assistance, check the information in this section to see if you can remedy any problems for yourself. If you do need assistance, please call the phone number on the Information section or contact your dealer.
- For more network-related information, refer to the MagicInfo Troubleshooting section.

### Problems related to the Installation (PC Mode)

### 🖉 Note

Problems related to the PDP Display installation and their solutions are listed.

Q: The PDP Display screen flickers.

A: Check if the signal cable between the computer and the PDP Display is securely connected.

(Refer to Connecting a Computer)

### Problems related to the Screen

## 🖉 Note

Problems related to the PDP Display screen and their solutions are listed.

- Q: The screen is blank and the power indicator is off.
- A: Ensure that the power cord is firmly connected and the PDP Display is on.

(Refer to the Connecting a Computer)

- Q: "Check Signal Cable" message.
- A: Ensure that the signal cable is firmly connected to the PC or video sources.

(Refer to the Connecting a Computer)

- A: Ensure that the PC or video sources are turned on.
- Q: "Not Optimum Mode" message.
- A: Check the maximum resolution and the frequency of the video Adaptor.
- A: Compare these values with the data in the Preset Timing Modes Chart.
- Q: The picture rolls vertically.
- A: Check if the signal cable is securely connected. Re-connect it, if necessary.

(Refer to Connecting a Computer)

- Q: The image is not clear; picture is blurred.
- A: Run Frequency **Coarse** and **Fine** tuning.
- A: Turn on again after removing all accessories (video extension cable, etc.)
- A: Set the resolution and frequency to the recommended ranges.
- Q: The picture image is unstable and shakes.
- A: Check if the resolution and frequency set for the computer video card falls in the range supported by the PDP Display. If not, reset them referring to the current Information under the PDP Display menu and Preset Timing Modes.
- Q: Ghost images are shown in the picture.
- A: Check if the resolution and frequency set for the computer video card falls in the range supported by the PDP Display. If not, reset them referring to the current Information under the PDP Display menu and Preset Timing Modes.
- Q: The image is too light or too dark.
- A: Adjusts the **brightness** and **contrast**.

(Refer to the Brightness, Contrast)

- Q: The screen color is inconsistent.
- A: Adjust color using **Custom** under OSD Color Adjustment menu.
- Q: The color image is distorted by dark shadows.
- A: Adjust color using **Custom** under OSD Color Adjustment menu.
- Q: The color white is poor.
- A: Adjust color using **Custom** under OSD Color Adjustment menu.
- Q: The Power Indicator blinks.
- A: The PDP Display is currently saving the changes made in the settings to the OSD memory.
- Q: The screen is blank and the power indicator light blinks every 0.5 or 1 seconds. The PDP Display is using its power management system. Press any key on the keyboard.
- A: The PDP Display is using its power management system.
- A: Press any key on the keyboard.
- Q: The screen is blank and it is blinking.
- A: If you see the "**TEST GOOD**" message on the screen when you pressing the MENU button, check the cable connection between the PDP Display and the computer to ensure that the connector is properly connected.

### **Problems related to Audio**

### Note

Problems related to audio signals and their solutions are listed below.

- Q: No sound.
- A: Ensure that the audio cable is firmly connected to both the audio-in port on your PDP Display and the audio-out port on your sound card.

(Refer to the Connecting a Computer)

- A: Check the volume level.
- Q: The sound level is too low.
- A: Check the volume level.
- A: If the volume is still too low after turning the control to its maximum, check the volume control on the computer sound card or software program.
- Q: The sound is too high or too low.
- A: Adjusts the **Treble** and **Bass** to the appropriate levels.

### Problems related to the Remote Control

### Note 🖉

Problems related to the remote control and their solutions are listed.

Q: The remote control buttons do not respond.

- A: Check the polarities (+/-) of the batteries.
- A: Check if the batteries are empty.
- A: Check if the power is on.
- A: Check if the power cord is securely connected.
- A: Check if a special fluorescent or neon lamp is on in the vicinity.

### **Problems related to MagicInfo**

### 🖉 Note

Making a Bootable USB Flash Disk.

- Q: Making a Bootable USB Flash Disk
- A: 1) You can turn a common 512-MB or bigger USB storage media into a bootable disk using a USB bootable disk creation tool. (For example, the HP USB Disk Storage Format Tool)
- A: 2) Copies the OS ghost image and executables to your USB disk.
- A: 3) Enter the BIOS menu of your set by pressing the F2 key in the BIOS logo screen. Then, enable the USB Boot First option by selecting that option and pressing the Enter key in the Boot menu.
- A: 4) Switch your set on while your USB disk is connected and boot up in DOS mode.
- A: 5) Run C:\ghost.exe and choose Local  $\rightarrow$  Partition  $\rightarrow$  From Image from the menu. Choose the ghost image to update your USB disk with and choose the target disk.
- A: 6) When the ghost image update finishes, the set will be rebooted automatically.

#### Q & A

- Q: How can I change the frequency?
- A: The frequency can be changed by reconfiguring the video card.

### Note 🖉

That video card support can vary, depending on the version of the driver used. (Refer to the computer or the video card manual for details.)

- Q: How can I Adjusts the resolution?
- A: Windows XP:

Set the resolution in the Control Panel  $\rightarrow$  Appearance and Themes  $\rightarrow$  Display  $\rightarrow$  Settings.

A: Windows ME/2000:

Set the resolution in the Control Panel  $\rightarrow$  Display  $\rightarrow$  Settings.

\* Contact the video card manufacturer for details.

- Q: How can I set the Power Saving function?
- A: Windows XP:

Set the resolution in the Control Panel  $\rightarrow$  Appearance and Themes  $\rightarrow$  Display  $\rightarrow$  Screen Saver.

Set the function in the BIOS-SETUP of the computer. (Refer to the Windows / Computer Manual).

A: Windows ME/2000:

Set the resolution at the Control Panel  $\rightarrow$  Display  $\rightarrow$  Screen Saver.

Set the function in the BIOS-SETUP of the computer. (Refer to the Windows / Computer Manual).

- Q: How can I clean the outer case/PDP Panel?
- A: Disconnect the power cord and then clean the PDP Display with a soft cloth, using either a cleaning solution or plain water.

Do not leave any detergent or scratches on the case. Do not let any water enter the PDP Display.

- Q: How can I play the video?
- A: The video supports the MPEG1 and WMV codecs only. Install the corresponding codec to play the video. Note that some of the codecs can be incompatible.

## 🖉 Note

Before calling for assistance, check the information in this section to see if you can remedy any problems yourself. If you do need assistance, please call the phone number on the Information section or contact your dealer.

# **Specifications**

### General

General		
Model Name	SyncMast	ter P42HP
	SyncMast	ter P50HP
PDP Panel		
Size	SyncMaster P42HP	42 " Diagonal (107 cm)
	SyncMaster P50HP	50 " Diagonal (127 cm)
Display area	SyncMaster P42HP	933.89 mm (H) X 532.22 mm (V)
	SyncMaster P50HP	1105.65 mm (H) X 622.08 mm (V)
Pixel Pitch	SyncMaster P42HP	0.912 mm (H) X 0.693 mm (V)
	SyncMaster P50HP	0.810 mm (H) x 0.810 mm (V)
	_	
Synchronization	1	
Horizontal	30 ~ 81 k	Hz
Vertical	56 ~ 75 H	lz
Display Color		
Display Color 16.7 M		
Resolution		
Optimum resolu-	P42HP	1024 x 768 @ 60 Hz
tion	P50HP	1360 x 768 @ 60 Hz
Maximum resolu-	P42HP	1920 x 1080 @ 60 Hz
tion	P50HP	1920 x 1080 @ 60 Hz
Input Signal, Ter	rminated	
RGB Analog, DVI		jital RGB
0.7 Vp-p ±5 %	-	
Separate H/V syn	nc, Composite,	SOG(Option)
TTL level (V high	≥ 2.0 V, V low	≤ 0.8 V)

SyncMaster P42HP	170MHz (Analog,Digital)	
SyncMaster P50HP	170MHz (Analog,Digital)	

#### **Power Supply**

AC 100 - 240 V~ (+/- 10 %), 50/60 Hz ± 3 Hz

#### **Signal Cable**

15pin-to-15pin D-sub cable, Detachable

DVI-D to DVI-D connector, Detachable (Sold separately)

#### Dimensions (W x H x D) / Weight

SyncMaster P42HP	1027 x 630.4 x 96.8 mm ( 40.4 x 24.8 x 3.8 inch ) (Without Stand)
	1027 x 682.8 x 361.7 mm(40.4 x 26.9 x 14.2 inch)(With Stand) / 27.6kg (60.8 lbs)
SyncMaster P50HP	1204.6 x 724.1 x 97.1 mm ( 47.4 x 28.5 x 3.8 inch ) (Without Stand)
	1204.6 x 773.2 x 362.4 mm ( 47.4 x 30.4 x 14.3 inch ) (With Stand) / 33.7kg (74.3 lbs)

#### **VESA Mounting Interface**

600 x 400 mm

#### **Environmental considerations**

Operating	Temperature : 50°F ~ 104°F (10°C ~ 40°C)
	Humidity : 10 % ~ 80 %, non-condensing
Reliability - MTBF	More than 50,000 hours at 90% confidence level.
Storage	Temperature : -4°F ~ 113°F (-20°C ~ 45°C)
	Humidity : 5 % ~ 95 %, non-condensing

#### **Audio Characteristics**

Audio Input	RCA Jack Red(R) White(L), 0.5 Vrms (-9 dB)
Audio Output	RCA Jack Red(R) White(L), 0.5 Vrms (-9 dB)
PC Audio Input	3.5 øStereo Jack, 0.5 Vrms (-9 dB)
Frequency	RF: 80 Hz ~ 15 kHz (at -3 dB)
Response	AV: 80 Hz ~ 20 kHz (at -3 dB)

#### **Plug and Play Capability**

This PDP Display can be installed on any Plug & Play compatible system. The interaction of the PDP Display and the computer systems will provide the best operating conditions and PDP Display settings. In most cases, the PDP Display installation will proceed automatically, unless the user wishes to select alternate settings.

#### **Dot Acceptable**

PDP panels manufactured by using advanced semiconductor technology with precision of 1ppm (one millionth) above are used for this product. But the pixels of RED, GREEN, BLUE and WHITE color appear to be bright sometimes or some black pixels may be seen. This is not from bad quality and you can use it without any problems.

#### **Dot Acceptable**

For example, the number of PDP sub pixels contained in this product are 2,359,296 (P42HP).

For example, the number of PDP sub pixels contained in this product are 3,133,440 (P50HP).

## Ø Note

Design and specifications are subject to change without prior notice.

Class B Equipment (Information Communication equipment for residential use)

This product complies with the Electromagnetic Compatibility Directives for residential use and can be used in all areas including common residential areas. (Class B equipment emits less electromagnetic waves than Class A equipment.)

### **MagicInfo - Client**

### 🖉 Note

This is activated when a network box is installed.

lte	em	Specification	Remarks		
Contents	Photo	Supported File Format : BMP/JPEG	2274x1704 or less		
-	Music	Supported File Format : MP3	Sound bandwidth : 50 Hz to 15 kHz		
-	Movie	- MPEG1, WMV			
		- Max 1280 x 720 30 fps			
	File	MS Office(Word, Excel, Power Point), HTML, PDF	<ul> <li>Some files may not be supported depending on the format or the version.</li> <li>Install the proper viewing</li> </ul>		
			(freeware) program to see MS Office (Word, Excel, Power Point) or PDF docu- ments.		
Internet	Browser	MS Internet Explorer	Not Support Flash, Java Applet, Security Site		
Lang	uage	English			
0	S	Windows XP Embedded			

### **MagicInfo Pro - Server Requirement**

### Note 🖉

This is activated when a network box is installed.

	CPU	RAM	RAM Ethernet		Application		
Minimum	P1.8 GHz	256 M	100 M / 1 G	Windows XP	WMP later	9	or
	CPU	RAM	Ethernet	OS	Appli	cati	on
-------------	----------	---------	----------------	---------------	--------------	------	----
Recommended	P3.0 GHz	z 512 M	100 M / 1 G	Windows XP	WMP later	9	or

#### PowerSaver

This PDP Display has a built-in power management system called PowerSaver. This system saves energy by switching your PDP Display to low-power mode when it has not been used for a certain amount of time. The PDP Display automatically returns to normal operation when you press a key on the keyboard. For energy conservation, turn your PDP Display OFF when it is not needed, or when leaving it unattended for long periods. The PowerSaver system operates with a VESA DPM compliant video card installed in your computer. Use the software utility installed on your computer to set up this feature.

#### PowerSaver (When used as a Network PDP Display)

Sta	ate	Normal Oper- ation	Power saving mode	Power off
				EPA/ENERGY 2000
Power I	ndicator	Green	Green, Blink- ing	Red
Power Consump	- P42HP	380 W	Less than 5	Less than 5
tion	P50HP	470 W	watts	watts

#### PowerSaver (When used as a normal PDP Display)

State		Normal Oper- ation	Power saving mode	Power off	
				EPA/ENERGY 2000	
Power I	ndicator	Green	Green, Blink- ing	Red	
Power Consump	- P42HP	380 W	Less than 2	Less than 2	
tion	P50HP	470 W	watts	watts	

#### **Preset Timing Modes**

If the signal transferred from the computer is the same as the following Preset Timing Modes, the screen will be adjusted automatically. However, if the signal differs, the screen may go blank while the power LED is on. Refer to the video card manual and adjusts the screen as follows.

Display Mode	Horizontal Frequency (kHz)	Vertical Fre- quency (Hz)	Pixel Clock (MHz)	Sync Polarity (H/V)
IBM, 640 x 350	31.469	70.086	25.175	+/-
IBM, 640 x 480	31.469	59.940	25.175	-/-
IBM, 720 x 400	31.469	70.087	28.322	-/+
MAC, 640 x 480	35.000	66.667	30.240	-/-
MAC, 832 x 624	49.726	74.551	57.284	-/-
MAC, 1152 x 870	68.681	75.062	100.000	-/-

Display Mode	Horizontal Frequency (kHz)		Pixel Clock (MHz)	Sync Polarity (H/V)
VESA, 640 x 480	37.861	72.809	31.500	-/-
VESA, 640 x 480	37.500	75.000	31.500	-/-
VESA, 800 x 600	35.156	56.250	36.000	+/+
VESA, 800 x 600	37.879	60.317	40.000	+/+
VESA, 800 x 600	48.077	72.188	50.000	+/+
VESA, 800 x 600	46.875	75.000	49.500	+/+
VESA, 848 x 480	31.020	60.000	33.750	+/+
VESA, 1024 x 768	48.363	60.004	65.000	-/-
VESA, 1024 x 768	56.476	70.069	75.000	-/-
VESA, 1024 x 768	60.023	75.029	78.750	+/+
VESA, 1152 x 864	67.500	75.000	108.000	+/+
VESA, 1280 x 768	47.776	59.870	79.500	-/+
VESA, 1280 X 960	60.000	60.000	108.000	+/+
VESA, 1280 X 1024	63.981	60.020	108.000	+/+
VESA, 1280 X 1024	79.976	75.025	135.000	+/+
VESA, 1360 x 768	47.712	60.015	85.500	+/+
VESA, 1600 x 1200	75.000	60.000	162.000	+/+
VESA, 1920 x 1080	66.587	59.934	138.500	+/-

#### Horizontal Frequency



Vertical Frequency

Like a fluorescent lamp, the screen has to repeat the same image many times per second to display an image to the user. The frequency of this repetition is called the Vertical Frequency or Refresh Rate. Unit: Hz

The time to scan one line connecting the right edge



## Information

#### For Better Display

Adjust the computer resolution and screen injection rate (refresh rate) on the computer as described below to enjoy the best picture quality. You can have an uneven picture quality on screen if the best picture quality is not provided for PDP.

• Resolution: 1024 x 768 (P42HP)

Resolution: 1360 x 768 (P50HP)

• Vertical frequency (refresh rate): 60 Hz

PDP panels manufactured by using advanced semiconductor technology with a precision of 1ppm (one millionth) and above is used for this product. But the pixels of RED, GREEN, BLUE and WHITE color seem to be bright sometimes or some of black pixels could be seen. This is not from bad quality and you can use it without any problems.

 For example, the number of PDP sub pixels contained in this product are 2,359,296(P42HP) / 3,133,440(P50HP).

When cleaning the monitor and the panel outside, please apply the recommended small amount of cleaner by using a soft cloth to polish. Do not force the PDP area but rub softly. If excessive force is applied, you may stain it.

If you are not satisfied with the picture quality, you can get better quality of picture by performing the "Auto Adjustment function" in display screen that is appeared as window termination button is pressed. If there's still noise after the automatic adjustment, use the Fine/Coarse adjustment function.

When viewing a fixed screen for an extended period of time, a residual image or blurriness may appear. Change the mode to energy save or set a screensaver to move the picture when you need to be away from the monitor for an extended period of time.

#### **PRODUCT INFORMATION (Image Retention Free)**

#### What is Image Retention ?

Image retention may not occur when a PDP panel is operated under normal conditions.Normal conditions are defined as continuously changing video patterns. When the PDP panel is operated for a long time with a fixed pattern .

Phosphor degradation may occur and the brightness is decreased. To prevent this, the video pattern should be changed from time to time.

When viewing a still screen for a long time, the brightness of any part which was bright in the previous fixed pattern becomes lower than that of its surroundings.



Power Off, Screen Saver, or Power Save Mode

- Turn the power off for 4 hours after 20 hours in use
- Turn the power off for 2 hours after 12 hours in use
- Set the Monitor to power off with the PC Display Properties Power Scheme.
- Use a Screen saver if possible Screen saver in one color or a moving image is recommended.



#### Change the Color Information periodically

### Ø Note

Use Two different colors

Rotate the Color Information with 2 different colors every 30 minutes.

 Avoid using a combination of characters and background color with large difference in luminance.

Avoid using Grey colors, which can cause Image retention easily.

Avoid: Colors with big difference in luminance (Black & White, Grey)



Change the characters color periodically

- Use Bright colors with little difference in luminance.
  - Cycle : Change the characters color and background color every 30 minutes

FLIGHT : TIME	FLIGHT : TIME	FLIGHT : TIME	FLIGHT : TIME
OZ348 : 20:30	FLIGHT : TIME	OZ348 : 20:30	OZ348 : 20:30

• Every 30 minutes, change the characters with movement.

FLIGHT : TIME	-	AA1710 : 12:00 AA0025 : 12:35	1	FLIGHT : TIME
OZ348 : 20:30	-	UAUTTU - 13.30 KI 0125 - 13-50	l <b>† </b> →	OZ348 : 20:30
[ Step 1 ]	[ Step 2 ]			[ Step 3 ]

All area display Moving image together with Logo periodically.

- Cycle: Display moving image together with Logo for 60 seconds after 4 hours in use.

 The best way to protect your monitor from Image retention is to turn Power off, or set your PC, or System to operate a Screen Saver program when you are not using it. Also Warranty service will be limited based on instruction guide.

Apply the Screen Scroll function on Product

- Apply the Screen Scroll function
  - Symptom: Horizontal Bar with Black Color move up and down.

Horizontal Bar with Black color		
FLIGHT		ľ
OZ348	20:30	ł
UA102	21:10	

#### - Select method

- Instruction Guide : OSD Menu -> Set Up -> Safety Screen -> Screen Scroll
- Time Interval : 1 ~ 10 hours (Recommend : 1)
- Time Period : 1 ~ 5 second (Recommend : 5)

## 🖉 Note

( Please check CD's User Guide at "OSD Function", some model's will not available )

Apply the Screen Pixel function on Product

- Apply the Screen Pixel function
  - Symptom: Dot with Black Color move up and down.

FLIGHT	TIME
OZ348	20:30
UA102	21:10

#### - Select method

- Instruction Guide : OSD Menu -> Set Up -> Safety Screen -> Pixel
- Time Interval : 1 ~ 10 hours (Recommend : 1)
- Time Period : 10 ~ 50 second ( Recommend : 50 )
- Apply the Screen Bar function
  - Symptom: Horizontal / Vertical Bar with Black Color move up and down.



#### - Select method

- Instruction Guide : OSD Menu -> Set Up -> Safety Screen -> Bar
- Time Interval : 1 ~ 10 hours (Recommend : 1)
- Time Period : 10 ~ 50 second (Recommend : 50)

## 🖉 Note

(  $\ensuremath{\mathsf{Please}}$  check CD's User Guide at "OSD Function", some model's will not available. )

Apply the Screen Erasing function on Product

- Apply the Screen Erasing function
  - Symptom: 2 Vertical blocks move with erasing the display

GHT	TIME
OZ348	20:30
UA102	21:10

#### - Select method

• Instruction Guide : OSD Menu -> Set Up -> Safety Screen -> Eraser

- Time Interval : 1 ~ 10 hours (Recommend : 1)
- Time Period : 10 ~ 50 second ( Recommend : 50 )

# 🖉 Note

( Please check CD's User Guide at "OSD Function", some model's will not available )

# Appendix

#### Contact SAMSUNG WORLDWIDE

🖉 Note

If you have any questions or comments relating to Samsung products, please contact the SAMSUNG customer care center.

North America						
U.S.A	1-800-SAMSUNG(726-7864)	http://www.samsung.com/us				
CANADA	1-800-SAMSUNG(726-7864)	http://www.samsung.com/ca				
MEXICO	01-800-SAMSUNG (726-7864)	http://www.samsung.com/mx				
	Latin America					
ARGENTINE	0800-333-3733	http://www.samsung.com/ar				
BRAZIL	0800-124-421	http://www.samsung.com/br				
	4004-0000					
CHILE	800-SAMSUNG(726-7864)	http://www.samsung.com/cl				
COLOMBIA	01-8000112112	http://www.samsung.com/co				
COSTA RICA	0-800-507-7267	http://www.samsung.com/lat- in				
ECUADOR	1-800-10-7267	http://www.samsung.com/lat- in				
EL SALVADOR	800-6225	http://www.samsung.com/lat- in				
GUATEMALA	1-800-299-0013	http://www.samsung.com/lat- in				
HONDURAS	800-7919267	http://www.samsung.com/lat- in				
JAMAICA	1-800-234-7267	http://www.samsung.com/lat- in				
NICARAGUA	00-1800-5077267	http://www.samsung.com/lat- in				
PANAMA	800-7267	http://www.samsung.com/lat- in				
PUERTO RICO	1-800-682-3180	http://www.samsung.com/lat- in				
REP. DOMINICA	1-800-751-2676	http://www.samsung.com/lat- in				
TRINIDAD & TO- BAGO	1-800-SAMSUNG(726-7864)	http://www.samsung.com/lat- in				
VENEZUELA	0-800-100-5303	http://www.samsung.com/lat- in				

#### Europe

AUSTRIA

RIA 0810 - SAMSUNG (7267864, http://www.samsung.com/at € 0.07/min)

	Europe	
BELGIUM	02 201 2418	http://www.samsung.com/be
CZECH REPUBLIC	800 - SAMSUNG (800-726786)	http://www.samsung.com/cz
	Distributor pro Českou republiku: Samsung Zrt., česká organizační složka, Oasi	s Florenc, Sokolovská394/17, 180 00, Praha 8
DENMARK	8 - SAMSUNG (7267864)	http://www.samsung.com/dk
EIRE	0818 717 100	http://www.samsung.com/ie
FINLAND	30 - 6227 515	http://www.samsung.com/fi
FRANCE	3260 'dites' SAMSUNG (€ 0,15/Min)	http://www.samsung.com/fr
	0825 08 65 65 (€0.15/Min)	
GERMANY	01805 - SAMSUNG (7267864, € 0.14/Min)	http://www.samsung.de
HUNGARY	06-80-SAMSUNG (726-7864)	http://www.samsung.com/hu
ITALIA	800-SAMSUNG (726-7864)	http://www.samsung.com/it
LUXEMBURG	02 261 03 710	http://www.samsung.com/lu
NETHERLANDS	0900 - SAMSUNG (7267864, €0.10/Min)	http://www.samsung.com/nl
NORWAY	3 - SAMSUNG (7267864)	http://www.samsung.com/no
POLAND	0 - 801 - 1SAMSUNG (172678)	http://www.samsung.com/pl
	022 - 607 - 93 - 33	
PORTUGAL	808 20 - SAMSUNG (7267864)	http://www.samsung.com/pt
SLOVAKIA	0800-SAMSUNG (726-7864)	http://www.samsung.com/sk
SPAIN	902 - 1 - SAMSUNG(902 172 678)	http://www.samsung.com/es
SWEDEN	075 - SAMSUNG (726 78 64)	http://www.samsung.com/se
SWITZERLAND	0848 - SAMSUNG (7267864, CHF 0.08/min)	http://www.samsung.com/ch
U.K	0845 SAMSUNG (7267864)	http://www.samsung.com/uk
	CIS	
ESTONIA	800-7267	http://www.samsung.ee
LATVIA	8000-7267	http://www.samsung.com/lv
LITHUANIA	8-800-77777	http://www.samsung.lt
KAZAKHSTAN	8-10-800-500-55-500	http://www.samsung.com/ kz_ru
KYRGYZSTAN	00-800-500-55-500	
RUSSIA	8-800-555-55-55	http://www.samsung.ru
TADJIKISTAN	8-10-800-500-55-500	
	~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~	1 · · · · · · · · · · · · · · · · · · ·

UKRAINE

UZBEKISTAN

8-800-502-0000

8-10-800-500-55-500

http://www.samsung.ua

. kz\_ru

http://www.samsung.com/

#### Europe

Asia Facilic			
AUSTRALIA	1300 362 603	http://www.samsung.com/au	
CHINA	800-810-5858	http://www.samsung.com/cn	
	400-810-5858		
	010-6475 1880		
	HONG KONG:3698 - 4698	http://www.samsung.com/hk	
INDIA	3030 8282	http://www.samsung.com/in	
	1800 110011		
	1-800-3000-8282		
INDONESIA	0800-112-8888	http://www.samsung.com/id	
JAPAN	0120-327-527	http://www.samsung.com/jp	
MALAYSIA	1800-88-9999	http://www.samsung.com/my	
NEW ZEALAND	0800 SAMSUNG(0800 726 786)	http://www.samsung.com/nz	
PHILIPPINES	1800-10-SAMSUNG (726-7864)	http://www.samsung.com/ph	
SINGAPORE	1800-SAMSUNG(726-7864)	http://www.samsung.com/sg	
THAILAND	1800-29-3232	http://www.samsung.com/th	
	02-689-3232		
TAIWAN	0800-329-999	http://www.samsung.com/tw	
VIETNAM	1 800 588 889	http://www.samsung.com/vn	
Middle East & Africa			

# SOUTH AFRICA0860-SAMSUNG(726-7864)http://www.samsung.com/zaTURKEY444 77 11http://www.samsung.com/trU.A.E800-SAMSUNG(726-7864)http://www.samsung.com/ae8000-47268000-4726

#### Terms

Dot Pitch	The image on a monitor is composed of red, green and blue dots. The closer the dots, the higher the resolution. The dis- tance between two dots of the same color is called the 'Dot Pitch'. Unit: mm
Vertical Frequency	The screen must be redrawn several times per second in order to create and display an image for the user. The fre- quency of this repetition per second is called the Vertical Frequency or Refresh Rate. Unit: Hz
	Example: If the same light repeats itself 60 times per sec- ond, this is regarded as 60 Hz.
Horizontal Frequency	The time to scan one line connecting the right edge to the left edge of the screen horizontally is called the Horizontal Cycle. The inverse number of the Horizontal Cycle is called Horizontal Frequency. Unit: kHz

#### Asia Pacific

Interlace and Non-Interlace Methods	Showing the horizontal lines of the screen from the top to the bottom sequentially is called the Non-Interlace method while showing odd lines and then even lines in turn is called the Interlace method. The Non-Interlace method is used for the majority of monitors to ensure a clear image. The Inter- lace method is the same as that used in TVs.
Plug & Play	This is a function that provides the best quality screen for the user by allowing the computer and the monitor to ex- change information automatically. This monitor follows the international standard VESA DDC for the Plug & Play func- tion.
Resolution	The number of horizontal and vertical dots used to compose the screen image is called the 'resolution'. This number shows the accuracy of the display. A high resolution is good for performing multiple tasks as more image information can be shown on the screen.
	Example: If the resolution is 1024(1360) x 768(768), this means the screen is composed of 1024(1360) horizontal dots (horizontal resolution) and 768(768) vertical lines (vertical resolution).
SRS TS XT	This feature outputs sonorous and vivid 3D sound as for 5.1 channel speaker sound but through a 2-channel speaker. It has a good effect when stereo signals are input.

#### **Correct Disposal**

Correct Disposal of This Product (Waste Electrical & Electronic Equipment) - Europe only



(Applicable in the European Union and other European countries with separate collection systems)

This marking shown on the product or its literature, indicates that it should not be disposed with other household wastes at the end of its working life. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate this from other types of wastes and recycle it responsibly to promote the sustainable reuse of material resources.

Household users should contact either the retailer where they purchased this product, or their local government office, for details of where and how they can take this item for environmentally safe recycling.

Business users should contact their supplier and check the terms and conditions of the purchase contract. This product should not be mixed with other commercial wastes for disposal.

#### Authority

Information in this document is subject to change without notice.

© 2008 Samsung Electronics Co., Ltd. All rights reserved.

Reproduction in any manner whatsoever without the written permission of Samsung Electronics Co., Ltd. is strictly forbidden.

Samsung Electronics Co., Ltd. shall not be liable for errors contained herein or for incidental or consequential damages in connection with the furnishing, performance, or use of this material.

Samsung is the registered trademark of Samsung Electronics Co., Ltd.; Microsoft, Windows and Windows NT are registered trademarks of Microsoft Corporation; VESA, DPM and DDC are registered trademarks of Video Electronics Standard Association; the ENERGY STAR<sup>®</sup> name and logo are registered trademarks of the U.S. Environmental Protection Agency (EPA). All other product names mentioned herein may be the trademarks or registered trademarks of their respective owners.

 SRS(O)
 TruSurround XT, SRS and (•) Symbol are trademarks of SRS Labs, Inc.

 TruSurround XT technology is incorporated under license from SRS Labs, Inc.

CALIFORNIA USA ONLY (Applicable for networking models only.)

This Perchlorate warning applies only to primary CR( Manganese Dioxide ) Lithium coin cells in the product sold or distributed ONLY in California USA  $\,$ 

\*Perchloate Material - special handling may apply, See www.dtsc.ca.gov/hazardouswaste/perchlorate.\*