

# LINDY®

## CONNECTION PERFECTION

### 5.25" CD/DVD/BD Drive Enclosure

Installation Guide

Installationsanleitung

Manuel Utilisateur

Manuale d'uso

English

Deutsch

Français

Italiano

No. 42937 USB 2.0/eSATA/FW400

No. 43137 USB 3.0

[www.LINDY.com](http://www.LINDY.com)



For Home and Office Use  
Tested to Comply with FCC Standards

© LINDY ELECTRONICS LIMITED & LINDY-ELEKTRONIK GMBH - SECOND EDITION (NOVEMBER 2010)

#### Specification

- Internal Connection: SATA I/II Data & Power
- External Connections: eSATA I/II 3Gbps, FireWire 400 & USB 2.0 (42937); USB 3.0 (43137); Maximum drive depth: 20cm
- Aluminium housing and 40mm Fan for heat dissipation and cooling

#### Package Contents

- 5.25" CD/DVD/BD Drive Enclosure
- eSATA Cable & USB 2.0 A-B cable (42937)
- USB 3.0 A-B Cable (43137)
- External 100...240VAC PSU with country specific power cable
- Internal Power Adapter Cables SATA & IDE
- SATA to IDE/Atapi Adapter

#### Installation

##### English

1. Remove the two retaining screws to release the back plate.
2. Slide the top cover towards the back until it is free of the base.
3. Gently push the top corners of the front insert from inside the enclosure until the insert is removed.
4. Slide your CD/DVD/BD drive through the front of the enclosure and connect the SATA Data and Power cables to your drive. If using an IDE drive first install the SATA to IDE adapter and the corresponding internal adapter cables.
5. Position the drive as required and then fix the drive into position by applying screws through the enclosure's mounting slots into your drive.
6. Replace the cover, back plate and retaining screws.
7. Now connect the power supply, and connect the enclosure to your computer, using either an eSATA, FireWire or USB cable.

##### Deutsch

1. Entfernen Sie die beiden Schrauben und die Blende an der Rückseite.
2. Schieben Sie die obere Gehäusehälfte nach hinten hinunter.
3. Drücken Sie zum Einbau des CD/DVD/BD-Laufwerkes die vordere Innen-Blende von innen vorsichtig nach außen heraus
4. Schieben Sie das CD/DVD/BD-Laufwerk von vorne in die Blende hinein und schließen Sie das SATA Power und Datenkabel am

#### Certifications

##### FCC Certifications

This equipment has been tested and found to comply with the limits for a Class B Digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received; including interference that may cause undesired operation.

##### CE Statement

This equipment complies with the relevant EC Regulations for IT Equipment

#### Recycling Information



WEEE (Waste of Electrical and Electronic Equipment),  
Recycling of Electronic Products

In 2006 the European Union introduced regulations (WEEE) for the collection and recycling of all waste electrical and electronic equipment. The Wheelie bin symbol shown indicates that this product must not be disposed of with household waste. Instead the product must be recycled in a manner that is environmentally friendly. For more information on how to dispose of this product, please contact your local recycling centre or your household waste disposal service. Each individual EU member state has implemented the WEEE regulations into national law in slightly different ways. Please follow your national law when you want to dispose of any electrical or electronic products.

##### Germany / Deutschland

Die Europäische Union hat mit der WEEE Richtlinie umfassende Regelungen für die Verschrottung und das Recycling von Elektro- und Elektronikprodukten geschaffen. Das ElektroG – Elektro- und Elektronikgerätegesetz verbietet das Entsorgen von entsprechenden, auch alten, Elektro- und Elektronikgeräten über die Hausmülltonne! Diese Geräte müssen den lokalen Sammelsystemen bzw. örtlichen Sammelstellen zugeführt werden! Dort werden sie kostenlos entgegen genommen. Die Kosten für den weiteren Recyclingprozess übernehmen die Gerätehersteller.

Laufwerk an. Wenn Sie ein IDE/Atapi-Laufwerk verwenden, montieren Sie den SATA/IDE-Adapter und verwenden die entsprechenden internen Adapterkabel.

5. Positionieren Sie das Laufwerk im Gehäuse und schrauben Sie es mit den beiliegenden Schrauben seitlich fest.
6. Schieben Sie die obere Gehäusehälfte von hinten wieder auf und schrauben Sie die hintere Blenden mit den beiden Schrauben fest
7. Schließen Sie nun das Netzteil an. Die Verbindung zum Computer sollte immer nur mit einem Kabel erfolgen, entweder USB, eSATA oder FireWire!

##### Français

1. Retirez les deux vis de maintien, pour détacher le plateau arrière.
2. Glissez le couvercle du boîtier vers le fond.
3. Poussez avec précaution les coins de la façade vers l'intérieur du boîtier jusqu'à ce que l'ergot soit retiré.
4. Glissez votre lecteur CD/DVD par la façade du boîtier et connectez y les câbles d'alim et de données SATA. Si vous utilisez un lecteur IDE, installez d'abord un adaptateur SATA vers IDE et les câbles d'alimentation correspondants.
5. Positionnez le lecteur et fixez le avec les vis.
6. Remplacez le couvercle et le plateau arrière, et remettez les 2 vis.
7. A présent, connectez l'alimentation puis le boîtier à votre ordinateur, avec un câble eSATA, FireWire ou USB.

##### Italiano

1. Rimuovere le due viti di fissaggio della staffa posteriore
2. Far scorrere la copertura superiore dal retro
3. Spingere con cautela gli angoli del frontalino verso l'interno dell'alloggiamento fino a quando il perno viene rimosso
4. Far scorrere il drive CD/DVD/BD e collegare i cavi SATA dati e alimentazione. Se utilizzate un drive IDE, installate prima l'adattatore SATA a IDE e il cavo di alimentazione interno corrispondente.
5. Posizionare il drive e fissarlo con le relative viti nello slot all'interno dell'alloggiamento
6. Montare di nuovo le varie parti dell'alloggiamento con le relative viti.
7. Collegare l'alimentazione e collegare l'alloggiamento al computer tramite cavo eSATA, FireWire o USB.

LINDY No.42937, 43137



For Home and Office Use  
Tested to Comply with FCC Standards

[www.lindy.com](http://www.lindy.com)