

PCI-7020

PCI Half-sized Intel® LGA775
Processor Card with VGA/Single
Gigabit LAN

Trusted ePlatform Services

ADVANTECH

Copyright

The documentation and the software included with this product are copyright 2009 by Advantech Co., Ltd. All rights are reserved. Advantech Co., Ltd. reserves the right to make improvements in the products described in this manual at any time without notice. No part of this manual may be reproduced, copied, translated or transmitted in any form or by any means without the prior written permission of Advantech Co., Ltd. Information provided in this manual is intended to be accurate and reliable. However, Advantech Co., Ltd. assumes no responsibility for its use, nor for any infringements of the rights of third parties, which may result from its use.

Acknowledgements

AWARD is a trademark of Phoenix Technologies Ltd.

IBM and PC are trademarks of International Business Machines Corporation.

Intel[®], Core[™] 2 Duo, Pentium[®] D, Pentium[®] 4, and Celeron[®] D are trademarks of Intel Corporation.

WinBond is a trademark of Winbond Corporation.

All other product names or trademarks are the properties of their respective owners.

A Message to the Customer

Advantech Customer Services

Each and every Advantech product is built to the most exacting specifications to ensure reliable performance in the harsh and demanding conditions typical of industrial environments. Whether your new Advantech equipment is destined for the laboratory or the factory floor, you can be assured that your product will provide the reliability and ease of operation for which the name Advantech has come to be known.

Your satisfaction is our primary concern. Here is a guide to Advantech's customer services. To ensure you get the full benefit of our services, please follow the instructions below carefully.

Technical Support

We want you to get the maximum performance from your products. So if you run into technical difficulties, we are here to help. For the most frequently asked questions, you can easily find answers in your product documentation. These answers are normally a lot more detailed than the ones we can give over the phone.

So please consult this manual first. If you still cannot find the answer, gather all the information or questions that apply to your problem, and with the product close at hand, call your dealer. Our dealers are well trained and ready to give you the support you need to get the most from your Advantech products. In fact, most problems reported are minor and are able to be easily solved over the phone.

In addition, free technical support is available from Advantech engineers every business day. We are always ready to give advice on application requirements or specific information on the installation and operation of any of our products.

Declaration of Conformity

FCC Class A

Note: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

Caution! *There is a danger of a new battery exploding if it is incorrectly installed. Do not attempt to recharge, force open, or heat the battery. Replace the battery only with the same or equivalent type recommended by the manufacturer. Discard used batteries according to the manufacturer's instructions.*



Memory Compatibility

Brand	Size	Speed	Type	Memory
Apacer(RoHS)	512 MB	DDR2 533	DDR2	ELPIDA E5108AG-5C-E (64x8)
	512 MB	DDR2 667	DDR2	ELPIDA E5108AG-6E-E (64x8)
	1 GB	DDR2 533	DDR2	SAMSUNG K4T51083QB-ZKD5 (128x4)
	1 GB	DDR2 533	DDR2	ELPIDA E5108AGBG-6E-E (64x8)
	1 GB	DDR2 667	DDR2	ELPIDA E5108AGBG-6E-E (64x8)
	2 GB	DDR2 667	DDR2	SEC K4T1G08400 (128x8)
DSL	512 MB	DDR2 533	DDR2	infineon HYB18T512 800AF37 FSS43331 (64x8)
	1 GB	DDR2 533	DDR2	ELPIDA E5108AE-5C-E (64x8)
	1 GB	DDR2 667	DDR2	ELPIDA E5108AGBG-6E-E (64x8)
	2 GB	DDR2 667	DDR2	ELPIDA E1108ACSE-6E-E(128x8)
Kingston(RoHS)	2 GB	DDR2 667	DDR2	Micron 7KE12 D9HNL (128x8)
Transcend(RoHS)	256 MB	DDR2 533	DDR2	infineon HYB18T512160AF3.7 3VV21710 (32x16)
	256 MB	DDR2 533	DDR2	SAMSUNG 443 K4T56083QF-GCD5 (32x8)
	512 MB	DDR2 533	DDR2	SEC K4T51083QC ZCD5 (64X8)
	512 MB	DDR2 667	DDR2	SAMSUNG K4T51083QC ZCE6 (64x8)
	1 GB	DDR2 667	DDR2	SEC K4T51083QE ZCE6 (64x8)
	1 GB	DDR2 667	DDR2	SEC K4T51083QG HCE6 (64x8)
	2 GB	DDR2 667	DDR2	SAMSUNG K4T1G084QD-ZCE6 (128x8)
	2 GB	DDR2 667	DDR2	Micron 7HE12 D9HNL (128x8)
	2 GB	DDR2 667	DDR2	SAMSUNG K4T1G084QA-ZCE6 (128x8)

Network Feature Comparison

LAN/Model	PCI-7020F	PCI-7020VG	PCI-7020LV
LAN1: Intel® 82574L	Yes	Yes	No

Processor Support

Intel Core™ 2 Duo Desktop Processor	Long-term supported P/N: E7400, E6400, E4300, E2160, Celeron 440
Intel® Pentium® Dual-Core Desktop Processor	
Intel Celeron® Processor 400	
<hr/>	
Intel Pentium D Processor	
Intel Pentium 4 Processor	
Intel Celeron D Processor	

Note! *PCI-7020 CPU cooler (p/n:1960035861N000), It must use the CPU thermal design power lower than 65 Watt.*



Product Warranty (2 years)

Advantech warrants to you, the original purchaser, that each of its products will be free from defects in materials and workmanship for two years from the date of purchase.

This warranty does not apply to any products which have been repaired or altered by persons other than repair personnel authorized by Advantech, or which have been subject to misuse, abuse, accident or improper installation. Advantech assumes no liability under the terms of this warranty as a consequence of such events.

Because of Advantech's high quality-control standards and rigorous testing, most of our customers never need to use our repair service. If an Advantech product is defective, it will be repaired or replaced at no charge during the warranty period. For out-of-warranty repairs, you will be billed according to the cost of replacement materials, service time and freight. Please consult your dealer for more details.

If you think you have a defective product, follow these steps:

1. Collect all the information about the problem encountered. (For example, CPU speed, Advantech products used, other hardware and software used, etc.) Note anything abnormal and list any onscreen messages you get when the problem occurs.
2. Call your dealer and describe the problem. Please have your manual, product, and any helpful information readily available.
3. If your product is diagnosed as defective, obtain an RMA (return merchandise authorization) number from your dealer. This allows us to process your return more quickly.
4. Carefully pack the defective product, a fully-completed Repair and Replacement Order Card and a photocopy proof of purchase date (such as your sales receipt) in a shippable container. A product returned without proof of the purchase date is not eligible for warranty service.
5. Write the RMA number visibly on the outside of the package and ship it prepaid to your dealer.

Initial Inspection

Before you begin installing your single board computer, please make sure that the following materials have been shipped:

- PCI-7020 Intel® LGA775 processor-based single board computer
- 1 PCI-7020 user manual
- 1 CD with driver utility and manual (in PDF format)
- 2 Power cable 12P / Big 4P P/N: 1700006196
- 1 Dual COM cable 2.0 mm pitch P/N: 1700008762
- 1 Serial ATA HDD data cable P/N: 1700003194
- 1 Serial ATA HDD power cable P/N: 1703150102
- 1 Printer port cable 2.0 mm pitch P/N: 1700002223
- 1 Y cable for PS/2 keyboard and PS/2 mouse P/N: 1700060202
- 1 USB cable with 4 ports P/N: 1700014398
- ATX feature cable P/N: 1700002343
- 1 Jumper pack P/N: 9689000002
- CPU cooler P/N: 1960035861N000
- 1 warranty card

If any of these items are missing or damaged, contact your distributor or sales representative immediately. We have carefully inspected the PCI-7020 mechanically and electrically before shipment. It should be free of marks and scratches and in perfect working order upon receipt. As you unpack the PCI-7020, check it for signs of shipping damage. (For example, damaged box, scratches, dents, etc.) If it is damaged or it fails to meet the specifications, notify our service department or your local sales representative immediately. Also notify the carrier. Retain the shipping carton and packing material for inspection by the carrier. After inspection, we will make arrangements to repair or replace the unit.

Note! PCI-7020 CPU cooler (p/n:1960035861N000), It must use the CPU thermal design power lower than 65 Watt.



Contents

Chapter 1 Hardware Configuration.....1

1.1	Introduction	2
1.2	Features	2
1.3	Specifications	3
1.3.1	System	3
1.3.2	Memory	3
1.3.3	Input/Output	3
1.3.4	Ethernet LAN	3
1.3.5	Industrial Features	3
1.3.6	Mechanical and Environmental Specifications.....	3
1.4	Jumpers and Connectors	4
	Table 1.1: Jumpers.....	4
	Table 1.2: Connectors	4
1.5	Board Layout: Jumper and Connector	5
	Figure 1.1 Jumper and connector location (top)	5
	Figure 1.2 Jumper and connector location (bot)	5
1.6	PCI-7020 Block Diagram.....	6
	Figure 1.3 PCI-7020 block diagram	6
1.7	Safety Precautions	7
1.8	Jumper Settings	7
1.8.1	How to Set Jumpers.....	7
1.8.2	CMOS Clear (CMOS1)	7
	Table 1.3: CMOS (CMOS1).....	8
1.8.3	Watchdog Timer Output (JWDT1)	8
	Table 1.4: Watchdog Timer Output (JWDT1)	8
1.9	System Memory	8
1.9.1	CPU FSB and Memory Speed	8
1.10	Memory Installation Procedures.....	8
1.11	Cache Memory	9
1.12	Processor Installation	9
1.13	Power Model Setting and Installation.....	10
	Figure 1.4 ATX power setting of PCI-7020 with backplane	10
	Figure 1.5 ATX power setting of PCI-7020 with single board	10
	Figure 1.6 AT power setting of PCI-7020 with backplane.....	11
	Figure 1.7 AT power setting of PCI-7020 with single board	11

Chapter 2 Connecting Peripherals13

2.1	Introduction	14
2.2	Parallel Port (LPT1).....	14
2.3	VGA Connector (VGA1)	15
2.4	Serial Ports (COM1, COM2)	15
2.5	PS/2 Keyboard and Mouse Connector (KBMS1)	16
2.6	External Keyboard & Mouse (KBMS2).....	16
2.7	CPU Fan Connector (CPUFAN1).....	17
2.8	Front Panel Connectors (JFP1, JFP2).....	17
2.9	H/W Monitor Alarm (JOBS1)	18
	Table 2.1: Hardware Monitor Alarm Setting	18
2.10	LAN RJ45 Connector (LAN1).....	18
2.11	HD Link Connector (HDAUD1).....	19
2.12	Serial ATA2 Interface (SATA1 ~ SATA3).....	19
2.13	LAN LED Connector (LAN LED1)	20
	Table 2.2: Front Panel LAN Indicator Connector.....	20
2.14	USB (USB12, USB34, USB56)	21

2.15	Case Open (JCASE1)	21
Chapter 3	Award BIOS Setup	23
3.1	Introduction	24
3.1.1	CMOS RAM Auto-backup and Restore	24
3.2	Entering Setup	24
	Figure 3.1 Award BIOS setup initial screen	24
3.3	Standard CMOS Setup	25
	Figure 3.2 Standard CMOS features screen	25
3.4	Advanced BIOS Features	26
	Figure 3.3 Advanced BIOS features screen	26
3.5	Advanced Chipset Features.....	28
	Figure 3.4 Advanced chipset features screen	28
3.6	Integrated Peripherals.....	30
	Figure 3.5 Integrated peripherals	30
	Figure 3.6 On-Chip IDE device.....	30
	Figure 3.7 Onboard device	31
	Figure 3.8 Super I/O device.....	32
3.7	Power Management Setup	34
	Figure 3.9 Power management setup screen.....	34
	Figure 3.10 Power management setup screen (Conn.).....	34
	Table 3.1: Power Saving	35
3.8	PnP/PCI Configurations	36
	Figure 3.11 PnP/PCI configurations screen	36
3.9	PC Health Status	37
	Figure 3.12 PC health status screen	37
3.10	Frequency / Voltage Control	38
	Figure 3.13 Spread spectrum control screen	38
3.11	Password Setting	39
	Figure 3.14 Enter password	39
3.12	Load Setup Defaults	40
	Figure 3.15 Load setup defaults screen	40
3.13	Save & Exit Setup	41
	Figure 3.16 Save to CMOS and Exit	41
3.14	Exit Without Saving.....	42
	Figure 3.17 Quit Without Saving.....	42
Chapter 4	Chipset Software Installation Utility	43
4.1	Before You Begin	44
4.2	Introduction	44
4.3	Windows XP Driver Setup.....	45
Chapter 5	VGA Setup	49
5.1	Introduction	50
5.2	Windows XP Driver Setup.....	50
Chapter 6	LAN Configuration	55
6.1	Introduction	56
6.2	Features.....	56
6.3	Installation	56
6.4	Win XP Driver Setup	57

Appendix A Programming the Watchdog Timer..59

A.1	Programming the Watchdog Timer	60
A.1.1	Watchdog timer overview.....	60
A.1.2	Jumper selection.....	60
A.1.3	Programming the Watchdog Timer	60
	Table A.1: Watchdog Timer Registers	62
A.1.4	Example Program	63

Appendix B I/O Pin Assignments.....67

B.1	Front Panel Connectors (JFP1)	68
	Table B.1: Front Panel Connectors (JFP1).....	68
B.2	USB Ports (USB12/USB34)	68
	Table B.2: USB Ports (USB12/USB34).....	68
B.3	IR Connector (JIR1)	69
	Table B.3: IR Connector (JIR1).....	69
B.4	Serial Ports (COM12).....	69
	Table B.4: Serial Ports (COM12)	69
B.5	PS/2 Keyboard / Mouse Connector (KBMS2)	70
	Table B.5: PS/2 Keyboard / Mouse Connector (KBMS2)	70
B.6	LAN LED Connector (LANLED1)	70
	Table B.6: LAN LED Connector (LANLED1/LANLED2).....	70
B.7	ATX Feature Connector (ATXF1).....	70
	Table B.7: ATX Feature Connector (ATXF1)	70
B.8	CPU FAN Connector (CPUFAN1).....	71
	Table B.8: CPU FAN Connector (CPUFAN1)	71
B.9	System FAN Connector (SYSFAN1).....	71
	Table B.9: System FAN Cconnector (SYSFAN1)	71
B.10	Audio Interface Connector (HDAUD1)	71
	Table B.10:Audio Interface Connector (HDAUD1).....	71
B.11	GPIO Header (GPIO1)	72
	Table B.11:GPIO Header (GPIO1)	72
B.12	DVI LCD Panel Connector (DVI1).....	72
	Table B.12:DVI LCD Panel Connector (DVI1)	72
B.13	Low Pin Count Header (LPC1).....	73
	Table B.13:Low Pin Count Header (LPC1)	73
B.14	ATX Power Control Connector (ATX1)	73
	Table B.14:ATX Power Control Connector (ATX1).....	73
B.15	VGA Connector (VGA1)	74
	Table B.15:VGA Connector (VGA1)	74
B.16	H/W Monitor Alarm (JOBS1)	74
	Table B.16:H/W Monitor Alarm (JOBS1)	74
B.17	Watchdog Timer Output (JWDT1).....	74
	Table B.17: Watchdog Timer Output (JWDT1)	74

Appendix C System Assignments77

C.1	System I/O Ports	78
	Table C.1: System I/O Ports	78
C.2	DMA Channel Assignments	79
	Table C.2: DMA Channel Assignments.....	79
C.3	Interrupt Assignments	79
	Table C.3: Interrupt Assignments.....	79
C.4	1st MB Memory Map	79
	Table C.4: 1st MB Memory Map	79

Chapter 1

Hardware Configuration

1.1 Introduction

The PCI-7020 is a half-size CPU card designed with the Intel® 945GC and ICH7R chipset (I/O controller) to support Core® 2 Duo / Dual-Core Pentium® / Pentium® 4 / Celeron® D processors (refer to "Processor Support" on page v) with a 533/800/1066 MHz front side bus and DDR2 533/667 MHz memory up to 4 GB. It is the best solution for high-performance computing and applications in which a wide I/O bandwidth is demanded.

The PCI-7020 offers a high-performance cost-saving integrated graphics unit, built into the Intel® 945GC chipset, and features the unique Intel® Extreme Graphics architecture to maximize VGA performance and share system memory up to 224 MB. It has 2 SODIMM sockets in two separated memory channels. It accepts up to 4 GB DDR2 SDRAM memory, enough for most applications. The PCI-7020 has a single Gigabit Ethernet LAN via dedicated PCI Express x 1 bus, which offers bandwidths up to 500 MB/s, eliminating network data flow bottlenecks, and incorporating Gigabit Ethernet. High reliability and outstanding performance make the PCI-7020 the ideal platform for industrial networking applications.

Three Serial ATA2 ports (up to 300 MB/s) allow the use of thin and long SATA cables for storage devices, eliminating cabling issues inside the industrial-grade chassis. In addition, the PCI-7020 also provides most of the popular I/O interfaces such as six USB 2.0 ports, 2 RS-232 ports and enhanced parallel port interface.

The PCI-7020 is designed with consideration for extended reliability, and is built especially to suit demanding industrial environments. The CMOS data backup and restore function protects the BIOS setup data from loss due to battery failure.

1.2 Features

- Supports LGA 775 Intel® Core® 2 Duo / Pentium® Dual-Core / Pentium® D / Pentium® 4 / Celeron® 400 / Celeron® D FSB 533/800/1066 MHz processors (refer to "Processor Support" on page v)
- Supports Dual Channel DDR2 533/667 SDRAM up to 4 GB
- Single Gigabit Ethernet via PCI Express x1 port
- 3 SATA2 connector; supports S/W RAID 0, 1 (LV sku has NO S/W RAID)
- 6 USB 2.0 ports
- 6 COM port supports (2 ports RS-232, and can add optional 4 port RS-232/422/485 by PCA-COM232 or PCA-COM485 module)
- CMOS automatic backup and restore to prevent accidental data loss of BIOS setup

1.3 Specifications

1.3.1 System

- **CPU:** Intel® LGA 775 Core® 2 Duo, Pentium Dual-Core, Pentium 4, Celeron D up to 2.93/2.7/3.4/3.6 GHz, (refer to "Processor Support" on page v), FSB 533/800/1066 MHz.
- **L2 cache:** CPU has built-in 4 MB (for Core® 2 Duo), 2 MB (for Pentium Dual-Core CPU), 2 MB (for Pentium 4 CPU), 512 KB (for Celeron D CPU) full-speed L2 cache
- **BIOS:** Award Flash BIOS (8 MB Flash Memory)
- **System chipset:** Intel 945GC with ICH7R/ICH7
- **SATA hard disk drive interface:** Three on-board SATA2 connectors with data transmission rate up to 300 MB/s; supports S/W RAID 0, 1 (LV sku has NO S/W RAID)

1.3.2 Memory

- **RAM:** Up to 4 GB in two 200-pin SODIMM sockets. Supports dual-channel DDRII 533/667 SDRAM.

1.3.3 Input/Output

- **PCI bus:** 32 bit / 33MHz to the backplane
- **Parallel port:** One EPP/ECP parallel port
- **Serial ports:** Two serial RS-232 ports (and can add optional 4 port RS-232/422/485 by PCA-COM232 or PCA-COM485 module)
- **Keyboard and PS/2 mouse connector:** One 6-pin mini-DIN connector is located on the mounting bracket for easy connection to a keyboard or PS/2 mouse. An on board keyboard pin header connector is also available
- **USB port:** Supports up to six USB 2.0 ports with transmission rate up to 480 Mbps (2 ports on rear I/O, 4 ports onboard by 2.0 mm pitch box header)

1.3.4 Ethernet LAN

- Supporting single 10/100/1000Base-T Ethernet port(s) via PCI Express x1 bus which provides 500 MB/s data transmission rate
- **Controller:**
 - LAN 1: Intel® 82574L

1.3.5 Industrial Features

Watchdog timer: Can generate a system reset. The watchdog timer is pro-gramma-ble to 255 levels, with each unit set to equal either one second or one minute.

1.3.6 Mechanical and Environmental Specifications

- **Operating temperature:** 0 ~ 60° C (32 ~ 140° F, depending on CPU)
- **Operating humidity:** 40° C @ 85% RH Non-Condensing
- **Storage temperature:** -40 ~ 85° C (-40 ~ 185° F) non-condensing
- **Power supply voltage:** +5 V, +12 V, +5 VSBY
- **Power consumption:** +5 V @ 4.86 A, +12 V @ 4.38 A, +5 VSB @ 0.39 A (Intel Core 2 Duo 2.8 GHz, 65 W, 800 MHz FSB + 2 x 2 GB DDR2 667)
- **Board size:** 185 x 122 mm (7.28" x 4.8")
- **Board weight:** 0.185 kg (0.4 lbs.)

1.4 Jumpers and Connectors

Connectors on the PCI-7020 single board computer link to external devices such as hard disk drives and a keyboard. In addition, the board has a number of jumpers used to configure the system for any desired application.

The tables below list the function of each of the board jumpers and connectors. Later sections in this chapter give instructions on setting jumpers. Chapter 2 gives instructions for connecting external devices to the motherboard.

Table 1.1: Jumpers

Label	Function
CMOS1	CMOS clear
JWDT1	Watchdog timer output selection

Table 1.2: Connectors

Label	Function
LPT1	Parallel port
VGA1	VGA connector
CF1	CF socket
COM12	RS232 serial ports connector
KBMS1	PS/2 keyboard and mouse connector
KBMS2	External keyboard/mouse connector
JIR1	Infrared connector
JOBS1	HW Monitor Alarm Close: Enable OBS Alarm Open: Disable OBS Alarm
CPUFAN1	CPU FAN connector
JFP1	Power and Reset Button connector
JFP2	HDD LED/Speaker connector
LAN1	LAN RJ45 connector
LANLED1	LAN1 LED connector
HDAUD1	HD Audio connector
SATA1	Serial ATA1
SATA2	Serial ATA2
SATA3	Serial ATA3
USB12	Two USB port pin headers
USB34	Two USB port pin headers
USB5	USB connector
USB6	USB connector
DIMMA1	Memory connector channel A
DIMMB1	Memory connector channel B
LPC1	Low pin count connector
SPI1	BIOS SPI Interface
JCASE1	Case open
DVI1	DVI connector (only for F sku)

1.5 Board Layout: Jumper and Connector




Figure 1.1 Jumper and connector location (top)




Figure 1.2 Jumper and connector location (bot)

1.6 PCI-7020 Block Diagram




Figure 1.3 PCI-7020 block diagram

1.7 Safety Precautions

Warning! *Always completely disconnect the power cord from your chassis whenever you work with the hardware. Do not make connections while the power is on. Sensitive electronic components can be damaged by sudden power surges. Only experienced electronics personnel should open the PC chassis.*



Caution! *Always ground yourself to remove any static charge before touching the boards. Modern electronic devices are very sensitive to static electric charges. As a safety precaution, use a grounding wrist strap at all times. Place all electronic components on a static-dissipative surface or in a static-shielded bag when they are not in the chassis.*



Caution! *The computer is provided with a battery-powered real-time clock circuit. There is a danger of explosion if battery is incorrectly replaced. Replace only with same or equivalent type recommended by the manufacturer. Discard used batteries according to manufacturer's instructions.*



Caution! *There is a danger of a new battery exploding if it is incorrectly installed. Do not attempt to recharge, force open, or heat the battery. Replace the battery only with the same or equivalent type recommended by the manufacturer. Discard used batteries according to the manufacturer's instructions.*



1.8 Jumper Settings

This section provides instructions on how to configure your PCI-7020 by setting the jumpers. It also includes the PCI-7020's default settings and your options for each jumper.



1.8.1 How to Set Jumpers

You can configure your PCI-7020 to match the needs of your application by setting the jumpers. A jumper is a metal bridge that closes an electrical circuit. It consists of two metal pins and a small metal clip (often protected by a plastic cover) that slides over the pins to connect them. To "close" (or turn ON) a jumper, you connect the pins with the clip. To "open" (or turn OFF) a jumper, you remove the clip. Sometimes a jumper consists of a set of three pins, labeled 1, 2, and 3. In this case you connect either pins 1 and 2, or 2 and 3. A pair of needle-nose pliers may be useful when setting jumpers.

1.8.2 CMOS Clear (CMOS1)

The PCI-7020 single board computer contains a jumper that can erase CMOS data and reset the system BIOS information. Normally this jumper should be set with pins 1-2 closed. If you want to reset the CMOS data, set CMOS1 to 2-3 closed for just a few seconds, and then move the jumper back to 1-2 closed. This procedure will reset the CMOS to its default setting.



Table 1.3: CMOS (CMOS1)

Function	Jumper Setting
Keep CMOS data *	<div>1</div>  <div>1-2 closed</div>
Clear CMOS data	<div>1</div>  <div>2-3 closed</div>
*default setting	

1.8.3 Watchdog Timer Output (JWDT1)

The PCI-7020 contains a watchdog timer that will reset the CPU in the event the CPU stops processing. This feature means the PCI-7020 will recover from a software failure or an EMI problem. The JWDT1 jumper settings control the outcome of what the computer will do in the event the watchdog timer is tripped.

Table 1.4: Watchdog Timer Output (JWDT1)

Function	Jumper Setting
NC	<div>1</div>  <div>1-2 closed</div>
Reset*	<div>1</div>  <div>2-3 closed</div>
*default setting	

1.9 System Memory

The PCI-7020 has two sockets for 200-pin dual inline memory modules (SODIMMs) in two memory channels. All these sockets use 1.8 V unbuffered double data rate synchronous DRAMs (DDR2 SDRAM). They are available in capacities of 256, 512, 1024 and 2048 MB. The sockets can be filled in any combination with DIMMs of any size, giving a total memory size between 256 MB and 4 GB.

1.9.1 CPU FSB and Memory Speed

The PCI-7020 supports Intel LGA775 CPUs with FSB 533/800/1066. The PCI-7020 can accept DDR2 SDRAM memory chips without parity. Also note: The PCI-7020 accepts DDR2 533/667MHz SDRAM. The PCI-7020 does NOT support ECC (error checking and correction).

1.10 Memory Installation Procedures

To install DIMMs, slowly slide the DIMM module along the plastic guides on both ends of the socket. Then press the DIMM module right down into the socket, until you hear a click. This is when the two handles have automatically locked the memory module into the correct position of the DIMM socket.


1.11 Cache Memory

PCI-7020 supports built-in 4 MB CPU cache (for Core® 2 Duo), 2 MB (for Pentium Dual-Core CPU), 2 MB (for Pentium 4 CPU), 512 KB (for Celeron D) L2 cache. The built-in second-level cache in the processor yields much higher performance than conventional external cache memories.


1.12 Processor Installation

PCI-7020 is designed for Intel® LGA 775 socket CPUs.

Step 1. Pull the bar beside the CPU socket outward and lift it.



2. Align the triangular marking on the processor with the cut edge of the socket.



Step 3. Put back the socket cap and press down the bar to fix it.



1.13 Power Model Setting and Installation

PCI-7020 can support AT or ATX power model settings. It can be used with backplanes and single boards.

Installation as below.

ATX Power Supply	
With backplane	Please refer to Figure 1.4
	1. Use 3 pin ATX signal cable (P/N:1700002343) to connect the ATXF1 on the CPU card with PS-ON (CN1) on the backplane.
	2. Use power cable (P/N:1700006196) to connect power supply with ATX1 connector on the CPU card.
	3. Connect the power supply and ATX1 connector on the backplane.
Single board	Please refer to Figure 1.5
	1. Remove the jumper on CPU card ATXF1 1-2 pins.
	2. Use power cable (P/N:1700000265) to connect the power supply with the ATX1 connector on the CPU card.




Figure 1.4 ATX power setting of PCI-7020 with backplane




Figure 1.5 ATX power setting of PCI-7020 with single board

AT Power Supply	
With backplane	Please refer to Figure 1.6
	1. Short ATXF1 1-2 pins on CPU card and PS-ON(CN1) 1-2 pins on backplane.
	2. Use power cable (P/N:1700006196) to connect the power supply with ATX1 connector on CPU card.
	3. Connect the power supply and the ATX1 connector on the backplane.
Single board	Please refer to Figure 1.7
	1. Short ATXF1 1-2 pins on CPU card.
	2. Use the power cable (P/N:1700006196) to connect the power supply with the ATX1 connector on the CPU card.




Figure 1.6 AT power setting of PCI-7020 with backplane




Figure 1.7 AT power setting of PCI-7020 with single board


Chapter 2

Connecting
Peripherals

2.1 Introduction

You can access most of the connectors from the top of the board while it is installed in the chassis. If you have a number of cards installed or have a packed chassis, you may need to partially remove the card to make all the connections.


2.2 Parallel Port (LPT1)



The parallel port is normally used to connect the single board computer to a printer. The PCI-7020 includes an onboard parallel port, accessed through a 26-pin flat-cable connector, LPT1. The card comes with an adapter cable which lets you use a traditional DB-25 connector. The cable has a 26-pin connector on one end and a DB-25 connector on the other, mounted on a retaining bracket. The bracket installs at the end of an empty slot in your chassis, giving you access to the connector.


To install the bracket, find an empty slot in your chassis. Unscrew the plate that covers the end of the slot. Screw in the bracket in place of the plate. Next, attach the flat-cable connector to LPT1 on the CPU card. Wire 1 of the cable is red or blue, and the other wires are gray. Make sure that wire 1 corresponds to pin 1 of LPT1. Pin 1 is on the upper right side of LPT1.

2.3 VGA Connector (VGA1)



The PCI-7020 includes a VGA interface that can drive conventional CRT displays. VGA1 is a standard 15-pin D-SUB connector commonly used for VGA. Pin assignments for CRT connector VGA1 are detailed in Appendix B.


2.4 Serial Ports (COM1, COM2)



The PCI-7020 offers two serial ports COM1, COM2. These ports can connect to serial devices, such as a mouse or to a communications network.


The IRQ and address ranges for all ports are fixed. However, if you want to disable the port or change these parameters later, you can do this in the system BIOS setup. Different devices implement the RS-232 standard in different ways. If you are having problems with a serial device, be sure to check the pin assignments for the connector.

2.5 PS/2 Keyboard and Mouse Connector (KBMS1)




One 6-pin mini-DIN connectors (KBMS1) on the card mounting bracket provide connection to a PS/2 keyboard or a PS/2 mouse, respectively. KBMS1 can also be connected to an adapter cable (P/N: 1700060202) for connecting to both a PS/2 keyboard and a PS/2 mouse.

2.6 External Keyboard & Mouse (KBMS2)




In addition to the PS/2 mouse/keyboard connector on the PCI-7020's rear plate, there is also an extra onboard external keyboard and mouse connector. This gives system integrators greater flexibility in designing their systems.

2.7 CPU Fan Connector (CPUFAN1)




If a fan is used, this connector supports cooling fans of 12 V/1 A (12 W) or less.

2.8 Front Panel Connectors (JFP1, JFP2)



There are several external switches to monitor and control the PCI-7020.

2.9 H/W Monitor Alarm (JOBS1)




(JOBS1) is a 2-pin jumper to enable/disable the alarm for on board security events.

Table 2.1: Hardware Monitor Alarm Setting


Pin Setting	Function
closed	Enable OBS alarm
open	Disable OBS alarm

2.10 LAN RJ45 Connector (LAN1)




PCI-7020 uses the Intel 82574L Gigabit LAN chip which is linked to PCIe x1 link. With this chip, PCI-7020 may provide high throughputs for a heavy load networking environment. It provides one or two RJ-45 connectors in the rear side and is convenient for most industrial applications.

2.11 HD Link Connector (HDAUD1)




The PCI-7020 provides HD audio through PCA-AUDIO-HDA1 module from Advantech.

2.12 Serial ATA2 Interface (SATA1 ~ SATA3)



The PCI-7020 features a high performance serial ATA2 interface (up to 300MB/s) which eases cabling to hard drives with thin and long cables.

2.13 LAN LED Connector (LAN LED1)



PCI-7020 provides an external LAN LED Pin header for connecting to the front side of the chassis. With this convenient design users can easily see whether the LAN port is active or not. Refer to Appendix B for detailed information on the pin assignments.






Table 2.2: Front Panel LAN Indicator Connector			
LAN Mode		LED1	LED2
1000 Mbps	Link On	Green On	On
	Active	Green on	Green Flashes
	Link Off	Off	Off
100 Mbps	Link On	Orange On	Green On
	Active	Orange On	Green Flashes
	Link Off	Off	Off
10 Mbps	Link On	Off	Green On
	Active	Off	Green Flashes
	Link Off	Off	Off

2.14 USB (USB12, USB34, USB56)



The PCI-7020 board provides up to Six USB (Universal Serial Bus) ports. This gives complete Plug and Play, and hot attach/detach for up to 127 external devices. The USB interfaces comply with USB specification Rev. 2.0, and are fuse protected. The USB interface is accessed through the 5 x 2-pin flat-cable connector, CN9 (USB0, 1), CN10 (USB2, 3). You will need an adapter cable if you use a standard USB connector. The adapter cable has a 5 x 2-pin connector on one end and a USB connector on the other. The USB interfaces can be disabled in the system BIOS setup.

2.15 Case Open (JCASE1)



PCI-7020 provides 2-Pins pin header for case open detection. This function could be enabled or disabled in the BIOS setting. When the PIN is shorted, it will cause the on board buzzer to sound.

Chapter 3

Award BIOS Setup

3.1 Introduction

Award's BIOS ROM has a built-in setup program that allows users to modify the basic system configuration. This type of information is stored in battery backed-up memory (CMOS RAM) so that it retains the setup information when the power is turned off.

3.1.1 CMOS RAM Auto-backup and Restore

The CMOS RAM is powered by an onboard button cell battery. When you finish BIOS setup, the data in CMOS RAM will be automatically backed up to Flash ROM. If operation in harsh industrial environments causes a soft error, BIOS will recheck the data in CMOS RAM and automatically restore the original data in Flash ROM to CMOS RAM for booting.

Note! *If you intend to change the CMOS setting without restoring the previous backup, you have to click on "DEL" within two seconds of the "CMOS checksum error..." display screen message appearing. Then enter the "Setup" screen to modify the data. If the "CMOS checksum error..." message appears again and again, please check to see if you need to replace the battery in your system.*



3.2 Entering Setup

Turn on the computer and press to enter the BIOS setup.




Figure 3.1 Award BIOS setup initial screen

3.3 Standard CMOS Setup

- **Date**
The date format is <week>, <month>, <day>, <year>.
- **Time**
The time format is <hour> <minute> <second>, based on the 24-hour clock.
- **IDE channel 0/1 Master/Slave**
 - **IDE HDD Auto-Detection:** Press “Enter” to select this option for automatic device detection.
 - **IDE Device Setup:**
 - Auto:** Automatically detects IDE devices during POST
 - None:** Select this when no IDE device is used. The system will skip the auto-detection step to make system start up faster.
 - Manual:** User can manually input the correct settings.
 - **Access Mode:** The options are CHS/LBA/Large/Auto
 - **Capacity:** Capacity of currently installed hard disk.
 - **Cylinder:** Number of cylinders
 - **Head:** Number of heads
 - **Precomp:** Write precomp
 - **Landing Zone:** Landing zone
 - **Sector:** Number of sectors
- **Halt On**
This category determines whether system start-up will halt or not when an error is detected during power up.
The options are: No Errors/All Errors/All, But Keyboard/All, But Diskette/All, But Disk/Key
- **Memory**
This category displays base memory, extended memory, and total memory detected during POST (Power On Self Test).




Figure 3.2 Standard CMOS features screen

3.4 Advanced BIOS Features

The “Advanced BIOS Features” screen appears when choosing the “Advanced BIOS Features” item from the “Initial Setup Screen” menu. It allows the user to configure the PCI-7020 according to his particular requirements. Below are some major items that are provided in the Advanced BIOS Features screen. A quick booting function is provided for your convenience. Simply enable the Quick Booting item to save yourself valuable time.




Figure 3.3 Advanced BIOS features screen

■ CPU Features

– Delay Prior to thermal

This feature controls the activation of the Thermal Monitor's automatic mode. It allows you to determine when the Pentium 4's Thermal Monitor should be activated in automatic mode after the system boots. For example, with the default value of 16 Minutes, the BIOS activates the Thermal Monitor in automatic mode 16 minutes after the system starts booting up. The choices are 4 Min, 8 Min, 16 Min, and 32 Min.

– Limit CPUID MaxVal

Set Limit CPUID MaxVa1 to 3. This should be disabled for WinXP.

– C1E Function

"Enabled" or "Disabled" C1E function.

– Execute Disable Bit

When disabled, forces the XD feature flag to always return 0.

– Virtualization Technology

"Enabled" and "Disabled" the Virtualization Technology

■ Hard Disk Boot Priority

Set hard disk boot device priority.

■ Virus Warning

Enables or disables the virus warning.

■ CPU L1& L2 Cache

Enabling this feature speeds up memory access. The commands are “Enabled” or “Disabled.”

■ CPU L3 Cache

Enabling this feature speeds up memory access. The commands are “Enabled” or “Disabled”.

■ **Quick Power On Self Test**

This allows the system to skip certain tests to speed up the boot-up procedure.

■ **First/Second/Third Boot Device**

The BIOS tries to load the OS with the devices in the sequence selected. Choices are: "LS120", "Hard Disk", "CDROM", "ZIP100", "USB-FDD", "USB-ZIP", "USB-CDROM", "LAN1", "LAN2" and "Disabled".

■ **Boot Other Device**

Use this to boot another device. The options are "Enabled" and "Disabled".

■ **Boot Up NumLock Status**

Sets the boot up status Num Lock. The options are "On" and "Off".

■ **Gate A20 Option**

"Normal": A pin in the keyboard controller controls GateA20. Fast (Default) lets chipset control GateA20.

■ **Typematic Rate Setting**

The typematic rate is the rate key strokes repeat when a keypress is held. The commands are "Enabled" or "Disabled". Enabling allows the typematic rate and delay to be selected.

■ **Typematic Rate (Chars/Sec)**

The BIOS accepts the following input values (characters/second) for typematic auto repeat rate: 6, 8, 10, 12, 15, 20, 24, and 30.

■ **Typematic Delay (msec)**

Typematic delay is the keypress time interval before auto repetition begins. The input values for this category are: 250, 500, 750, and 1000 (ms).

■ **Security Option**

This category determines whether the password is required when the system boots up or only when entering setup. The options are:

- **System:** The system will not boot, and access to Setup will be also denied unless the correct password is entered at the prompt.
- **Setup:** The system will boot, but access to Setup will be denied unless the correct password is entered at the prompt.

Note! *To disable security, select PASSWORD SETTING in the main menu. Then, you will be asked to enter a password. Simply press <Enter> to disable security. When security is disabled, the system will boot and you can enter Setup freely.*



■ **APIC Mode**

This setting allows you to enable the APIC mode. The choices are "Disabled" or "Enabled."

■ **MPS Version Control For OS**

This setting allows you to select the MPS version. The choices are "1.1" or "1.4".

■ **Debug Port Selector: PCI**

Select port 80 error code forward to PCI/LPC.

3.5 Advanced Chipset Features

By choosing the “Advanced Chipset Features” option from the “Initial Setup Screen” menu, the screen below will be displayed. This sample screen contains the manufacturer’s default values for the PCI-7020, as shown in Figure 3.4:




Figure 3.4 Advanced chipset features screen

Note! *DRAM default timings have been carefully chosen and should ONLY be changed if data is being lost. Please first contact technical support.*



■ DRAM Timing Selectable

This item allows you to control the DRAM speed. The selections are “Manual” or “By SPD”.

■ CAS Latency Time

When DRAM Timing Selectable is set to [Manual], this field is adjustable. This controls the CAS latency, which determines the time interval between SDRAM starting a read command and receiving it. The options are [3T], [4T], [5T], [6T] and [Auto].

■ DRAM RAS# to CAS# Delay

When DRAM Timing selectable is set to [Manual], this field is adjustable. When DRAM is refreshed, the rows and columns are addressed separately. This setup item allows users to determine the timing of the transition from RAS (row address strobe) to CAS (column address strobe). The less the clock cycles are, the faster the DRAM speed is. Setting options are [2T] to [6T], and [Auto].

■ DRAM RAS# Precharge

When the DRAM Timing Selectable is set to [Manual], this field is adjustable. This setting controls the number of cycles for Row Address Strobe (RAS) to be allowed to precharge. If sufficient time has not been allowed for the RAS to accumulate its charge before DRAM refresh, refreshing may be incomplete and DRAM may fail to retain data. This item applies only when synchronous DRAM is installed in the system. Setting options are [2T] to [6T], and [Auto].

■ Precharge Delay (RAS)

This item allows you to select the value in this field, depending on whether the board has paged DRAMs or EDO (extended data output) DRAMs. The choices are: “4” to “15” and “Auto”.

- **System Memory Frequency**
To adjust the frequency of memory. The choices are: "400 MHz", "533 MHz", "667 MHz", and "Auto".
- **System BIOS Cacheable**
Selecting "Enabled" allows caching of the system BIOS ROM at F0000h-FFFFFh, resulting in better system performance. However, if any program writes data to this memory area, a system error may occur. The choices are "Enabled", and "Disabled".
- **Video BIOS Cacheable**
Selecting "Enabled" allows caching of the video BIOS, resulting in better system performance. However, if any program writes to this memory area, a system error may occur. The choices are "Enabled", and "Disabled".
- **Memory Hole At 15M-16M**
Enabling this feature reserves 15 MB to 16 MB memory address space for ISA expansion cards that specifically require this setting. This makes memory from 15 MB and up unavailable to the system. Expansion cards can only access memory up to 16 MB. The default setting is "Disabled".
- **On-Chip Frame Buffer Size**
The On-Chip Frame Buffer Size can be set to 1 MB or 8 MB. This memory is shared with the system memory.
- **DVMT Mode**
Displays the active system memory mode.
- **DVMT / FIXED Memory Size**
Specify the size of DVMT / FIXED system memory to allocate for video memory.
- **Init Display First**
Choose the first display interface to initiate while booting. The choice is "PCI Slot" or "Onboard".

3.6 Integrated Peripherals




Figure 3.5 Integrated peripherals




Figure 3.6 On-Chip IDE device

- **IDE HDD Block Mode**
If your IDE hard drive supports block mode select Enabled for automatic detection of the optimal number of block read/writes per sector the drive can support.
- **IDE DMA Transfer Access**
Use this field to enable or disable IDE DMA transfer access.
- **On-Chip Primary / Secondary IDE Device**
IDE Primary Master/Slave PIO/UDMA Mode (Auto). The channel has both a master and a slave, making four IDE devices possible. Because two IDE devices may have a different Mode timing (0, 1, 2, 3, 4), it is necessary for these to be independent. The default setting “Auto” will allow auto detection to ensure optimal performance.

■ On-Chip Serial ATA

Choose the status of serial ATA. The default setting is “Auto” which lets the system arrange all parallel and serial ATA resources automatically. The “Disabled” setting disables the SATA controller. The “Combined Mode” combines PATA and SATA, and maximum of 2 IDE drives in each channel. The “Enhanced Mode” enables both SATA and PATA, and a maximum of 6 IDE drives are supported. The “SATA Only” setting means SATA is operating in legacy mode.




Figure 3.7 Onboard device

■ USB Controller

Select Enabled if your system contains a Universal Serial Bus (USB) controller and you have USB peripherals. The choices are “Enabled” and “Disabled”.

■ USB 2.0 Controller

This entry is to disable/enable the USB 2.0 controller only. The BIOS itself may may not have high-speed USB support. If the BIOS has high speed USB support built in, the support will automatically turn on when a high speed device is attached. The choices are “Enabled” or “Disabled”.

■ USB Keyboard / Mouse Support

Select Enabled if you plan to use an USB keyboard. The choices are “Enabled” and “Disabled”.

■ Azalia Audio Select

Select “Disable” if you do not want to use audio.

■ Onboard LAN1 Control

Options are “Enabled” and “Disabled”. Select “Disabled” if you don’t want to use onboard LAN controller1.




Figure 3.8 Super I/O device

■ Onboard Serial Port 1

The settings are “3F8/IRQ4”, “2F8/IRQ3”, “3E8/IRQ4”, “2E8/IRQ3”, and “Disabled” for the on-board serial connector.

■ Onboard Serial Port 2

The settings are “3F8/IRQ4”, “2F8/IRQ3”, “3E8/IRQ4”, “2E8/IRQ3”, and “Disabled” for the on-board serial connector.

■ UART Mode Select

This item allows you to select UART mode. The choices: “IrDA”, “ASKIR”, and “Normal”.

■ RxD, TxD Active

This item allows you to determine the active level of the RxD and TxD serial lines. The Choices: “Hi, Hi”, “Lo, Lo”, “Lo, Hi”, and “Hi, Lo”.

■ IR Transmission Delay

This item allows you to enable/disable IR transmission delay. The choices are “Enabled” and “Disabled”.

■ UR2 Duplex Mode

This item allows you to select the IR half/full duplex function. The choices are “Half” and “Full”.

■ Use IR Pins

The choices are “RxD2, TxD2” and “IR-Rx2Tx2”.

■ Onboard Parallel Port

This field sets the address of the on-board parallel port connector. You can select “378/IRQ7”, “278/IRQ5”, “3BC/IRQ7”, or “Disabled”. If you install an I/O card with a parallel port, make sure there is no conflict in the address assignments. The single board computer can support up to three parallel ports.

■ Parallel Port Mode

This field allows you to set the operation mode of the parallel port. The setting “Normal” allows normal speed operation, but in one direction only. “EPP” allows bi-directional parallel port operation at maximum speed. “ECP” allows the parallel port to operate in bi-directional mode and at a speed faster than the maximum data transfer rate. “ECP + EPP” allows normal speed operation in a two-way mode.

- **EPP Mode Select**
This field allows you to select EPP port type 1.7 or 1.9. The choices are "EPP1.9" and "EPP1.7".
- **ECP Mode Use DMA**
This selection is available only if you select "ECP" or "ECP + EPP" in the Parallel Port Mode field. In ECP Mode, you can select DMA channel 1 or DMA channel 3. Leave this field on the default setting.
- **Onboard Serial Port 3 (Optional)**
The settings are "CA0", "CA8" and "Disabled" for the on-board serial connector 3.
- **Series port 3 use IRQ**
The settings are "IRQ10", "IRQ11" and "Disabled" for the on-board serial connector 3.
- **Onboard Serial Port 4 (Optional)**
The settings are "CA0", "CA8" and "Disabled" for the on-board serial connector 4.
- **Series port 4 use IRQ**
The settings are "IRQ10", "IRQ11" and "Disabled" for the on-board serial connector 4.
- **Onboard Serial Port 5 (Optional)**
The settings are "CA0", "CA8" and "Disabled" for the on-board serial connector 5.
- **Series port 5 use IRQ**
The settings are "IRQ10", "IRQ11" and "Disabled" for the on-board serial connector 5.
- **Onboard Serial Port 6 (Optional)**
The settings are "CA0", "CA8" and "Disabled" for the on-board serial connector 6.
- **Series port 6 use IRQ**
The settings are "IRQ10", "IRQ11" and "Disabled" for the on-board serial connector 6.

3.7 Power Management Setup

The power management setup controls the single board computer's "green" features to save power. The following screen shows the manufacturer defaults.




Figure 3.9 Power management setup screen




Figure 3.10 Power management setup screen (Conn.)

■ PCI express PM Function

This is to setup PCI Express's PME function "Enable" or "Disable".

■ Power Supply Type

PCI-7020 can support both "ATX" and "AT" power supplies. Customers can choose the PSU type through this selection. The choices are "ATX" and "AT". Selecting "AT" disables the ACPI function automatically.

■ ACPI Function

The choices are: "Enabled" and "Disabled".

■ Power Management

This category allows you to select the type (or degree) of power saving and is directly related to the following modes:

- HDD Power Down
- Suspend Mode
- There are three selections for Power Management, and they have fixed mode settings.

Table 3.1: Power Saving

Saving Mode	Function
Min Saving	Minimum power management., Suspend Mode = 1 hr., and HDD Power Down = 15 min.
Max Saving	Maximum power management., Suspend Mode = 1 min., and HDD Power Down = 1 min.
User Defined (Default)	Allows you to set each mode individually. When not disabled, each of the ranges are from 1 min. to 1 hr. except for HDD Power Down which ranges from 1 min. to 15 min., and disabled.

■ **Video Off Method**

Use this to select the method to turn off the video. The choices are "Blank Screen", "V/H SYNC+ Blank", and "DPMS".

■ **Video Off In Suspend**

When the system is in suspend mode, the video will turn off. The choices are "No" and "Yes".

■ **Suspend Type**

The choices are "Stop Grant" and "PwrOn Suspend".

■ **Modem Use IRQ**

This determines the IRQ that the MODEM can use. The choices are "3", "4", "5", "7", "9", "10", "11", and "NA".

■ **Suspend Mode**

Please refer to Table 3.1.

■ **HDD Power Down**

Please refer to Table 3.1.

■ **Soft-Off by PWR-BTTN**

If you choose "Instant-Off", then pushing the ATX soft power switch button once will switch the system to "system off" power mode. You can choose "Delay 4 sec". If you do, then pushing the button for more than 4 seconds will turn off the system, whereas pushing the button momentarily (for less than 4 seconds) will switch the system to "suspend" mode.

■ **CPU THRM-Throttling**

The ability is control how much percent of your CPU's clock speed will be throttled down when the CPU overheats. You can set "75.0%", "50.0%", and "25.0%".

■ **PowerOn by LAN**

This item allows you to power on the system by LAN. The choices are "Enabled" and "Disabled".

■ **PowerOn by Modem**

To enabled or disable the function to power on the system via a Modem connection from a remote host. The choice "Enabled" and "Disabled".

■ **PowerOn by Alarm**

The choices are "Enabled" and "Disabled". Fields that follow below indicate date of current month and time of alarm settings, if enabled.

■ **Primary IDE 0 (1) and Secondary IDE 0 (1)**

When Enabled, the system will resume from suspend mode if Primary IDE 0 (1) or Secondary IDE 0 (1) becomes active. The choices are "Enabled" and "Disabled".

- **FDD, COM, LPT PORT**

When Enabled, the system will resume from suspend mode if the FDD, interface, COM port, or LPT port is active. The choices are “Enabled” and “Disabled”.

- **PCI PIRQ [A-D]#**

When Enabled, the system resumes from suspend mode if an interrupt occurs. The choices are “Enabled” and “Disabled”.

- **PWRON After PWR-Fail**

Use this to set up the system after power failure. The “Off” setting keeps the system powered off after power failure, the “On” setting boots up the system after failure, and the “Former-Sts” returns the system to the status before power failure.

3.8 PnP/PCI Configurations




Figure 3.11 PnP/PCI configurations screen

- **Reset Configuration Data**

The default is Disabled. Select Enabled to reset Extended System Configuration Data (ESCD) if you have installed a new add-on card, and system configuration is in such a state that the OS cannot boot.

- **Resources Controlled By**

The commands here are “Auto (ESCD)” or “Manual”. Choosing “Manual” requires you to choose resources from the following sub-menu. “Auto (ESCD)” automatically configures all of the boot and Plug and Play devices, but you must be using Windows 95 or above.

- **PCI / VGA Palette Snoop**

This is set to “Disabled” by default.

- **Maximum Payload Size**

This allows you to set the maximum TLP payload size for PCI Express devices. The options are [128 bytes].

3.9 PC Health Status




Figure 3.12 PC health status screen

- **Case Open Warning**
Enable this to detect if the case is open or closed.
- **CPU Warning Temperature**
This item will prevent the CPU from overheating. The choices are “Disabled”, “50C/122F”, “53C/127F”, “56C/133F”, “60C/140F”, “63C/145F”, “66C/151F”, “70C/158F”.
- **Shutdown Temperature**
The system will shut down automatically when the CPU temperature is over the selected setting. This function can prevent CPU damage caused by overheating.
- **Current System Temperature**
This shows you the current temperature of system.
- **Current CPU Temperature**
This shows the current CPU temperature.
- **CPU FAN Speed**
This shows the current CPU FAN operating speed.
- **SYS FAN Speed**
This shows the current CPU FAN operating speed.
- **CHA FAN Speed**
This shows the current CHA FAN operating speed.
- **VCORE and Other Voltages**
This shows the voltage of VCORE, +3.3 V, +5 V and +12 V, VBAT (V).

3.10 Frequency / Voltage Control




Figure 3.13 Spread spectrum control screen

■ Spread Spectrum

This setting allows you to reduce EMI by modulating the signals the CPU generates so that the spikes are reduced to flatter curves. This is achieved by varying the frequency slightly so that the signal does not use any particular frequency for more than a moment. The choices are “Disabled” and “Enabled”.

3.11 Password Setting

Follow these steps to change the password.

1. Choose the "Set Password" option from the "Initial Setup Screen" menu and press <Enter>. The screen displays the following message:




Figure 3.14 Enter password

2. Fill in the password, and press <Enter>.
3. Please confirm your password, type the current password and press <Enter>.
4. After pressing <Enter> (ROM password) or the current password (user-defined), you can change the password stored. The password must be no longer than eight (8) characters.

3.12 Load Setup Defaults




Figure 3.15 Load setup defaults screen

When you press <Enter> on this item, you get a confirmation dialog box with a message similar to:

Load setup Defaults (Y/N)? N

Pressing 'Y' loads the default values that are factory settings for optimal performance system operations.

3.13 Save & Exit Setup




Figure 3.16 Save to CMOS and Exit

If you select this and press <Enter>, the values entered in the setup utilities will be recorded in the CMOS memory of the chipset. The processor will check this every time you turn your system on and compare this to what it finds as it checks the system. This record is required for the system to operate.

3.14 Exit Without Saving




Figure 3.17 Quit Without Saving

Selecting this option and pressing <Enter> lets you exit the setup program without recording any new values or changing old ones.

Chapter 4

Chipset Software
Installation Utility

4.1 Before You Begin

To facilitate the installation of the enhanced display drivers and utility software, read the instructions in this chapter carefully. The drivers for the PCI-7020 are located on the software installation CD. The Intel® Chipset Software Installation Utility is not required on any systems running Windows NT 4.0. Updates are provided via Service Packs from Microsoft*.

Note!



The files on the software installation CD are compressed. Do not attempt to install the drivers by copying the files manually. You must use the supplied SETUP program to install the drivers.

Before you begin, it is important to note that most display drivers need to have the relevant software application already installed in the system prior to installing the enhanced display drivers. In addition, many of the installation procedures assume that you are familiar with both the relevant software applications and operating system commands. Review the relevant operating system commands and the pertinent sections of your application software's user manual before performing the installation.

4.2 Introduction

The Intel® Chipset Software Installation (CSI) utility installs the Windows INF files that outline to the operating system how the chipset components will be configured. This is needed for the proper functioning of the following features:

- Core PCI and ISAPNP Services
- PCIe Support
- IDE/ATA33/ATA66/ATA100 Storage Support
- SATA Storage Support
- USB Support
- Identification of Intel (R) Chipset Components in the Device Manager

Note!



This utility is used for the following versions of Windows system, and it has to be installed before installing all the other drivers:

- Microsoft Windows Vista
- Microsoft Windows Vista x64 Edition
- Microsoft Windows XP Professional x64 Edition
- Microsoft Windows XP with Service Pack 2
- Microsoft Windows 2000 with Service Pack 4

4.3 Windows XP Driver Setup


1. Insert the driver CD into your system's CD-ROM drive. Select the folder "Intel INF" then click "infinst_autol.exe". A message pops up telling you to install the CSI utility before other device drivers. Windows XP is used as an example in the following steps.
2. Click "Next" when you see the following message.




3. Click "Yes" when you see the following message.



4. Click "Next" when you see the following message.



5. Click "Next" when you see the following message.



6. When the following message appears, click “Finish” to complete the installation and restart Windows.



Chapter 5

VGA Setup

5.1 Introduction


The Intel 945GC integrated graphics controller provides an analog display port. You need to install the VGA driver to enable the function. The Intel 945GC integrated graphics controller incorporates the latest Microsoft* DirectX*9 support capabilities. It allows software developers to create life like environments and characters. Enhanced display modes for widescreen flat panels, and optimized 3D support delivers an intense and realistic visual experience without requiring a separate graphics card.

5.2 Windows XP Driver Setup

Note! Before installing this driver, make sure the CSI utility has been installed in your system. See Chapter 4 for information on installing the CSI utility.




1. Insert the driver CD into your system's CD-ROM drive. Select the folder "VGA" then click the proper VGA driver for the OS. Windows XP is used as an example in the following steps.
2. Click "Next" when you see the following message.




3. You will see a welcome window. Please click "Next" to continue the installation.




4. Click "Yes" when you see the following message.



5. When you see the following message , please click "Next" to continue the installation.



6. Please click "Next" to continue the installation.



7. Click “Finish” to complete the installation and restart the computer now or later.



Chapter 6

LAN Configuration

6.1 Introduction

The PCI-7020 has a single Gigabit Ethernet LAN via dedicated PCI Express x 1 bus (Intel® 82574L), which offers bandwidth of up to 500 MB/s, eliminating the bottleneck of network data flow and incorporating Gigabit Ethernet to operate at 1000 Mbps.

6.2 Features

- Integrated 10/100/1000 BASE-T transceiver
- 10/100/1000 BASE-T triple-speed MAC
- High-speed RISC core with 24-KB cache
- On-chip voltage regulation
- Wake-on-LAN (WOL) support
- PCI Express X1 host interface

6.3 Installation


Note! *Before installing the LAN drivers, make sure the CSI utility has been installed on your system. See Chapter 4 for information on installing the CSI utility.*




The PCI-7020 Intel 82574L Gigabit integrated controller supports all major network operating systems. However, the installation procedure varies with different operating systems. In the following sections, refer to the one that provides the driver setup procedure for the operating system you are using.

6.4 Win XP Driver Setup


1. Insert the driver CD into your system's CD-ROM drive. Select the folder "LAN" then click the proper LAN driver for the OS. Windows XP is used as an example in the following steps.
2. Select "I accept the terms in the license agreement" and click "Next" to continue.




3. Click "Next" to continue.



4. Click "Install" to start the installation procedure.



5. Click "Finish" to complete the installation and the LAN function will be enabled after the installation.



Appendix **A**

Programming the Watchdog Timer

A.1 Programming the Watchdog Timer

The PCI-7020 watchdog timer can be used to monitor system software operation and take corrective action if the software fails to function within the programmed period. This section describes the operation of the watchdog timer and how to program it.

A.1.1 Watchdog timer overview

The watchdog timer is built in to the super I/O controller W83627HG. It provides the following functions for user programming:

- Can be enabled and disabled by user's program.
- Timer can be set from 1 to 255 seconds or 1 to 255 minutes.
- Generates an interrupt or reset signal if the software fails to reset the timer before time-out.

A.1.2 Jumper selection

The JWDT1 jumper is used to select reset in the event the watchdog timer is tripped. See Chapter 1 for detailed jumper settings.

A.1.3 Programming the Watchdog Timer

The I/O port address of the watchdog timer is 2E(hex) and 2F(hex). 2E (hex) is the address port. 2F(hex) is the data port. You must first assign the address of register by writing an address value into address port 2E (hex), then write/read data to/from the assigned register through data port 2F (hex).




Table A.1: Watchdog Timer Registers

Address of Register (2E)	Attribute	
Read/Write	Value (2F) & description	
87 (hex)	-----	Write this address to I/O address port 2E (hex) twice to unlock the W83627HG
07 (hex)	write	Write 08 (hex) to select register of watchdog timer.
30 (hex)	write	Write 01 (hex) to enable the function of the watchdog timer. Disabled is set as default.
F5 (hex)	write	Set seconds or minutes as units for the timer.
Write 0 to bit 3: set second as counting unit. [default]		
Write 1 to bit 3: set minutes as counting unit		
F6 (hex)	write	0: stop timer [default] 01~FF (hex): The amount of the count, in seconds or minutes, depends on the value set in register F5 (hex). This number decides how long the watchdog timer waits for strobe before generating an interrupt or reset signal. Writing a new value to this register can reset the timer to count with the new value.
F7 (hex)	read/write	Bit 6: Write 1 to enable keyboard to reset the timer, 0 to disable.[default] Bit 5: Write 1 to generate a timeout signal immediately and automatically return to 0. [default=0] Bit 4: Read status of watchdog timer, 1 means timer is "timeout".
AA (hex)	-----	Write this address to I/O port 2E (hex) to lock the watchdog timer 2.

A.1.4 Example Program

1. Enable watchdog timer and set 10 sec. as timeout interval

```

;-----
Mov dx,2eh          ; Unlock W83627HG
Mov al,87h
Out dx,al
Out dx,al
;-----
Mov al,07h          ; Select registers of watchdog timer
Out dx,al
Inc dx
Mov al,08h
Out dx,al
;-----
Dec dx              ; Enable the function of watchdog timer
Mov al,30h
Out dx,al
Inc dx
Mov al,01h
Out dx,al
;-----
Dec dx              ; Set second as counting unit
Mov al,0f5h
Out dx,al
Inc dx
In al,dx
And al,not 08h
Out dx,al
;-----
Dec dx              ; Set timeout interval as 10 seconds and start counting
Mov al,0f6h
Out dx,al
Inc dx
Mov al,10
Out dx,al
;-----
Dec dx              ; lock W83627HG
Mov al,0aah
Out dx,al

```

2. Enable watchdog timer and set 5 minutes as timeout interval

```

;-----
Mov dx,2eh          ; unlock W83627HG
Mov al,87h
Out dx,al
Out dx,al

```

```

;-----
Mov al,07h          ; Select registers of watchdog timer
Out    dx,al
Inc    dx
Mov    al,08h
Out    dx,al
;-----
Dec dx              ; Enable the function of watchdog timer
Mov    al,30h
Out    dx,al
Inc    dx
Mov    al,01h
Out    dx,al
;-----
Dec dx              ; Set minute as counting unit
Mov    al,0f5h
Out    dx,al
Inc    dx
In     al,dx
Or    al,08h
Out    dx,al
;-----
Dec dx              ; Set timeout interval as 5 minutes and start counting
Mov    al,0f6h
Out    dx,al
Inc    dx
Mov    al,5
Out    dx,al
;-----
Dec dx              ; lock W83627HG
Mov    al,0aah
Out    dx,al
3.  Enable watchdog timer to be reset by mouse
;-----
Mov dx,2eh          ; unlock W83627HG
Mov al,87h
Out dx,al
Out dx,al
;-----
Mov al,07h          ; Select registers of watchdog timer
Out    dx,al
Inc    dx
Mov    al,08h
Out    dx,al
;-----

```

```

Dec dx          ; Enable the function of watchdog timer
Mov  al,30h
Out  dx,al
Inc  dx
Mov  al,01h
Out  dx,al

```

```

;-----
Dec dx          ; Enable watchdog timer to be reset by mouse
Mov  al,0f7h
Out  dx,al
Inc  dx
In   al,dx
Or  al,80h
Out  dx,al

```

```

;-----
Dec dx          ; lock W83627HG
Mov  al,0aah
Out  dx,al

```

4. Enable watchdog timer to be reset by keyboard

```

;-----
Mov dx,2eh      ; unlock W83627HG
Mov al,87h
Out dx,al
Out dx,al

```

```

;-----
Mov al,07h      ; Select registers of watchdog timer
Out  dx,al
Inc  dx
Mov  al,08h
Out  dx,al

```

```

;-----
Dec dx          ; Enable the function of watchdog timer
Mov  al,30h
Out  dx,al
Inc  dx
Mov  al,01h
Out  dx,al

```

```

;-----
Dec dx          ; Enable watchdog timer to be strobed reset by keyboard
Mov  al,0f7h
Out  dx,al
Inc  dx
In   al,dx
Or  al,40h
Out  dx,al

```

```

;-----
Dec dx          ; lock W83627HG
Mov  al,0aah
Out  dx,al
5.  Generate a time-out signal without timer counting
;-----
Mov dx,2eh      ; unlock W83627HG
Mov al,87h
Out dx,al
Out dx,al
;-----
Mov al,07h      ; Select registers of watchdog timer
Out  dx,al
Inc  dx
Mov  al,08h
Out  dx,al
;-----
Dec dx          ; Enable the function of watchdog timer
Mov  al,30h
Out  dx,al
Inc  dx
Mov  al,01h
Out  dx,al
;-----
Dec dx          ; Generate a time-out signal
Mov  al,0f7h
Out  dx,al      ;Write 1 to bit 5 of F7 register
Inc  dx
In   al,dx
Or  al,20h
Out  dx,al
;-----
Dec dx          ; lock W83627HG
Mov  al,0aah
Out  dx,al

```


Appendix **B**

I/O Pin Assignments

B.1 Front Panel Connectors (JFP1)




Table B.1: Front Panel Connectors (JFP1)			
Pin	Signal	Pin	Signal
1	HDD LED+	2	HDD LED-
3	Power LED+	4	Power LED-
5	Suspend LED+	6	Suspend LED-
7	System Reset Button	8	GND
9	ATX Power Button	10	GND

B.2 USB Ports (USB12/USB34)




Table B.2: USB Ports (USB12/USB34)			
Pin	Signal	Pin	Signal
1	VCC	2	VCC
3	USB Data1-	4	USB Data2-
5	USB Data1+	6	USB Data2+
7	GND	8	GND
9	NC	10	

B.3 IR Connector (JIR1)




Table B.3: IR Connector (JIR1)

Pin	Signal
1	VCC
2	NC
3	IR_RX
4	GND
5	IR_TX

B.4 Serial Ports (COM12)




Table B.4: Serial Ports (COM12)

Pin	Signal	Pin	Signal
1	DCD1	2	DSR1
3	RX1	4	RTS1
5	TX1	6	CTS1
7	DTR1	8	RI1
9	GND	10	GND
11	DCD2	12	DSR2
13	RX2	14	RTS2
15	TX2	16	CTS2
17	DTR2	18	RI2
19	GND	20	GND

B.5 PS/2 Keyboard / Mouse Connector (KBMS2)




Table B.5: PS/2 Keyboard / Mouse Connector (KBMS2)

Pin	Signal
1	PS2 keyboard clock
2	PS2 keyboard data
3	PS2 mouse data
4	GND
5	VCC
6	PS2 mouse clock

B.6 LAN LED Connector (LANLED1)




Table B.6: LAN LED Connector (LANLED1/LANLED2)

Pin	Signal	Pin	Signal
1	LAN1_LINK/ACTIVITY#	2	LAN1_1000#
3	VCC3	4	LAN1_100#

B.7 ATX Feature Connector (ATXF1)




Table B.7: ATX Feature Connector (ATXF1)

Pin	Signal
1	5 V standby
2	VCC
3	PS_ON#

B.8 CPU FAN Connector (CPUFAN1)




Table B.8: CPU FAN Connector (CPUFAN1)

Pin	Signal
1	GND
2	+12 V
3	FAN_TACH
4	FAN_PWM

B.9 System FAN Connector (SYSFAN1)




Table B.9: System FAN Cconnector (SYSFAN1)

Pin	Signal
1	FAN_PWM
2	+12 V
3	FAN_TACH

B.10 Audio Interface Connector (HDAUD1)




Table B.10: Audio Interface Connector (HDAUD1)

Pin	Signal	Pin	Signal
1	ACZ_VCC	2	GND
3	ACZ_SYNC	4	ACZ_BITCLK
5	ACZ_SDOUT	6	ACZ_SDIN0
7	ACZ_SDIN1	8	ACZ_RST#
9	ACZ_12V	10	GND
11	GND	12	

B.11 GPIO Header (GPIO1)




Table B.11: GPIO Header (GPIO1)

Pin	Signal	Pin	Signal
1	GPIO1	2	GPIO5
3	GPIO2	4	GPIO6
5	GPIO3	6	GPIO7
7	GPIO4	8	GPIO8
9	VCC	10	GND

B.12 DVI LCD Panel Connector (DVI1)




Table B.12: DVI LCD Panel Connector (DVI1)

Pin	Signal	Pin	Signal
1	TDC0-	2	VCC
3	TDC0+	4	TLC-
5	GND	6	TLC+
7	TDC1-	8	GND
9	TDC1+	10	SC_DDC
11	GND	12	SD_DDC
13	TDC2-	14	HPDETT
15	TDC2+	16	NC
17	VCC	18	NC
19	NC	20	NC

B.13 Low Pin Count Header (LPC1)




Table B.13: Low Pin Count Header (LPC1)

Pin	Signal	Pin	Signal
1	LPC_CLK	2	LPC_LAD1
3	LPC_RST#	4	LPC_LAD0
5	LPC_FRAME#	6	+3.3 V
7	LPC_LAD3	8	GND
9	LPC_LAD2	10	NC
11	SERIRQ	12	PWROK
13	5 V Standby	14	+5 V

B.14 ATX Power Control Connector (ATX1)




Table B.14: ATX Power Control Connector (ATX1)

Pin	Signal	Pin	Signal
1	GND	7	GND
2	+5 V	8	GND
3	+5 V	9	5 V Standby
4	GND	10	PSON#
5	+5 V	11	GND
6	+5 V	12	+12 V

B.15 VGA Connector (VGA1)




Table B.15: VGA Connector (VGA1)

Pin	Signal	Pin	Signal
1	RED	9	CRT_VCCIN
2	VGA_G	10	GND
3	VGA_B	11	N/C
4	N/C	12	V_SDAT
5	GND	13	H-SYNC
6	GND	14	V-SYNC
7	GND	15	V_SCLK

B.16 H/W Monitor Alarm (JOBS1)



Table B.16: H/W Monitor Alarm (JOBS1)

Pin	Signal
1	BUZZ_VCC
2	FAILED_BEEP

B.17 Watchdog Timer Output (JWDT1)




Table B.17: Watchdog Timer Output (JWDT1)

Pin	Signal
1	NC
2	5VSB_WDTO
3	SYS RST

Appendix **C**

System Assignments

C.1 System I/O Ports

Table C.1: System I/O Ports

Addr. range (Hex)	Device
000-01F	Interrupt controller 1, master
022-023	Chipset address
040-05F	8254 timer
060-06F	8042 (keyboard controller)
070-07F	Real-time clock, non-maskable interrupt (NMI) mask
080-09F	DMA page register
0A0-0BF	Interrupt controller 2
0C0-0DF	DMA controller
0F0	Clear math co-processor
0F1	Reset math co-processor
0F8-0FF	Math co-processor
1F0-1F8	Fixed disk
278-27F	Parallel printer port 2 (LPT3)
290-297	On-board hardware monitor
2F8-2FF	Serial port 2
360-36F	Reserved
378-37F	Parallel printer port 1 (LPT2)
3B0-3BF	Monochrome display and printer adapter (LPT1)
3C0-3CF	Graphics adapter
3D0-3DF	Color/graphics monitor adapter
3F0-3F7	Diskette controller
3F8-3FF	Serial port 1
CA0-CA7	Serial port 3
CA8-CAF	Serial port 4
CB0-CB7	Serial port 5
CB8-CBF	Serial port 6
C80-C87	Serial port 7
C88-C8F	Serial port 8
C90-C97	Serial port 9
C98-C9F	Serial port 10

C.2 DMA Channel Assignments

Table C.2: DMA Channel Assignments

Channel	Function
0	Available
1	Available
2	Floppy disk (8-bit transfer)
3	Available
4	Cascade for DMA controller 1
5	Available
6	Available
7	Available

C.3 Interrupt Assignments

Table C.3: Interrupt Assignments

Priority	Interrupt#	Interrupt source
1	NMI	Parity error detected
2	IRQ0	Interval timer
3	IRQ1	Keyboard
-	IRQ2	Interrupt from controller 2 (cascade)
4	IRQ8	Real-time clock
5	IRQ9	Cascaded to INT 0A (IRQ 2)
6	IRQ10	Serial communication port 3/4/5/6
7	IRQ11	Serial communication port 7/8/9/10
8	IRQ12	PS/2 mouse
9	IRQ13	INT from co-processor
10	IRQ14	Primary IDE Channel
11	IRQ15	Secondary IDE Channel
12	IRQ3	Serial communication port 2
13	IRQ4	Serial communication port 1
14	IRQ5	Available
15	IRQ6	Available
16	IRQ7	Parallel port 1 (print port)

C.4 1st MB Memory Map

Table C.4: 1st MB Memory Map

Addr. range (Hex)	Device
E0000h - FFFFFh	BIOS
D0000h - DFFFFh	Unused
C0000h - CFFFFh	VGA BIOS
A0000h - BFFFFh	Video Memory
00000h - 9FFFFh	Base memory

www.advantech.com

Please verify specifications before quoting. This guide is intended for reference purposes only.

All product specifications are subject to change without notice.

No part of this publication may be reproduced in any form or by any means, electronic, photocopying, recording or otherwise, without prior written permission of the publisher.

All brand and product names are trademarks or registered trademarks of their respective companies.

© Advantech Co., Ltd. 2009