

windynation



Solar Panel Charge Controller

CHC-1224-10

CHC-1224-30

User's Manual

Table of Contents

1	Introduction	3
1.1	Features	3
1.2	System Diagram	3
1.3	Safety Information	4
1.4	Specifications	4
1.4.1	Electrical Specifications	4
1.4.2	Physical Specifications	4
2	Installation	4
2.1	Electrostatic (ESD) Precautions	4
2.2	Mounting	5
2.3	Connections	5
3	Operation	6
3.1	Power	6
3.2	LED Indicators	7
3.2.1	Charge LED	7
3.2.2	Battery LED	7
3.2.3	Load LED	8
3.3	Setting Modes	8
3.3.1	Normal Control	8
3.3.2	Night ON+ Day OFF Control Mode	8
3.3.3	Night ON + Set Time Delay OFF Mode	8
3.3.4	Common Controller Mode	9
3.3.5	Test Mode	9
3.3.6	Functional Matrix	9
4	Application	9
4.1	Wire Gauge Reference	9
4.1.1	Wire Thickness	9
5	Troubleshooting And Support	10
5.1	Maintenance & Care	10
5.2	Troubleshooting	10
5.3	Support	10
5.4	Warranty	11
5.4.1	Restrictions	11
5.4.2	Warranty Claims & Return Procedures	11
5.4.3	Disclaimer	11
5.4.4	Limitation of Liability	12

1 INTRODUCTION

The WindyNation Solar Panel Charge Controller provides a reliable charging and power management solution for solar power battery systems with many of the features that you would expect in a much higher priced controller. This is made possible by the board microprocessor and embedded intelligent software control.

The controller features automatic a 12V or 24V DC detect function that will identify the battery voltage upon initial charge and uses Pulse-Width Modulation (PWM) for automatic charge management and high efficiency. A built in temperature sensor provides software controlled charge compensation that accurately adjusts the over-discharge voltage and maximizes your batteries life.

Built in protection includes overload, short circuit, reverse connection, lightning/surge, PV panel reverse current, over charging, and discharging protection. In the event of a short circuit or overload event, the system will be protected and remain undamaged.

The enclosure is made of durable plastic with LED lights to provide status indications of charge, battery status, and system faults as well a user selectable Work Mode/timing interval that will power various DC powered systems for specified time intervals after dusk such as night/street lighting.


Please read this manual carefully before installing or using the controller and keep it for future reference.

1.1 FEATURES

- ✓ Compact size is easy to mount on wall or panel.
- ✓ Charge controller maintains batteries and extends battery life.
- ✓ Auto sensing for 12 or 24V systems
- ✓ Built-in battery test function
- ✓ Convenient screw terminals for wiring
- ✓ Separate connections for PV panel, battery, and load
- ✓ Built-in overload and short circuit protection
- ✓ Automatic self-recovery after fault removal
- ✓ LED system status indicators
- ✓ Requires no adjustments
- ✓ User selectable on, off, and time modes
- ✓ Wide operating temperature range -35°C to +55°C (-31°F to +131°F)

1.2 SYSTEM DIAGRAM

The MCU controller takes sample measurements from the storage battery voltage, discharge current, and ambient temperature to calculate and control the discharge rate.



1.3 SAFETY INFORMATION

Please read the installation and operating instructions carefully prior to use. Pay special attention to the **IMPORTANT** and **WARNING** statements in the manual.

WARNING:

Never install during a lightning storm or where unsafe voltages are present.

Solar panels produce power when exposed to light. Use caution when handling copper wiring.

Do not use with equipment that exceeds the rated power for this device.

1.4 SPECIFICATIONS

1.4.1 Electrical Specifications

Parameter	CHC-1224-10	CHC-1224-30
Rated Charge Current	10 Amps	30 Amps
Rated Load Current	10 Amps	30 Amps
Typical Idle Consumption	At idle < 5mA	
Overvoltage Protection	15.6V	31.2V
Low Voltage Indication	12.0V	24.0V
Overload Protection (DC load)	1.25 x I_{nom} > 60s 1.5 x I_{nom} > 5s	
Short Circuit Protection	3x I_{nom}	
Boost Charge	14.6V	29.2V
Float Charge Voltage	13.6V	27.2V
Equalization Charge	14.4V	28.8V
Overcharge Disconnection	14.8V	29.6V
Overcharge Recovery	13.2V	26.4 V
Over-discharge Disconnection	11.1V	22.2V
Over-discharge Reconnection	12.5V	25.0V
Temperature Compensation	-4.0 mV/°C/2V	

1.4.2 Physical Specifications

Parameter	Value
Dimension (H x W x D)	5.26" (133.5mm) x 2.76" (70mm) x 1.34" (34mm)
Unit Weight	0.3 lb. (142g)
Operating Temperature	-31°F to 131°F (-35°C to 55°C)
Operating Humidity	20 to 80% relative humidity (non-condensing)
Wire Size	Up to 6mm ²
Battery Type	Lead Acid including AGM and Flooded

2 INSTALLATION

- Insure all terminating connections are clean and tight to prevent arcing and overheating.
- The controller must be installed in an area that satisfies all of the following conditions:
 1. Dry: Avoid any location where water can contact the controller
 2. Cool: Ambient air temperature between 30°F and 105°F (0°C and 40°C)
 3. Ventilated: Allow at least 2 in (50 mm) of clearance above and below and at least 1 in (25 mm) on each side for proper air flow.

2.1 ELECTROSTATIC (ESD) PRECAUTIONS


All electronic circuits may be damaged by static electricity. To minimize the likelihood of electrostatic damage, discharge yourself by touching an electrical ground (e.g.: copper pipe) prior to handling the unit and

avoid touching components on the circuit boards. The risk of electrostatic damage is highest when relative humidity is below 40%.

2.2 MOUNTING

Mounting is optional; however, the environment must be dry and protected from water.

1. The controller can be mounted on a vertical or horizontal surface. If mounted vertically, the unit should be oriented such that neither end is at the top so foreign material cannot settle into the unit.
2. Install four user-supplied fasteners through the four mounting slots and into the mounting surface.
3. Tighten all the fasteners to ensure the controller cannot slide in any direction.




IMPORTANT: For best results, mount the charge controller and batteries as close to the panels as practical.

2.3 CONNECTIONS

WARNING: Loose connectors result in excessive voltage drop and may cause over heated wires and melted insulation, which can lead to electrical fires.

IMPORTANT: The NEC requires that the wires carrying the system current never exceed 80% of the conductor's current rating (sizing recommendations are located in Section 4).



IMPORTANT: The screw-down terminals on the charge controller accept 10~26AWG wire.

IMPORTANT: Strip the wire ends approximately 0.2" (5mm) before connecting to the charge controller. Use caution when handling the stripped wires to avoid electric shock.

1) Connect the Battery

Connect the battery wiring to the battery terminals on the charge controller. Note the polarity on the screw-down terminals. The charge controller self-protection feature will prevent damage from reverse polarity connections, but the charge controller will not function until the battery is connected properly.

IMPORTANT: A properly sized fuse needs to be placed in the positive wire connecting the charge controller to the battery.

2) Connect the Solar Panel Array

Connect the wires from the solar panel array to the PV port on the charge controller. Note the polarity on the screw-down terminals. The charge controller self-protection feature will prevent damage from reverse polarity connections, but the charge controller will not function until the solar panel array is connected properly. The green LED indicator will light up if there is enough sunlight.

IMPORTANT: A properly sized fuse needs to be placed in the positive wire connecting the solar panel(s) to the charge controller.

WARNING: High voltages may be present on the solar panel output wiring. Solar panels produce electricity when exposed to light. Use caution and avoid touching any conductors in the system circuit to avoid electric shock.

3) Connect the Load (Optional)

If you have a 12VDC application, connect the wires from the appliance to the load port on the charge controller. Note the polarity on the screw-down terminals. The charge controller self-protection feature will prevent damage from reverse polarity connections, but the charge controller will not function until the load is connected properly.

IMPORTANT: A properly sized fuse needs to be placed in the positive wire connecting the load (e.g. light bulb, etc.) to the charge controller.

If the red LED indicator light turns on, the battery capacity is low and needs to be charged before completing the system installation.

Press the Power/Mode button to turn on power to the load terminals.

3 OPERATION

3.1 POWER


Once properly connected to a battery and solar panel array, the charge controller will immediately begin operating. When first connected, the Load LED will be off, indicating that the power to the load is off. Press the Power/Mode button to turn on power to the load.

Note: The solar power charge controller can only be used with lead acid type batteries.

To test the system for proper connections, press the Power/Mode button on the charge controller until you see the number 7. (or 17; see description below).

IMPORTANT: Make sure the solar module(s) voltage and current do not exceed the ratings of the charge controller.

3.2 LED INDICATORS



LED	State	Description
Charge	OFF	No Charge (Nighttime)
	Solid Green	Solar power is charging the battery
	Blinking Green	The system is over voltage
Battery	Solid Green	Battery level is in the right range
	Slow Flash Green	Battery level is full
	Solid Yellow	Battery level is low
	Solid Red	Load cut-off
Load	Solid Red	The output is on
	Slow Flash Red	Overload
	Blinking Red	Load is short circuit

Note: The load output will shut off once there is an overload or short circuit. Disconnect all of the equipment and then wait a few seconds before reconnecting everything. Press the Power/Mode button and the controller will resume working after approximately 10 seconds, or in some instances, it may take a few moments longer.

3.2.1 Charge LED

When the connected solar panel is exposed to sunlight, the Charge LED will be green, indicating that the system is charging normally.

The Charge LED will flash green when an overcharge condition or an open battery circuit exists.

PWM mode is used during charging. If an over-discharge of the battery has occurred, the charger will switch to boost voltage for 10 minutes, then will return to direct voltage for at least 10 minutes to activate the battery, and finally to the float voltage state where it will remain to maintain the best state of the battery. This multistep charging process will help bring the battery to full charge and maximize its life span.

3.2.2 Battery LED

The Battery LED is green when the battery voltage is in normal condition. It will blink green slowly when the battery finishes its charge.

The LED is yellow when the voltage of the battery is below normal.

When the battery voltage goes down continuously into an over-discharge condition, the Battery LED will turn red and the Load output will switch off.

The system will automatically resume normal operation and switch on the load output and when the battery voltage recovers to the over-discharge return voltage.

3.2.3 Load LED

The load LED is red when a load output is operating normally.

If the load current is 1.25 times higher than the rated current of the controller for 60 seconds or 1.5 times higher than the rated current for 5 seconds, then the controller will shut down the output and the Load LED will blink red slowly to indicate that an overload condition occurred.

To resume normal operation, disconnect the load at fault and press the Power/Mode button. The charge controller will resume normal operation after 30 seconds.

The Load LED will blink red rapidly to indicate that a short circuit condition occurred. If a load short circuit occurs, the controller will shut down the output. If this happens, verify load connections. To resume normal operation, remove the short circuit at the load and press the Power/Mode button. The charge controller will resume normal operation after 30 seconds.

3.3 SETTING MODES

The charge controller has a mode setting function to set specific operation parameters. It is preset to the factory default of normal control. The load will draw from the battery at all times, and the PV panel will charge the battery when sunlight is available.



To set modes, press and hold the Power/Mode Button until the number on the LED display begins to flash (~5 seconds). Press the button repeatedly to choose the desired mode number. When the desired number is selected, stop pressing the button and wait for number to stop flashing, indicating that the setting is completed. The display will turn off after several seconds. Press the button to check the value.

IMPORTANT: Settings 10 through 17 may appear as a single digit and have a dot (.) after the mode number.

IMPORTANT: The controller requires about 10 minutes of continuous transition values before it starts working properly. These constraints avoid false transitions due to lighting or shading.

3.3.1 Normal Control

This is the default setting. The load will draw from the battery at all times, and the PV panel will charge the battery when sunlight is available. When selecting this mode (16 or 6-dot), press the Power/Mode button again after the mode is set to turn on the load output.

Note: In this mode only, the Power/Mode button will turn the load output on and off when pressed. After selecting this mode, make sure the load LED is on, indicating load output.

3.3.2 Night ON+ Day OFF Control Mode

The load will start working when it gets dark until it gets light. There is a 10 minute delay before turning on the load in order to make sure it is really dark and not a passing cloud etc.

3.3.3 Night ON + Set Time Delay OFF Mode

The load will switch on same as above, and remain on for a set duration. Once the selected time has elapsed, the load will switch off. The duration setting is listed in mode setting table. 1 to 15 hour delays can be selected, in increments of 1 hour. If the time setting overlaps with the occurrence of light control, then light control takes priority.

3.3.4 Common Controller Mode

The controller will work as a common controller, without light and time control, and no ON and OFF delay time. The load turns on immediately when there is no light, and off immediately when light is present on the PV panel.

3.3.5 Test Mode

This is used for the testing the system by directly turning on the load output. If there is light signal (sunlight), the load will be turned off (closed). If there is no light signal (sunlight), the load will be turned on (opened). It is convenient for checking the correctness of the system during installation and debugging.

3.3.6 Functional Matrix

MODE	LED	MODE	LED
Night ON + Day OFF	00	Night ON + 10 Hours delay OFF	10 or 0.
Night ON + 1 Hour delay OFF	01	Night ON + 11 Hours delay OFF	11 or 1.
Night ON + 2 Hours delay OFF	02	Night ON + 12 Hours delay OFF	12 or 2.
Night ON + 3 Hours delay OFF	03	Night ON + 13 Hours delay OFF	13 or 3.
Night ON + 4 Hours delay OFF	04	Night ON + 14 Hours delay OFF	14 or 4.
Night ON + 5 Hours delay OFF	05	Night ON + 15 Hours delay OFF	15 or 5.
Night ON + 6 Hours delay OFF	06	Normal Control	16 or 6.
Night ON + 7 Hours delay OFF	07	Test (no delay)	17 or 7.
Night ON + 8 Hours delay OFF	08		
Night ON + 9 Hours delay OFF	09		

4 APPLICATION

4.1 WIRE GAUGE REFERENCE

4.1.1 Wire Thickness

AWG	Diameter inches (mm)	Ohms per 1000ft	Break Force	Square mm2
16	0.051 (1.29)	4.016	75 lbs	1.30
14	0.064 (1.63)	2.525	119 lbs	2.08
12	0.081 (2.05)	1.588	197 lbs	3.30
10	0.102 (2.59)	0.999	314 lbs	5.26
8	0.129 (3.26)	0.628	480 lbs	8.30
6	0.162 (4.11)	0.395	760 lbs	13.30
4	0.204 (5.19)	0.249	1210 lbs	21.15
2	0.258 (6.54)	0.156	1930 lbs	33.62
1	0.289 (7.35)	0.124	2430 lbs	42.41
0 (1/0)	0.325 (8.25)	0.098	3060 lbs	53.49
00 (2/0)	0.365 (9.27)	0.078	3860 lbs	67.43
000 (3/0)	0.410 (10.4)	0.062	4860 lbs	85.01
0000 (4/0)	0.460 (11.68)	0.049	6120 lbs	107.22

5 TROUBLESHOOTING AND SUPPORT

The Controller requires minimal care. It is recommended to inspect all the connections at least two times per year for insulation damage or corrosion and to ensure all connections are tight and secure.

5.1 MAINTENANCE & CARE

Clean the area around the controller of any dirt or debris with a moistened cloth.

Tighten the screws on the DC input terminals. Inspect for loose, broken, or burnt wire connections.

Inspect any batteries for cracked or bulging cases and corroded terminals.

Make sure the PV array is clean and remove any debris.

5.2 TROUBLESHOOTING

Problem	Possible Remedies
The charge LED indicator doesn't light green when the solar panel is exposed to sunlight.	<ol style="list-style-type: none">1. Check if the solar panel cables are connected properly.2. Check to make sure the correct battery is being used.3. Check all wiring connections to make sure they are in their designated locations and make sure that there are no loose connections.4. Measure the PV array open-circuit voltage and confirm it is within its normal limits.5. Measure the PV voltage and the battery voltage at the controller terminals.<ol style="list-style-type: none">a. If the voltage at the terminals is within proper specifications, the PV array is charging the battery properly.b. If the PV voltage is within specifications to the open circuit voltage rating of the panels, but the battery voltage is low, the charge controller may not be charging the battery and it may be damaged.
The charge LED indicator flashes rapidly.	<ol style="list-style-type: none">1. System over voltage protection is active.2. Check for open circuit in battery, faulty battery connections to the system, or system charging circuit failure.3. Check the operating conditions to confirm that the voltage is higher than the specifications.<ol style="list-style-type: none">a. Consider temperature compensation. For example, at 0°C the charge controller will regulate at about 15 volts.
The load LED indicator is on but there is no power output.	<ol style="list-style-type: none">1. Load open circuit.2. Check cables and connections and any other load switches.3. Over discharge of the battery. The controller will resume normal operation after the battery has finished charging.
The load LED indicator light flashes and there is no power output.	<ol style="list-style-type: none">1. Check the output circuit for load short circuit or over load condition2. Remove the load and push the button; the controller will resume its work after 30 seconds.

5.3 SUPPORT

If you are experiencing technical problems, and cannot find a solution in this manual, you can contact Windy Nation Inc. for further assistance.

- Call: (805) 323-6445
- Email: support@windynation.com
- Write: 398 South Kalorama Street, Unit C, Ventura, CA 93001

For challenging issues or to just ask a question, consider using our FREE Community Forums! Consult our community of DIY'ers for fast answers to all your questions.

Post on our Forums: <http://www.windynation.com/community/>

5.4 WARRANTY

Windy Nation warrants that the Power Controller (the "Product"), will be free from manufacturing defects in materials and workmanship under normal authorized use consistent with product instructions for a period of one (1) year from the date the original purchaser ("Customer") receives the Product (the "Warranty Period"). This warranty extends only to the original purchaser. The Customer's sole and exclusive remedy and the entire liability of Windy Nation, its suppliers and affiliates for breach of the warranty is, at Windy Nation's option, either (i) to replace the Product (or defective component part(s)) with a new or reconditioned Product (or component part(s)); (ii) to repair the reported problem; or (iii) to refund the purchase price of the Product. Repaired or replaced products are warranted for the remainder of the original warranty period only. No employee, agent, dealer or other person is authorized to give any warranties on behalf of Windy Nation not expressly set forth in this limited warranty.

5.4.1 Restrictions

No warranty will apply if the Product (i) has been altered or modified except by Windy Nation; (ii) has not been installed, operated, repaired, or maintained in accordance with instructions supplied by Windy Nation; (iii) has been subjected to abnormal physical, thermal or electrical stress, misuse, negligence, or accident. If Windy Nation determines that the problem with the Product is not due to a manufacturing defect in Windy Nation's workmanship or materials, or otherwise does not qualify for warranty repair, then the Customer will be responsible for the costs of all necessary repairs and expenses incurred by Windy Nation.

5.4.2 Warranty Claims & Return Procedures

To be eligible for service under this warranty, the Customer must submit a service request within the Warranty Period by contacting Windy Nation in writing or via telephone and obtaining a Returned Materials Authorization ("RMA") number. This RMA must be obtained before returning any product under this warranty. Notification must include a description of the alleged defect, the manner in which the Product was used, the serial number, and the original purchase date in addition to the name, address, and telephone number of the Customer. Within five (5) business days of the date of notification, Windy Nation will provide the Customer with an RMA number and the location to which the Customer must return the defective Product. Any Product returned for warranty service shall be shipped at the expense and risk of the Customer. The Customer must return the entire Product kit (or, if authorized by Windy Nation, the defective component parts), within fifteen (15) days after issuance of the RMA number. Windy Nation will be under no obligation to accept any returned Product that does not have a valid RMA number. Customer's failure to return the Product within fifteen (15) days of its receipt of an RMA number may result in cancellation of the RMA. All parts that Windy Nation replaces shall become Windy Nation's property on the date Windy Nation ships the repaired Product or part back to the Customer. Windy Nation will use all reasonable efforts within thirty (30) days of receipt of the defective Product to repair or replace such Product. If a warranty claim is invalid for any reason, the Customer will be charged at Windy Nation's then-current rates for services performed and will be charged for all necessary repairs and expense incurred by Windy Nation. If Windy Nation determines that a warranty claim is valid, it will ship the repaired or replaced Product to Customer at Windy Nation's cost.

5.4.3 Disclaimer

EXCEPT FOR THE EXPRESS LIMITED WARRANTY SET FORTH IN THE PREVIOUS PARAGRAPH, WINDY NATION DISCLAIMS ALL WARRANTIES, EXPRESS, IMPLIED AND STATUTORY INCLUDING, WITHOUT LIMITATION, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A

PARTICULAR PURPOSE WITH RESPECT TO ANY PRODUCTS PROVIDED BY WINDY NATION. NO ORAL OR WRITTEN INFORMATION OR ADVICE GIVEN BY WINDY NATION, ITS DEALERS, DISTRIBUTORS, AGENTS OR EMPLOYEES SHALL IN ANY WAY INCREASE THE SCOPE OF THIS WARRANTY. WINDY NATION DOES NOT WARRANT THAT THE QUALITY OR PERFORMANCE OF THE PRODUCTS WILL MEET YOUR REQUIREMENTS OR THAT YOU WILL BE ABLE TO ACHIEVE ANY PARTICULAR RESULTS FROM USE OR MODIFICATION OF THE PRODUCTS. Some jurisdictions do not allow the limitation or exclusion of implied warranties or how long an implied warranty may last, so the above limitations may not apply to you. In any such jurisdiction, the warranty shall be limited to the minimum warranty and period required by law.

WINDY NATION EXPRESSLY DISCLAIMS ALL LIABILITY FOR BODILY INJURIES OR DEATH THAT MAY OCCUR, DIRECTLY OR INDIRECTLY, BY USE OF THE PRODUCT BY ANY PERSON.

5.4.4 Limitation of Liability

UNDER NO CIRCUMSTANCES WILL WINDY NATION OR ITS AFFILIATES OR SUPPLIERS BE LIABLE OR RESPONSIBLE FOR ANY LOSS OF USE, INTERRUPTION OF BUSINESS, LOST PROFITS, LOST DATA, OR INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES OF ANY KIND REGARDLESS OF THE FORM OF ACTION, WHETHER IN CONTRACT, TORT (INCLUDING NEGLIGENCE), STRICT LIABILITY OR OTHERWISE, EVEN IF WINDY NATION OR ITS AFFILIATE OR SUPPLIER HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

Some states do not allow the exclusion or limitation of incidental or consequential damages, so these limitations may not apply to you. Neither Windy Nation nor its affiliates or suppliers will be held liable or responsible for any damage or loss to any items or products connected to, powered by or otherwise attached to the Product. The total cumulative liability to Customer, from all causes of action and all theories of liability, will be limited to and will not exceed the purchase price of the Product paid by Customer. This warranty gives the Customer specific legal rights and the Customer may also have other legal rights that vary from state to state.