

OM2443



## Operation Manual for PSU1 Power Supply Unit

Distributed By:

**GMW Associates**

955 Industrial Road, San Carlos, CA, 94070 USA

PHONE: +1 650-802-8292 FAX: +1 650-802-8298

EMAIL: sales@gmw.com WEB: www.gmw.com



(89/336/EEC)  
EMC DIRECTIVE

Specifications may be subject to slight alteration without prior notice. This system is not qualified for use in explosive atmospheres or life support systems. Consult Bartington Instruments for advice.

The copyright of this document is the property of Bartington Instruments Ltd. The document is supplied on the condition that it is to be treated commercially confidential and it may not therefore be disclosed to any third party without written authorisation of the Managing Directors of Bartington instruments



[www.bartington.com](http://www.bartington.com)

**Bartington**<sup>®</sup>  
Instruments

Bartington Instruments Limited  
5, 10 & 11 Thorney Leys Business Park  
Witney, Oxford, OX28 4GE, England.

T: +44 (0)1993 706565  
F: +44 (0)1993 774813  
E: sales@bartington.com



## Table of Contents

How to use this Manual .....	3
Symbols Glossary .....	3
Important Safety Information .....	3
Applicability .....	4
Compatible Magnetometers .....	4
Introduction to the PSU1.....	5
Summary.....	5
Functional Description.....	5
Power.....	5
Signal Buffering.....	5
Filtering .....	5
PSU1 Inputs, Outputs and Controls.....	6
Back Panel Connections and Controls .....	6
Front Panel Controls.....	7
Installing the PSU1 .....	8
Installing and Replacing the Internal Batteries.....	8
Initial charging of the battery cells .....	11
Location of the Equipment .....	11
Potentially hazardous locations.....	11
Orientation.....	11
Temperature .....	11
Proximity to other equipment .....	11
Connecting the Equipment.....	12

## BARTINGTON INSTRUMENT

Initial Settings .....	12
Magnetometer output type selection .....	12
Using the PSU1 .....	13
Environmental Precautions .....	13
Switching On and Off .....	13
Troubleshooting .....	14
Troubleshooting (contd.).....	15
Care and Maintenance .....	16
Fuses .....	16
Calibration .....	16
Cleaning .....	16
End of Life Disposal .....	16

## How to use this Manual

This document describes the installation, operation and maintenance of the PSU1 Power Supply Unit.

Take the time to get well acquainted with your PSU1 by reading this manual. Knowing and understanding the equipment will ensure you experience the most reliable operation.

When service or maintenance is required, please contact Bartington Instruments or your local agent company.

Technical specifications for this product can be found in the appropriate datasheets. Details can be found on the [Bartington Instruments website](#).

Visit the Bartington Instruments website regularly for more information about any changes to our product range, for software downloads, datasheets and for support details. You can access all the information you need about your equipment, including service information at <http://www.bartington.com/>.

## Symbols Glossary

The following symbols used within this manual call your attention to specific types of information:



**WARNING:** Indicates a situation in which serious bodily injury or death could result if the warning is ignored.



**Caution:** Indicates a situation in which bodily injury or damage to your instrument, or both, could result if the caution is ignored.



This symbol identifies items that must be disposed of safely to prevent unnecessary damage to the environment.

**Note:** A note provides useful supporting information and sometimes suggests how to make better use of your purchase.

## Important Safety Information



**WARNING:** The PSU1 is fitted with AA size NiMH (Nickel Metal Hydride) rechargeable batteries. Only AA size rechargeable batteries, which are specified as compatible in the relevant datasheet can be used in this product.



**WARNING:** The fitting of non-approved battery cells may be dangerous and could affect the safety of users, damage the equipment and also invalidate the terms and conditions of the Warranty.

## Applicability



**Caution:** This manual applies only to the PSU1 Power Supply Unit. For the earlier Mag-03PSU, please use the manual supplied with that unit or visit the [Bartington Instruments website](#) to obtain a copy. If you require assistance locating the correct manual for your equipment, please contact the Bartington Instruments helpdesk.

## Compatible Magnetometers



**Caution:** Use of incompatible magnetometers may cause damage to the PSU1 and/or the magnetometer. The PSU1 is designed to operate with various magnetometers. For the current list refer to the datasheet.

## Introduction to the PSU1

### Summary

The PSU1 provides a battery backed power supply of  $\pm 12$  V for the Mag-03 series of three axis fluxgate magnetic sensors. It also contains filters for the analog outputs of the sensor.

### Functional Description

#### Power

The PSU1 will supply  $\pm 12$  V d.c. for powering a range of magnetometers. Please refer to the datasheet for the latest list of compatible products. The power is supplied from the internal, rechargeable batteries or from the plug-in power adapter, which is also used to charge the PSU1 batteries.

**Note:** The PSU1 will operate without any battery cells being installed. To install, or replace defective cells refer to the section on [Installing and Replacing the Internal Batteries](#).

#### Signal Buffering

Buffered, single-ended output signals on BNC connectors from differential or single-ended output magnetometers.

After filtering, each analog signal is fed to the appropriate BNC connector via a low impedance buffer. These buffers allow long cables and low input impedance data acquisition systems to be used. Refer to the appropriate datasheet for maximum loads.

The output common return is also buffered to eliminate crosstalk due to signal currents sharing the  $V_a$  common return. A high impedance ac path is also provided between the  $V_a$  common and cable screen to improve ac noise performance.

#### Filtering

Filtering is provided by a low-pass filter and selectable high-pass filter for d.c. or a.c. coupling.


A low pass and a high pass filter are included in each of the channels for the signals from the X, Y and Z axes of the sensor. Refer to the appropriate datasheet for the frequency response of the filters.

The low pass filters remove the high frequency noise components of the signal from the sensor.

The high pass filters are intended to isolate the DC or static field component so that the alternating components above this frequency can be measured or analysed.

## PSU1 Inputs, Outputs and Controls

### Back Panel Connections and Controls



1. X Signal Conditioned Output
2. Y Signal Conditioned Output
3. Z Signal Conditioned Output

The three BNC connectors carry the conditioned analogue output voltages. The conditioned outputs are the magnetometer X, Y and Z signals after they have been modified by the low/high pass filters and, if a balanced output magnetometer is connected, converted to single-sided signals.


4. Space for unique serial number
5. Magnetometer Socket

This multi-pin socket is for the connection of the magnetometer cable.



**Note:** Ensure correct orientation of the connector (indicated by the cut-out on the connector body aligning with the notch in the socket)



## Front Panel Controls





6. Magnetometer Output Type Selector Switch

Balanced (out)   
Unbalanced (in) 



**Caution:** This switch must be set to match your magnetometer output type to ensure correct results (see [Magnetometer output type selection](#))

7. DC/AC Coupling (High Pass Filter (HPF) Control)

DC (out)   
AC (in) 

8. Charge LED  
9. ON / OFF LED

10. On/Off Switch  
11. Socket for external charging adapter

## Installing the PSU1


### Installing and Replacing the Internal Batteries

The battery cells for the PSU1 are not installed before shipping. To install the batteries cells for first use (or to replace defective cells) use the following procedure:



**Key:** A – Enclosure lid retaining screw      B – Enclosure lid retaining screw  
C – Earth lead fixing (do not remove)

1. Place the PSU1 on a suitable surface with the underside facing up and the two enclosure lid retaining screws nearest to you.




2. Using a flat-bladed screwdriver of the appropriate size, fully loosen screw A to allow the edge of the lid to clear the enclosure end cap.




## BARTINGTON INSTRUMENT

3. Fully loosen screw B and the lid of the enclosure will lift due to the internal springs.



4. Lift the lid and place aside to gain access to the battery cell compartment.



5. Insert each cell into the compartment in turn. Always fit the negative end of the cell first. Press the cell back against spring pressure until the positive terminal can be located in the holder.

## BARTINGTON INSTRUMENT



6. When all 5 cells are in place, locate the back edge of the lid in the enclosure



7. Tighten screws A and B in any order
8. To remove discharged or defective cells follow the above procedure

## Initial charging of the battery cells

To charge the PSU1 battery, connect the mains charger and switch on the mains supply (if appropriate). The charging LED (item 8) will begin to flash indicating that “fast charging” is taking place. Once the fast charge cycle has completed the LED will stop flashing and be lit (ON) continuously to indicate “trickle charging” is ongoing.

**Note:** When battery cells are inserted for the first time, they should be continuously charged for 16 hours to ensure full capacity.

**Note:** The PSU1 can be used whilst charging the battery cells or directly from mains power without any battery cells being installed. However the outputs may carry some charger noise.

**Note:** If the PSU1 is powered by the mains charger with no batteries cells installed, the charging LED may flash. This is normal and can be ignored.

**Note:** To prepare for long periods away from a charging source battery cells may be pre-charged and used to replace discharged cells in the field.

## Location of the Equipment

### Potentially hazardous locations



**WARNING:** The charger supplied with this equipment is powered by mains electricity. It should not be used in wet or damp locations, where water may enter the unit and create a safety hazard.

### Orientation

The PSU1 can be orientated horizontally or vertically.

### Temperature

To minimise temperature induced drift effects, position the PSU1:

- In a constant ambient temperature
- Out of direct sunlight

### Proximity to other equipment

The PSU1 contains no high frequency electronics likely to cause emissions which could cause interference with other equipment. The unit is unlikely to be affected by interference from other equipment in the normal operating environment.

**Note:** The PSU1 is inherently magnetic and should, therefore, be sited as far from any magnetometers as possible.

## Connecting the Equipment



**Caution:** Connection between the magnetometer and the power supply should not be made or broken with the power supply switched on as this could cause damage to the magnetometer.

Connect the equipment in the following sequence:

1. Ensure the ON/OFF switch, item 10, is OFF (position “0”).
2. Connect the magnetometer to the PSU1 magnetometer socket. Ensure the connector pins are correctly aligned with those in the socket. The locking ring should be hand-tightened only.
3. Connect BNC outputs to your external equipment, as required.

## Initial Settings

### Magnetometer output type selection

Before switching on the equipment, set the magnetometer output type selector switch to the correct position for your magnetometer. Refer to the appropriate magnetometer datasheets.

## Using the PSU1

### Environmental Precautions

Refer to the Mag-03 datasheet for maximum environmental, electrical and mechanical ratings for the PSU1.



**Caution:** Exceeding the maximum environmental ratings may cause irreparable damage to the equipment.

### Switching On and Off



**Caution:** Connect the magnetometer before switching on the PSU1, as connecting a “live” cable to the magnetometer may cause damage. Similarly, switch off the PSU1 before disconnecting the magnetometer.

With the Power switch (item 10) ON (position “1”), the power LED (item 9) will be continuously lit (ON).

**Note:** For best results, after switching on the power, leave the PSU1 for 20 minutes for the internal temperature to stabilise, before performing any measurements.

## Troubleshooting

If the PSU1 exhibits unexpected behaviour, please check possible causes in the following table:

<b>Fault</b>	<b>Possible Cause</b>	<b>Solution</b>
No power output from the PSU1	Battery flat	Recharge
	Battery expired	Replace batteries and charge
	Battery not fitted	Fit batteries and charge
	None of the above	Return to Bartington Instruments for repair
PSU1 does not charge	Failed 12V charger	Replace charger
	Battery not fitted	Fit batteries and charge
	None of the above	Return to Bartington Instruments for repair
PSU1 does not hold its charge (reduced battery operation)	Batteries expired	Replace batteries and charge
PSU1 stuck in AC or DC coupling mode	Defective component	Return to Bartington Instruments for repair
PSU1 stuck in Balanced or Unbalanced mode	Defective component	Return to Bartington Instruments for repair
One or both LEDs do not light correctly	Defective component	Return to Bartington Instruments for repair



## Troubleshooting (contd.)

Fault	Possible Cause	Solution
With a sensor connected all output signals are faulty	Coupled incorrectly	Check position of AC/DC coupling switch
	Balance mode set incorrectly	Check position of balanced/unbalanced mode switch
	Defective sensor cable	Check sensor cable using relevant datasheet. Return to BI if found to be defective
	Sensor defective	Return PSU1 and sensor to Bartington Instruments for repair
	PSU1 defective	Return PSU1 and sensor to Bartington Instruments for repair
With a sensor connected one, or two output signals are faulty	Defective sensor cable	Check sensor cable using relevant datasheet. Return to BI if found to be defective
	Sensor defective	Return PSU1 and sensor to Bartington Instruments for repair
	PSU1 defective	Return PSU1 and sensor to Bartington Instruments for repair

If the solutions suggested above do not fix the fault, please contact the Bartington Instruments helpdesk.

## Care and Maintenance

The PSU1 requires no routine maintenance. There are no user serviceable parts.

### Fuses

As a safety feature the PSU1 is fitted with a thermal fuse. If the PSU1 overheats, which could occur as a result of the fitment of incorrect battery cells, the charging circuit will be permanently isolated. The PSU1 must be returned to Bartington Instruments for checks and repair.



**Caution:** No attempt should be made by a user to repair the unit. Repairs by unauthorised people may be dangerous and could affect the safety of users, damage the equipment and also invalidate the terms and conditions of the Warranty.

### Calibration

No calibration is required.

### Cleaning



**Caution:** Disconnect the electrical supply before performing any cleaning operation.

Periodic cleaning is not normally required.

If the system becomes soiled and cleaning is necessary:

- 1/ Use a damp cloth to clean the outer surfaces.
- 2/ Use an air duster to blow debris from the connectors.



**Caution:** Ensure water does not enter the system. The system must be completely dry before the electrical supply is reconnected.



**Caution:** Never use chemicals, such as solvents, when cleaning the PSU1.



**Caution:** Take particular care when cleaning around electrical connections. Bent or damaged pins may cause the magnetometer to malfunction.

## End of Life Disposal



This symbol of the crossed-out wheeled bin indicates that the product (electrical and electronic equipment) should not be placed in municipal waste. Check local regulations for disposal of electronic products.



# Bartington® Instruments

Bartington Instruments Limited  
5, 10 & 11 Thorney Leys Business Park  
Witney, Oxford, OX28 4GE, England.

T: +44 (0)1993 706565  
F: +44 (0)1993 774813  
E: [sales@bartington.com](mailto:sales@bartington.com)

The specifications of the products described in this brochure are subject to change without prior notice. Bartington® is a registered trademark of Bartington Instruments Ltd

[www.bartington.com](http://www.bartington.com)