



70584

**PCI 32 bit P&P
1S (16C650 32FIFO)**

Installation Guide

◆ Description

The 70584 32Bit PCI bus Plug & Play 1S I/O card is equipped with one High-Speed RS-232.V24 Standard Serial Interface. The serial port includes 32 Byte FIFO with a speed up to 921Kb/Sec. 70584 includes one 9 pin male connector for attaching the peripheral's unit.

◆ Hardware Specification

Serial Port:

UART Chipset: SUN1889, Hardware FIFO are 32Byte FIFO

Compatible chips: with 16C650, 16C550 and 16C450.

IEEE standard: RS-232 Interface

Driver Chipset: TI-75232, speed up to 100Kb/Sec, length 300-500M.

Max. Speed: Up to 921Kb/Sec (HYPER Terminal program)

◆ Hardware Installation

- Turn off the power of your computer
- Plug the 70584 Serial Adapter to the PCI bus of your computer
- Connect the peripheral (Printer, Modem, Scanner... etc.) to this adapter
- Turn on the power of your computer

PCI device listing display (for example...)

Bus No	Device No	Func No	Vendor ID	Device ID	Device Class	IRQ
0	7	1	8086	7010	IDE Controller	14
0	13	0	1409	7168	Simple COMM. Controller	10

When Vendor ID, Device ID, Device Class or IRQ aren't displayed or an error occurs, please change the PCI slot.

After correct hardware installation you can start installing the software from the driver CD.

◆ Pin Assignments

Serial 9 Pin male connector pin assignments:

Serial 9 Pin male connector:							
Pin	Signal	Pin	Signal	Pin	Signal	Pin	Signal
1	CD	4	DTR	6	DSR	8	CTS
2	RD	5	GROUND	7	RTS	9	RI
3	TD						

◆ Technical Specification

Compatibility:	PCI 32Bit card for 486/586/Pentium/Pentium-II/ P-III/C5/K6
Operating system:	WIN 9.x/ME/NT/2000/XP, LINUX, DOS
Chips:	1 x SUN1889
Connections:	1 x DB 9 m connector serial
PCB:	2 Layer / 120 x 51 mm



This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operations.