

Setup Instructions

Octabank

Style Series: 3661, 3662

Description

The 5' & 7' **OCTABANK** is supported by eight (8) fiberglass rods and has a silver interior with a removable internal baffle and a removable exterior diffuser panel. It is constructed of specialized, flameproof fabric near the light and weighs less than 5 pounds. It offers a diagonal large light source with a very even light spread with generally less than ½ stop light loss from center to edge. The Octabank now comes standard with a Mounting and Tilter Bracket to allow the weight of the soft box to be placed on the light stand and not the actual light itself.

Product Contains

- [1] Octabank
- [8] Assembly Rods
- [1] Inner Round Baffle
- [1] Outer Diffusion Panel
- [1] 2303 Grip Adapter
- [1] Tilter Bracket
- [1] Carry Case

INSTRUCTIONS

To assemble, place your first rod in one of the eight- (8) holes on the ring and then position the opposite rod directly across from the first one. Continue alternating until you have placed six (6) of the rods in the ring. The last two (2) will be easier to slide in the ring if you gently push down on the middle of the rod causing it to bow inward, allowing the tip to pop into the hole in the ring. To disassemble gently push down on the ring with one hand and the rod with the other and pop the rod out of the hole on the ring. Continue to do this in the same alternating method that you did to set it up.

GRIP HEAD ADAPTERS

To mount the #2300 – place the silver block between one of the cross members of the adapter ring, lining up the screw holes in the silver blocks. Insert the two- (2) screws in the holes in the blocks. Insert the brass stud(s) into the bottom of the silver block and you are ready to mount to your adapter into your tilter bracket and then onto your stand.

All lights over 1000 watts are recommended to use a two-stand setup.

