RSTI-EP Slice I/O

### GFK-2962 November 2015



Specialty Module

# Specialty Modules EP-5111, EP-5112, EP-5212, EP-5422, EP-5442

GE provides several RSTi-EP specialty modules, which can be used to meet specific needs in your system. Each module has a Module Status LED and each channel has a LED for visual indication of connectivity.

The counter module EP-5111 can read one square-wave signal (1 channel) (for example, from an incremental encoder) with a maximum input frequency of 100 kHz. The 32-bit counter can count up or down within a predetermined range of values.

The digital counter module EP-5112 can read two square-wave signals (2 channels) (for example, from an incremental encoder) with a maximum input frequency of 100 kHz. Depending on the operating mode, both 32-bit counters can count up or down independent of each other in a preset range of values. The counters can be controlled via software by setting the appropriate control word. The digital counter module EP-5212 can read frequency of one square-wave signal (1 channel) from one or two external sensors with a maximum input frequency of 100 kHz. Frequencys to be counted are applied to channel CH0 and/or channel CH1, the measurement will be started via control word 1 and 2 respectively. Measuring cycles can be defined in µs. The longer the measuring cycle the more exactly the measurement.

The digital pulse width modulation modules EP-5422 and EP-5442 are used for the control of small motors with current requirements of 0.5 A up to 2 A which can also be used for the control of valve flaps. The switching frequencies are adjustable up to 40 kHz and, in addition to this, the push/pull output levels can be used for motor activation; for example: change of rotation direction. As with all modules of the RSTi-EP system, the characteristics are outstanding – from the modular design and the interchangeable electronics to the removable plug-in terminal strip.

The RSTi-EP station is usually installed on a horizontally positioned DIN rail. Installation on vertically positioned DIN rails is also possible.

Modules should to be allowed to de-energize for a minimum 10 seconds after power down, prior to starting any maintenance activity.

Refer to the *RSTi-EP Slice I/O User Manual* (GFK-2958) for additional information. Refer to the RSTi-EP Power Supply Reference Guide, a software utility available on

PME V9.00, for detailed power-feed requirements.

#### Module Features

- Spring style technology for ease of wiring
- DIN rail mounted
- Double-click installation for positive indication of correct installation
- Compatible for 2 and 3 wire connection
- 32-bit counter, 24 V DC
- Counting frequency 100 kHz max (A/B channel, 1/2/4- times sampling or pulse and direction, invertible)
- Gate input (hardware gate, HW gate), reset input, digital output controlled by an internal comparator
- Alarm and diagnostic function with µs time stamp
- Digitally adjustable input filter to suppress interferences(17 filter frequencies gradually adjustable between 3 Hz and 187 kHz)
- Digital pulse width modulation modules can control from 0.5A to 2A.

© 2015 General Electric Company. All Rights Reserved.

\* Indicates a trademark of General Electric Company and/or its subsidiaries. All other trademarks are the property of their respective owners.

# Ordering Information

Module	Description			
EP-5111	1 Channel High Speed Counter, AB 100 kHz 1 DO 24VDC, 0.5A			
EP-5112	112 2 Channel High Speed Counter, AB 100 kHz			
EP-5212	2 Channel Frequency Measurement, 100 kHz			
EP-5422 2 Channels PWM Output, Positive Logic, 24VDC, 2.0 A				
EP-5442	2 Channels PWM Output, Positive Logic, 24VDC, 0.5 A			

# Specifications

	EP-5111	EP-5112	EP-5212		
System Data					
Data	Process, parameter, and diagnostic data depend on the network adapter used.				
Interface	RSTI-EP System bus				
System bus transfer rate	48 Mbps				
Galvanic isolation		500 V DC betweer	n the current paths		
Inputs		1			
Number of counter inputs	1	2	2		
Туре	Incremental encoders and c sensor types 1 and 3 are in (	other input characteristics for accordance with EN 61131-2			
Input filter	Filter time adjustab	Adjustable between 3 Hz and 187 kHz (333 ms and 5 µs)			
Low input voltage		< 5 V			
High input voltage		> 11 V			
Max. input current per channel		3.5 mA			
Sensor supply		Yes			
Sensor connection	2-wire and 3-wire				
Reverse polarity protection	Yes				
Module diagnostics	Yes				
Individual channel diagnostics	Yes	Yes	No		
Counter width	32 bits				
Maximum input frequency	100 kHz				
Latch, gate, reset input	Yes				
Mode of operation	Pulse and direction / AB mode with 1-, 2-, 4-times sampling	Pulse and direction / AB mode with 1-, 2-, 4-times sampling	Pulse rising edge		
Status, alarm, diagnostics					
Status indicator		Yes			
Process alarm	Yes, parametrizable	Yes, parametrizable			
Diagnostic alarm	Yes	Yes			
Outputs					
Number	1				
Output Current	0.5 A				
Reverse polarity protection	Yes				
Module diagnosis	Yes				
Individual channel diagnosis	Yes				
Supply	1				
Supply voltage	20.4V – 28.8V				
Current consumption from system current path I <sub>SYS</sub>	8 mA				
Current consumption from output current path l <sub>in</sub>	35 mA plus output current for the digital output	35 mA	35 mA plus sensor supply current		
· · ·			•		

General data				
Operating temperature	-20°C to +60°C (-4 °F to +140 °F)			
Storage temperature	-40°C to +85°C (-40 °F to +185 °F)			
Air humidity	EV to DEV pancondensing as par IEC 61171.2			
(operation/transport)	570 to 3570, noncondensing as per rec 01151-2			
Width	11.5 mm (0.45 in)			
Depth	76 mm (2.99 in)			
Height	120 mm (4.72 in)			
Weight	83 g (2.93 oz)	72 g (2.54 oz)	83 g (2.93 oz)	

3

	EP	-5422	EP-5442			
System Data						
Data	Process, parameter, and diagnostic data depend on the network adapter used.					
Interface		RSTI-EP sy	/stem bus	·		
System bus transfer rate	48	Mbps	48 1	Mbps		
Outputs				1		
Number		2		2		
Туре	PN out	put stage	PN outp	out stage		
Response time	< (	).1 µs	< 0.	.1 µs		
Period duration		25 µs t o 175 ms	s (40 kHz to 6 Hz)	•		
May autaut aurant	per channel	0.5 A	per channel	2 A		
Max. output current	per module	1 A	per module	4 A		
	Resistive load (min. 47 Ω)	static, 6 Hz to 40 kHz	Resistive load (min. 12 Ω)	6 Hz to 40 kHz		
Switching frequency	Inductive load (DC 13)	static, 6 Hz to 40 kHz	Inductive load (DC 13)	6 Hz to 40 kHz		
	Lamp load (12 W)	static, 6 Hz to 40 kHz	Lamp load (48 W)	6 Hz to 40 kHz		
Actuator connection	2-wire, 3-wire, 3-wire + FE					
Actuator supply	max. 2 A per plug, total max. 4 A max. 2 A per plug, total max. 8 A					
Pulse/period ratio	0–100 % PN-switching or P-switching, adjustable					
Short-circuit-proof	Yes					
protective circuit	< 100 µs					
Module diagnosis		Ye	es			
Individual channel diagnosis	No					
Reactionless		Ye	es			
Supply						
Supply voltage	20.4V -	- 28.8V				
Current consumption from system current path Isys	8 mA					
Current consumption from output current path IouT	40 mA + Load					
General data						
Operating temperature	-20°C to +60°C (-4 °F to +140 °F)					
Storage temperature	-40°C to +85°C (-40 °F to +185 °F)					
Air humidity (operation/transport)	5% to 95%, noncondensing as per IEC 61131-2			2		
Width	11 5 mm (0.45 in)					
Depth	76 mm (2.99 in)					
Height	120 mm (/i 72 ir		(4 72 in)			
Weight	77 n	(2.72 oz)	82 a (2.89 oz)			
	77 g (2.72 02)		82 y (2.89 02)			

RSTi-EP Slice I	/0	Specialty	Modules
-----------------	----	-----------	---------

## LEDs

LED	EP-5111	EP-5112	EP-5212	EP-5422	EP-5442	
Module	Green: Communication over the system bus					
Status	Red: Module System Fault or Diagnostic Fault					
				Yellow: PWM output	Yellow: PWM output	
				0 – 100%, P-switching	0 – 100%, P-switching	
1.1	Yellow: A/pulse controlled	Yellow: CH0 A pulse controlled		Yellow flashing at 2 Hz: PWM output 0 is > 0 and < 100%, PN-switching or P-switching	Yellow flashing at 2 Hz: PWM output 0 is > 0 and < 100%, PN- switching or P- switching	
1.2						
1.3						
1.4	Yellow: B/direction	direction controlled	(1-level)			
2.1	Yellow: output set	direction controlled				
2.2	· · · · ·					
2.3						
2.4	Yellow: reset input controlled					
3.1	Yellow: latch input controlled	<b>Yellow:</b> CH1 A pulse controlled		Yellow: PWM output 1 – 100%, P-switching Yellow flashing at 2 Hz: PWM output 0 is > 0 and < 100%, PN-switching or P-switching	Yellow: PWM output 1 – 100%, P-switching Yellow flashing at 2 Hz: PWM output 0 is > 0 and < 100%, PN- switching or P- switching	
3.2						
3.3						
3.4	Yellow: gate input (HW gate) controlled		Yellow: CH0 active (1-level)			
4.1		Yellow: CH1 B direction controlled				
4.2						
4.3						
4.4						

## Field Wiring

The connection frame can take up to four connectors, and four wires can be connected to each connector. The *Spring style* technology allows for either finely stranded or solid wire with crimped wire-end ferrules or ultrasonically welded wires, each with a maximum cross-section of 1.5 mm<sup>2</sup> (16 guage), to be inserted easily through the opening in the clamping terminal without having to use tools. To insert fine stranded wires without wire-end ferrules, the pusher must be pressed in with a screwdriver and released to latch the wire.

5



Connector Block with Four Wire Connectors

Connector Specifications:

- conductor cross-section 0.14 to 1.5 mm<sup>2</sup> (26 16 guage)
- max. ampacity: 10 A
- 4-pole

The pushers are color-coded for the following connections:

- White Signal
- Blue GND
- Red 24 V DC
- Green Functional earth (FE)

The modules do not have a fused sensor/activator power supply. All cables to the connected sensors/actuators must be fused corresponding to their conductor cross-sections (as per Standard DIN EN 60204-1, section 12).

Refer to the RSTi-EP Slice I/O User Manual (GFK-2958) for additional information.

For technical assistance, go to <u>http://support.ge-ip.com</u>.

### **Connection Diagrams**





7

Connection Block Diagrams





For public disclosure



9

#### Installation in Hazardous Areas

EQUIPMENT LABELED WITH REFERENCE TO CLASS I, GROUPS A, B, C & D, DIV. 2 HAZARDOUS AREAS IS SUITABLE FOR USE IN CLASS I, DIVISION 2, GROUPS A, B, C, D OR NON-HAZARDOUS AREAS ONLY

WARNING - EXPLOSION HAZARD - SUBSTITUTION OF COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS I, DIVISION 2; WARNING - EXPLOSION HAZARD - WHEN IN HAZARDOUS AREAS, TURN OFF POWER BEFORE REPLACING OR WIRING MODULES; AND

WARNING - EXPLOSION HAZARD - DO NOT CONNECT OR DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NONHAZARDOUS.

#### ATEX Marking

🐼 II 3 G Ex nA IIC T4 Gc

Ta: -20°C to +60°C (-4° F to +140 °F)

### **Release History**

Catalog Number	Firmware Version	Date	Comments
EP-5111, EP-5112, EP-5212, EP-5422, EP-5442	N/A	Nov-2015	Initial Release

### Important Product Information for this Release

Updates

Initial Release

#### Funcional Compatibility

Initial Release

#### Problems Resolved by this Release

None – Initial Release

#### New Features and Enhancements

None – Initial Release

#### Known Restrictions and Open Issues

None

#### **Operational Notes**

None

### **Product Documentation**

RSTi-EP Slice I/O Module User Manual (GFK-2958) RSTi-EP Slice I/O Functional Safety Module User Manual (GFK-2956)



**GE Intelligent Platforms** 

1-800-433-2682 1-434-978-5100 <u>www.ge-ip.com</u>

For public disclosure