



Reloaded[®] Board For Shocker[™]



ReloadedTM Board

For ShockerTM

Software version 1.5

PERFORMANCE

HIGHLIGHTS

- Developed for hard gamers. Sustained rate of fire in all situations!
- High Trigger scan priority for maximum sensitivity.
- Automatic filtering of trigger bounces. No need to consider it!
- Automatic dwell adjustment depending of fire rate to avoid drop off. Nothing to adjust!
- Just drop in and PLAY! No need for mechanical mods of the Shocker.
- Seamless setup through the XTEND board

FEATURES

- High Trigger polling rate
- Up to 27 bps while the eyes are enabled
- Automatic Drop Off Control (ADOC).
- Automatic Trigger Debounce (ATD).
- Power Aware Design (PAD) for maximum battery life.
- Exclusive Auto-Adaptive Loader Delay (A²LD)
- Automatic Force Fire (AF²) in case of obstructed barrel and empty breech while eyes are on.
- First Shot Boost (FSB) after inactivity
- Automatic eyes de-activation in case of loader problem
- All Adjustment parameters stored in non volatile memory.
- On board buzzer, vibrator and Tricolor led.
- Reloaded XtendTM LCD extension port
- NXL legal full auto mode with 15bps limit

RELOADED[®] Board 1.0 for Shocker[®] and Nerve[®]

This board is a French Connection Paintball product designed for TONTON.

The TONTON team has developed a new board for the popular Smart Part[®] SHOCKER[®] and NERVE[®].

The **RELOADED[®]** board process data from the trigger and the eyes using a unique combination of hardware and software improvements. Its objective is to provide a repeatable and accurate rate of fire, whatever the situation in the field.

The **RELOADED[®]** is a flexible and state of the art electronic board that will ensure a sustained rate of fire while the player is under pressure, therefore allowing him to concentrate on the action instead of on his finger.

The **RELOADED[®]** allows for fast programming through its unique GAME TYPE parameter. Five GAME TYPES are available: Tournament, Enhanced1, Enhanced2, NXL mode, Max speed Full and Millennium mode.

Just, set this parameter and the gun will automatically adjust all other parameters based on user defined starting values.

The **RELOADED[®]** board can be extended through its on board **RELOADED XTEND[®]** port.

The **RELOADED XTEND[®]** board is a remote control with an embedded LCD matrix.

The **RELOADED XTEND[®]** remote control offers a valuable advantage over other SHOCKER[®] boards. It allows you to seamlessly program your favorite modes with crystal clear messages displayed on the LCD matrix.

ReloadedTM Board For ShockerTM

Software version 1.5

Table of contend

1	Overview of the Board	4
2	How to install your board?	5
3	Starting instructions	6
4	Turning the RELOADED® ON	6
5	Going to GAME mode	7
5.1	EYES OPERATION	7
6	Going to PROGRAMMING Mode	8
6.1	PARAMETERS DESCRIPTION	9
6.1.1	GAME TYPE	9
6.1.2	DWELL	11
6.1.3	SENSITIVITY	12
6.1.4	ALARM TIMER DURATION	12
6.1.5	AUTOMATIC DROP-OFF CONTROL	13
6.1.6	AUTOMATIC TRIGGER DEBOUNCE	13
7	Switching the GUN OFF	13
8	How to program the board?	14
8.1	IN PROGRAMMING MODE	14
8.2	SAFETY	16
8.3	MEMORY CORRUPTION	16
8.4	PROGRAMMING VISUAL HELP	17
8.4.1	POWERING THE GUN	17
8.4.2	TURNING THE GUN ON	17
8.4.3	SELECTING GAME MODE	17
8.4.4	TURNING THE GUN OFF	18
8.4.5	GOING TO PROGRAMMING MODE	19
9	Troubleshooting	20
9.1	SHOCKER® IS DIFFICULT TO SWITCH ON/OFF	20
9.2	BREACKING PAINT	20
9.3	VELOCITY IS INCONSISTENT	20
9.4	THE SHOCKER® EXHIBIT LOW VELOCITY	21
9.5	THE SHOCKER® IS DROPPING OFF	21
9.6	THE SHOCKER® IS GASSED UP, BUT DOES NOT SHOOT	21
9.7	THE GUN FIRES AT A VERY LOW ROF WHATEVER THE RATE OF MY FINGERS	21
10	Funny acronyms glossary	23

Reloaded Board™ For Shocker™


Software version 1.5

1 Overview of the Board

The drawing below shows the different buttons and peripheral of the **RELOADED®**.

In the future we will refer to the buttons using the capital letters given within brackets.

This drawing does not represent the upper stock board of the SHOCKER™. The **On/Off button referred as (O)** is located on this second board. It lights in blue and can be found at the back of the grip frame when the stock board is in place.



ReloadedTM Board

For ShockerTM

Software version 1.5

2 How to install your board?

1. Unscrew the grips and lift up the left part.
2. Unplug the 10 wire connector from the back of the stock board. Unplug the 9v battery from the stock board, if any.
3. Remove the two metal pins that retain the trigger switch and board in the frame.
4. Pull back on the top half of the stock board so the trigger switch can clear the frame then extract the stock board out of the frame, finishing with the bottom half.
5. Do the exact same step in reverse order with the **RELOADED®**. Starting with the bottom half and trigger switch facing the trigger, gently insert the board in the retaining slot at the bottom of the grip frame.
6. Line up the trigger switch with the two pin holes then insert the two retaining pins back into the frame and through the trigger switch mounting holes.
7. Plug the 10 wire connector into the **RELOADED®** board. Plug the 9V battery in the power socket beginning with the negative pole. Then gently insert in the remaining space of the grip frame.
8. Put the grips back in place or proceed to programming steps...

ReloadedTM Board

For ShockerTM

Software version 1.5

3 Starting instructions

First install the reloaded in the frame grip of the gun and plug the ribbon cable in the Reloaded to connect the Dwell board to the Reloaded.

Only, connect a *good* 9v battery (PP3 type) to the battery socket of the **RELOADED@**. The reloaded board tolerates down to 5.6v. To prevent bad battery, you must connect your battery beginning with the negative pole or the positive pole, not both at the same time. Not respecting that will lock the board in an alarm cycle. The board flashes its LED until you properly insert the battery.

Right after you correctly plugged the battery, the board will perform a complete peripheral check.

The Tricolor LED will flash green, then red. The blue LED will flash and the buzzer emit a three tone beep. Finally the board vibrates once to complete the boot sequence. This means the battery is correctly connected and has enough power. From this point, the **RELOADED@** is asleep and ready to serve (Sleep mode). The Power Aware Design (PAD) of the **RELOADED@** ensures more than 2 months in this mode.

4 Turning the **RELOADED@** ON

To turn the **RELOADED@** board ON, just press and hold the power button (O) located on the back of the Frame Grip for more than two seconds.

The Blue LED on the back of the frame will flash rapidly and stop on solid. The board will vibrate once and play the welcome music.

You are now in **ON-STATE**. From this point you have three possibilities.

1. Quickly Press and Release the trigger (T) once to go to **GAME mode**.
2. Quickly Press and Release the orange button (P) once to go to **PROGRAMMING mode**.
3. Press and hold the ON/OFF button (O) for more than two seconds to switch the gun back off (Sleep mode)

ReloadedTM Board

For ShockerTM

Software version 1.5

5 Going to **GAME mode**

Entering **GAME mode** is signaled by a three tone beep. In this mode, your gun is ready to deliver an unlimited amount of ball per second (bps). Just pull the trigger!

The **RELOADED@** will automatically take care of the dwell regulation, Drop-off control (ADOC), recharge time, debounce, eyes activation and deactivation. This ensures no drop off during sustained sequences of fire. No need for you to manually handle the eyes. No need for fuzzy debounce considerations.

Just play, shoot and enjoy!

The board exhibits a default 27 bps!

The question is... Will you make it?

While in **GAME mode**, you can turn the gun OFF at any time by pressing and holding the power button (O) for more than two seconds. At this point, the Gun will vibrate twice, the "Good bye" music will sound and all LEDs will turn off.

In **GAME mode** the blue led located on the back of the grip frame, is blinking. How fast it blinks depends on Eyes options. See below for more in depth explanations.

5.1 EYES OPERATION

By default, the Eyes are systematically enabled when the marker is first turned on.

Due to its unique Auto Adaptive Loader Delay (AALD) feature the **RELOADED@** board will adjust its Eyes setting to the loader delivery rate.

If no ball is presented to the eyes after a short delay, the board will automatically deactivate the Eyes feature for a very short period of time. This is the Automatic Forced Fire (AF²) feature.

ReloadedTM Board

For ShockerTM

Software version 1.5

This allows an incredible flexibility when in the middle of a strategic move. If a ball is blocked at the entrance of the barrel and the breech is empty while Eyes are on, the **RELOADED®** will automatically disconnected the eyes, for this single shot. You won't even notice it! **Just concentrate on the action! The RELOADED® is in charge!**

Note: In order to be able to "dry fire", the eyes system does not need to be turned off. Simply remove the loader, and the **RELOADED®** will adapt to the new situation.

If for some reason (you fool!), you want to turn the Eyes, and all associated actions, off or back on, just push and release the power button quickly. This will toggle the Eyes on or off.

When the Eyes system is active, the blue led at the back of the frame grip blinks rapidly. When it is disabled the blue led will change to a slow blinking sequence.

6 Going to PROGRAMMING Mode

Entering the **PROGRAMMING mode** is signaled by a "welcome" music. In this mode, you can adjust the parameters for your particular gun and game style.

The Programming Button is the only button on the **RELOADED®** board. To access it, open the left side of the grip, and look at the edge of the board. The button is right there, orange. You can't miss it!

Once, in this mode the board LED will light up GREEN. This means first parameter is selected.

Because the **RELOADED®** exhibits an incredible level of sophisticated auto adaptive functions, there are very few parameters to set...

... **It's a crystal clear 1, 2, 3 philosophy.**

ReloadedTM Board

For ShockerTM

Software version 1.5

There are actually six different parameters that can be adjusted. DWELL , Sensitivity, ADOC and ATD are set once for all. The **RELOADED®** will automatically modulate those settings to ensure an appropriate service of the gun.

In the same time, you just have to set the GAME type parameter to drastically change the behavior of the gun.

Possible parameters are shown below and explained in the following sections:

1. Game type.
2. Dwell.
3. Sensitivity.
4. Alarm Timer Duration.
5. Automatic Drop-Off Control.
6. Automatic Trigger Debounce.

6.1 PARAMETERS DESCRIPTION

6.1.1 GAME TYPE

GAME TYPE is used to rapidly set the game style. It will automatically adjust all inside parameters of the **RELOADED®** board so you have nothing else to do!

GAME type parameter has 4 states:

1. Tournament
2. Enhanced level 1
3. Enhanced level 2
4. NXL mode
5. Max speed Full
6. MILLENNIUM tournament

ReloadedTM Board

For ShockerTM

Software version 1.5

Tournament type is the default setting. This mode is used for NPPL game type. In this mode, one trigger action will end up with one shoot. The rate of fire is the exact same rate as the player's finger. Even debounce timings are automatically adjust by the board to get a fully legal shoot behavior.

In this mode, the sensitivity parameter is ignored, but all other advanced features hereafter are available:

- Automatic Drop-Off Control (ADOC)
- Automatic Trigger Debounce (ATD)
- Auto-Adaptive Loader Delay (A²LD)
- Automatic Force Fire (AF²)
- Automatic Eyes De-activation (AEDA) in case of loader problem

Please see glossary for further explanation of funny acronyms!

WARNING: THE TWO FOLLOWING MODES ARE NOT ALLOWED IN MANY TOURNAMENTS. THOSE MODES ARE HERE FOR FUN AND EXTREME SENSATIONS!

IT IS THE PLAYER'S RESPONSIBILITY TO SET THE APPROPRIATE MODE COMPLYING WITH THE KIND OF TOURNAMENT HE PARTICIPATS.

THE RELOADED® CAN NOT DO THIS FOR YOU!

Enhanced level 1 type is dedicated for player who wants to fire at a reasonable rate of fire without too much concentration on their finger action. The **RELOADED®** board will detect a burst of fire. It will therefore increase the rate of fire during those small periods of time. For ease of pain, the reloaded will actually maintain a high rate of fire until your finger slows under half the sensitivity. During slow bursts the **RELOADED®** is in tournament mode.

Enhanced level 2 is dedicated to aggressive player style or training game when players want to concentrate on strategy instead of finger action.

Reloaded Board™ For Shocker™

Software version 1.5

This mode will maintain a high rate of fire as soon as the sensitivity has been reached even if the actual rate of the finger slows down to half the sensitivity. Erratic breaks in the sequence are also compensated like in Enhanced level 1. If you stop shooting, the burst mode is reset and you must reach the Sensitivity threshold again to benefit from the enhance mode. During slow sequences the **RELOADED®** is in tournament mode.

NXL mode is **LEGAL in NXL league**. It will allow a full mode after 3 balls in tournament mode (for safety reasons). Once those balls have been fired, the gun is set to full, with a legal limitation of 15 bps. This mode is maintained for 1 second after the last shoot. Pressing the trigger within this second will continue to fire in full. If one second elapses without any shoot, the full mode is lost and a 3 balls sequence must be fired again. The SENSITIVITY parameter is ignored in this mode.

Max speed Full mode is dedicated to those sci-fi fans who ever wanted to possess a laser beam! In this mode, pulling and holding the trigger will fire the gun at its **maximum rate of fire**. The limitation is not in the Reloaded board but in the gun and loader technology. If you can feed its appetite, the reloaded will allow 27 bps !!!!! The SENSITIVITY parameter is ignored in this mode.

In this mode, you better get a good loader to feed the unlimited appetite of the **RELOADED®**...
...and pray for your opponents!

MILLENNIUM Tournament mode is **LEGAL in the MILLENNIUM league**. It will allow every features available in Game type 1 (Tournament) except that the Rate Of Fire (ROF) is limited to 15 balls per second.

6.1.2 DWELL

DWELL is used to set the opening time of the solenoid of the gun. You must set this parameter accordingly with your gun technology.

We have noticed that many things can influence this setting. First be sure that your Regulator is sufficiently

ReloadedTM Board

For ShockerTM

Software version 1.5

and correctly greased. Second, depending on your Bolt weight, you will have to tune this value.

The **RELOADED**[®] board handles automatically all associated recharge time to properly service the gun. The range of settings is limited to truly usable and stable values.

No fooling around with fuzzy option tuning!

Explanation: Experiencing drop off or bolt not completely cycling are symptoms of poor adjustments. In this case you should turn the opening time up (the DWELL parameter). A dwell fewer than 7ms or above 12ms doesn't make sense, since efficiency would be very poor, and risk of ball breakage very high!

Some boards will allow this. We don't!

Dwell parameter can be adjust between 7ms and 12ms by steps of 0.5 ms.

6.1.3 SENSITIVITY

SENSITIVITY is used to indicate the **RELOADED**[®] the minimum number of balls per second that can be considered a burst.

Sensitivity can be adjusted between 1 and 4 by steps of 1. A setting of 1 corresponds to a very sensitive setting, 4 is the least sensitive.

For information only, if Game type is set to Enhanced1, the sensitivity can be interpreted as follow: 1=6bps, 2=9 bps, 3=12 bps & 4=16 bps.

While in Enhanced2, it would be: 1=8bps, 2=12bps, 3=16bps & 4=20bps. (don't set to 4, knowing that 20 is impossible to reach!)

6.1.4 ALARM TIMER DURATION

ALARM TIMER DURATION is used to indicate that x times 30 seconds (approx.) have elapsed. X ranging from 0, for no alarm, to 14 for 7 minutes. The Alarm counter starts immediately when you enter the GAME mode. If you want, you can wait for the beginning of the game in ON-STATE mode and press the trigger (T) to enter the GAME mode in the very last seconds of the OFFICIAL count down. When the Alarm timer duration has elapsed the gun vibrates three times and automatically restarts its count down.

ReloadedTM Board

For ShockerTM

Software version 1.5

6.1.5 AUTOMATIC DROP-OFF CONTROL

AUTOMATIC DROP-OFF CONTROL (ADOC) is provided for fine tuning the gun.

Depending on Bold characteristics, dwell mechanics and whether your regulator is greased or not, the gun can experience some drop-off, especially on the first shot and after a period of inactivity. So, you can therefore indicate the gun what "bonus dwell" should be added to this particular ball. The value is tunable between 0 and 8, 0 meaning no ADOC and 1 to 8 meaning milliseconds increment by steps of 0.5ms. For example, setting to 8 would add 4 ms of Dwell opening. **Beware of to much ADOC. Since the more you open the DWELL the riskier you break a ball!**

6.1.6 AUTOMATIC TRIGGER DEBOUNCE

AUTOMATIC TRIGGER DEBOUNCE (ATD) is used to indicate the **RELOADED®** the minimum number of milliseconds it should wait before allowing the gun to accept another trigger event. This additional delay is added **only on the two or three first shots**. After that the delay is removed and the gun can cycle to its maximum rate of fire. This parameter can be set between 0, for no ATD, to 5 by steps of 10 ms. For example; setting to 3 will add 30ms of delay on the first 2 or 3 balls.

7 Switching the GUN OFF

Switching the gun off can be done while in **ON-STATE** or in **GAME mode**.

Turning it off from **PROG. mode** is not possible since you first must save your parameters. If you want to do so while in **PROG. mode**, first exit the **PROG mode** (see PROG mode section to learn more on how to do that) then switch off from the **GAME mode**.

To switch the gun off, just press and hold the **ON/OFF** button (**O**) for more than two seconds.

The gun will vibrates twice and the goodbye music will sound. All LED are now off and the board is asleep. With a brand new battery, the **RELOADED®** board can hibernate for more than 2 months.

ReloadedTM Board

For ShockerTM

Software version 1.5

EXAMPLES

Setting the Game type to Enhanced L2

1. Open the left side of the grip
2. Turn on the marker.
3. Push the Prog. Button once to enter Programming mode.
4. Push the prog button twice to set value of game type to Enhanced L2.
5. Press and hold the trigger for 2 seconds to save and exit AND enter the GAME mode

Your Game type is programmed and ready to be tested

8 How to program the board?

The **RELOADED**[®] board sets a new standard in Gun programming behavior. Forget what you have been doing for years with other boards. **You've entered the RELOADED[®] world.**

Three things to know:

- Each action is acknowledged by a beep.
- The programming mode acts in a cycle manner. Pushing buttons will jump to next value. Each time you reach the maximum value; the RELOADED[®] adds one different beep and brings you back to the minimum value.

8.1 IN PROGRAMMING MODE

In **PROGRAMMING mode** you have four possible actions:

- The programming button is used to increment the value of parameters.
- The on/off button is used to change the active parameter.
- The trigger is used to **Save & Exit** the **PROGRAMMING mode**. If you press and hold it for more than 2 seconds.
- The trigger is used to **read** the **current value**, if you quickly press and release it.

The board LED color will help you to figure out which parameter is selected.

Solid Green	➔	Game type
Solid Orange	➔	Dwell
Solid Red	➔	Sensitivity
Blinking Green	➔	Timers
Blinking Orange	➔	FSB
Blinking Red	➔	AMB

NOTE: FOR SAFETY REASONS, PROGRAMMING THE GUN SHOULD BE DONE WITHOUT ANY BALL IN THE FEEDER SINCE YOUR GOING DIRECTLY TO GAME MODE AFTER PROGRAMMING.

Reloaded Board™ For Shocker™

Software version 1.5

Programming Example 2:

Setting the Sensitivity to 1:

1. Open the left side of the grip
2. Turn on the marker.
3. Push the Prog. Button once to enter Programming mode.
4. Push the On/Off button twice to select the SENSITIVITY parameter.
5. Starting from a sensitivity of 2, for example, push the programming button 3 times to set value of SENSITIVITY to 1. You have cycled through the whole range and jumped back to the min value.
6. Press and hold the trigger for 2 seconds to save and exit AND enter the GAME mode.

Your Sensitivity is programmed.

- 1 First you need to select the parameter you want to set.

Push and release the on/off button to cycle through parameters.

Push and hold the on/off button to cycle faster and automatically through the parameters.

- 2 You now need to change the value of the parameter.

Push and release the Programming button to cycle through values.

Push and hold the Programming button to cycle faster and automatically through the values.

Remember: Each time you reach the maximum value, you jump to the minimum value. This situation will be indicated by a second and different beep.

Each time the value is incremented, a beep is emitted making the tuning very easy.

- 3 If you don't remember the value of a parameter, just quickly press & release the Trigger (T). The board will play one beep per increment of the parameter (10 beeps for a value of 10).
- 4 Once you are all set and satisfied with your tunings, just press and hold the trigger (T) for more than 2 seconds.

Your parameters are saved in the non volatile memory of the board so that you don't need to reprogram everything, next time you turn your gun on.

**You are now ready to test the new settings...
...Enjoy!**

Note : Pressing the trigger saves and exits **AND** gets you to the GAME mode with the parameters you just set. No need to turn the gun OFF and ON.

Reloaded Board™ For Shocker™

Software version 1.5

8.2 SAFETY

The Saving of your parameters in the memory is acknowledged by the Blue LED blinking six times and a GAME mode welcome music. Release the trigger before the end of the music for maximum safety.

For safety reason there is also a one second latency when you jump from PROG mode to GAME mode added to blue led blinking and music.

8.3 MEMORY CORRUPTION

WARNING : Unpowering the board during save sequence will corrupt your parameters.

If this happens, just go back to prog mode, and press and hold the prog button UNTILL you hear the two tone beep (it can be long, but no more than 255 beeps, so be patient!) of the board indicating that you have cycled to a correct value.

Repeat this for each parameter. Once you are done, save all your parameters by pressing and holding the trigger for more than 2 seconds.

During **PROGRAMMING mode**, powering the gun off is not allowed (nor advised) because of memory access. To turn your gun off, simply press and hold the trigger to **Save & Exit**, then press and hold the on/off button as usual, to switch off.

Factory default programming is:


- Game type = Tournament
- Dwell = 8ms
- Sensitivity = 2
- Alarm Timer duration = 0
- Anti Drop Off Control = 1 (for 0.5 ms)
- Automatic Trigger Debounce = 3 for 30 ms

Reloaded Board™ For Shocker™

Software version 1.5

EXAMPLES

Typical sequence example:



Examples of possible sequences in GAME mode:

You can do this:

1 → 2 → ... → 2 → 2 → ... → 2 → 5

or this...

1 → 5 → 2 → ... → 2 → 4 → 2 → 5

8.4 PROGRAMMING VISUAL HELP

Here are some visual helps for better comprehension.

8.4.1 POWERING THE GUN

Action	What happens?
1 Plug the battery into the socket.	<ul style="list-style-type: none"> ✓ The board vibrates once and emits a two tone beep. ✓ The gun is ON <u>but asleep!</u>

8.4.2 TURNING THE GUN ON

First, power the gun. Then...

Action	What happens?
1 Press & hold on/off for 2 sec.	<ul style="list-style-type: none"> ✓ The Green, Blue and Red LED flash once. ✓ The gun vibrates once and plays the welcome music.

8.4.3 SELECTING GAME MODE

First, power the gun and turn it ON. Then...

Action	What happens?
1 Press and release the trigger.	<ul style="list-style-type: none"> ✓ The gun plays a three tone beep ✓ The gun is in GAME mode. ✓ The BLUE LED blinks rapidly.
2 Pull the trigger to fire as many times as you want!	<ul style="list-style-type: none"> ✓ The gun fires. ✓ Rate of fire depends on programmed parameters. ✓ Each time you fire the BLUE LED flashes.
3 Press & release the On/Off button	<ul style="list-style-type: none"> ✓ The EYES are OFF. ✓ The BLUE LED blinks slowly.
4 Press & release the On/Off button	<ul style="list-style-type: none"> ✓ The EYES are ON. ✓ The BLUE LED blinks rapidly.

Reloaded Board For Shocker™

Software version 1.5

8.4.4 TURNING THE GUN OFF

This is not possible while in Prog. mode.


Action	What happens?
1 Press & hold the On/Off button for more than 2 seconds	<ul style="list-style-type: none">✓ The gun vibrates twice and plays the Goodbye music.✓ The gun is <u>asleep and can remain so for months.</u>

Reloaded Board™ For Stocker™

Software version 1.5

EXAMPLES

Typical sequence example:



Examples of possible sequences in PROG mode:

You can do this to set you gun to Full auto:

①→③→③→③→④

You can do this to change Dwell from 8ms to 9ms (by steps of 0.5ms) and Sensitivity from 1 to 3:

①→②→②→③→③→②→③→③→④

8.4.5 GOING TO PROGRAMMING MODE

Action	What happens?
① Press and release the Programming button.	<ul style="list-style-type: none"> ✓ The gun plays a Welcome Prog. music. The gun is in PROGRAMMING mode. ✓ The GREEN LED is ON, meaning "Game type" parameter is selected.
② Press and release the On/Off button or press & hold the On/Off button to cycle through parameters.	<ul style="list-style-type: none"> ✓ The gun beeps once for each action or beeps rapidly if you hold the button. The LED will cycle accordingly. SOLID GREEN→SOLID ORANGE→SOLID RED→BLINKING GREEN→BLINKING ORANGE→BLINKING RED for each action. ✓ When you reach the parameter you want to set, stop your action. ✓ Press and release (T) to hear one beep per unity (see 4bis). ✓ If you reach the last parameter the gun plays a different beep once and jumps to the first parameter.
③ Press and release the Programming button or press & hold the programming button.	<ul style="list-style-type: none"> ✓ The gun beeps once for each action or beeps rapidly if you hold the button. The LED is ON and its color indicates the active parameter you are setting. ✓ If you reach the last value the gun vibrates once and jumps to the first value.
④ Press & hold the trigger for 2 seconds	<ul style="list-style-type: none"> ✓ The gun "Saves & Exits" the programming mode and Jumps to GAME mode where you can instantly test the new setup.
④ bis Press & release the trigger	<ul style="list-style-type: none"> ✓ The gun will "read" the current value of the parameter. It sounds once for each increment of the value. <ul style="list-style-type: none"> ● 1 beep for Tournament ● 2 beeps for Enhanced L1 ● 3 beeps for Enhanced L2 ● 4 beeps for NXL legal tournament ● 5 beeps for Max speed Full ● 6 beeps for Millennium tournament

Reloaded Board™ For Shocker™

Software version 1.5

9 Troubleshooting

Below text in italic is extracted from the SHOCKER® user manual.

9.1 SHOCKER® IS DIFFICULT TO SWITCH ON/OFF

- ✓ *Check the solenoid wiring harness. It is maybe in the way of the on/off button. To do so, remove the grip frame. Relocate wires away from switch and check for damage.*
- ✓ *Check if battery is not low ($V < 5.5V$) or dead.*
- ✓ *We have noticed that the switch on the solenoid board is sometime soldered to far from the frame. In this case contact your Smart part dealer for adjustment...*

9.2 BREAKING PAINT

Most of the time Breaking paint is due to mechanical problems. *The Shocker® Users manual says:*

- ✓ *Paint to barrel match is wrong. The paint you are using is too large for the barrel you are shooting it through.*
- ✓ *Ball Detents are damaged or missing. Check to make sure white delrin ball is intact and reactive on both sides. Replace if damaged or missing.*
- ✓ *Paint is too low quality or too brittle. Switch to a name brand, high quality manufacturer.*
- ✓ *Loader may not be keeping up if you deactivate the eye system in this case, check loader batteries or use a faster loader.*
- ✓ *Check Reloaded battery. It may be low, causing incomplete cycling.*

9.3 VELOCITY IS INCONSISTENT

Warning: Velocity is very related with weather conditions. Outside temperature and humidity can drastically modify pressure regulation and paints diameter.

ReloadedTM Board For ShockerTM

Software version 1.5

Most of the time inconsistent velocity is due to mechanical problems. *The Shocker[®] Users manual* says:

- ✓ Clean regulator and inspect seat assembly. (See separate Max-Flo manual)
- ✓ Check paint to barrel match. Paint may be too large or too small for the barrel you are shooting it through. Find a paintball that fits your barrel properly.
- ✓ Check the Shocker[®] and Max-Flo regulator for leaks.

9.4 THE SHOCKER[®] EXHIBIT LOW VELOCITY

- ✓ Your Reloaded battery is low. Replace with fresh name brand battery.
- ✓ Turn the on/off valve on all the way.
- ✓ Check your operating pressure so that it is at @190psi. Increase to 190psi if lower.
- ✓ If pressure is at @190psi, slowly increase dwell setting.

9.5 THE SHOCKER[®] IS DROPPING OFF

- ✓ **FIRST OF ALL**, clean and grease the Shocker[®] and the regulator and ckeck again.
- ✓ Increase the dwell slightly.

9.6 THE SHOCKER[®] IS GASSED UP, BUT DOES NOT SHOOT

- ✓ Turn the Reloaded board on.
- ✓ Battery may be dead. Replace with fresh name brand battery.
- ✓ Check to see if solenoid wiring harness has come free from either end of the circuit board. If yes then reconnect.

9.7 THE GUN FIRES AT A VERY LOW ROF WHATEVER THE RATE OF MY FINGERS

Due to its AFF feature, while in Vision mode, the gun will fire wheter there are balls present or not.

Reloaded Board™ For Shocker™

Software version 1.5

- ✓ But if balls have odd shapes or are badly discolored. Each ball detection will have a penalty causing the gun to lower its ROF to 10 bps. You can remove the Vision eye or choose a different type of ball or check to see if you have previously broken a ball. Broken paint may cover the actual Vision eye and cause it to misread. Clean it with a paper towel and a small amount of alcohol. If this does not work, the eye may be damaged and will need to be replaced. Call Smart Parts or your local Smart Parts dealer for parts.
- ✓ The Vision may not read certain dark shell paints, such as black. While it is not a given that the Vision does not see black shell paint, continued failure of the Vision system with black shell paints should indicate for you to try a bit of a brighter shell paintball.

ReloadedTM Board

For ShockerTM

Software version 1.5

10 Funny acronyms glossary

Automatic Intelligent Trigger Debounce (AITD) – Each time you press the trigger, the switch is activated. The switch is made of metal plates that will bounce for a short period of time. At the Board level those bounces are considered as independent trigger actions. Therefore the board must be able to filter those “false events”. In the case of the **RELOADED®** board, the player has **NOTHING to set up** to handle this inherent property of a switch. The **RELOADED®** board knows exactly what to do with this intrinsic characteristic of the switch.

Trigger/Switch Debounce (TSD) – Each time you press the trigger, it pushes on the switch lever. The switch is made of metal plates and springs. There is a position where the main metal plate is in an unstable equilibrium. In this forced state, the spring and the trigger give very little room to the plate, it has ALMOST nowhere to go, but touches nearly nothing. In this configuration, the plate will/can oscillate between ON and OFF, causing the gun to “Run Away”. The **RELOADED®** board allows the player **to set up a parameter that avoids this behaviour**.

Automatic Drop Off Control (ADOC) – The dwell’s solenoid is energized each time you fire. The ADOC feature controls and adapts the duration of the excitation depending on the situation. The more the dwell is open the faster you shoot. The **RELOADED®** board will automatically adjust all associated parameters to properly service the gun. Experiencing drop off, bolt not completely cycling or ball breakage are symptoms of poor adjustments. The solenoid service is a question of compromise between dwell opening duration and recharge time. The **RELOADED®** will take care of that automatically.

ReloadedTM Board

For ShockerTM

Software version 1.5

Auto Adaptive Loader Delay (A²LD) – After each shot, the gun must make sure a slight delay is added to the cycle to ensure you won't chop the next ball. Thanks to its unique A²LD technology, the **RELOADED® sets the appropriate delay for each ball, without any user action!**

First Shot Boost (FSB) – Due to electrical and pneumatic leakages of the solenoid, when the marker has been left sitting for a long period (approx. more than 30 seconds), the first shot suffers of drop off. To avoid this, The FSB feature will add an additional dwell boost to the first shot after such a long inactivity.

WARNING: After 10 seconds of inactivity, the first ball velocity will be slightly higher (approx. 15 to 30 fps higher). Don't forget to fire at least once before a chrony check!

Recharge time – This is the amount of time needed to recharge the gun after a shoot. This includes: waiting for a ball to be present, let the air flow to the regulator, debounce the trigger, wait for the bolt to be pulled backward, etc... Some of those delays take place at the same time, some are unavoidable.

The **RELOADED®** board **automatically adjusts the different delays** to service the gun at his optimum performance, **what ever the circumstances.**

Auto Force Fire (AF²) – This feature will force the fire in the event a ball has been pushed slightly into the detents where the Eyes are unable to detect it. In this situation the **RELOADED®** will automatically handles the situation and corrects the problem so you can continue firing normally. **You won't even notice the problem as occurred.**

Automatic Eyes De-activation (AEDA) – In case of repetitive loading problem the **RELOADED®** will instantly activate its AEDA feature. This allows jumping from an HALO feeding rate to a "dry shoot" mode, in a snap, without any user action.

ReloadedTM Board

For ShockerTM

Software version 1.5

It is very important that you read the next two pages carefully.

LIMITATION OF LIABILITY

FRENCH CONNECTION PAINTBALL WILL NOT BE RESPONSIBLE FOR ANY DAMAGES OR INJURIES THAT ACCOMPANY OR RESULT FROM YOUR USE OF ITS PRODUCTS. THESE INCLUDE (BUT ARE NOT LIMITED TO) DAMAGES OR INJURY CAUSED BY ANY: (1) USE OF (OR INABILITY TO USE) THE RELOADED[®] BOARD; (2) USE OF (OR INABILITY TO USE) ANY PRODUCT TO WHICH YOU INTERFACE FROM OUR RELOADED[®] BOARD; (3) FAILURE OF PERFORMANCE; (4) ERROR; (5) OMISSION; (6) INTERRUPTION; (7) DEFECT; OR (8) DELAY IN OPERATION; WE ARE NOT LIABLE FOR ANY CONSEQUENTIAL OR INCIDENTAL DAMAGES, WHICH ARE DAMAGES INTENDED TO COMPENSATE SOMEONE DIRECTLY FOR A LOSS OR INJURY, DAMAGES REASONABLY EXPECTED TO RESULT FROM A LOSS OR INJURY, OR OTHER MISCELLANEOUS DAMAGES AND EXPENSES RESULTING DIRECTLY FROM A LOSS OR INJURY. FURTHERMORE, WE ARE NOT LIABLE EVEN IF WE HAVE BEEN NEGLIGENT OR IF OUR AUTHORIZED REPRESENTATIVE HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES—OR BOTH.

HOWEVER, IN CERTAIN STATES WHERE THE LAW MAY NOT ALLOW US TO LIMIT OR EXCLUDE LIABILITY FOR THESE INCIDENTAL OR CONSEQUENTIAL DAMAGES, THE ABOVE LIMITATION MAY NOT APPLY AND YOU MAY HAVE THE RIGHT TO RECOVER THESE TYPES OF DAMAGES. IN ANY EVENT, OUR LIABILITY TO YOU FOR ALL LOSSES, DAMAGES, INJURIES AND CLAIMS OF ANY KIND, WHETHER THE DAMAGES ARE CLAIMED UNDER THE TERMS OF A CONTRACT, OR THEY ARE CLAIMED TO BE CAUSED BY NEGLIGENCE OR OTHER WRONGFUL CONDUCT OR ANY OTHER LEGAL THEORY, WILL NOT BE GREATER THAN THE AMOUNT YOU HAVE PAID TO GET THE RELOADED[®] BOARD.

DISCLAIMER

THE MATERIAL IN THIS DOCUMENT IS PROVIDED AS IS. THIS MEANS THAT FRENCH CONNECTION PAINTBALL DISCLAIMS ALL EXPRESS AND IMPLIED WARRANTIES ABOUT THE RELOADED[®] BOARD DESCRIBED IN THE DOCUMENT. THIS INCLUDES, BUT IS NOT LIMITED TO, WARRANTIES THAT: (1) THE RELOADED[®] BOARD IS OF ANY PARTICULAR LEVEL OF QUALITY OR IS FIT FOR A PARTICULAR PURPOSE; (2) THAT THE FUNCTIONAL ELEMENTS CONTAINED IN THE RELOADED[®] BOARDS WILL BE UNINTERRUPTED OR ERROR-FREE; (3) THAT DEFECTS WILL BE CORRECTED; OR (4) THAT INFORMATION CONTAINED IN THE DOCUMENT IS ACCURATE AS OF ANY PARTICULAR DATE.

ReloadedTM Board For ShockerTM

Software version 1.5

Trade and other Marks

All products and company names mentioned in this document may be trade, service or registered marks of their respective owners. Use of any RELOADED® Logo or acronyms for commercial or non-commercial purposes without prior written consent of French Connection Paintball may constitute infringement of a registered mark.

Ownership of Materials

The information and images contained in this document is copyrighted and may not be distributed, modified, reproduced in whole or in part without the prior written permission of French Connection Paintball.

Third Companies and Products

Mention of third party products, companies and web sites in this document is for informational purposes only. French Connection Paintball assumes no responsibility with regard to the selection, performance or use of these products or vendors.

Enforcement of Intellectual property rights

French Connection Paintball actively and aggressively enforces its intellectual property rights.

Piracy

In many countries copyright law provides for severe civil and criminal penalties for the unauthorized reproduction or distribution of copyrighted material.

Feedback and Information


Any feedback you provide French Connection Paintball with shall be deemed non confidential and French Connection Paintball shall be free to use such information on an unrestricted basis.

Official Language

French is the Official Language of the French Connection Paintball and will prevail in all questions of interpretation.

Legal Contacts

If you have questions concerning the licensing or usage of French Connection Paintball marks or copyrighted materials contact French Connection Paintball by email at: reloaded@tontons-flingueurs.com



Reloaded BoardTM For ShockerTM

Software version 1.5

Personal notes:

