



8200/8200a

Cordless telephone User Guide



This telephone has been designed for ease of use. Please read the instructions and keep it handy for future reference.

If you have any problems with your phone, refer to the Help section of this User Guide.



Introduction

To your Telstra 8200 Digital Cordless Telephone/ Telstra 8200a Digital Cordless Telephone with Answering Machine

- Phonebook - lets you store up to 20 names and numbers for easy dialling.
- Calling Number Display* - lets you see who's calling. Your phone stores details of the last 10 callers in the Calls list.
- Hands-free facility allows you to talk to callers without holding the handset.
- Integrated Digital Answering Machine (8200a only)

* IMPORTANT You need to subscribe to Telstra's Calling Number Display service to be able to see the caller's number or name when called, or in the Missed and Received Calls logs. See page 32 for more details.

IMPORTANT

This equipment requires electricity to work. You will not be able to make any telephone calls when the power fails. Alternative arrangements should be made to access emergency services in times of power failure.

As a Digitally Enhanced Cordless Telecommunications (DECT) product, your Telstra 8200/8200a provides:

- Digital clarity
- Digital range
- Digital security

This User Guide provides you with all the information you need to get the most from your phone. Before you make your first call you will need to set up your phone. Follow the simple instructions on the next few pages.

Some Telstra services such as MessageBank® and Calling Number Display may attract feature and usage charges. Please visit Telstra.com for details.

Need help?

SHOULD YOU EXPERIENCE ANY OPERATIONAL DIFFICULTIES WITH YOUR TELSTRA PRODUCT PLEASE CONTACT THE TECHHELP INFORMATION LINE 1300 369 193, OR CONTACT US BY E-MAIL AT: tcpsupport@ingrammicro.com.au.

You may also find assistance in the Help section at the end of this user guide.

Hearing aid?

Please note that the Telstra 8200/8200a works by sending radio signals between the base and handset. These signals may interfere with some hearing aids, causing a humming noise

Got everything?

The package contains the following items:

- Telstra 8200 or 8200a handset
- Telstra 8200 or 8200a base unit
- AC power adapter
- Telephone line cord
- Telephone adaptor plug
- 2 rechargeable batteries
- 1 User manual

If you have purchased a Telstra 8200/8200a multi handset pack you will also have the following for each additional handset:

- Telstra 8200 or 8200a handset
- Telstra 8200 or 8200a base unit
- 2 x NiMH batteries
- AC power adaptor (for the charger)

In this guide

1	Important safety instructions	8	4	Using your phone	22
2	Installing your phone	10	4.1	Make a call	22
2.1	Connecting the base	10	4.1.1	Preparatory dialling	22
2.2	Installing and charging the batteries	11	4.1.2	Direct dialling	22
3	Getting to know your phone	12	4.1.3	Call from the phonebook	22
3.1	Overview of the handset	12	4.1.4	Call from the call list	22
3.2	Base overview	15	4.1.5	Call from the redial list	22
3.3	Base with telephone answering machine (TAM) control	16	4.1.6	Call timer	22
3.4	Display icons and symbols	18	4.2	Answer a call	23
3.5	Menu structure	19	4.3	End a call	23
3.6	Text and digit entry table	20	4.4	Adjust earpiece and handsfree volume	23
3.6.1	Latin character set	21	4.5	Mute a call	23
			4.6	To turn the ringer off	24
			4.7	Turn on the keypad lock	24
			4.8	Redial the last number	24
			4.8.1	Redial a number from the redial list	24
			4.8.2	Store a redial number into the phonebook	25

In this guide

4.8.3	Delete a redial number	25
4.8.4	Delete the entire redial list	25
4.9	Find the handset	25
4.10	Using multiple handsets	26
4.10.1	Intercom with another handset	26
4.10.2	Call all handsets	26
4.10.3	Transfer an external call to another handset	27
4.10.4	Make a 3-way conference call	27
5	Phonebook	28
5.1	Add a new phonebook entry	28
5.2	Search a phonebook entry	29
5.3	View a phonebook entry	29
5.4	Edit a phonebook entry	29
5.5	Delete a phonebook entry	30
5.6	Delete the entire private phonebook	30
5.7	Check the phonebook usage	31

6	Calling Number Display	32
6.1	View the call list	32
6.2	Store a call list number into the phonebook	33
6.3	Delete an entry in the call list	33
6.4	Delete the entire list of the call list	33
6.5	View the details of the call list entry	33
7	Flashing Message Indicator	34
7.1	Telstra Home Messages 101®	34
7.1.1	To call Telstra Home Messages 101®	34
7.2	Using Call Waiting	34
7.2.1	To answer an incoming call whilst you are on the phone	35
7.3	3-Way Chat	35
7.3.1	How to use 3-Way Chat	35

In this guide

8	Phone settings	36	8.3.7	Set the auto answer	41
8.1	Date and time settings	36	8.4	Base settings	41
8.1.1	Change the date format	36	8.4.1	Set the base ringer melody (8200a only)	41
8.1.2	Change the time format	36	8.4.2	Set the ringer volume	42
8.1.3	Set the time	36	8.4.3	De-register a handset	42
8.1.4	Set the date	37	8.4.4	Change the dial mode	42
8.2	Alarm settings	37	8.4.5	Change the system pin code	43
8.2.1	Turn on/off the alarm	38	8.5	Registration	44
8.2.2	Set the alarm time (if the alarm is set to be on)	38	8.6	Reset your phone	44
8.3	Handset settings	39			
8.3.1	Set the ringer melody for internal calls	39	9	Answering machine (Telstra 8200a only)	45
8.3.2	Set the ringer melody for external calls	39	9.1	Turn on/off the answering machine	45
8.3.3	Set the ringer volume	40	9.2	Listen to the messages in the answering machine	46
8.3.4	Set alert tones	40	9.3	Delete all messages in the answering machine	48
8.3.5	Rename the handset	40	9.4	Record memo	49
8.3.6	Choose the information to be displayed in idle	41	9.5	Answering machine settings	49

In this guide

9.5.1	Set the answer mode	49
9.5.2	Record your own outgoing message (ogm)	50
9.5.3	Playback and delete the outgoing message (ogm)	51
9.5.3.1	Playback the ogm	51
9.5.3.2	Delete the personalised ogm	51
9.5.4	Set the answer delay	52
9.5.5	Set the recording time of incoming message	52
9.5.6	Turn on or off the base screening	53
9.5.7	Change the compression rate	53
9.5.8	Activate remote access	53
9.5.8.1	Change the 4-digit remote access pin	54
9.5.8.2	Activate or deactivate the remote access	54

9.5.8.3	Access your answering machine remotely	55
9.5.9	Call screening	56
10	Help	57
11	General Information	59
11.1	Replacing the handset batteries	59
11.2	Safety	59
11.3	Cleaning	60
11.4	Environmental	60
11.5	Telstra accessories and replacement items	61
11.6	How many telephones can you have?	61
12	Product warranty & Customer service	62

1 Important safety instructions

When using your telephone equipment, basic safety precautions should always be followed to reduce the risk of fire, electric shock and injury, including the following:



- 1 Read and understand all the instructions.
- 2 Follow all warnings and instructions marked on the product.
- 3 Unplug this product from the wall outlet before cleaning. Do not use liquid cleaners or aerosol cleaners. Use a damp cloth for cleaning.
- 4 Do not use this product near water (for example, near a bath tub, kitchen sink, swimming pool).
- 5 Do not overload wall outlets and extension cords as this can result in the risk of fire or electric shock.
- 6 Unplug this product from the wall outlet and contact TechHelp on 1300 369 193 under the following conditions:
 - When the power supply cord or plug is damaged or frayed.
 - If the product does not operate normally by following the operating instructions.
 - If the product has been dropped and the outer casing has been damaged.
 - If the product exhibits a distinct change in performance.


Important safety instructions

- 7 Avoid using a telephone (other than a cordless type) during an electrical storm. There may be a remote risk of electric shock from lightning.
- 8 Do not use the telephone to report a gas leak in the vicinity of the leak.
- 9 Use only the supplied NiMH (Nickel Metal Hydride) batteries. The operation periods for the handsets are only applicable with the default battery capacities
- 10 The use of other battery types or non-rechargeable batteries/primary cells can be dangerous. These may cause interference and/or unit damage. The manufacturer will not be held liable for damage arising from such non-compliance.
- 11 Use only the AC power adaptors supplied with this product. Please contact TechHelp on 1300 369 193 for replacement adaptors.
- 12 Please note the correct polarity while inserting the batteries.
- 13 Do not immerse batteries in water, do not place in fire.


2 Installing your phone

2.1 Connecting the base

- 1 Plug the power supply  and line cord  into the base .
- 2 Plug the power supply and line cord into the respective wall sockets.
- 3 Always use the cables provided in the box.




8200/8200a Extension Charger




2.2 Installing and charging the batteries

- 1 Slide open the battery compartment cover.
- 2 Place the 2 batteries as indicated. Note the polarity of the batteries.
- 3 Slide the battery compartment cover back until it clicks into place.
- 4 Put the handset on the base and charge for at least **14 hours** for the first time. A beep indicates that the handset is properly placed on the base or charger.

Use only the power pack provided for the base
Use only 500mAh Nickel Metal Hydride (NiMH)
rechargeable batteries.



3 Getting to know your phone



3.1 Overview of the handset

1. LEFT SOFT KEY (MENU/OK)

In idle mode:

Press to access the main menu

In sub-menu mode:

Press to confirm selection shown on-screen

During a call:

Press to access Intercom/ Phonebook/ Redial List/ Call List

2. RIGHT SOFT KEY (CLEAR/BACK/MUTE/INTERCOM)

In main menu mode:

Press to go back to idle screen

In sub-menu mode:

Press to go back to previous level

In sub-menu mode:

Press and hold to go back to idle screen

In editing/predialling mode:

Press to clear a character/digit

In editing/predialling mode:

Press and hold to delete all the characters/digits

During a call:

Press to mute/unmute the microphone

In idle mode:

Press to use the intercom to contact another handset

3. UP

In idle mode:

Press to access the call list

In menu mode:

Press to scroll up the menu items

In Phonebook list/Redial list/

Call List:

Press to scroll up the list

During a call:

Press to increase the volume

In ringing:

Press to increase the ringer volume

4. DOWN

In idle mode:

Press to access the redial list

In menu mode:

Press to scroll down the menu items

In Phonebook list/Redial list/

Call List:

Press to scroll down the list

During a call:

Press to decrease the volume

In ringing:

Press to decrease the ringer volume

5. TALK ON

In idle/predialling mode:

Press to make a call

In Redial list/Call List/

Phonebook entry:

Press to make a call to the selected entry in the list

During ringing:

Press to answer a call

6. TALK OFF

During a call:

Press to end a call and go back to idle screen

In menu/editing mode:

Press to go back to previous menu

In menu/editing mode:

Press and hold to go back to idle screen

In idle mode:

Press and hold to power off the handset

In idle mode (when the handset is powered off:)

Press and hold to power on the handset

7. ALPHANUMERIC KEYPAD,

*** (STAR), # (HASH)**

Press to insert a digit/
character/*/#

1 *key in idle mode:*

Press *and hold* to access the
Telstra Home Messages 101®
or MessageBank®

2 *Press and hold key during
a conversation to answer Call-
Waiting.*

3 *Press and hold key to
use the Telstra 3-Way-Chat
feature.*

***** *key in idle mode:*
Press *and hold* to enable or
disable the keypad lock

*key in idle mode:*
Press *and hold* to turn on/off
the ringer

0 *key in idle/predialling/
number editing mode:*

Press *and hold* to insert a
pause

*key in Call List mode:*
Press to review caller's
number if applicable

8. SPEAKERPHONE

During a call:

Press to turn on/off the
speakerphone.

*In Idle mode/predialling mode/
Redial list/Call List/Phonebook
entry:*

Press to make a call with
speakerphone

During ringing:

Press to answer a call with
speakerphone

9. PHONEBOOK

In idle mode:

Press to access the phonebook
list

10. RECALL

In idle/predialling mode:

Press to dial a recall

During a call:

Press to dial a recall

11. MICROPHONE


12. EARPIECE


3.2 Base overview

1. PAGE

Press Page on the base to page your handset. The handset will ring for approximately 60 seconds.

2. CHARGING CRADLE





3.3 Base with telephone answering machine (TAM)

1. PAGE

Press Page on the base to page your handset. The handset will ring for approximately 60 seconds.

2. CHARGING CRADLE

3. TAM ON/OFF

Press to turn on the answering machine. Press again to turn off the answering machine

4. PLAY

Press to play the message

5. STOP

Press to stop the

message playback

6. SKIP BACKWARD

Press to repeat playing the current message from the beginning. Press twice to skip backward to the previous message

7. SKIP FORWARD

Press to skip the current message and play the next message

8. VOLUME DOWN (-)

Decrease speaker volume during message playback

9. VOLUME UP (+)

Increase speaker volume during message playback

10. DELETE

Press once to delete the message during playback. Press *and hold* to delete all the messages

Note: New voice messages will not be deleted.

11. 7-Segment LED DISPLAY

-- When answering machine is OFF

00 *Steadily ON:* No voice messages in TAM

XX *Flash:* There are XX new voice messages received where XX is from 01 to 59

Steadily ON: Playing the current XX incoming message

XX/FF

Flashing XX alternatively with FF: There are XX new voice messages received where XX is from 01 to 59 and the TAM memory is full

Flashing FF only: TAM is full and only old voice messages are being stored in the TAM memory

--/XX

Flashing XX alternatively with --: Time is not set and there are XX new voice messages received where XX is from 01 to 59

Flashing – only: Time is not set and there are only old voice messages in the TAM memory

YY

Steadily ON: There are YY old voice messages (no new voice messages)

A1/A2

Steadily ON: Playing the current outgoing message (OGM where A1, A2 are the OGM of Answer & Record and Answer Only mode respectively)

XX/AN

Flashing XX alternatively with An: XX incoming message is now recording

LA


Flashing: Remote access is in progress





















LX

Steadily ON: Indicates the current volume level where X is from 1 to 8


3.4 Display icons and symbols


The LCD display gives you information on the current status of the telephone.



-  Scroll up / down the menu items / Phonebook list / Redial list / Call List.
-  Steady when the handset is in range of the base. Flashes when out of range of the base or not registered to the base.
-  Steady when an intercom is in progress. Flashes when there is an incoming internal call.
-  Indicates a call is in progress.
-  Indicates that handsfree is being used.
-  Indicates that the ringer is switched off.
-  Steady when an alarm is set. Flashes when the alarm time set before reaches.
-  Indicates that the keypad is locked.
-  Indicates when the battery is fully charged. Flashes when the unit is charging.
-  Indicates when the battery needs charging. Flashes when low battery power level is detected.
-  Indicates when there are more characters before the text currently displayed.
-  Indicates when there are more characters after the text currently displayed.
-  (MENU) Press this symbol to select more menu options if applicable.
-  OK Press this symbol to confirm the current selection if applicable.
-  (INT) Press this symbol to conduct Intercom call when idle.
-  (BACK) Press this symbol to go back to previous menu level or cancel the current action if applicable.
-  Press this symbol to clear a character or stop the alarm if applicable, press to mute / unmute during a call.
-  Indicates when there are received new messages on your Telstra Home Messages 101® or MessageBank® service.
-  Indicates the Calls list has an unanswered call.
-  (for Telstra 8200a only) Indicates when the telephone answering machine is turned on. Flashes when new messages are received.

3.5 Menu structure

In idle mode, press  OK to access the Call List menu. Refer to the following for the menu structure.





3.6 Text and digit entry table

The following table shows you where each letter and punctuation character can be found. A character table will be used when the corresponding menu language is selected. This will be helpful when storing a name in the phonebook and renaming your handset.

In editing mode, a cursor is displayed to indicate the current text entry position. It is positioned at the right of the last character entered.

Writing tips:

1. Once a character is selected, the cursor will move to the next position after a short pause.
2. You can move the cursor within the text by  or  to amend the text entry.
3. Press **C** to delete the last character.
4. Press *and hold* **C** to delete the entire text string.

3.6.1 Character set

Alphanumeric editing

(For phonebook name editing and renaming handset)

Number editing




(For phone number editing, date/time editing)

Number of presses											
Key	1st	2nd	3rd	4th	5th	6th	7th	8th	9th	10th	
1	space	-	1								1
2	A	B	C	2							2
3	D	E	F	3							3
4	G	H	I	4							4
5	J	K	L	5							5
6	M	N	O	6							6
7	P	Q	R	S	7						7
8	T	U	V	8							8
9	W	X	Y	Z	9						9
0	0										0, P (Pause)
*	*	?	/	\	(*
#	#	'	,	-	.	&					#



4 Using your phone

4.1 Make a call









4.1.1 Preparatory dialling

Enter the phone number and press  or  to dial the number. Press  to clear the entry.









4.1.2 Direct dialling

Press  or  to access the line and enter the phone number.






4.1.3 Call from the phonebook

Press  to access the phonebook and press  or  to select the desired phonebook entry. Press  or  to dial out to the selected phonebook entry. Alternatively, press  OK then  or  to access the phonebook to get the desired phonebook entry.

4.1.4 Call from the call list

Press  to access the Call List and press  or  to select the desired Call List entry. Press  or  to dial out to the selected Call List entry. Alternatively, press  OK then  or  to access the Call List from the main menu.

4.1.5 Call from the redial list



Press  to access the redial list and press  or  to select the desired redial number. Press  or  to dial out to the selected redial number.

4.1.6 Call timer

Your handset automatically times the duration of every call. The call timer will display for a few seconds after the call has ended. It is shown in hours, minutes and seconds format (HH:MM:SS).

4.2 Answer a call


If the handset is not on the charging cradle:

When the phone rings, press  or  to answer a call.

If the handset is on the charging cradle or the base and if **AUTO ANSWER** is set to ON:

When the phone rings, pick up the handset to answer a call.

4.3 End a call

During a call connection, press  to end the call.



OR

Put the handset on the base to end the call.

4.4 Adjust earpiece and handsfree volume

There are 5 volume levels (VOLUME 1 to VOLUME 5) to choose from for each of earpiece and handsfree volume.



During a call:

Press  or  to select volume 1-5. The current setting is shown on-screen. When you end the call, the setting will remain at the last selected level.


4.5 Mute a call

You can talk to someone nearby without letting the caller hear you during a call.



During a call:

Press  to mute the microphone and MUTED will display on the screen. Your caller cannot hear you. Press  again to unmute the microphone.

4.6 To turn the ringer off

In idle, press *and hold*  to turn off the handset ringer. The  icon is displayed on the screen.







4.7 Turn on the keypad lock

In idle, press *and hold*  to turn on the keypad lock. The  icon is displayed on the screen.

4.8 Redial the last number






You can redial up to 5 of the last numbers called. If you have stored a name in the phonebook to go with the number, the name will be displayed instead. The most recent number dialled will display at the top of the redial list.

4.8.1 Redial a number from the redial list




1. In idle mode, press  to access the redial list.
If redial entry is shown with a name, press  to view the number.
2. Press  or  to browse the redial list.
3. Press  or  to dial to the selected redial number.

Note: If there are no numbers in the redial list, the display shows **EMPTY**




4.8.2 Store a redial number into the phonebook

1. Follow Steps 1 and 2 in section 4.8.1.
2. Press  and  or  to select ADD TO PB
3. Press **OK** to enter the name.
4. Press **OK** to store the redial number into the phonebook.
5. Press **OK** to select phonebook melody.
6. Press  or  to browse the melody list.
The chosen melody will be played when browsing the melody list.
7. Press **OK** to confirm.







4.8.3 Delete a redial number

1. Follow Steps 1 and 2 in section 4.8.1.
2. Press  and  or  to select DELETE
3. Press **OK** to confirm.

4.8.4 Delete the entire redial list

1. Follow Steps 1 and 2 in section 4.8.1.
2. Press  and  or  to select DELETE ALL
3. Press **OK** to confirm.
4. Press **OK** to confirm again.


4.9 Find the handset

You can locate the handset by pressing  on the base . All the handsets registered to the base will produce the paging tone and PAGING is displayed on the screen. You can stop the paging by pressing  /  /  /  on any handset or  on the base again.


Note: If there is an incoming call during paging, paging will cease and the phone will ring with the incoming call instead


4.10 Using multiple handsets


This feature is only applicable when you have purchased a multi handset pack. It allows you to make internal calls, transfer external calls from one handset to another handset and make conference calls. If the called handset is not answered within 60 seconds, the called handset will stop ringing and the calling handset will return to standby mode.

Note: If only one handset is registered to the base, pressing  will display NOT POSSIBLE



4.10.1 Intercom with another handset

1. In idle mode, press  and the available handsets will display except the calling handset.
2. Enter the desired handset number with which to connect via intercom.

3. When the called handset rings press  on the called handset to establish the internal call.


Note: If only two handsets are registered to the base pressing  on one handset will connect to the other handset immediately.

4.10.2 Call all handsets

1. In idle mode, press  and all registered handsets will display.
2. Press  to ring to all registered handsets.
3. The first handset to answer will intercom with the calling handset



4.10.3 Transfer an external call to another handset

During an external call:

1. Press  and  or  to select INTERCOM
2. Press **OK** to select the second handset with

which to connect via intercom. If you have more than 2 handsets, the available handset numbers will be displayed on the screen.


To intercom a specific handset, press the handset number on the keypad. If you press 9 on the keypad all handsets will ring.

3. The external call is put on hold automatically and the called handset rings.
4. Press  on the called handset to establish an internal call.
5. Press  on the calling handset or put the calling handset on the charging cradle to end the current call with the external party on that handset.
6. The external call is transferred to the called handset.

4.10.4 Make a 3-way conference call

The conference call feature allows one external call to be shared over two handsets using intercom mode. The three parties can share the conversation and no network subscription is required.

During an external call:

1. Follow Steps 1 to 4 in section 4.10.3.
2. Press *and hold*  on the calling handset to establish the conference call.


Any handset that hangs up during a conference call will leave the other handset still connected to the external call.

5 Phonebook




Your phone can store up to 20 phonebook entries with names and numbers. Each phonebook entry can have a maximum of 20 digits for the phone number and 12 characters for the name. You can also select different ringtones for your phonebook entries. Phonebook entries are stored alphabetically by name.




5.1 Add a new phonebook entry

In idle:

1. Press  to access the phonebook.




OR

Press  and  or  to select **PHONEBOOK** main menu item and then press **OK** to access the phonebook.

2. Press  to select **ADD**.
3. Press **OK** to enter the name.
4. Press **OK** to enter the number.
5. Press **OK** and  or  to select the desired ringtone for your phonebook entry.
6. Press **OK** to store the phonebook entry.









5.2 Search a phonebook entry

In idle:



1. Press  to access the phonebook.
2. Enter the first character of the name using the keypad letters, eg press 5 once for names starting with J, twice for names starting with K etc, or
3. Press  or  to select the desired phonebook entry.

5.3 View a phonebook entry

In idle:









1. Press  to access the phonebook.
2. Press  or  to select the desired phonebook entry.
3. Press  and  or  to select VIEW.
4. Press **OK** and  or  to review the name, number and melody of the selected

phonebook entry.

Note: If number is more than 12 digits, press  or  to view the remaining digits.







5.4 Edit a phonebook entry

In idle:







1. Press  to access the phonebook.
2. Press  or  to select the desired phonebook entry.
3. Press  and  or  to select EDIT
4. Press **OK** and the current contents of the selected phonebook entry will display.
5. Edit the name (if applicable) and press **OK**
6. Edit the number (if applicable) and press **OK**
7. Press  or  to select the ringtone (if applicable) and press **OK** to confirm.

5.5 Delete a phonebook entry

In idle:





1. Press  to access the phonebook.
2. Press  or  to select the desired phonebook entry.
3. Press  and  or  to select **DELETE**.
4. Press **OK** to confirm.

5.6 Delete the entire private phonebook

1. Press  to access the phonebook.
2. Press  or  to select the desired phonebook entry.
3. Press  and  or  to select **DELETE ALL**.
4. Press **OK** to confirm.
5. Press **OK** to re-confirm.

5.7 Check the phonebook usage

You can check how many phonebook entries have been occupied in your phone and how many phonebook entries are available for you to store in the phonebook.

1. Press  to access the phonebook.
2. Press  and  or  to select PB STATUS
3. Press **OK** to confirm.

6 Calling Number Display








If you have subscribed to Telstra's Calling Number Display*, and provided the caller's number is not blocked, the number (or name if stored in the phonebook) will be displayed when the phone is ringing. With some incoming calls, if the telephone number is not available, the handset may display one of the following explanations:

- UNAVAILABLE - the number is not available
- PRIVATE - the caller has withheld their number
- PAYPHONE - the caller is ringing from a payphone
- MOBILE - The incoming call is from a mobile telephone within Australia






* Call features and charges may apply.

6.1 View the call list




All received calls are saved in the Call List with the latest call placed at the top of the list. When the call list is full, the oldest call will be replaced by a new call. An unanswered call which has not been read is marked with a ★ at the centre of the bottom line of the display.

1. Press  to access the call list.
OR Press  and  or  to select CALL LIST
2. Press  or  to select the desired entry.
3. Press  to view the caller's number if applicable.




6.2 Store a call list number into the phonebook

1. Follow Steps 1 and 2 in Section 6.1.
2. Press  and  or  to select **ADD TO PB**
3. Press **OK** to enter the name.
4. Press **OK** and the selected call list number is displayed.
5. Edit the number if necessary.
6. Press **OK** and  or  to select the melody.
7. Press **OK** to confirm.




6.3 Delete an entry in the call list

1. Follow Steps 1 and 2 in Section 6.1.
2. Press  and  or  to select **DELETE**
3. Press **OK** to confirm.

6.4 Delete the entire list of the call list



1. Follow Steps 1 and 2 in Section 6.1.
2. Press  and  or  to select **DELETE ALL**
3. Press **OK** to confirm.
4. Press **OK** to re-confirm.

6.5 View the details of the call list entry

1. Follow Steps 1 and 2 in Section 6.1.
2. Press  and  or  to select **DETAILS**
3. Press **OK** to display the date and time of the selected call list entry.
4. Press **OK** to go back to previous screen.

7 Flashing Message Indicator

The Telstra 8200/8200a is designed to provide visual indication when a new message is left in your Telstra Home Messages 101[®] or MessageBank[®] service. To arrange connection of the Flashing Message Indicator service, simply call Telstra on 13 2200.

When a new message is left, an  icon will be displayed on the handset. After you have listened to your message(s) the  icon will disappear.


7.1 Telstra Home Messages 101[®]

You can get messages from your Telstra fixed home phone when you are away from the phone, busy on another call or using the Internet. Callers will hear a standard greeting inviting them to leave a message. To access Telstra Home Messages 101[®], you can:



7.1.1 To call Telstra Home Messages 101[®]

Dial 101.

OR

While the handset is in standby press *and hold* the  key. The handset will dial 125101.



OR

Press  and then press *and hold* the  key. The handset will dial 125101.

7.2 Using Call Waiting

Call Waiting tells you if a new caller is trying to contact you when you are already on the phone. A discreet tone alerts you to the new caller, so you can answer your second incoming call by putting the first caller on hold.

7.2.1 To answer an incoming call whilst you are on the phone

1. Press *and hold* the  button. Your first caller is put on hold and you can talk to your second caller.
2. To revert back to the original caller, press *and hold* the  button again.



NOTE: if you have subscribed to Telstra Calling Number Display, the second caller's number will appear on the handset display when they call

7.3 3-Way Chat

This service is available on most lines ready for you to use! If you are already on a call, you can add another person and then have a 3-Way Chat.

7.3.1 How to use 3-Way Chat

To put existing call on hold and make a new call then to 3-Way Chat

1. Press  while in the first call
2. Dial the second phone number
3. Press *and hold*  to connect the 3-way chat

To split a 3-Way Chat or switch between callers

1. Press *and hold*  while in the call










8 Phone settings

Your Telstra 8200/8200a comes with a choice of settings so that you can personalise your phone the way you like it to work.










8.1 Date and time settings

You will need to set the correct time and date so that you know when Answering Machine messages were received (8200a only). If you have Telstra Calling Number Display, the date/time will be set automatically after an incoming call.








8.1.1 Change the date format

1. Press  and  or  to select HS SETTINGS
2. Press **OK** and  or  to select DATE & TIME
3. Press **OK** and  or  to select DATE FORMAT
4. Press  or  to select your desired date format (DD-MM-YY or MM-DD-YY).
5. Press **OK** to confirm.

8.1.2 Change the time format








1. Press  and  or  to select HS SETTINGS
2. Press **OK** and  or  to select DATE & TIME
3. Press **OK** and  or  to select TIME FORMAT
4. Press  or  to select your desired time format (12 HR or 24 HR).
5. Press **OK** to confirm.

8.1.3 Set the time

1. Press  and  or  to select HS SETTINGS
2. Press **OK** and  or  to select DATE & TIME
3. Press **OK** and  or  to select SET TIME
4. Press **OK** to enter the time information. The time entered will be in the format you set in Section 8.1.2
5. Press **OK** to confirm.




Note: If time has been set before, the current time will display, otherwise, HH:MM will display.

8.1.4 Set the date



1. Press  and  or  to select HS SETTINGS
2. Press **OK** and  or  to select DATE & TIME
3. Press **OK** and  or  to select SET DATE
4. Press **OK** to enter the date information. The date entered will be in the format you set in Section 8.1.1.
5. Press **OK** to confirm.

Note: If date has been set before, the current date will display, otherwise, DD-MM-YY will display.








8.2 Alarm settings

When an alarm is set, the  displays on the screen. When the alarm time is reached, the  and **ALARM ON** will flash on the screen and the alarm melody will ring for 45 seconds. You can press any key to disable the alarm. If snooze function is activated, the alarm will sound again at the end of the snooze period of seven minutes. You can also press *and hold*  to terminate the snooze function.

Note:



- The alarm will turn off when the alarm time is reached or by pressing any key while the alarm is sounding (even if the handset keypad is locked.)
- The alarm volume level is the same as the settings of the handset ringer volume. If the handset ringer is set to VOLUME OFF, the alarm will sound at VOLUME 1 level.
- During an external call or internal call, if an alarm is set and when the alarm time is reached, the  and ALARM ON will flash on screen. An alarm tone will be emitted from the earpiece to notify user the alarm time is reached. Once user presses any key or presses and holds  to disable the alarm, it will revert to the call duration screen.
- During paging or ringing, the alarm will not sound when the alarm time is reached. However, if snooze function is enabled, the alarm will sound again at the end of the snooze period provided that it is not ringing or in paging mode at the end of the snooze period.

8.2.1 Turn on/off the alarm

- Press  and  or  to select HS SETTINGS
- Press **OK** and  or  to select ALARM
- Press **OK** and  or  to select ON/OFF
- Press **OK** to confirm.










Note: If ON is selected, you will be asked to set the alarm time in accordance with paragraph 8.2.2.

8.2.2 Set the alarm time (if the alarm is set to be on)

- Follow Steps 1 to 4 in Section 8.2.1.
- Enter the alarm time in the time format you set in Section 8.1.2
- Press **OK** to set the snooze function.
- Press **OK** and  or  to select ON/OFF
- Press **OK** to confirm.










8.3 Handset settings

8.3.1 Set the ringer melody for internal calls

1. Press  and  or  to select HS SETTINGS
2. Press **OK** and  or  to select RING SETUP
3. Press **OK** and  or  to select INT RING
4. Press **OK** and  or  to select the desired ringer melody (10 melodies are available for internal calls).
5. Press **OK** to confirm.











Note: Ringer melodies will be played when the melody is highlighted while browsing the melody list.

8.3.2 Set the ringer melody for external calls

1. Press  and  or  to select HS SETTINGS
2. Press **OK** and  or  to select RING SETUP
3. Press **OK** and  or  to select EXT RING
4. Press **OK** and  or  to select the desired ringer melody (10 melodies are available for external calls).
5. Press **OK** to confirm..

Note: Ringer melodies will be played when the melody is highlighted while browsing the melody list.

8.3.3 Set the ringer volume










1. Press  and  or  to select HS SETTINGS
 2. Press **OK** and  or  to select RING SETUP
 3. Press **OK** and  or  to select RING VOLUME
 4. Press **OK** and  or  to select the desired ringer volume (6 ringer volume levels including VOLUME OFF are available).
- If VOLUME OFF is selected,  will display.
5. Press **OK** to confirm.

Note: Ringtone will be played at the highlighted ringer volume while browsing the volume list.






8.3.4 Set alert tones

A single beep is emitted when you press a key. You can turn on or off the key tone. You can also turn on the alert tones when low battery and out of range are detected. Low battery tone will also be emitted while you are talking

with the phone to alert you that you need to charge up your battery








1. Press  and  or  to select HS SETTINGS
2. Press **OK** and  or  to select TONE SETUP
3. Press **OK** and  or  to select KEY TONE/
BATTERY TONE/OUT OF RANGE.
4. Press **OK** and  or  to turn on or off these tones.
5. Press **OK** to confirm.

8.3.5 Rename the handset

1. Press  and  or  to select HS SETTINGS
2. Press **OK** and  or  to select RENAME HS
3. Press **OK** and enter the name of your handset.
4. Press **OK** to confirm.








8.3.6 Choose the information to be displayed in idle

You can choose to display time or handset name in your idle screen.

1. Press  and  or  to select HS SETTINGS
2. Press **OK** and  or  to select HS DISPLAY
3. Press **OK** and  or  to select HANDSET NAME or TIME
4. Press **OK** to confirm.

8.3.7 Set the auto answer








If you turn on the Auto Answer, you can pick up the call from the cradle without pressing any key.

1. Press  and  or  to select HS SETTINGS
2. Press **OK** and  or  to select AUTO ANSWER
3. Press **OK** and  or  to turn on or off the auto answer feature.
4. Press **OK** to confirm.

8.4 Base settings








The current settings are marked with an asterisk in the relevant menu, which is displayed at the right-hand side of the menu item.

8.4.1 Set the base ringer melody (8200a only)

1. Press  and  or  to select BS SETTINGS
2. Press **OK** and  or  to select BS RINGER
3. Press **OK** and  or  to select the desired ringer melody (5 ringer melodies are available for the base ringer).
4. Press **OK** to confirm.


Note: Ringer melodies will be played when the melody is highlighted while browsing the melody list.

8.4.2 Set the ringer volume (8200a only)










1. Press  and  or  to select BS SETTINGS
2. Press **OK** and  or  to select RING VOLUME
3. Press **OK** and  or  to select the desired ringer volume (6 ringer volume levels including VOLUME OFF are available).
4. Press **OK** to confirm.

Note: Ringtones will be played at the highlighted ringer volume while browsing the volume list.

8.4.3 De-register a handset

You are requested to enter the 4-digit PIN in order to de-register a handset from the base . The  icon on the de-registered handset will blink.

Note: You cannot de-register the handset that you are currently using.

1. Press  and  or  to select BS SETTINGS
2. Press **OK** and  or  to select DELETE HS
3. Press **OK** and  or  and you are requested to enter the 4-digit system PIN.
4. Enter the 4-digit system PIN.
5. Press **OK** and a list of registered handsets is displayed.
6. Press  or  to select one of the handsets that you want to de-register.
7. Press **OK** to confirm.

8.4.4 Change the Recall(Flash) time

Short=100mS.






Medium=270mS.

Long=600mS.

For the Telstra network, always leave at the default 100mS (Short) setting.


8.4.5 Change the system pin code





A 4-digit system PIN code is used for changing the system settings of the base . It is used to protect your phone against unauthorised use. The default system PIN code is 0000.



1. Press  and  or  to select BS SETTINGS
2. Press **OK** and  or  to select CHANGE PIN
3. Press **OK** and enter the old system PIN.
4. Press **OK** and enter the new system PIN.
5. Press **OK** and enter the new system PIN again.
6. Press **OK** to confirm.

Note: If the new PIN entered in Step 5 is not matched with the new system PIN entered in Step 4, user will be prompted to enter the valid system PIN again in Step 4.

8.5 Registration




Your handset and base are pre-registered. If for some reason, the handset is not registered to the base ( flashes even when the handset is near the base), register your handset according to the following procedure.

1. Press *and hold*  on the base for about five seconds. The base will be entered into registration mode.
2. Press  and  or  to select REGISTRATION.
3. Press **OK** and enter the 4-digit system PIN.
4. Press **OK** to confirm.

If the handset registration is successful, you will hear a confirmation tone and the  will stop flashing. The handset will automatically be allocated the next available handset number. This handset number is shown in the handset display in standby mode. If the handset registration is unsuccessful, the  will still flash.

8.6 Reset your phone

You can reset your phone to the default settings. After reset, all your personal settings and call list entries will be deleted, but your phonebook remains unchanged.

1. Press  and  or  to select **DEFAULT**.
2. Press **OK** and enter the 4-digit system PIN.
3. Press **OK** to confirm.
4. Press **OK** to re-confirm.

9 Answering machine (Telstra 8200a only)



Your Telstra 8200a includes a telephone answering machine that records unanswered calls when it is switched on. The LED message counter (two digits) seven segment display on the base will show the number of the messages when the answering machine is on. The answering machine can store up to 59 messages within the maximum recording time of approximately 15 minutes. As well as recording incoming messages, you can record memos for other users of your phone. If the answering machine memory is full, the handset will display TAM FULL and the handset name alternatively in standby, or display TAM FULL and the date/time information in standby which depends on which option has been selected in the handset setup.


Note: Your answering machine is designed to answer calls after 14 rings when it is switched off. This is to enable you to operate the remote access functions of your answering machine in the event your answering machine is switched off.

9.1 Turn on/off the answering machine








You can turn the answering machine on or off through the base or handset. When the answering machine is set to ON, calls will be answered after the set answer delay and the caller can then leave you a message. When the answering machine is set to OFF, calls will be answered after 14 rings and the answer only message will be played to your callers. They will not be able to leave you a message.



Through the base:

1. Press  on the base .
 - If answering machine is set to ON,  displays on the handset LCD and the 7-segment LED on the base will display the number of incoming messages.


- If answering machine is set to OFF,  will disappear from the handset screen and the 7-segment LED on the base will display --.

Through the handset:




1. Press  and  or  to select ANS. MACHINE
2. Press **OK** and  or  to select TAM ON/OFF
3. Press **OK** and  or  to select ON OR OFF
4. Press **OK** to confirm.

- If answering machine is set to ON,  displays on the handset screen and the 7-segment LED on the base will display the number of incoming messages.
- If answering machine is set to OFF,  will disappear from the handset screen and the 7-segment LED on the base will display --.


9.2 Listen to the messages in the answering machine

When new messages are recorded on the answering machine,  flashes on the handset display and the message counter on the base flashes with the number of new messages in the answering machine until all the new messages are played. Old messages will be played after all new messages are played completely. The message counter LED stays steady to indicate the number of old messages stored in the answering machine.






Listen to new messages through the base:

1. Press  on the base .
2. The new messages are played from the loudspeaker on the base in the sequence they are recorded.
3. Press  or  to increase or decrease the volume during message playback respectively.

Answering machine (Telstra 8200a only)



Note: If there are no new messages, 00 will display steadily in the message counter on the base. Pressing  will have no effect and an alert tone will be emitted.

Listen to new messages through the handset:


1. Press  and  or  to select ANS. MACHINE
2. Press **OK** and  or  to select MSG PLAYBACK
3. Press **OK** to start message playback and the screen displays the date and time information of the message received.

Note: ★ is placed at the centre of the bottom of the LCD to indicate that it is a new message. If this message has been read or listened, the ★ will disappear and will be reflected next time when you listen to this message again.

Note: if there are no new messages, 00--00 00--00 is displayed briefly and you will be automatically returned to the ANS. MACHINE menu.

4. During message playback, press  or  to increase or decrease the message playback volume respectively.


Note: After new message is played, the new message will be saved as an old message automatically unless it is deleted.


5. Press  to select **STOP, FORWARD, PREVIOUS, DELETE** to perform these functions during message playback.
STOP: Stop the current message playback and return to the ANS. MACHINE menu.
FORWARD: Skip to play the next message. The date and time information of the next message will display if there is a next message.
PREVIOUS: Skip to repeat playing the


current message from the beginning. The date and time information of the current message will display.

DELETE: Delete the current message and the next message will be played.


Alternatively, you can use the following shortcut keys to control different operation during message playback.

Press  to stop message playback.

Press  to skip to repeat playing the current message from the beginning.

Press  twice to skip backward to the previous message.

Press  to skip to play the next message.

Press  to delete the current message playback.

6. Press **OK** to confirm.

9.3 Delete all messages in the answering machine






Delete all messages through the base:

In idle:

1. Press *and hold*  on the base .
2. All the old messages will be deleted.

Note: New messages will not be deleted. If there are no more messages in the answering machine, 00 will display on the base .






Delete all messages through the handset:

1. Press  and  or  to select **ANS. MACHINE**.
2. Press **OK** and  or  to select **DELETE ALL**.
3. Press **OK** to confirm.
4. Press **OK** to delete all old messages.


Note: If there are no more messages in the answering machine, EMPTY will display and return back to ANS. MACHINE menu.

9.4 Record memo

You can record your memo message for another user. When you record a memo, the message counter will increase by one and the message can be played back in the same way as answering machine messages. Memo recording can still function even when the answering machine is turned off.

1. Press  and  or  to select ANS. MACHINE
2. Press **OK** and  or  to select MEMO
3. Press **OK** to start memo recording and RECORDING is displayed.
4. Press **OK** to stop memo recording and save the memo. The memo is played back.

OR








4. Press  to stop memo recording without saving and return back to ANS. MACHINE menu.



9.5 Answering machine settings

You can use the TAM SETTINGS menu through the handset to change the settings of your answering machine.

9.5.1 Set the answer mode












By default, the answer machine is set in ANS & REC mode which allows callers to leave a message. This mode can be changed to ANSWER ONLY which does not allow callers to leave a message. In that case, your callers will be prompted to call back later.


1. Press  and  or  to select ANS. MACHINE
2. Press **OK** and  or  to select TAM SETTINGS
3. Press **OK** and  or  to select ANSWER MODE

4. Press **OK** and  or  to select **ANS & REC OR ANSWER ONLY**
5. Press **OK** to confirm.

9.5.2 Record your own outgoing message (OGM)

You can record your own OGM for **ANS & REC** mode or **ANSWER ONLY** mode. When you record your own OGM, it will be used when the answering machine answers the call. If your personalised OGM is deleted, the pre-set OGM will be restored automatically.












1. Press  and  or  to select **ANS. MACHINE**
2. Press **OK** and  or  to select **TAM SETTINGS**
3. Press **OK** and  or  to select **OGM SETTINGS**
4. Press **OK** and  or  to select **ANS & REC OR ANSWER ONLY**
5. Press **OK** and  or  to select **RECORD MESS**

6. Press **OK** to start recording your personalised OGM and **RECORDING** is displayed on the screen.
7. Press **OK** to stop and save your personalised OGM. Your newly saved OGM will playback automatically. Alternatively, press  to return to previous screen without saving the personalised OGM.

9.5.3 Playback and delete the outgoing message (OGM)

You can playback your own personalised OGM or the pre-set OGM for **ANS & REC** mode or **ANSWER ONLY** mode and choose to delete your personalised OGM during playback and record a new one whenever you want. Please note the pre-set OGM cannot be deleted.

9.5.3.1 Playback the OGM

1. Press  and  or  to select **ANS. MACHINE**
2. Press **OK** and  or  to select **TAM SETTINGS**
3. Press **OK** and  or  to select **OGM SETTINGS**
4. Press **OK** and  or  to select **ANS & REC
OR ANSWER ONLY**
5. Press **OK** and  or  to select **PLAYBACK**
6. Press **OK** to playback your personalised OGM (if you have recorded a personalised OGM before) and **PLAYING OGM** will be displayed on the screen.
7. Press **OK** to stop the OGM playback and return to the previous menu.

Note: If a personalised OGM is not recorded, the pre-set OGM will be played.

9.5.3.2 Delete the personalised OGM







1. Repeat Steps 1 to 6 in Section 9.5.4.1
2. Press **C** to delete your personalised OGM and return to previous menu and the pre-set OGM will be restored automatically.

Note: If pre-set OGM is playing, you are not able to delete the pre-set OGM and thus **C** will not display. Only **OK** will display.

9.5.4 Set the answer delay








You can set the number of rings before the answering machine answers and starts playing your OGM. You can set the answering machine to answer after two to eight rings or **TIME SAVER**.



1. Press  and  or  to select **ANS. MACHINE**
2. Press **OK** and  or  to select **TAM SETTINGS**

3. Press **OK** and  or  to select **OGM SETTINGS**
4. Press **OK** and  or  to select **ANSWER DELAY** (Available options: 2 RINGS, 4 RINGS, 6 RINGS, 8 RINGS or TIME SAVER).
5. Press **OK** and  or  to select your desired answer delay.
6. Press **OK** to confirm.

9.5.5 Set the recording time of incoming message










You can set the maximum length of the recording time of the incoming messages.

1. Press  and  or  to select **ANS. MACHINE**
2. Press **OK** and  or  to select **TAM SETTINGS**
3. Press **OK** and  or  to select **RECORD TIME** (Available options: 60, 120, 180 seconds or UNLIMITED).

4. Press **OK** and  or  to select your desired recording time.
5. Press **OK** to confirm.

9.5.6 Turn on or off the base screening










You can turn the call screening on or off on the base, using the TAM SETTINGS menu on your handset.

1. Press  and  or  to select **ANS. MACHINE**
2. Press **OK** and  or  to select **TAM SETTINGS**
3. Press **OK** and  or  to select **BS SCREENING**
4. Press **OK** and  or  to select **ON OR OFF**
5. Press **OK** to confirm.

9.5.7 Change the compression rate

Three different compression rates. HIGH, MID and LOW are provided for you to select








different quality levels of recording incoming message. The lower the compression rate, the higher the recording quality level attained.

1. Press  and  or  to select **ANS. MACHINE**
2. Press **OK** and  or  to select **TAM SETTINGS**
3. Press **OK** and  or  to select **COMPRESSION**
4. Press **OK** and  or  to select your desired compression rate.
5. Press **OK** to confirm.

9.5.8 Activate remote access










Your phone lets you check your messages, or otherwise operate your answering machine, remotely. You can do this by calling the answering machine when you are away from home and entering a 4-digit remote access PIN on a tone-dialling phone. Use the 4-digit remote access PIN code to prevent unauthorised access to your answering machine.

9.5.8.1 Change the 4-digit remote access pin

1. Press  and  or  to select **ANS. MACHINE**
2. Press **OK** and  or  to select **TAM SETTINGS**
3. Press **OK** and  or  to select **CHANGE PIN**
4. Press **OK** to enter the old PIN. (Default Remote Access PIN is 0000).
5. Press **OK** to enter the New PIN.
6. Press **OK** to enter the New PIN again.
7. Press **OK** to reconfirm.


Note: If the new PIN entered in Step 6 is not matched with the new system PIN entered in Step 5, user is requested to enter the valid system PIN again in Step 5


9.5.8.2 Activate or deactivate the remote access

1. Press  and  or  to select **ANS. MACHINE**
2. Press **OK** and  or  to select **TAM SETTINGS**
3. Press **OK** and  or  to select **REMOTE ACCESS**
4. Press **OK** and  or  to select **ON** or **OFF** to turn the remote access on or off respectively.
5. Press **OK** to confirm.

9.5.8.3 Access your answering machine remotely

You can ring your Telstra 8200a from another tone-dialling phone to switch the answering machine on or off and listen to your messages remotely.


1. Place a call from a tone-dialling phone to your Telstra 8200a.
2. When the answering machine answers the calls and starts playing the OGM, press .

Note: You must enter  while the OGM is still playing, in order to access the answering machine remotely.

3. Enter the 4-digit Remote Access PIN.

Note: If the 4-digit Remote Access PIN is entered incorrectly three times consecutively, the call will be terminated automatically

4. Press the appropriate keys from the table on the next page to carry out your desired function.

Note: If your Answering Machine is switched off, it will answer after 14 rings and play the ANSWER ONLY OGM. Press , then enter the 4-digit remote access PIN (Default Remote Access PIN is 0000 to activate the remote access feature.)


When your answering machine memory is full and the answer mode is in ANS & RECORD, the answer mode will change to ANSWER ONLY automatically. It will change to ANS & RECORD mode automatically after some messages have been deleted.

9.5.9 Call screening

When the answering machine is set to ON and when there is an incoming message, the base will start call screening automatically after the preset numbers of rings of answer delay.

Answering machine (Telstra 8200a only)

Key	Function	Function
	While message is NOT playing	While message is playing
2	-	Delete the current message playback
4	-	Skip to repeat playing the current message from the beginning. Press <i>twice</i> to skip backward to the previous message.
5	Play the message	Stop the current message playback
6	-	Skip to play the next message
7	Turn on the answering machine	-
8	-	Stop the current message playback
9	Turn off the answering machine	-
*	Enter the 4-digit remote access PIN	-

At any time if you want to pick up the call, you can press  on the handset and the message recording will be stopped automatically. If the answering machine is in the process of recording, the message already stored will be saved.

No display

- The batteries may be dead. Recharge or replace the batteries - see 'Installing and charging the batteries', page 11.
- Is the handset switched off? To switch the handset on, see page 13.

No dial tone

- Check that the telephone line cord is plugged into the phone socket.
- Check that the base is connected to the mains power and switched on.

You cannot link up with the base

- Check that the base is connected to the mains power and switched on.
- Are you out of range? Move the handset closer to the base.
- Are the batteries low or flat? If so, charge the batteries or replace them if necessary.

No ring on the handset

- Check that the ringer volume is switched on, see page 40.
- Check that the base is plugged into the phone socket and that it is also connected to the mains power and switched on.

Buzzing noise on my radio, TV, computer or hearing aid

- Sometimes, your Telstra 8200/8200a and other cordless telephones can interfere with other electrical equipment if placed too close. Try moving it at least one metre away from such appliances.

The phone does not appear to be working

- Check that the base is plugged into the mains socket and switched on.
- Check that you are using the correct mains power adaptor.
- Check that the handset has slotted correctly into the base.
- Check that the handset batteries have been correctly fitted.

Interference on my cordless handset

- Move the base unit at least 1 metre away from other electrical appliances
- If you have an ADSL internet service ensure correct filters are installed to prevent interference

TecHelp line 1300 369 193

Call the Helpline:

- if you are having difficulties using your Telstra 8200/8200a
- if you need replacement batteries or mains power lead



11 General information

11.1 Replacing the handset batteries

After a time, you may find that the handset batteries are running out of charge more quickly.

This is a standard sign of wear and the batteries will need replacing. Rechargeable 550mAH Nickel Metal Hydride (NiMH) batteries can be purchased from TechHelp line on 1300 369 193 or your local electrical retailer. Slide off the battery compartment cover and remove existing batteries. Insert new batteries and replace the compartment cover.

IMPORTANT

This equipment requires electricity to work. You will not be able to make any telephone calls when the power fails.

Alternative arrangements should be made for access to emergency services in times of power failure.

11.2 Safety

- Only use the power supply included with the product. Using an unauthorised power supply will invalidate your guarantee and may damage the telephone.
- Use only the approved rechargeable batteries supplied. Spare rechargeable batteries can be purchased from TechHelp line on 1300 369 193 or your local electrical retailer.
- Do not open the handset (except to replace the handset batteries or the base). This could expose you to high voltages or other risks. Contact TechHelp for all repairs.

General information

- Radio signal transmitted between the handset and base may cause interference to hearing aids.
- It is recommended that advice from a qualified expert be sought before using this product in the vicinity of emergency/intensive care medical equipment.
- Your product may interfere with other electrical equipment, e.g. TV and radio sets, clock/ alarms and computers if placed too close. It is recommended that you place your product at least one metre away from such appliances to minimise any risk of interference.

Please note Telstra accepts no responsibility for damage caused to your Telstra 8200/8200a handset by using any other type of batteries

- Never dispose of batteries in a fire. There is a serious risk of explosion and/or the release of

highly toxic chemicals.

- Dispose of batteries as per local/state requirements.

11.3 Cleaning

Simply clean the handset and base with a damp (not wet cloth, or an anti-static wipe). Never use household polish as this will damage the product. Never use a dry cloth as this may cause a static shock.

11.4 Environmental

- Do not expose to direct sunlight.
- The product may heat up when the batteries are being recharged or during prolonged periods of use. This is normal. However, we recommend that to avoid damage you do not place the product on antique/veneered wood.
- Do not stand your product on carpets or

other surfaces, which generate fibres, or place it in locations preventing the free flow of air over its surface.

- Do not submerge any part of your product in water and do not use it in damp or humid conditions, such as bathrooms.
- Do not expose your product to fire, explosive or other hazardous conditions.
- There is a slight chance that your phone could be damaged by an electrical storm.

We recommend that you unplug the power and telephone line cord from the base for the duration of the storm.

11.5 Telstra accessories and replacement items

For a full range of accessories and replacement items for Telstra products, please call 1300 369 193.

11.6 How many telephones can you have?

All items of telephone equipment have a Ringer Equivalence Number (REN), which is used to calculate the number of items which may be connected to any other telephone line. Your Telstra 8200/8200a has a REN of 0.1. A total REN of 3 is allowed, if the total REN of 3 is exceeded, the telephone may not ring. With different telephone types there is not guarantee of ringing, even when the REN is less than 3.

12 Customer service & Product warranty

IMPORTANT

Please retain this booklet with your sales receipt as proof of the date of purchase

Customer Service

If you require assistance in operating this product please call the TechHelp Information Line on 1300 369 193 or contact us by e-mail at: tcpsupport@ingrammicro.com.au

If you are trying to access a Telstra Network Service and require assistance specifically related to the network service or would like to subscribe to the service, contact Telstra on 132200 for residential or 132000 for business.

Product Warranty

Subject to the conditions below, Telstra guarantees this product against any defect in materials or workmanship under conditions of normal use for a period of 24 months from date of purchase. The benefits conferred

by this warranty are in addition to other warranties and remedies that are implied under the Trade Practices Act and similar State and Territory laws (Statutory Rights). Subject to your Statutory Rights, the goods will not be eligible for service under this warranty if:

- a. Proof of purchase cannot be provided;
- b. The defect was caused by an accident, misuse, abuse, improper installation or operation, vermin infestation, lack of reasonable care, unauthorised modification, loss of parts, tampering or attempted repair by a person not authorised by Telstra;
- or
- c. The product has been damaged by lightning or a mains power surge.

To obtain service during the term of this warranty call the TechHelp Information Line on 1300 369 193 or contact us by e-mail at: tcpsupport@ingrammicro.com.au

If it is necessary to have the product serviced, the Customer Service Representative will inform you of the product return process.

Please ensure that:

- a. You provide proof of purchase;
- b. Your product is suitably packaged;
and
- c. You have included all components from the original purchase.

Subject to your Statutory Rights:

- a. Any claim under this warranty is limited to the cost of repair or replacement of the product; and
- b. If the goods are found to be in sound working order by the authorised service centre, you may be charged a fee for service and for any other direct costs associated with having the product delivered for service.

For your records

Date of purchase:

Place of purchase:

Serial number:

For guarantee purposes proof of purchase is required so please keep your receipt.



www.telstra.com

© COPYRIGHT 2008 Telstra Corporation Limited

This work is copyright. All rights reserved. Other than for purposes and subject to conditions prescribed under the Copyright Act, no part of it may in any form or by any means (electronic, mechanical, photo copying, microcopying, scanning, recording or otherwise) be reproduced, stored in a retrieval system or transmitted without prior permission from Telstra Corporation Limited ABN 33 051 775 556.

™ Trade Mark of Telstra Corporation Limited

® Registered Trade Mark of Telstra Corporation Limited