

ULTRA DIGITAL WIRELESS, QUAD SURVEILLANCE SYSTEM

LW2201 SERIES - QUICK START GUIDE

NOTE: AVOID INSTALLING IN A LOCATION WHICH REQUIRES THE WIRELESS SIGNAL TO PASS THROUGH CEMENT, CONCRETE AND METAL STRUCTURES. THIS WILL REDUCE THE TRANSMISSION RANGE.

Time



Under 15 Minutes*
* Installation time may vary based on application and camera location

Tools



Hand Tools

Skills - Easy



Plug & Play connections, On screen set up

Getting Started



The Digital Wireless Surveillance System comes with the following monitoring components:

- Digital Wireless Color Cameras with Sunshade*
- Camera* Stands
- Wireless Receiver
- Wireless Antenna's for cameras* and receiver
- Power Adaptors for cameras* and receiver
- RCA/BNC Adaptor
- Mounting Hardware
- Double Sided Tape for Receiver
- Instruction Manual kits

*** Number of cameras may vary by model. Check your package for specific content information.**

A. Connect the Camera

- 1** Mount camera stand to the wall
- 2** Connect the Wireless Antenna to the camera.
- 3** Secure Camera to the Stand.
- 4** Connect one end of the camera Power Adaptor to the camera and the other end to an electrical outlet.

B. Connect the Receiver to an Observation System / DVR for recording or TV for large screen viewing**

- 1** Attach the included Wireless Antenna to the receiver by screwing it on.
- 2** **OPTIONAL** Take the double sided tape supplied to securely attach the receiver to a flat surface.
- 3** View your Camera on any Observation Monitor with BNC inputs or TV with RCA inputs**.
 - 1** **Observation Monitor or DVR with BNC:** Attach included RCA/BNC adaptor to RCA cable and plug into Observation Monitor or DVR. Connect the Audio end of the RCA cable to the Audio input of the Observation Monitor or DVR.
 - 2** **TV with RCA Inputs:** Connect the RCA Video and Audio ends of the RCA Audio/Video cable to the Video and Audio inputs on your TV.

** Requires viewing/recording device with RCA Video or BNC Video input. Viewing/Recording device sold separately.
- 4** Connect one end of the Receiver Power Adaptor to the receiver and the other end to an electrical outlet.
- 5** Press the "Pair" button to scroll through the different camera views.


NOTE: Before you install a camera, carefully plan where and how it will be positioned, and where you will route the cable that connects the camera to the power adaptor. Before starting permanent installation, verify its performance by observing the image on a monitor when the camera is positioned where it will be permanently installed.

NOTE: Wireless cameras require a power source to operate.

NOTE: When adding cameras that were not included in the original box, you will need to pair up the camera with the receiver. Please refer to the Camera Pairing Section of the User Manual.

C. Adding Additional Cameras OPTIONAL

The System comes with a camera that has already been paired. The Pairing Function assigns each camera to a different channel on the Wireless Receiver (up to 4 Cameras), and is necessary for configuring additional cameras. By default, the camera included with the system appears on channels 1 on the wireless receiver. Please refer to the included Owner's Manual for detailed steps.



Pairing Button

ULTRA DIGITAL WIRELESS, QUAD SURVEILLANCE SYSTEM

LW2201 SERIES - QUICK START GUIDE

D. Receiver Function Buttons

1. Wireless Antenna: Connects to the back of the receiver.
2. Channel LEDs: When lit in green, indicates the active viewing mode.
3. VGA/QVGA* button: Press to switch between VGA and QVGA video resolutions; press and hold for several seconds to enable/disable Auto Scan.
4. Front LED: Lit in green to indicate power to the receiver.
5. Pair: Press to switch between CH1-4, Quad split-screen mode, and Auto-Scan; press and hold to pair a camera to the receiver.
6. USB Port: Not used.
7. Antenna Jack: Connection for the wireless antenna.



*VGA (Video Graphics Array) has a resolution of 640 x 480; QVGA (Quarter Video Graphics Array) has a resolution of 320 x 240.

4 Camera Digital Wireless Monitoring System



Family Room Office



Front Door



Day Care



Warehouse



Backyard

The LW2201 series product is **EXPANDABLE UP TO 4 CAMERAS***
To order additional cameras, please visit our website at www.lorexcctv.com

*NOTE: You can install additional cameras (maximum of 4 cameras). When adding cameras that were not included in the original box, you will need to pair up the cameras with the receiver. Refer to the camera pairing section of the included user manual for more details.

REGISTER NOW!
TO RECEIVE 3 MONTHS WARRANTY EXTENSION
VISIT: WWW.LOREXCCTV.COM AND CLICK ON "WARRANTY REGISTRATION"

It's all on the Web

For detailed setup information, please refer to your User's Manual. For additional information and accessory purchases, please visit our website www.lorexcctv.com/support



*Images simulated.



www.lorexcctv.com

©2008 Lorex Technology Inc.
As our product is subject to continuous improvement, Lorex Technology & subsidiaries reserve the right to modify product design, specifications, prices & warranty without notice and without incurring any obligation. E&OE