

## **6/12V Sealed Lead Acid Battery Charger**

### **User Manual**

#### **Instructions**

- 1) Read instruction before charging your battery.
- 2) Plug the detachable plug or the alligator clips into the output lead of the charger.
- 3) Insert the charger into the AC outlet.
- 4) Select the appropriate battery voltage (6V or 12V) through the voltage selector on the unit.
- 5) Connect the alligator clips to the appropriate terminals on the battery, or plug the detachable plug into the battery if applicable.
- 6) The charging process will commence.
- 7) Disconnect the charger from the AC outlet when the battery is full or not in use.
- 8) Remove the batteries from the charger.
- 9) The recommended charge current for lead acid batteries is around 10% of battery capacity.

#### **Warnings:**

- 1) For indoor use ONLY!
- 2) Do not charge non-rechargeable batteries.
- 3) Use this charger with 6V or 12V Lead Acid batteries only
- 4) During charging the battery must be placed in well ventilated area.
- 5) If the supply cord is damaged, it shall be replaced by the manufacturer, the service agent or a qualified person in order to avoid a hazard.
- 6) The appliance is not intended for use by children without supervision.
- 7) After charging, disconnect the battery charger from the supply mains. Then remove the chassis connection and then the battery connection
- 8) The battery is to be disposed of safely.
- 9) The battery terminal not connected to the chassis has to be connected first. the other connection is to be made to the chassis, remote from the battery and fuel line. The battery charger is then to be connected to the supply mains.

#### **Specifications:**

Input Voltage: 230V~50Hz 39W

Output Voltage: 6.0/12.0V  1800mA 21.6VA (max.)

Battery capacity: 6V 12Ah (max.); 12V 4.5Ah(max.)

Distributed by:  
TechBrands by Electus Distribution Pty. Ltd.  
320 Victoria Rd, Rydalmere  
NSW 2116 Australia  
Ph:1300 738 555  
Int'l: +61 2 8832 3200  
Fax: 1300 738 500

[www.techbrands.com.au](http://www.techbrands.com.au)  
Made In China