



SB1000 Digital Seebeck Effect Controller



Installation & Operators Guide

Rev E - July 2014



This document outlines the installation and setup of the MMR SB1000 Digital Seebeck Controller.



CONTENTS

About the SB1000 Digital Seebeck Controller

Specifications	3
System Requirements	3
Environmental and Safety	3

Hardware Installation

Installation	4
Changing Port Numbers in Windows	5
Front / Rear Panel Interface	6
Getting Started	7

General Operation

Main Software Suite Interface and Spooler	8
Theory of Operation	9
Stage Preparation	13
Sample Preparation	14
Experiment Setup	15
Seebeck Software Layout	16
Seebeck Software	17
Seebeck Statistics View	18
Communications Protocol	19

Troubleshooting

Troubleshooting	21
------------------------	-----------

Additional Information

Help Desk and MMR Contact Information	22
Declaration of Conformity	23



Specifications

The SB1000 Seebeck Effect controller is built on and intended to replace the proven SB100 Seebeck Controller previously offered by MMR Technologies. See Page 9 for the Theory of Operation. This device provides accurate Thermo Electric voltage readings from an MMR Seebeck Stage and Refrigerator assembly. These devices are intended for use with MMR Refrigerators only.

Voltage:	115VAC - 220VAC 50/60Hz (Dual Voltage)
Power Consumption:	30W
Heater Power:	0 - 1W
Communications:	RS232 or USB1.0 (See communications protocol)
Standalone Operation:	Yes
Weight:	5Lbs
Dimensions:	8.5"(W) x 1.5"(H) x 14.25"(D)
Environmental:	Indoor use only, 5C - 40C Temperature, 2000M Max Altitude, 80% Humidity for temperatures up to 31 °C decreasing linearly to 50 % Rel humidity at 40 °C.

System Requirements

The SB1000 Seebeck Controller is designed for use with 'MMR Technologies Suite' which must be installed prior to using this device. For custom control of this device see page 19. Please note that MMR may not support custom configurations, and in some cases the warranty may be void.

Operating System:	Windows 2000, Windows XP, Windows 7, Windows 8
Hardware:	32BIT / 64BIT INTEL or AMD Processor
Memory RAM:	2GB
Memory Hard Disk:	1GB
Peripheral Interface:	1x RS232 Serial or USB1.0.
Mac OS:	Not Supported
Linux / Unix:	Not Supported

Environmental and Safety

The SB1000 Seebeck Effect controller is built on and intended to replace the proven SB100 Seebeck Controller previously offered by MMR Technologies. Please observe the following safety warnings: do not open the enclosure, do not operate on any voltage other than specified, do not attempt to service or modify the equipment, do not operate in wet/damp locations. Warning, electrical shock, injury or death may occur if the device is opened or the earth modified. Use only the cables supplied with the device and ensure a proper Ground is present. The SB1000 should only be used as intended and should not be used for any other purpose. Any non-intended use could cause fire, loss of life, loss of equipment, and bodily harm. User assumes all risk should the equipment be misused, modified, or used in an unintended manner. Contact MMR for service requirements.




Installation

Before proceeding please ensure the MMR Technologies Software Suite is installed and the following items are present:

- 1x SB1000 Seebeck Controller
- 1x K2000 Temperature Controller (*If Temperature control is required*)
- 1x AC Power Cable
- 1x RS232 DB9 Serial Cable
- 1x USB 3FT Cable
- 1x User Manual and Software / Driver Installation CD
- 1x 4FT Refrigerator Ribbon Cable
- 1x MMR 4-Wire Kelvin Connection Breakout Board
- 1x SB1000 - K2000 Link Cable


Please connect the SB1000 as shown below. Do not connect both the RS232 Serial cable and USB cable simultaneously, these are provided as an option should you be short of spare PC ports.



Once connected and with the PC Running, you may now power up the SB1000 device. Please first ensure the AC Power switch at the rear of the unit is 'ON' (*see page 6 for further information*). Press the front button labeled 'Power' to activate the unit. If the USB cable was used, Windows will automatically assign a Comm Port. This must be identified and, if necessary, changed to be in the range of 1-16 (*See page 5 or contact your system administrator*). Please note down the assigned Comm Port Number as this will be required to communicate with the device.


Changing Port Numbers in Windows

(Note: Administrator access maybe needed, contact your IT department)




1/. Open Device Manager.
(Control Panel -> Device Manager)

2/. Select the corresponding Serial Converter Device.
(Right Click -> Left Click Properties)



3/. Click on the 'Port Settings' Tab.

4/. Click Advanced.




5/. Select a Comm Port between 1 - 16 that is not in-use by other hardware. Click OK.

(Note: On some computers you may need to disconnect (unplug) and reconnect the device to make the changes permanent)

Front / Rear Panel Interface



Note: The Power button must be held for 3 seconds to power down the unit.




*Replace fuse with 3.15A Slow Blow (IEC 127-2 or similar) ONLY.



Getting Started



Step 1 - Device ports are easily verified through the welcome screen above. Select the port number the SB1000 Seebeck Controller is connected to (*shown as present next to the SB1000*) and press 'Poll'. If the SB1000 is connected to that port and powered on, it will respond with a Device name and Version number.




If the port number is not visible try refreshing the port list by clicking the refresh icon above the "Poll" buttons. If this does not resolve the issue try restarting the computer. For further assistance contact your system administrator and finally, the MMR Helpdesk (See contact information on Page 27).

Step 2- Select 'Seebeck Experiment.' This will load the Seebeck experiment module. If there is no K2000 present, deselect "K2000" under hardware. This will disable temperature control for all Seebeck experiments. Errors will occur if K2000 remains selected when not present.

Step3 - Press 'Begin'

Main Interface




The main interface of the MMR Technologies Suite is shown above. This is the primary container for all MMR applications. The applicable items for the SB1000 Temperature Controller are shown above.

SB1000 Spooler


[Main Suite -> SB1000 -> Show Spooler]

This window shows the communications queue and response from the associated device; in this case the SB1000 Seebeck Controller. Troubleshooting is the primary use for this window. However clicking "Send" is a short cut to the 'Main Communications Console' outlined in the Software Installation Guide.




Theory of Operation

The system described below measures the thermo voltage (Seebeck Voltage) of metals and semiconductors. It also provides the user with the opportunity to study the temperature dependence of the Seebeck Voltage for different materials. Below is a picture of the Seebeck Stage which is attached to the cold stage of the MMR refrigerator.



Low Temperature Kapton Stage



High Temperature Ceramic Stage

Theory of Operation

The Seebeck Stage has two pairs of thermocouples: one of copper and a metal with known properties, and the other pair of copper and a metal with properties to be determined. One of the junctions in each pair is considered a reference junction, and the other the working or temperature modulated junction. The Stage also has a computer controlled heater, located close to the working junctions of each pair, and remote from the reference junctions. This heater is controlled by the MMR Programmable Seebeck Controller SB1000. The Seebeck stage is attached to the cold stage of an MMR refrigerator, which provides a given stable temperature for the measurement. The MMR Cold stage is controlled by the MMR K20000 Digital Temperature Controller. The Seebeck Stage has two outputs: V1 and V2, which are monitored by a computer through the SB1000.

The principle of operation is the following: assume that all four thermocouples are at the same temperature. Then V1 and V2 will be zero because each member of each pair of thermocouples compensates the voltage of the other. If power is applied to the heater, then a temperature difference will be created between the working and the reference junctions because they are located at different distances from the heater. As a result, thermo voltages will be generated in each pair giving non zero output voltages V1 and V2. These are given by:

- (1). $V1 = \epsilon_1 \Delta T(P)$ and
- (2). $V2 = \epsilon_2 \Delta T(P)$

Where ϵ_1 and ϵ_2 are the specific thermo-voltages of the sample and known thermocouples respectively, and $\Delta T(P)$ is the temperature difference between the working and the reference junctions created by applying power (P) to the computer controlled heater. We expect, that the temperature difference $\Delta T(P)$ will be the same for both pairs because the stage has a symmetrical shape. The value of the specific thermo-voltage of the unknown junction is then:

- (3). $\epsilon_1 = \epsilon_2 V1/V2$

However, one should use a small temperature deviation ΔT in order to obtain representative data in the temperature domain. Therefore, the values of V_1 and V_2 will also be small. Because of this, a direct measurement will not give high accuracy because of instrumental errors, and any undesired thermo-voltage effects from wires, connectors, etc. These effects can create substantial offset voltages which, in addition to the temperature drifts and offsets of the input amplifiers, can contribute a major source of measurement error. These can be eliminated, however, by taking measurements at two different temperature offsets, using two different power settings, and then using the difference signal. We show this as follows; the real values of V_1 and V_2 acquired by the SB1000 are given by:

$$(4). V_1(P_1) = \epsilon_1 \Delta T(P_1) + \Delta V_1 \text{ and}$$

$$(5). V_2(P_2) = \epsilon_2 \Delta T(P_2) + \Delta V_2$$

Where ΔV_1 and ΔV_2 are the instrument and extraneous thermal offset voltages discussed above, and P_1 is the power applied to the heater at the first measurement point. Now, if the heater power is changed to a new value P_2 , we obtain a second pair of values for V_1 and V_2 :

$$(6). V_1(P_2) = \epsilon_1 \Delta T(P_2) + \Delta V_1 \text{ and}$$

$$(7). V_2(P_2) = \epsilon_2 \Delta T(P_2) + \Delta V_2$$


The offset voltages ΔV_1 and ΔV_2 can be assumed to be independent of power P , because only the temperature in the immediate neighborhood of the reference and sample junctions change, not those where these other offset voltages originate.

Subtracting equations (6) and (7) from (4) and (5), respectively, we obtain the true value of ϵ_1 from the following:


$$(8). \epsilon_1 = \epsilon_2 \{V_1(P_1) - V_1(P_2)\} / \{V_2(P_1) - V_2(P_2)\}$$

(8) does not include ΔV_1 and ΔV_2 . The offsets have been removed.

Certain hardware and software precautions have also been implemented to eliminate any possible electrical coupling between the heater and measurement circuits as well.



Measurement Process: (Data collected in green areas)



The power or the heater $P(t)$ is changed from zero to level P . $V1$ and $V2$ are plotted schematically to show the corresponding changes of the thermo-voltages, as the temperature of the working junctions change. The green areas show the time intervals during which readings are taken. The average value of $V1$ and $V2$ for power levels 0 and P are used at the end of every period to calculate the specific thermo-voltage of the sample. The initial and operating time delays provide time for the system to stabilize thermally before taking the data.

The MMR Seebeck System allows the temperature of the MMR Cold Stage and attached Seebeck Stage to be controlled over a wide temperature range. One can thus study the temperature dependence of the specific thermo voltage of the samples by repeating the measurements at a series of temperatures. The Seebeck System allows this to be done automatically.

Definitions.

In the following, various terms used in this Manual and in the operation of the System are defined.

- 1. Measurement point.** The set temperature for the Seebeck stage provided by the MMR Cold Stage. Different measurement points are used in order to study the temperature dependence of the specific thermo-voltage.
- 2. Experiment.** The process that includes a sequence of measurement points; starting from the Initial Temperature and finishing with the Final Temperature. Including data acquisition at every measurement point, calculation and final presentation of the results.
- 3. Initial and Final Temperatures.** These temperatures set the range of the data acquisition process. If the Initial Temperature is less than the Final Temperature, then the sample will be heated during data collection. If the Final Temperature is lower, then the sample will be cooled. The Initial and Final Temperatures are always displayed during the experiment. The permitted range of the settings for these temperatures depends on the type of Thermal Stage used. Refer to the corresponding data sheets.



4 . Stand-by Temperature. The temperature to which the Seebeck stage is to be set after the experiment is completed.

5. Current Temperature. The actual, present temperature of the Cold Stage.

6. Target Temperature. The temperature at which the present activity of the system is targeted. It can be the Initial Temperature, the Measurement point Temperature, or the Standby Temperature. The temperature setting process is complete when the Current Temperature is equal to the Target Temperature.

7. Current Power. The power being applied presently to the MMR Cold Stage by the 'K2000 MMR Temperature Controller.'

8. Temperature Step. The difference between two successive measurement points.

9. Sweep Speed (Ramp Rate). The rate at which the temperature is changed from one measurement point to the next.

10. Modulation Power. The value of the power applied to the Seebeck stage heater to produce a temperature gradient across the samples.

11. Initial Time Delay. The waiting period from the time the Cold Stage reaches the measurement temperature, until the system takes the first set of readings. This delay is needed to allow the Seebeck Stage to reach equilibrium with the Cold Stage.


12. Operating Time Delay. The waiting period from the time the Seebeck Stage heater is turned on, until the second set of readings are taken. This allows a steady state to be reached across the Seebeck Stage.

13. Reference Thermo-Voltage. The specific thermo voltage (Seebeck Coefficient) of the known junction; used in the Seebeck Stage as a reference. Since this parameter changes with temperature, the data acquisition software includes a file with a look-up table to provide the value which corresponds to that for the set temperature. The Standard MMR Seebeck System is supplied with a lookup table for Constantan (as the reference material) relative to copper along with Constantan relative to PdAg.

14. Averaging Parameter. The parameter that defines the number of acquired data readings made during the measurement time interval, which are subsequently averaged at one measurement point. The parameter can vary from 0 to 7. The actual number of data readings is calculated as a corresponding power of 2, so a parameter 0 means 2⁰, or one reading, while a parameter 7 means 2⁷, or 128 readings. MMR Recommends a setting of '2' for most experiments.

Stage Preparation

1. Stage Installation.




- 1.1. Remove a Seebeck Stage from the package.
- 1.2. Put a thin layer of thermal grease on the large Copper plate (*underside*).
- 1.3. Unlock the ZIF connector (if present) on the pre-amplifier board in the vacuum chamber. Using thumbs on each side of the connector, insert the Seebeck stage fully.
- 1.4. Affix the Seebeck Stage to The Cold Stage by the spring fasteners. Be extremely careful! Do not apply any downward force on the refrigerator. Use tweezers to adjust the fasteners during installation. You can move the Seebeck Stage backwards and forwards by a couple of millimeters to get the best location.
- 1.5. Lock the ZIF connector (if present).
- 1.6. Install the cover on the vacuum chamber.
2. Connect the Ribbon cable from the Chamber to the SB1000. If a K2000 is present for temperature control, ensure the Link Ribbon Cable is installed from the SB1000 to the K2000.
3. If you are going to use the system at temperatures below ambient, you should also install all system components required for cooling according to the MMR Refrigerators Manual.

Sample Preparation

The MMR Seebeck System can be used for measurement of the Seebeck coefficient of a wide range of different conductive substances, metals, organic conductors, and semiconductors. Samples should be in the form of a thin strip or wire to be installed on the Seebeck Stage. The actual dimensions and the shape of samples are not critical, but should be considerably smaller than the Seebeck stage itself. We recommend that the width of the samples not exceed 1mm (40 mils), and the length 5 mm (200 mils).

For proper installation of the samples, good electrical and thermal contacts must be provided at both ends of the sample to the Seebeck Stage Areas (*shown below*). The unknown sample should be installed to the left or the Seebeck Stage center, and the reference sample to the right. Do not switch these locations; otherwise you will get completely incorrect results! For attaching the samples to copper surfaces, one can either use regular soldering alloys, or electrically/thermally conductive cement or epoxy. The bonding substance should be able to withstand the temperature range of the proposed measurements. Materials of high specific resistivity and low thermal conductivity should not be used. The resistance of the sample plus the bonding material to the Seebeck Stage should be less than 100Kohm.




Install the unknown sample first, using the bonding material of your choice. The working junction should be located as close as possible to the slot that separates the two copper surfaces of the unknown and reference samples (*see page 10*). The location of the other end of the sample is much less critical. If the sample cannot be formed or folded, attach it at any convenient point on the copperplate which is common to the unknown and reference samples, and as close to the center as possible. Install the reference sample in a similar manner. Cut approximately 5 millimeters (0.2") of the reference material wire supplied with the System. For the standard Seebeck System version this is a wire of Constantan. Attach one end of the wire piece to the copper plate which is common to both samples. Use the same point as for the unknown sample. The unknown and reference samples should have direct thermal contact in this point. Attach the other end of the reference sample taking into account the same considerations as for the tested sample. The working junctions of both samples should have symmetrical locations relative to the stage heater. Finally, using an appropriate fluid, clean the Seebeck Stage of possible surface contamination. We recommend the use of Freon's and/or methyl or ethyl alcohol. Any cleaning materials used must be non-conductive.

Notice: Be very careful while mounting the samples. Bad electrical or thermal contacts, asymmetrical location of the working junctions, and surface contamination can cause serious measurement errors.

Experiment Setup

New Project



As mentioned in the Seebeck Definitions on Page 12, the Experiment parameters can now be entered. If no K2000 Temperature Controller is present select 'Skip Temperature Settings,' this will carry out the experiment at Ambient Temperature (300K will be used for all calculations).

Sample Mounting Stage: Select the appropriate stage type that the sample is mounted on.

High Impedance Input: Select the appropriate Impedance Setting that relates to the Amplifier in use.

Gain: Select the appropriate Gain value that relates to the Amplifier in use.

Note: Impedance and Gain settings are indicated on the Amplifier board inside the chamber. The correct settings must be used or erroneous data will result.

Click 'OK'

Seebeck Software Layout

Experiment View




Before selecting 'Start' check the voltages and temperature data (if a K2000 is present), and check the SB1000 status in the 'Experiment Setup' box to verify proper communication ('Ready'). As shown above, the voltages are close to 0 and equal. Improper material mounting will cause erroneous voltages.

If 'Auto Standby' was selected the 'K2000 Temperature Controller' will first set the Standby Temperature.

Selecting start will begin the Automated Data Collection process. The progress and status will be shown on the right hand side of the Experiment window. If the experiment is 'Started' before the standby temperature is reached, the experiment will wait until the temperature is reached and then begin automatically.

If a K2000 Temperature Controller is present, the temperature plot will automatically begin recording temperature data.


Seebeck Software



The above 'Complete' Experiment shows the data collected. The user has the option of :


- 1/. Saving the data to the internal database to retrieve later (Main Suite -> SB1000 -> Open).
- 2/. Printing the Data (in Data View click 'Print')
- 3/. Printing the Plot (in Graph View click 'Print')
- 4/. Exporting Data to *Comma Separated Values* (in Data View click 'Export .csv') for further analysis in third party software such as Microsoft Excel.
- 5/. Viewing statistics, (in Data View click 'Statistics')

Note: Some options are only available when the Experiment has completed successfully.



The above plot shows the Temperature Control during the Seebeck Experiment. This data can be printed from within the K2000 Temperature Graph Window if needed.

Seebeck Software Statistics



The above Statistical Results view displays the Average Values at every Temperature point. Standard Deviation is also present along with the Percentage Change and Min Max Values. If no temperature control is present only 1 point will be plotted.



Communications Protocol

Main Communications Type:	Serial
Communications Interfaces:	RS232, USB1.0
Serial Settings:	9600,N,8,1
Handshaking:	Hardware RTS/CTS
Echo:	Yes
Bus Pairing:	Parallel
Hardware CTS Timeout:	1000ms
Data Format:	ASCII / Plain Text

System Commands

Command	Format	Example	Description
SM	SMX	SM1 (1-7) Averaging Parameter 2^n Readings	Start Measurement
GV	GVX	GV1 (1 or 2) Valid when unit is in standby.	Get Voltage
SH	SHXXX	SH300 (300mW)	Set Heater
N	N1		Get Device ID
O	O1		Power Down Unit

Note: Sending command SMx starts constant measurement at desired average rate.

Communications & Byte Order

Command Example: 'SM2' (starts measurement at $2^2 = 4$ readings per average)

- 1/. Set RTS High
- 2/. Wait for CTS
- 3/. Send 'S' as a Character (VB Example on Next Page)
- 4/. Send 'M' as a Character (VB Example on Next Page)
- 5/. Send Average as a 2-Byte Word (Highbyte First, Lowbyte Second)
- 6/. Set RTS Low



Communications Protocol

Visual Basic Example - Sending a start measurement command. 'SM2'

Private Sub Form_Load()

```
MSComm1.CommPort = 2
MSComm1.DTREnable = False
MSComm1.Settings = "9600,N,8,1"
MSComm1.RTSEnable = False
MSComm1.OutBufferSize = 1024
MSComm1.RThreshold = 1
MSComm1.SThreshold = 0
MSComm1.PortOpen = True
```

End Sub

Function StartMeasurement()

```
Dim command As Long
Dim var As Integer
Dim counter As String
```

val = 2

```
counter = 0
MSComm1.RTSEnable = True
While MSComm1.CTSHolding <> True
    counter = counter + 1
    If counter > 200000 Then
        MSComm1.RTSEnable = False
        MsgBox ("Time Out")
        Exit Function
    End If
Wend
MSComm1.OutBufferCount = 0
MSComm1.InBufferCount = 0
MSComm1.Output = Chr$(S) + Chr$(M) + Chr$(val / 256) + Chr$(val Mod 256)
MSComm1.RTSEnable = False
```

'Start Measurement 2^2

'Set RTS High

'Wait for CTS Signal

'Reset RTS

'Clear Buffers

End Function



Troubleshooting

Symptom	Solution
Cannot Communicate with SB1000	Ensure Unit is properly connected and powered on. Press Reset. Check that the device is connected to the correct Communications Port and the drivers are successfully loaded.
No Lights on SB1000	Ensure Unit is plugged into an AC Power source, and the rear power switch is on. Check Fuse.
Readings are unstable	Check refrigerator is under vacuum. Check sample mounting quality
Refrigerator doesn't Cool or Heat	Refer to Refrigerator Operators Manual, and check for damage to refrigerator.
Temperature Accuracy has degraded	Return Refrigerator to MMR for Sensor service.
Software has an Error message	Contact MMR helpdesk

For all other errors or issues please contact the MMR Help Desk (*see Page 22*)



Help Desk and MMR Contact Information

Help Desk Email Address: support@mmr-tech.com

Bug Reporting: spdbugs@mmr-tech.com

Technical Support Email Address: matt@mmr-tech.com

Sales & Marketing Department: sales@mmr-tech.com

Help Desk: +1 650 962 9620

Office Hours: 7:30am - 5:00pm (Pacific Time)
Monday - Friday

Physical Address: 41 Daggett Drive,
San Jose, California 95134
USA





Declaration of Conformity



Manufacturer: MMR Technologies
Model Name: SB1000
Date: July 2014
Expires: July 2018



UL / IEC 61010

Application of Council Directives:

Low Voltage Directive (LVD) 2006/95/EC

Standards to which Conformity is Declared: IEC EN 61010-1 3rd Edition

Electrical equipment for measurement, control, and laboratory use

Pressure Equipment Directive (97/23/EC)

Conformity is declared to Annex I Essential Requirements of the Directive

Application of Council Directives:

Electromagnetic Compatibility Directive (EMC) 2004/108/EC

Conformity is declared to Annex I and II (EMC) 2004/108/EC