

- Full-colour touch-screen LCD with near-photo realism
- Fully customizable to your individual wishes
- Built-in database and self-learning capability covers all equipment brands
- Extended 8 MB memory and unlimited macro functionality
- Intuitive user interface for controlling your total home environment
- Software upgradeable, and Internet community support
- IR and RF transmission – with optional RF receivers for total home control



# SBC RU970

## Standard product information

• Power supply	Rechargeable AAA battery pack (included)
• Processor	Motorola DragonBall MC68328
• SRAM	512 Kb
• Flash memory	8 Mb
• PC port	RS232 Serial port (3 wire connector)
• Transmission type	IR universal/ RF universal
• Transmission system	Modulated
• Operating distance	IR 10 meters/ RF 50 meters open air
• Transmission angle	30 deg.
• No. direct access buttons	10
• Audio	Piëzo speaker with adjustable volume
• Weight	250g, with batteries
• Dimensions (mm)	141 x 94 x 32 (L x W x H)
• Environment	Operating temperature (5°C - 45°C) Storage temperature (-25°C - 70°C)
• Warranty	1 year European warranty

## LCD information

• Display type	FSTN
• Dimension (mm)	77 x 58
• Resolution	320 x 240, 0.24mm pitch
• Position	Portrait
• Refresh rate	70 Hz
• Number of colours	256
• Dynamic LCD input	Finger or blunt object
• EL backlighting	Yes

## Installation

• Pre-installed	RC5, RC6 (Philips & Marantz ready)
• Learnable	Yes
• No. of devices	Unlimited (within memory)
• No. of learnable codes	Unlimited (within memory)
• Built-in IR codes	549 brands
• IR learning frequencies	Up to 56 kHz and 455 kHz

## Features

• Direct-access buttons	Mute Channel Up/Down Volume Up/Down Right/Left Configuration buttons Backlight button 2 free programmable buttons
• Customisable User Interface	manual or via PC
• Software upgradeable	Yes
• Macro functionality	Yes, Unlimited (within memory)
• Timer functionality	Yes, Unlimited (within memory)
• Automatic backlighting	Yes
• LCD Contrast adjustment	Yes
• Auto power on/off	Yes
• Automatic power mgmt	Auto power up/down

## Packaging

• Type	Carton box
• Dimensions (mm)	245 x 130 x 210
• Languages	GB
• Languages	d.n.y.a.
• 12NC	9082 100 00512
• EAN code	87 10101 67892 4
• Contents	ProntoPro remote control, docking station, serial cable, instructional manual, rechargeable battery pack and ProntoProEdit softwarepackage on CD rom

## Inner carton

NON

## Outer carton

• Contents	1
• Dimensions (mm)	d.n.y.a.
• Weight (Kg)	d.n.y.a.
• EAN code	87 10101 87202 5

## Full-colour touch-screen display

The ProntoPro, with its large 256-color touch-screen LCD brings near photo-quality images to interacting with your home entertainment environment. Add images of users and full-colour network logos to the intuitive user interface.

## Pick it up and the buttons light up

Pick up your ProntoPro and the screen light up straight away - even before you press it. Tilt sensor backlighting adds extra convenience to viewing in the dark.

## Intelligent remote control

You can customize the user interface to meet your own specific wishes and personal requirements - and those of all other users in your home. Add new buttons, redesign the layout, and enhance the colours. It's as individual as you are.

## Self-learning and a built-in database

With the biggest database of control codes ever built-in to a universal remote, the ProntoPro can control any other IR remote controlled product - regardless of brand. It also includes a powerful self-learning capability to ensure absolute compatibility with every IR remote control on the market.

## Extended 8 MB memory and macro function

The extended 8 MB memory depth easily holds your graphics, custom configurations and macros. The unlimited macro facility allows you to combine as many commands or key-strokes as you like under a single button. Imagine, just one touch of the colour screen to close the curtains, dim the lights, start the TV and play the DVD. Home cinema as it is supposed to be!

## Intuitive user interface

You control your complete electronic environment - from home entertainment products to any other equipment using IR remote control from the direct-access touch-screen and hardware buttons. It is supplied with a logically configured standard interface and you can modify it or create your own using graphics, icons and menus. ProntoPro's intuitive controls are extremely user friendly.

## Software upgradeable

With ProntoProEdit software, which is supplied on CD-ROM and freely available on the Internet, you can create configurations, and download graphics, templates and macros. And the Internet is also host to independent communities of ProntoPro users.

## IR and RF transmission

ProntoPro works with all IR-based remote control links. The optional RF receivers can be used to use ProntoPro to control audio/video equipment and accessories anywhere in your home - even through walls. It's an intelligent RF link too, filtering out signals from other wireless devices working at similar frequencies.



## Docking station

The recharge docking station keeps your ProntoPro ready for use at all times. ProntoPro can also be used while docked, and can be connected to a PC via the docking station.

<http://www.pronto.philips.com>  
<http://www.remotecentral.com>

Let's make things better.



PHILIPS