

INTELLIGENT CONTROLLERS

SHOW DESIGNER II

- 1024 DMX Channels, (3&5 Pin Outputs)
- 48 fixtures up to 32 channels each
- Large DMX Fixture library
- Effects Engine with 48 Factory chases
- 1152 Programmable Chases
- 4752 Programmable Scenes
- 1152 Programmable Shows
- 1152 Programmable Presets
- 8 Faders allow for control of up to 32 DMX channels per fixture and scene masters.
- 48 Fixture Groups
- Scene Preview with "Go" feature
- Factory ready Color, Gobo, Focus & Effect Presets
- Controller comes "Tabletop Style"--Includes removable rubber rails to fit standard 19-inch rack mount

FRONT PANEL

- 80 Character backlit LCD Display for easy programming
- 4 x Menu and control data wheels
- PAN/TILT Joystick
- 48 Multi function Quick access buttons
- 8 Faders x 4 banks
- XLR light connector
- On/Off Power switch

REAR PANEL

- 2 x (3 Pin) DMX Outputs
- 2 x (5 Pin) DMX Outputs
- Midi-In & Out ports
- 3.5" Disk drive (Show Designer 2D version only)
- Keyboard Input (Show Designer 2D version only)
- RS-232 Port, for PC interface
- 2 x DMX Polarity Switches per output (3 Pin Outs Only)
- RCA Audio input for Chases

TECHNICAL SPECS AND DATA

- Polarity switch (2-,3+ / 2+, -3-) 3 Pin XLR only
- 1 MB memory
- Battery back up
- 19" rack mountable, 6 space
- Dimensions: 19" x 10.5" x 4"
- Weight: 10 lbs
- Voltage: 120V/220V (9-12v DC / 1200ma)



Computer keyboard not included.




SHOW DESIGNER 2D

- Same features as the Show Designer II
- Includes 3.5" PC Floppy Disc Drive on rear
- Includes PS-2 keyboard input



SHOW DESIGNER UPDATE CABLE
Model # SD-DC



DVD
Instructional DVD available.