

# FMM-462 Series POPIT Addressable Manual Stations

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Single-gang mounting
- ▶ Latching alarm lever and key-locked reset
- ▶ Rugged die-cast housing with 14 gauge (1.9 mm) plated steel back and corrosion-resistant construction
- ▶ Optional scored acrylic breakrod

The FMM-462 Series Addressable Manual Stations allow people evacuating a building to initiate an alarm and alert others still inside. This UL-listed initiating device is compatible with the Bosch Security Systems, Inc. G Series Control Panels and the D9124 Fire Alarm Control Panel (FACP).

The POPIT module is addressed using on-board slide switches. It is then connected to a D9124 data expansion loop. The POPIT is polled by the control panel and sends reports on any opens, shorts, or ground faults on the manual station's wiring. The addressable feature allows the agencies responding to alarm or trouble conditions to go to the point that initiated the alarm or trouble report.

These low-profile manual stations are die cast with rounded edges to fit most design applications. All metallic components are painted or plated to inhibit corrosion. The FMM-462 Series Manual Stations conform with the Americans with Disabilities Act (ADA) standards.

## Functions

### Addressable Operation

The POPIT connects to a two-wire data expansion circuit from the control panel. Device address is set through slide switches on the POPIT Module, allowing programmable device identification by the control panel.

## Certifications and Approvals

ADA	Complies with Americans with Disabilities Act ADA 4.28.3
NFPA	Complies with National Fire Protection Association NFPA 72

Region	Certification	
USA	UL	UNIU: Boxes, Non-Coded (UL38)
	CSFM	7150-1615:0122

## Installation/Configuration Notes

### Compatibility Information

The FMM-462 Series Addressable Manual Stations are compatible with the following products:

Category	Product ID	Product Description
Control	D7212G	Control panel
Panels:	D7412G	Control panel
	D9412G	Control panel
	D9124	Addressable FACP
Modules	D9127U	POPIT module

### Mounting Considerations

The FMM-462 manual stations are for indoor use only. The FMM-462 or FMM-462-D and the wiring from the control panel data expansion loop fit into a single-gang back box for flush mounting. Use the larger FMM-100BB-R Back Box for surface mounting and to provide additional room for system wiring and the module.

## Parts Included

Quant.	Component
1	Manual station
1	D9127U POPIT module
1	FMM-100GR scored acrylic breakrod
1	D102 Key (1358)
1	Literature pack

## Technical Specifications

### Environmental Considerations

Temperature (operating):	+14°F to +120°F (-10°C to +49°C)
--------------------------	----------------------------------

### Mechanical Properties

Activation Force:	5 lb (2.3 kg)
Alarm Response Time:	1 sec (approximately)
Dimensions (HxWxD):	4.75 in. x 3.2 in. x 0.875 in. (12.1 cm x 8.1 cm x 2.2 cm)
Material:	Painted die-cast metal, plated steel back and painted steel front

### Power Requirements

Current (alarm):	0.8 mA
Current (normal):	0.5 mA
Voltage (operating):	7 VDC to 15 VDC supplied by the control panel

## Ordering Information

### FMM-462 Single-Action Manual Station

A UL-listed initiating device compatible with the Bosch Security Systems, Inc. G Series Control Panels and the D9124 Fire Alarm Control Panel (FACP)  
Order number **FMM-462**

### FMM-462-D Double-Action Manual Station

A UL-listed initiating device compatible with the Bosch Security Systems, Inc. G Series Control Panels and the D9124 Fire Alarm Control Panel (FACP)  
Order number **FMM-462-D**

### Accessories

#### D102 Replacement Key

Replacement key (#1358) for the D101 lock.  
Order number **D102**

#### FMM-100BB-R Surface-mount Back Box (red)

Red cast-metal back box  
Order number **FMM-100BB-R**

#### FMM-100GR Scored Acrylic Break Rods

Scored acrylic rods (12 per package)  
Order number **FMM-100GR**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
al.securitysystems@bosch.com  
www.boschsecurity.com