



## Technical Specifications



# EURORACK UB1622FX-PRO

Ultra-Low Noise Design 16-Input 2/2-Bus Mic/Line Mixer with Premium Mic Preamplifiers and Multi-FX Processor

# UB1622FX-PRO

## Ultra-Low Noise Design 16-Input 2/2-Bus Mic/Line Mixer with Premium Mic Preamplifiers and Multi-FX Processor

- Ultra-low noise design, highest possible headroom, ultra-transparent audio
- 4 state-of-the-art, studio-grade IMP "Invisible" Mic Preamps with 130 dB dynamic range for 24-bit, 192 kHz sampling rate inputs
- Studio-grade stereo FX processor with 100 awesome presets including reverb, chorus, flanger, delay, pitch shifter and various multi-effects
- Effective, extremely musical 3-band EQ with semi-parametric mid band plus switchable low-cut filter on all mono channels
- Inserts on each mono channel for flexible connection of outboard equipment
- 12 balanced high-headroom line inputs with +4/-10 level selection on stereo channels
- 2 aux sends per channel: one pre/post fader switchable for monitoring/FX applications, one post fader (for internal FX or as external send)
- Clip LEDs, mute, main mix and subgroup routing switches plus solo and PFL functions on all channels
- 2 subgroups with separate outputs for added routing flexibility
- 2 multi-functional stereo aux returns with flexible routing
- Main mix outputs with jack and gold-plated XLR connectors, separate control room, headphone and 2-track outputs
- Control room/headphone outputs with multi-input source matrix
- 2-track inputs assignable to main mix or control room/headphone outputs
- Switchable +48 V phantom power for condenser microphones
- Rack mount brackets included
- Internal switch-mode power supply for maximum flexibility (100 – 240 V~), noise-free audio, superior transient response plus lowest possible power consumption for energy saving
- High-quality component components and exceptionally rugged construction ensure long life
- Conceived and designed by BEHRINGER Germany

## Specifications

### Microphone Inputs (IMP Invisible Mic Preamp)

Type	XLR, electronically balanced, discrete input circuit
<b>Mic E.I.N. (20 Hz - 20 kHz)</b>	
@ 0 Ω source resistance	-134 dB / 135.7 dB A-weighted
@ 50 Ω source resistance	-131 dB / 133.3 dB A-weighted
@ 150 Ω source resistance	-129 dB / 130.5 dB A-weighted
Frequency response	<10 Hz - 150 kHz (-1 dB), <10 Hz - 200 kHz (-3 dB)
Gain range	+10 to +60 dB
Max. input level	+12 dBu @ +10 dB Gain
Impedance	approx. 2.6 kΩ balanced
Signal-to-noise ratio	110 dB / 112 dB A-weighted (0 dBu In @ +22 dB gain)
Distortion (THD+N)	0.005% / 0.004% A-weighted

### Line Input

Type	¼" TRS connector electronically balanced
Impedance	approx. 20 kΩ balanced 10 kΩ unbalanced
Gain range	-10 to +40 dB
Max. input level	+22 dBu @ 0dB Gain

### Fade-Out Attenuation<sup>1</sup> (Crosstalk Attenuation)

Main fader closed	90 dB
Channel muted	89 dB
Channel fader closed	89 dB

**Frequency Response****Microphone input to main out**

<10 Hz - 90 kHz	+0 dB / -1 dB
<10 Hz - 160 kHz	+0 dB / -3 dB

**Stereo Inputs**

Type	¼" TRS connector, electronically balanced
Impedance	approx. 20 kΩ
Max. input level	+22 dBu

**EQ Mono Channels**

Low	80 Hz / ±15 dB
Mid	100 Hz - 8 kHz / ±15 dB
High	12 kHz / ±15 dB

**EQ Stereo Channels**

Low	80 Hz / ±15 dB
Low Mid	500 Hz / ±15 dB
High Mid	3 kHz / ±15 dB
High	12 kHz / ±15 dB

**Aux Sends**

Type	¼" TS connector, unbalanced
Impedance	approx. 120 Ω
Max. output level	+22 dBu

**Stereo Aux Returns**

Type	¼" TRS connector, electronically balanced
Impedance	approx. 20 kΩ bal. / 10 kΩ unbal.
Max. input level	+22 dBu

**Main Outputs**

Type	¼" TS connector unbalanced
Impedance	approx. 240 Ω balanced / 120 Ω unbalanced
Max. output level	+22 dBu

**Control Room Outputs**

Type	¼" TS connector unbalanced
Impedance	approx. 120 Ω
Max. output level	+22 dBu

**Headphones Outputs**

Type	¼" TRS connector, unbalanced
Max. output level	+19 dBu / 150 Ω (+25 dBm)
DSP	24-bit
Converter	24-bit Sigma-Delta, 64/128-times oversampling
Sampling rate	40 kHz

**Main Mix System Data<sup>2</sup>****Noise**

Main mix @ -∞, Channel fader @ -∞	-101 dB
Main mix @ -0 dB, Channel fader @ -∞	-96 dB
Main mix @ 0 dB, Channel fader @ 0 dB	-83 dB

**Power Supply**

Mains voltage	100 to 240 V~, 50/60 Hz
Power consumption	37 W
Fuse	100 - 240 V~: T 1.6 A H 250 V
Mains connection	Standard IEC receptacle

**Physical/Weight**

Dimensions (H x W x D)	approx. 3.8 x 11.9 x 13.8" approx. 97 x 301 x 351 mm
Weight (Net)	approx. 9.5 lbs / 4.3 kg

Measuring conditions:

- 1 kHz rel. to 0 dBu; 20 Hz - 20 kHz; line input; main output; unity gain.
- 20 Hz - 20 kHz; measured at main output. Channels 1 - 4 unity gain; EQ flat; all channels on main mix; channels 1/3 as far left as possible, channels 2/4 as far right as possible. Reference = +6 dBu.

BEHRINGER is constantly striving to maintain the highest professional standards. As a result of these efforts, modifications may be made from time to time to existing products without prior notice. Specifications and appearance may differ from those listed or illustrated.

TECHNICAL SPECIFICATIONS AND APPEARANCES ARE SUBJECT TO CHANGE WITHOUT NOTICE AND ACCURACY IS NOT GUARANTEED. BEHRINGER IS PART OF THE MUSIC GROUP (MUSIC-GROUP.COM). ALL TRADEMARKS ARE THE PROPERTY OF THEIR RESPECTIVE OWNERS. MUSIC GROUP ACCEPTS NO LIABILITY FOR ANY LOSS WHICH MAY BE SUFFERED BY ANY PERSON WHO RELIES EITHER WHOLLY OR IN PART UPON ANY DESCRIPTION, PHOTOGRAPH OR STATEMENT CONTAINED HEREIN. COLORS AND SPECIFICATIONS MAY VARY FROM ACTUAL PRODUCT. MUSIC GROUP PRODUCTS ARE SOLD THROUGH AUTHORIZED FULLFILLERS AND RESELLERS ONLY. FULLFILLERS AND RESELLERS ARE NOT AGENTS OF MUSIC GROUP AND HAVE ABSOLUTELY NO AUTHORITY TO BIND MUSIC GROUP BY ANY EXPRESS OR IMPLIED UNDERTAKING OR REPRESENTATION. THIS MANUAL IS COPYRIGHTED. NO PART OF THIS MANUAL MAY BE REPRODUCED OR TRANSMITTED IN ANY FORM OR BY ANY MEANS, ELECTRONIC OR MECHANICAL, INCLUDING PHOTOCOPYING AND RECORDING OF ANY KIND, FOR ANY PURPOSE, WITHOUT THE EXPRESS WRITTEN PERMISSION OF MUSIC GROUP IP LTD. ALL RIGHTS RESERVED. © 2012 MUSIC GROUP IP LTD. TRIDENT CHAMBERS, WICKHAMS CAY, P.O. BOX 146, ROAD TOWN, TORTOLA, BRITISH VIRGIN ISLANDS