



-  **The LED indicator on the front of the interface will light to indicate “IR data” when a button on the remote is pressed.**
-  **The IR sensor is located on the front of the interface; however, the IR sensor may be relocated by using the IR Ext. port on the back of the interface (not included).**
-  **The Xpress™ 512-Plus will only play back scenes *AFTER* they have been successfully uploaded into the interface with the Upload screen.**

The Xpress™ 512-Plus interface features wireless triggering of up to 18 scenes in standalone operation. These are accessed using the CHAUVET® proprietary remote shown below.

The scenes will only be available after they have been programmed with ShowXpress™ and uploaded into the interface. Please see the ShowXpress™ User Manual for details on this operation.

The model number for a replacement battery is CR2025 (standard) or CR2032 (high capacity).



Operation

Please see the following notes on operation.

-  **The “Normal Speed” button will cause the speed to revert back to the original programmed speed.**
-  **Playback speed modification affects ALL of the programs proportionally. It is NOT possible to modify individual scenes.**