## 14PT1422 14PT1482

- Black Matrix CRT
- 3 W RMS
- Smart Picture
- Smart Sound
- · Power Chip
- Personal Preference
- Teletext (14PT1422 only)
- Wake-up Timer
- Sleep Timer
- Front headphone and AV inputs













## 14PT1422 14PT1482

## **Product Information**

**Picture** 

Screen size Picture tube

Viewing area Smart Picture modes

Black Matrix CRT 34 cm Soft, Natural, Rich, Personal

14" (37 cm)

Power Chip

Sound

Sound output Loudspeakers Smart Sound modes 3 W RMS Full Range Speaker Theatre, Music, Voice,

VST tuning,

Reception

Tuning system

PLL tuning for NTSC UV, S and Hyperband, Full cable for NTSC Channel selection 80 presets

TV systems Video playback

See table NTSC 3.58 / 4.43

Teletext (14PT1422 only)

Text standards Number of teletext buttons

WST / FLOF 5 buttons (On/Off, Subcode/Time Display, Enlarge, Hold, Reveal)

Connectors

Front

Headphone out (3.5 mm)

Audio / Video input Rear Audio / Video input

Audio / Video output (monitor out)

Operation

Remote control RC0770/01 Number of remote 29 buttons control buttons

**Features** 

Sharpness Control

Personal Preference (13 x RF, 1 X AV)

Auto Search and Store

Swap

Wake-up Timer Sleep Timer Auto Switch Off

Measurements

100 - 250V, 50/60 Hz 160 - 250V, 50/60 Hz

38 W Power consumption (Normal Operation)

8 W (Standby)

8 kg Net weight Gross weight 10 kg

Set dimension  $374 \times 379 \times 350$ 

 $(W \times D \times H mm)$ 446 × 445 × 420 Box dimension  $(W \times D \times H mm)$ 

Container loading 700 sets (per 40 ft, loose)

**Product Highlights** 

Smart Picture provides the option of selecting one of four preset positions (Soft, Natural, Rich, Personal) to enhance enjoyment of video games, sports and movies. Select the desired option and all important picture elements are instantly adjusted to optimize viewing pleasure.

Smart Sound provides the option of selecting one of four preset positions (Theatre, Music, Voice, Normal) to optimize each individual sound preference when viewing different programmes or sources.

Power Chip boasts of a Philips BIMOS Picture Improvement Circuitry which provides better contrast, good colour transience, accurate colour reproduction and optimum sharpness for improved picture quality.

Personal Preference allows the viewer to personally select and program different picture settings and sound volume level combinations for 13 different RF channels and 1 AV channel. This is to cater to the different transmission signal conditions of various broadcasting stations.

Sleep Timer automatically turns off the TV at a preset time of up to 120 minutes from the time the feature is activated. Sleep timer settings are programmed in 15-minute intervals.

	Features	PAL B/G						PAL I, PAL D/K		NTSC M	PAL B/G, PAL D/K, SECAM BG/DK (K1)
		/50	/67	/68	/70	/75	/79	/57	/73	/71	/59
14PT1422	Mono, Teletext	•		•		•					
14PT1482	Mono	•	•	•	•	•	•	•	•	•	•

: L7 Chassis

Release Date : March 1998

Reference : LSS/14SYM/LOB BTV Features and specifications subject to change without notice



