

28" Stereo SYM FSQ



- *Black Line FX Picture Tube*
- *Contrast Plus*
- *Stereo*
- *10W RMS*
- *2 On Board Speakers*
- *Plug & Play*
- *5 page Fastext*
- *Sleep Timer*

Black Line FX



Plug & Play
→



Let's make things better.



PHILIPS

28" Stereo SYM FSQ



Product Information

Picture

- Screen Size : 28" (70 cm)
- Visible screen size : 67 cm
- Picture Tube : Black Line FX
- Contrast Plus
- Sharpness Control
- Noise Reduction
- Colour Temperature

Sound

- Sound Power : 10W RMS
20 Music Power
- Ultra Bass
- 2 On Board Speakers

Ease of Use Installation

- Plug & Play
- 100 Preset channels
- Autostore
- Fine Tuning Sorting
- Smart ATS/ACI

Ease of Use Utilisation

- RC2543 (suitable for VCR)
- Smart Picture Control : Soft, Natural, Rich, Personal
- Smart Sound Control : Movie, Speech Music, Personal
- Dual I-II
- Sleep Timer
- 16:9 Compress
- 4:3 Expand (formatter)

Connections

Front

- Headphone Jack 3,5 mm out

Back

- Euro A/V connector Ext1 (RGB in, CVBS in/out)
- Euro A/V connector Ext2 (S-Video in, CVBS in/out)

Information

- 5 Page TOP/FLOF Teletext
- Program Information Line

Reception

- Tuning System : PLL digital tuning
- Tuner : VHF, UHF, S-Channel, Hyperband
- Aerial Input : 75 ohm Coaxial
- TV System : See table
- Stereo System : See table
- Video Playback : NTSC 4.43/3.58

Miscellaneous

- Mains : AC 220-240V, 50/60 Hz (stroke /01, /05)
AC 90-276V, 50/60 Hz (stroke /58)
- Power Consumption : tbc Normal Operation
< 3W Stand by
- Set Weight : 32 kg
- Weight Incl. Packaging : 36 kg
- Set Dimension (WxHxD) : 694x470x579 mm
- Box Dimension (WxHxD) : 792x576x711 mm
- TV Colour : Metallic Antracite (10897)

Product Highlights

Black Line FX

A new Philips picture tube with dark glass for better contrast and highly pigmented phosphors giving brighter and more natural colours.

Contrast Plus

A special electronic circuit has been incorporated into this television to enhance the darker portions of the picture for added realism and improved picture quality.

Stereo

Two channel sound signal able to deliver different sound from left and right channels

RMS

The standard professional measure of sound output power. All our TV's are measured in RMS with 10% Distortion. There are other terms than RMS which often show higher numbers but are not comparable.

Plug & Play

Having connected the tv, it automatically searches for all channels and installs them.

5 page Teletext

Teletext information available.

Sleeptimer

The Television can be programmed to go into standby mode at a time defined by the user.

| version | | stereo system | | | | | | transmission system | | | | | |
|----------|-----|---------------|----------|--------|----------|---------|-----------|---------------------|--------|-------|----------|----------|-----------|
| | | 2CS DK | NICAM DK | 2CS BG | NICAM BG | NICAM I | NICAM LL' | PAL BG | PAL DK | PAL I | SECAM BG | SECAM DK | SECAM LL' |
| 28PT2665 | /01 | | • | • | • | • | • | • | • | • | • | • | • |
| 28PT2665 | /05 | | • | • | • | • | • | • | • | • | • | • | • |
| 28PT2665 | /58 | • | • | • | • | • | | • | • | | • | • | |

Predecessor : 28PT4404
Chassis : L9 LS
Introduction : Year 2001

Features and specifications subject to change without notice

Let's make things better.



PHILIPS