**MODEL 500 DUST COLLECTOR** 

The new JET DC-500 Dust Collector is perfect for small shops with limited space. The lightweight design combines a ridged tubular frame for strength and large wheels for portability. Quick and easy assembly, no tools required. 4" dust collection hose is provided for immediate use. The powerful 1/2HP motor along with 500 CFM of performance is ideal for use with most woodworking machines.



## **AIR FILTRATION SYSTEM**

The new JET AFS-400 Air Filtration unit can either be hung from the ceiling by four hooks to save shop space or be used as benchtop. This little powerhouse cleans and circulates air in a 20' x 20' x 8' shop, 7 cycles per hour to provide you with a cleaner, healthier shop environment. Three speeds 260, 362 and 409 CFM allow you to choose the most efficient air filtration for your shop. The remote control with built-in timer settings for 1, 2 and 4 hours will shut off automatically at the end of the designated time, cleaning the air in your shop even while you are away.



# MODEL 500 DUST COLLECTOR & AIR FILTRATION SYSTEM



#### **FEATURES**

- · Quick, tool-less assembly
- · Rigid, lightweight frame
- · Quick install filter and collection bags
- · Large wheels for mobility
- 500 CFM performance for efficient dust collection
- 30 micron filtration for cleaner air

### **SPECIFICATIONS**

Stock Number	708660
Model Number	DC-500
Remote Control	No
Blower Wheel Diameter (in.)	9.5
Sound Rating (dB)	65
1-Hose Connection Diameter (in.)	4
Bag Diameter (in)	14
Filter Bag/Canister Length (in.)	24
Collection Bag Capacity (cu. ft.)	1.9
Collection Bag Length (in.)	21
Air Flow @ 4" (CFM)	500
Amps	4.5
Motor HP	1/2HP
Motor Phase	1Ph
Motor Voltage	115V
Prewired	115V
Net Weight (lbs.)	36

#### ACCESSORIES

Replacement 30 Micron Filter Bag	708385
Replacement 30 Micron Collection Bag	708386
115V RF Remote (Includes Transmitter)	708636C
Transmitter for RF Remote	708636T





#### **FEATURES**

- Remote control has built-in timer with 1, 2 and 4 hour settings; automatically shuts system off at the end of the time setting
- Select from three speeds 273, 333, 381 CFM for the most efficient air filtration
- Disposable electrostatic outer filter attracts more dust particles than standard filters
- · Inner pocket filter is removable for cleaning out with ease
- Rubber feet prevent marring of surface when placed on workbench
- Four hooks let you hang unit from shop ceiling
- Easy grip handle for portabilility

#### SPECIFICATIONS

3FECIFICATION3	
Stock Number	710612
Model Number	AFS-400
Speeds (CFM)	273, 333, 381
Filter Cycle (min.)	8.4
Cycles per Hour (20' x 20' x 8')	7
Timer Settings (hours)	1, 2 and 4
Outer Filter (microns)	5
Inner Filter (microns)	1
Motor Amps	0.9
Motor HP	1/8
Motor Phase	1
Motor Voltage	115V
Prewired	115V
Net Weight (lbs.)	31

#### ACCESSORIES

AFS-400 Replacement Inner Pocket Filter	710621
AFS-400 Replacement Electrostatic Outer Filter	710622
AFS-400 Replacement Remote Control	710623







710621 710622 710623