

DVD Receivers

Model		RX-DV5R	RX-DV3R
<b>SPECIFICATIONS</b>			
<b>AMPLIFIER SECTION</b>			
Output Power (IEC 268-3/DIN)	Stereo	80 watts per channel, min. RMS, driven into 8 ohms at 1kHz, with no more than 0.9% total harmonic distortion	80 watts per channel, min. RMS, driven into 8 ohms at 1kHz, with no more than 0.9% total harmonic distortion
	Surround	(Front & Centre Channels) 80 watts x 3, min. RMS, driven into 8 ohms at 1kHz, with no more than 0.8% total harmonic distortion	(Front & Centre Channels) 80 watts x 3, min. RMS, driven into 8 ohms at 1kHz, with no more than 0.8% total harmonic distortion
		(Surround Channels) 80 watts x 2, min. RMS, driven into 8 ohms at 1kHz, with no more than 0.8% total harmonic distortion	(Surround Channels) 80 watts x 2, min. RMS, driven into 8 ohms at 1kHz, with no more than 0.8% total harmonic distortion
Total Harmonic Distortion		0.8%* at 80W, 8 ohms, 1kHz	0.8%* at 80W, 8 ohms, 1kHz
Input Sensitivity/Impedance	VCR/TV/DBS/TAPE	240mV/47 k ohms	240mV/47 k ohms
Signal-to-Noise Ratio (66 IHF/DIN)	VCR/TV/DBS/TAPE	87dB/67dB	87dB/67dB
Frequency Response	VCR/TV/DBS/TAPE	20Hz - 20kHz (±1dB)	20Hz - 20kHz (±1dB)
Tone Control	Bass	±10dB (100Hz)	±10dB (100Hz)
	Treble	±10dB (10kHz)	±10dB (10kHz)
<b>TUNER SECTION</b>			
Tuning Range	FM	87.5 - 108MHz	87.5 - 108MHz
	AM	522 - 1,629kHz	522 - 1,629kHz
<b>VIDEO SECTION</b>			
Horizontal Resolution		500 Lines	500 Lines
Output Level	RGB	0.7Vp-p/75 ohms	0.7Vp-p/75 ohms
	S-Video - Y	1.0Vp-p/75 ohms	1.0Vp-p/75 ohms
	-C	0.286Vp-p/75 ohms	0.286Vp-p/75 ohms
	Composite	1.0Vp-p/75 ohms	1.0Vp-p/75 ohms
<b>GENERAL</b>			
Dimensions (W x H x D)	mm	435 x 100 x 403.5	435 x 100 x 403.5
Mass	kg	8.0	8.0
<b>FEATURES</b>			
<b>DVD SECTION</b>			
<b>MECHANISM/SERVO</b>			
Type		Single	Single
Playable Formats	DVD-Audio	●	●
	DVD-Video	●	●
	DVD-R (VIDEO Format)**	●	●
	CD	●	●
	SVCD/VCD	●	●
	CD-R/RW	●	●
	MP3 (CD-R/RW)	●	●
	JPEG (CD-R/RW)	●	●
NTSC Playback on PAL TV		●	●
<b>VIDEO</b>			
Ultra-High-Performance 1-Chip AV Decoder		●	●
Adaptive Geometrical Chroma Mapping		●	●
Video D/A Converter		10-bit/54MHz	10-bit/54 MHz
VFP (Video Fine Processor)	Number of Parameters	7	7
	Number of Presets (Presets 2/Manual 2)	●	●
Variable Search (Forward/Reverse)		●	●
Variable Slow (Forward/Reverse)		●	●
RESUME (Bookmark) Function		●	●
DIGEST Play (9 Pictures)		●	●
STROBE Play (9 Pictures)		●	●
ANGLE LIST (9 Angles)		●	●
ZOOM Play		● (10 Steps)	● (10 Steps)
<b>GENERAL</b>			
On-Screen Display	New GUI (Graphical User Interface)	●	●
	On-Screen Language	English/French/German	English/French/German
	Numerical Bit-Rate Indicator	●	●
	Language Indicator	●	●
	Screen Saver	●	●
<b>RECEIVER SECTION</b>			
<b>CIRCUITRY</b>			
Audio D/A Converter		192kHz/24-bit (P.E.M. D.D. Converter)	96kHz/24-bit
Surround Sound	Dolby Digital Decoder Built-in	●	●
	DTS Decoder Built-in	●	●
	Dolby Pro Logic II	●	●
DAP for 2-Channel Sources	HALL/DANCE CLUB/LIVE CLUB/PAVILION	●	●
ALL CHANNEL STEREO Mode		●	●
PCM/Dolby Digital/DTS Digital Out		●	●
<b>INPUT/OUTPUT</b>			
◆: Assignable / □: Initial Settings (Default)			
		Audio	21-Pin Scart
		Analogue	Audio
		Digital	Digital
		Optical	Coaxial
TV	IN	□	◆
STB	IN	◆	□
TAPE/CDR (ASSIGNABLE)	IN/OUT	●/□	◆
VCR	IN/OUT	●	◆
Total Number of Inputs		1	1
Total Number of Outputs		1	1
Pre-Out	Subwoofer	●	●
Speaker Terminals	Main L/R	●	●
	Centre	●	●
	Surround L/R	●	●
<b>FUNCTIONS</b>			
On-Screen Display		●	●
Fluorescent Display	Dot-Matrix Display	●	●
	Dimmer	●	●
TV Direct Mode		●	●
Tone Control	Bass	●	●
	Treble	●	●
Balance		●	●
<b>TUNER</b>			
RDS Tuner: PS/PTY/RT, PTY Search		●	●
	TA/NEWS/INFO	●	●
Number of Presets		30 FM and 15 AM	30 FM and 15 AM
<b>MISCELLANEOUS</b>			
Remote Control Unit	Multi-Brand A/V	●	●
	Liquid Crystal Display	●	●

\* Measured by JVC Audio Analysis System.

\*\* DVD-R discs recorded with the DVD VIDEO format can be played back, though some may not be played back because of the disc characteristics or recording condition.