

6 head HIFI Stereo VCR

- Easy Link / NexTV Link bus system for automatic installation, automatic time & date setup
- SMART Picture for an individual picture preference setting
- Crystal Clear Video for an excellent picture quality
- Shuttle for a more intuitive tape-handling
- Audio Stereo inputs and outputs to connect to your HIFI system and enjoy a complete Home Cinema System
- Front AV input for easy recording from your Camcorder
- Manual audio level control possibility



SHOWVIEW











Product Information

Reception

Tuner: Full (UHF + VHF + Hyperband) Tuner Tuning: PLL, CH - FREQ entry, 99 presets Tuning/Install Features: Guide Channel Mapping, Manual Search/Store, Plug & Play

User Interface

Time/Date Download: PDC , Text (Time/Date)

Special Features: Child Lock, Demo mode
Picture Improvement System: Digital Studio Picture Control,
Crystal Clear Video, SMART Picture

Additional Playback Standard: Black & White, NTSC
Audio Recording System: Audio only, FM Audio, Linear
Audio Recording Level: Automatic, Manual
TV-Related Functions: 16:9 (pin 8), Follow TV, Direct Record
TV-Related Digital Bus Functions: Easy Link / Cinema Link (pin 10)

Programming

Number of Events: 6/month Programming Mode: OTR, Remote

Record Control & Transmitter Identification: PDC, VPS

Automatic Sat. Recording: From Ext. 1 and Ext.2 Record Speed: Long Play, Standard Play

Tape Deck

Number of Video / FM Audio / Flying Erase Heads: 4 / 2 / 0 Play: +1, -1, Repeat Additional Playback Features: Still, Multiple Search Speeds,

Variable Slow Motion Speed
Index Related Functions: Next/Previous index search

Tape Length Recognition: Automatic

Tape Counter: Linear relative, Linear time used/left

Automatic Functions at Tape End: Rewind after Play -Eject after Record
Winding / Rewinding Time (E180): 90 sec.
Head Cleaning Mode: Automatic, Manual

Connectors Rear

EXT1: Black, Euro CVBS in/out

EXT2: Blue, Euro CVBS in/out, Euro Decoder, RGB loop through

Audio Conn. Rear: Cinch stereo in, Cinch stereo out Terrestrial Antenna In & Out: 75 Ohms (IECtype) Mains Connector: Standard (IECtype)

Connectors Front

Audio/Video Conn. Front: Cinch CVBS in, Cinch stereo in

Voltage: 198-264 V

Frequency: 50Hz
Backup Presets & Timer Events: 1yr
Backup Clock & Calendar: 7hrs
Power Cons. in Play / Std-By / Low Power Std By: 18.0 / 6.0 /

Equipment Supplied: Aerial cable, Mains cord, Remote Control, **Batteries**

Weight incl. / excl. package in kg: 6.5 / 4.3 Set Size - W x D x H (mm): 435 x 290 x 93 Packaging - W x D x H (mm): 553 x 384 x 180

6 head HiFi Stereo VCR

Product Highlights

Easy Link / NexTView Link

What would you say if your VCR could be installed automatically just by connecting it to your TV?

Wouldn't it be nice if the TV could switch on automatically when you use the VCR?

. Wouldn't it be ideal if, after having surfed through the Electronic Programme Guide, you could programme the VCR's timer by just selecting the film you want and without leaving the TV remote control?

This is not a dream. This is NexTView Link.

Crystal Clear Video

With this unique feature, our engineers have put all their knowledge on the drawing board. The result?

- · New laser cut video heads: You have the ultimate in head technology and an extended life duration.
- Digital Studio Tracking system: A guarantee that the head will not drift away from the track and therefore that your picture will be
- Natural Colours: Thanks to a sophisticated Noise-Reduction circuit, the colours look brighter and are virtually noise free.
- Digital Studio Picture Control: Regardless of the tape quality you use, we make sure that you get the optimum picture quality out of it.

SMART Picture

With SMART picture, you can adapt the picture to your own preference: you can exaggerate the contours on this cartoon or suppress the noise from that rental tape. We offer you the possibility to play your tapes the way you like to see them.

Auto Seek Modulator

Your VCR will automatically search for the best frequency to tune the modulator to. This guarantees the best possible picture on your

• Multibrand Remote Control

Should we say it? Our remote-controls can communicate with more than 190 different brands of TVs.

	/02	/07	/16	/39	/58
TV System Off Air	PAL B/G	PAL I	PAL B/G	PAL B/G, PAL I, SECAM B/G, SECAM L/LI	PAL B/G, PAL D/K, SECAM B/G, SECAM D/K
Sound System Off Air	German Stereo, Mono	Mono, NICAM	German Stereo, Mono, NICAM	German Stereo, Mono, NICAM	German Stereo, Mono, NICAM
Modulator System	Pal G	Pal I	Pal G	Splitter	Pal GK (switchable)
Modulator Features	Auto Seek, Electr.	Auto Seek, Electr.	Auto Seek, Electr.		Auto Seek, Electr.
	On/Off switch	On/Off switch	On/Off switch		On/Off switch
Modulator Range	Ch 21 - Ch 55	Ch 21 - Ch 55	Ch 21 - Ch 55		Ch 21 - Ch 55
Modulator Preadjustment	591.25 MHz (Ch 36)	583.25 MHz (Ch 35)	591.25 MHz (Ch 36)		591.25 MHz (Ch 36)
OSD Menu Languages	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Spanish, Swedish	English	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Spanish, Swedish	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Spanish, Swedish	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Spanish, Swedish
Delivery Menu Language	English	English	English	French	English
Record/Playback Standard	PĂL	PAL	PAL	MESECAM, PAL, Secam	MESECĂM, PAL
Programming System	Daily/Weekly, Showview	Daily/Weekly, VideoPlus+	Daily/Weekly, Showview	Daily/Weekly, Showview	Daily/Weekly, Showview
Remote Control RT198	/101	/101	/101	/104	/101

Subject to modification without notice

ShowView and VideoPlus are Trademarks of Gemstar Development Group



