

CES26WSD7-B

26" HD Ready LCD with Digital Tuner



Piano Black Finish with Silver Speaker

Resolution - 1366x768

Brightness - 500cd/m²

Contrast - 800:1

Viewing Angle(H/V) - H:160 V:150

Response Time - 8 ms

500 Teletext Page Memory

100 Analogue Channels

999 Digital Channels

NICAM Stereo

Bass Expander

Automatic Volume Level Control

2 X 8 Watts Speaker Output

Head Phone Volume Control

Black Stretch

Blue Stretch

Color Temperature Control

Wide Picture Mode

Auto Wide Selection

Picture Selection Mode - Dynamic, Natural, Cinema

Of Timer

Child Lock

Power Supply

Voltage / Current - 100V-240V AC

Standby Mode - 2.7 Watts

Power On - 160 Watts

Size = (W)69.9 x (H)49.9 x (D)12.6 cm

Weight = 11.5 kg

Analogue Broadcasting

F/S Tuning

Full Auto Tuning

Channel Swap

Fine Tuning

Plug & Play

ATS (Automatic Tuning System)

Auto Sort

Digital Broadcasting

Full Auto Tuning

Auto Logical Channel Sort

Manual Channel Sort

EPG

AV1 - SCART 1 (AV-IN,RF-OUT,RGB-IN)

AV2 - SCART 2 (AV-IN,MONITOR-OUT)

AV3 - FAV IN

AV4 - SVHS

Audio out

2 HDMI - HD READY / DVI

YPbPr - (720p/ 1080i Resolution)

PC-in(VGA)

PC-Audio In

Headphone Jack

Software Download Terminal

Filename: CES26WSD7-B
Directory: C:\Users\g.day\AppData\Local\Microsoft\Windows\Temporary Internet Files\OLKACAA
Template: C:\Users\g.day\AppData\Roaming\Microsoft\Templates\normal.dot
Title: CES26WSD7-B
Subject:
Author: n.south
Keywords:
Comments:
Creation Date: 14/05/2008 11:03:00
Change Number: 2
Last Saved On: 14/05/2008 11:25:00
Last Saved By: n.south
Total Editing Time: 12 Minutes
Last Printed On: 17/06/2008 09:54:00
As of Last Complete Printing
Number of Pages: 1
Number of Words: 175 (approx.)
Number of Characters: 998 (approx.)