



What's in the box

Watch

Cradle

An optional AC adapter can be purchased separately.



1. Charging and setup

Charge this product before using it for the first time.


1. Connect the cradle to a power source.

- » Using a PC
Connect the cradle's USB plug to the computer's USB port.
Do not use a USB hub. Instead, connect the cradle directly to the computer.
- » Using the optional AC adapter
Connect the cradle's USB plug to the AC adapter's USB port.

We recommend using the optional AC adapter (model number: SFAC04). If you do not use a supported AC adapter, you may not be able to charge the product or it may not operate correctly.

2. Place the product into the cradle.


Check that the contact points on the product are pointing up and match the contact marks on the cradle. After placing the product into the bottom of the cradle with the LCD screen facing out, push carefully on the top of the product until it clicks into place.




When the product is placed correctly, the alarm sounds, the charging screen is displayed, and charging starts.

3. When charging is complete, remove the product from the cradle.

Hold the cradle and press the product down into the lower part of the cradle to release the product.



4. Follow the on-screen instructions to set the language, units, and user information.



5. When you are in a location with no obstructions overhead, select Yes.

A signal is received from the GPS and time is automatically synchronised.



NOTE

When you do not use the product for a while, it enters sleep mode and the time display turns off. This is not a malfunction as the display is restored the next time you move the product. If time synchronisation fails, the time screen will automatically be updated the next time a GPS signal has been received. You can proceed to section 2, "Using RUNSENSE View."

2. Using Epson RUNSENSE View (Windows® PC)

Installing Epson Run Connect Software

This product allows you to manage measured data using the RUNSENSE View web app. To upload measurement data, you need to install Epson Run Connect on your Windows PC and connect to the Internet.

NOTE

Install Epson Run Connect before connecting the product to your PC.


1. Visit epson.com/support/sf810 (U.S.) or epson.ca/support/sf810 (Canada) and download Epson Run Connect for PC.
2. Run the downloaded file and follow the instructions displayed on the setup screen.

Creating an account

1. Connect the cradle with a USB cable to the PC on which Epson Run Connect is installed.


2. Place the product into the cradle.

Check that the contact points on the product are pointing up and match the contact marks on the cradle.



Epson Run Connect starts.

3. Click Create Account and enter your details.



Uploading your data

Connect your RUNSENSE product to the computer. The following box automatically appears. Enter your **Login ID** and **Password** and click **Upload**.



Viewing your data

1. Click **Start RUNSENSE View** on the Run Connect screen. Or visit <https://go-wellness.epson.com/runsense-view/>.
2. Click the data you want to check from the list.

NOTE

For information on using the RUNSENSE View, see the RUNSENSE View Help.

3. Using the Epson Run Connect app

Installing Epson Run Connect

Download and install Epson Run Connect from your mobile device's app store.

NOTE

- The following mobile devices are supported:
- iPhone 4s, iPhone 5, iPhone 5c, iPhone 5s, iPhone 6, and iPhone 6 Plus with iOS 6 or later.
 - Mobile devices running Android™ 4.3 or later with Bluetooth® Smart.

Pairing your product

1. Start the Epson Run Connect app.
2. Tap **Pairing**.
3. Tap **Start Pairing**.
4. Press and hold **D** on the product.



5. Tap OK on your mobile device.



Your product displays a passcode.

6. Enter the 6-digit passcode on your mobile device and tap OK or Pair.


7. Tap OK to finish pairing.

NOTE

For more information on using the Epson Run Connect app, see the online iOS or Android user manual.

4. Wearing your SF-810

Wear the product snugly around your wrist as shown in the illustration below. Tighten the wristband if your pulse is not measured correctly while exercising.



NOTE

After putting on the product, press **A** on the Time screen, and check that your pulse is being measured.

Caring for your SF-810

Your Runsense product is made from materials commonly used in watches and other consumer products. Since you may wear your product over extended periods, including when you are exercising and sweating, it is important that you take care of your skin and your product according to these instructions. Prolonged wearing of your product without proper care could lead to skin irritation or rash. Please follow the precautions below to ensure full enjoyment and benefit of your Runsense product:

- Keep Runsense and skin clean.
- Keep Runsense and skin dry.
- Give skin a rest and some air.

Proper wear and care of your SF-810 is an important part of your enjoyment of this product. Make sure to see the online *User Manual* for more detailed information on caring for your product.

Safety Instructions

The following symbols are used in this guide to indicate possible dangerous operations or handling. Make sure you understand these warnings before using the product.

	Warning	This symbol indicates information that, if ignored, could possibly result in serious personal injury.
	Caution	This symbol indicates information that, if ignored, could possibly result in personal injury or damage the product.

	This symbol indicates an action that should be done.
	This symbol indicates an action that must not be done.

Notes on Using the Product and Components

		Warning
	Exercise according to your physical capabilities. Stop exercising and consult your doctor if you feel unwell during exercise.	This product is not intended for use to diagnose, prevent, or treat disease or other conditions, and is not a medical device. If you have any concerns, consult your doctor before using this product.
	Do not use or store this product in the following environments. It may cause an electric shock or fire, or the product may malfunction or be damaged. <ul style="list-style-type: none"> •Locations with very high or low temperatures or humidity •Near volatile substances •Dusty places •Near a strong magnetic field (for example, near a loudspeaker) 	Do not disassemble this product, and do not attempt to repair this product by yourself. It may cause an electric shock or accident.
Do not leave this product within reach of young children.		Do not leave this product within reach of young children.
The cradle cords included with this product contain chemicals, including lead, known to the State of California to cause birth defects or other reproductive harm. Wash hands after handling. (This notice is provided in accordance with Proposition 65 in Cal. Health & Safety code § 25249.5 and following.)		

		Caution
	Persons with high skin sensitivity, eczema, allergies, or asthma may be more likely to experience skin irritation or an allergic reaction from the Runsense product or similar products. Even persons without such conditions may start to experience redness or skin irritation on wrists from prolonged use or if the product is not cleaned regularly as indicated above. If you experience such symptoms: <ul style="list-style-type: none"> •Stop wearing and remove your product immediately. Do not put it back on. •If symptoms persist for more than 2-3 days after removing the product, consult a dermatologist. •Make sure to follow the wear and care instructions above and in the online <i>User Manual</i>. 	

Using your SF-810

This product has a Time screen, Measurement screen, Settings screen (Settings menu and Measure set. menu), and History screen, and you can perform operations with the following buttons.



Button Operation	Time screen	Measurement screen	Settings screen
A Short press	Starts heart rate measurement.	Changing between screen.	Confirm a selection.
A Long press*1	Turns the power on or off.	Displays the time screen. (Not available while measuring.)	From the Settings menu, the time screen is displayed. From the Measure set. menu, the measurement screen is displayed.
B Short press	Turns the light on or off. The light turns on for approximately 10 seconds.		
B Long press*1	Displays the Settings menu. > Settings screen	Displays the Measure set. menu. (Not available while measuring.)	-
C Short press	Performs GPS positioning, and displays the Measurement screen.	Starts, stops, or resumes measuring.	Selects the upper item. Increases the value.
C Long press*1	-	Displays the time screen. (Not available while measuring.)	Selects the upper item. Scrolls through the values.
D Short press	Displays your workout history.	Records laps while measuring.	Selects the lower item. Decreases the value.
D Long press*1	Sync to Bluetooth device. Use this when uploading measurement data.	Resets*2 while measuring is stopped.	Selects the lower item. Scrolls through the values.


*1 Hold down for at least two seconds until the screen changes.

*2 When you reset the display, it returns to the status before measuring started allowing you to start the next measurement. Data that has been measured up to that point is stored in the product's memory.

If no operations are performed after three minutes when the System settings, User settings, or History screens are displayed, you are returned to the time screen.

Using the chronograph

This function allows you to measure split times and lap times simultaneously.



You can record laps by pressing **D** on the product during Chronograph measurement, or by using the AT lap function.

Measuring



1. Press **C** on the measurement screen to start measuring.
2. To record a lap, press **D**.




3. Press **C** again to stop recording.
4. Press and hold **D** for a few seconds when you have finished recording to reset the measurement display.

NOTE

- The Chronograph screen is composed of four screens, and you can change the screen display by pressing **A**. You can change the content displayed on screens 1 to 4 by going to Measure set. > Screen. For more details, see the online *User Manual*.
- After resetting, press and hold **A** or **C** for a few seconds to return to the time screen.
- If no operations are made for 60 minutes on a screen other than the measuring screen, the Time screen is displayed.
- As well as the Chronograph function, there are a variety of other measurement functions. Please see the online *User Manual* for details.

Checking the history

1. Press **D** on the Time screen. The Recall screen is displayed.



2. Press **C** or **D** to select the history you want to display, and then press **A**.



3. To check the history, press **C** or **D** to scroll through the history screen. Detailed recorded results for the activity type, recorded day/start time, time, distance, and calories burned are displayed on the detailed recall screen. You can also check the pace for each lap.



Press **A** to return to the recall screen. Hold down **A** to return to the time screen.

Understanding the icons

	Run mode		Split time
	Walking mode		Average pace
	Bike mode		Calories burned
	Stops flashing: The signal is being received from the GPS (GPS On)		Stride
	GPS positioning		Lap
	Heart rate ON		Editable data
	Distance		Current settings

Setting goals

Goals

This function allows you to measure until a set time or distance set is reached.

Time race

Allows you to set a time as your goal and measure the remaining time until that goal is reached.



Distance race

Allows you to set a distance as your goal and measure the remaining distance until that goal is reached.




1. **Display the measurement screen:**
Press **C** on the time screen. GPS positioning starts, and the measurement screen is displayed once positioning is complete.
2. **Display the Measure set. menu:**
Hold down **B** on the measurement screen.
3. **Select Mode.**
4. **Select Goal.**
5. **Select Time or Distance.**
6. **Set the Time or Distance.**
7. **Select OK.**
8. **Press **C** to start measuring.**
When the set time or distance is reached, the Finish screen is displayed.
An alarm notifies you when you reach 50% and 90% of the set time or distance.

NOTE

Set the Estimated Time or Estimated Distance in your screen settings to view and keep track of your progress. For more details, see the online *User Manual*.

AT Lap


When a time or distance set in advance is reached, laps are recorded automatically. Set the lap time or distance. You can set five preset times or distances.



1. **Display the measurement screen:**
Press **C** on the time screen. GPS positioning starts, and the measurement screen is displayed once positioning is complete.
2. **Display the Measure set. menu:**
Hold down **B** on the measurement screen.
3. **Select AT Lap.**
4. **Select one of the No Data from 1 to 5.**
5. **Select whether to set Time or Distance as the length of the lap.**
6. **Set the Time or Distance.**
7. **Press **A** to complete the settings.**
8. **Hold down **A** again to return to the measurement screen.**
9. **Press **C** to start measuring.**

AT Pause

This function stops measuring automatically when you stop running, and resumes when you continue running.




1. **Display the measurement screen:**
Press **C** on the time screen. GPS positioning starts, and the measurement screen is displayed once positioning is complete.
2. **Display the Measure set. menu:**
Hold down **B** on the measurement screen.
3. **Select AT Pause.**
4. **Select ON.**
5. **Press **A** to complete the settings.**
6. **Hold down **A** again to return to the measurement screen.**
7. **Press **C** to start measuring.**

Maintenance

Cleaning your product

To clean the product, wipe the contact points and sensor lightly with a damp cloth and allow the product to air dry.



If charging or communicating becomes unstable, clean the contact points on the product and the cradle with a damp cotton swab.

Do not use any cleaning products on this product.

Resetting your product

You can reset the system by following the steps below.

Hold down all of the buttons (**A/**B**/**C**/**D**).**

The screen is reset and the product restarts.

Initialize the product after restarting. See section 1, "Charging and setup."

Setting data and measurement data remain as they were before the reset was performed.



NOTE

The time screen will automatically be updated the next time a GPS signal has been received.

Where to get help

Internet support and user manuals

Visit epson.com/support/sf810 (U.S.) or epson.ca/support/sf810 (Canada) for solutions to common problems. You can get tips, usage information, and FAQs, download utilities, view the user manuals, or e-mail Epson.

Telephone support services

Call (800) 241-5789, (562) 276-4394 (U.S.), or (905) 709-3839 (Canada).

Support hours are 6 AM to 8 PM, Pacific Time, Monday through Friday, and 7 AM to 4 PM, Pacific Time, Saturday.

Days and hours of support are subject to change without notice. Toll or long distance charges may apply.

Notices

Make sure you read the manuals (Quick Start Guide and User Manuals) first to use this product safely. Also, this product is equipped with Bluetooth Smart technology as a built-in wireless function. See the section "Notes on Electromagnetic Waves" in the online *User Manual* for further details.

The product may malfunction, or an accident may occur if it is handled incorrectly.

- Keep the manuals handy to help you resolve any problems.
- When taking this product out of the country of purchase, check the laws and regulations in the destination country before you travel.
- This product is not a medical device. Use this product to track physical exercise.

	The product is water resistant at 5 bar (5 ATM). Although you can use the product while swimming, do not perform button operations under water.
	Do not pour water directly from the tap onto this product. The power of the tap water stream may be strong enough to compromise the product's water resistance.
	Do not wear this product in a bath or sauna. The steam and soap may compromise the water resistance or cause corrosion.

Notes on Using the Cradle

	Do not use the cradle or AC adapter if they are in any way damaged, faulty or contaminated by foreign material such as dust, water or dirt. Do not use any adapter other than the specified adapter for charging.

Epson America, Inc. Limited Warranty

One-Year Limited Warranty

What Is Covered: Epson America, Inc. ("Epson") warrants to the original retail purchaser of the Epson product enclosed with this limited warranty statement that the product, if purchased new and operated in the United States, Canada, or Puerto Rico will be free from defects in workmanship and materials for a period of one (1) year from the date of original purchase. For warranty service, you must provide proof of the date of original purchase.

What Epson Will Do To Correct Problems: If your product requires service during the limited warranty period, please call the Epson ConnectionSM at the number on the bottom of this statement and be prepared to provide the model, serial number, and date of original purchase. An Epson service technician will provide telephone diagnostic service to determine whether the product requires service. If service is needed, Epson will, at its option, repair or replace the defective unit, without charge for parts or labor. When Epson authorizes an exchange for the defective unit, Epson will ship a replacement product to you, freight prepaid, so long as you use an address in the United States, Canada, or Puerto Rico. You are responsible for securely packaging the defective unit and returning it to Epson within five (5) working days of receipt of the replacement. Epson requires a debit or a credit card number to secure the cost of the replacement product in the event that you fail to return the defective one. When warranty service involves the exchange of the product or of a part, the item replaced becomes Epson property. The exchanged product or part may be new or equivalent to new in reliability and performance, and at Epson's option, the replacement may be another model of like kind and quality. Exchange or replacement products or parts assume the remaining warranty period of the product covered by this limited warranty.

What This Warranty Does Not Cover: This warranty covers only normal use in the United States, Canada or Puerto Rico. This warranty does not cover normal wear and tear; including nicks and scratches, and battery life, unless the damage was caused by a manufacturing defect in materials and workmanship. This warranty does not cover damage caused by parts or services not manufactured, distributed, or certified by Epson nor any losses attributable to the loss or restoration of customer data. Epson does not warrant that the operation of the product will be error-free, that we will correct errors, or your use of the product and software will be uninterrupted. This warranty does not cover misuse caused by high impact wear or damage caused by exposure to water as specified in the product user manual. This warranty does not cover skin irritation arising from wear. See the *Runsense User's Guide* and *Quick Start Guide* for wear and care instructions. This warranty is not transferable. Software for this product is not covered under this warranty. See the Epson Runsense Website for software warranties. Epson is not responsible for warranty service should the Epson label or logo or the rating label or serial number be removed. Epson is not responsible for warranty service should the product fail to be properly maintained or fail to function properly as a result of misuse, abuse, improper installation, neglect, improper shipping, damage caused by disasters such as fire, flood, and lightning, improper electrical current, software problems, interaction with non-Epson products, or service other than by Epson or an Epson Authorized Servicer. Postage, insurance, or shipping costs incurred in presenting your Epson product for warranty service are your responsibility. If a claimed defect cannot be identified or reproduced in service, you will be held responsible for costs incurred.

DISCLAIMER OF WARRANTIES: THE WARRANTY AND REMEDY PROVIDED ABOVE ARE EXCLUSIVE AND IN LIEU OF ALL OTHER EXPRESSED OR IMPLIED WARRANTIES INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT. UNLESS STATED HEREIN, ANY STATEMENTS OR REPRESENTATION MADE BY ANY OTHER PERSON OR FIRM ARE VOID.

Remedies: Your exclusive remedy and Epson's entire liability for a material breach of this Agreement will be limited to a refund of the price paid for the Epson product covered by this Agreement. Taxes and shipping will not be refunded. Any action for breach of warranty must be brought within 3 months of the expiration date of the warranty. Epson is not liable for performance delays or for nonperformance due to causes beyond its reasonable control. EXCEPT AS PROVIDED IN THIS WRITTEN WARRANTY, NEITHER EPSON NOR ITS AFFILIATES SHALL BE LIABLE FOR ANY LOSS, INCONVENIENCE, OR DAMAGE, INCLUDING DIRECT, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES, INCLUDING LOST PROFITS, COST OF SUBSTITUTE EQUIPMENT, DOWNTIME, CLAIMS OF THIRD PARTIES, INCLUDING CUSTOMERS, OR INJURY TO PROPERTY, RESULTING FROM THE USE OR INABILITY TO USE THE EPSON PRODUCT, WHETHER RESULTING FROM A BREACH OF WARRANTY OR ANY OTHER LEGAL THEORY. Some jurisdictions do not allow limits on warranties or remedies for breach in certain transactions. In such jurisdictions, the limits in this paragraph and the preceding paragraph may not apply.

In Canada, warranties include both warranties and conditions.

Arbitration, Governing Laws: Any disputes arising out of this Agreement will be settled by arbitration to be conducted before a single arbitrator in Los Angeles, California, in accordance with the commercial Arbitration Rules of the American Arbitration Association, and judgment upon the award rendered by the arbitrator may be entered in any court having jurisdiction thereof. This Agreement shall be construed in accordance with the laws of the State of California, except this arbitration clause which shall be construed in accordance with the Federal Arbitration Act.

To find the Epson Authorized Reseller nearest you, please visit our website at: epson.com.

For product support, please visit our website at: epson.com/support.

To contact the Epson Connection, please call (800) 241-5789 or (562) 276-4394 in the U.S. and (905) 709-3839 in Canada or write to Epson America, Inc., P.O. Box 93012, Long Beach, CA 90809-3012.

EPSON is a registered trademark, EPSON Exceed Your Vision is a registered logomark, and Runsense is a trademark of Seiko Epson Corporation. Epson Connection is a service mark of Epson America, Inc.

iPhone is a trademark of Apple Inc., registered in the U.S. and other countries.

The Bluetooth word mark is owned by Bluetooth SIG, Inc.

Android is a trademark of Google Inc.

General Notice: Other product names used herein are for identification purposes only and may be trademarks of their respective owners. Epson disclaims any and all rights to those marks.

This information is subject to change without notice.

© 2015 Epson America, Inc., 2/15

CPD-42816

Printed in Japan