# **Cordless FM Surround headphone**

SBCHC8900

(suitable for Home Cinema) (CD sound quality) Charging Docking Station Auto tuning High sound quality meters PHILIPS

Let's make things better.



**PHILIPS** 

## **Cordless FM Surround** headphone

## Standard product information

## **System information**

 Carrier frequencies channel 1: 863.250 MHz

channel 2: 863.500 MHz channel 3: 863.750 MHz channel 4: 864.000 MHz channel 5: 864.250 MHz channel 6: 864.500 MHz channel 7: 864.750 MHz

• Effective linear range Up to 100 meters

Modulation

## Transmitter information

• Input sensitivity 250 mV, 3 V 3.5 mm stereo jack Audio input connect • Audio cable length 2 meter (jack to jack) 12 V, 200 mA • Power supply • Mains voltage 200 - 230 V • Auto shut-off Yes ALC Νo • Cabinet material ABS • Cabinet colour Metallic Silver/Metallic · Graphics colour

## **Receiver information**

Electro-dynamic Type • Acoustic system Semi - Closed 10 - 24 000 Hz • Frequency range > 40 dB Channel separation 90 dB • S/N ratio • Batteries used

 $2 \times R03,AAA$  (NiMH) 12 hours (with NiMh batteries) • Playing time

 Mute Yes

 Volume control Stereo Cabinet material ABS Metallic Cabinet colour · Graphics colour Metallic

## **Packaging information**

• FM transmitter SBC HC8902

• FM headphone SBC HC8905

AC/DC adapter

• Hi-fi audio cable

• Rechargeable batteries • Instructions For Use

• 3.5 - 6.3 mm stereo adapter

· Jack to cinch adapter

## **Product packaging**

 Type • Size 350 x 250 x 100 mm • Material 450 gsm ccnb • 12NC 9082 100 00173 87 10101 65145 3 EAN

## Inner carton

Carton box Type • Size 312 x 362 x 271 mm • Qty 3 pieces • EAN 87 10101 99246 4

## **Outer carton**

 Type Carton box Size 645 x 380 x 578 mm • Qty 12 pieces 87 10101 99247 1 EAN



#### Cordless Surround (suitable for Home Cinema) For the special Surround Sound feature in the HC8900 the headphone is equipped with (\*) \$888 HEADPHONE to create a three-dimensional, full-bodied sound. The wearer experience 'live' musical sounds from the headphones but

without the excess volume of extra speakers. This feature is controllable on the headphone set.

**Charge docking station**The SBC HC8900's transmitter unit has a built-in charge circuit that recharges the headphone's batteries to provide up to 15 hours of continuous music pleasure.

## Auto tuning

This feature eliminates tiresome manual tuning; just press the Auto Tune button and you are quickly tuned for optimum

### Clear Sound (CD sound quality)

Innovative signal processing combines the quality of CD sound with the benefits of cordless operation. Improved dynamic range (90 dB) is achieved by using state-of-the-art Dynamic Signal Levelling. The finest musical details are transmitted, thanks to an Extended Frequency Response Technique that achieves a smooth frequency response up to

## High sound quality up to 100 meters

The SBC HC8900 offers unlimited freedom of movement up to 100 meters from the music source while maintaining perfect sound quality throughout, thanks to Philips innovative interference-free RF technology.

OF SAS HEADPHONE and the symbol are trademarks of SRS Labs, Inc. in the United States and selected foreign countries.

( ) SAS HEADPHONE technology is incorporated under license from SRS Labs, Inc.

## **Philips Accessories**

Data subject to change without notice ©2000 Royal Philips Electronics All rights reserved

http://www.philips.com



