PORTFOLIOTM

HOUSING



TRIM

HOUSING

HA3MR=Low Voltage MR16 Directional, 120/277V HA3MRCP=Low Voltage MR16 Directional, 120/277V Chicago Plenum

3" Low Voltage Directional MR16

Dimensions	Length	Width	Height	Cutout	
Standard Housing	12-1/8"	12"	5-9/16"	4-9/16"	
Chicago Plenum	12-1/8"	12"	5-9/16"	4-9/10	

Low Voltage MR16 adjustable fixture for flat or slope ceilings. Use open downlight for general and task lighting. Pinhole hides lamp and provides clean ceiling. Lens wall wash for even illumination along vertical surfaces. Lockable 361° rotation and 45° tilt with center beam optics provides full output with no flash back. Top lamp accessible. Integral magnetic transformer.

OPTIONS

DR37=DeRated Wattage Label for 37W Maximum DR50=DeRated Wattage Label for 50W Maximum

Λ	C	r	c	c	c	n	D	IE	c
M		6	-	0	0	U	n		9

HB26=C Channel Bar Hanger, 26" Long, Pair HB50=C Channel Bar Hanger, 50" Long, Pair RMB22=Wood Joist Bar Hanger, 22" Long, Pair L100 Series=Color Filters and Lens FK5=Field Installed Fuse Kit. 5 Amp

TRIM

Open Downlight FINISH **OPTIONS** LI=Low Iridescent Clear WF=White 3451=Self Flanged BB=Black Baffle . MR16 75W Max 3450=Metal Trim Ring, H=Haze (3450 only) Painted Flange WMH=Warm Haze WB=White Baffle White (Self Flanged **G**=Gold (3450 only) only) WH=Wheat B=Black W=Gloss White 3-1/2" **GP**=Graphite **GPH**=Graphite Haze K=Cognac **KH**=Cognac Haze TRIM FINISH **OPTIONS** WF=White 3471=Self Flanged LI=Low Iridescent Clear BB=Black Baffle 3470=Metal Trim Ring, H=Haze (3470 only) Painted Flange WB=White Baffle White WMH=Warm Haze (Self Flanged G = Gold(3470 only) only) WH=Wheat B=Black W=Gloss White **GP**=Graphite **GPH**=Graphite Haze K=Cognac KH=Cognac Haze TRIM 3470PIN=Pin Hole, Black MR16 75W Max Shielding Cone and Oculus, White Metal Trim Ring 1-1/2" 5-1/8 **FINISH OPTIONS** TRIM Lens Wall Wash 3481=Self Flanged LI=Low Iridescent Clear WF=White MR16 75W Max 3480=Metal Trim Ring, H=Haze Painted Flange WMH=Warm Haze White (Self Flanged G=Gold onlv) WH=Wheat B=Black W=Gloss White 3 - 1/2**GP**=Graphite **GPH**=Graphite Haze K=Cognac KH=Cognac Haze Housing Trim Accessories **Ordering Example** HA3MRDR50 3450LI HB26

-m



Angle Cut MR16 75W Max



Pinhole



