

# PORTFOLIO™

## HOUSING

6"



MA6S  
Magnetic



MA6S  
Electronic

### 6" Shallow Directional Metal Halide PAR20

Open directional downlight using a single PAR20 ceramic metal halide lamp. Low profile allows use where vertical clearance is limited. Use for vertical downlighting in sloped ceiling or for accent/display lighting. Lockable 365° rotation and 35° tilt with center beam optics providing full output with no flashback. Medium base extended husk socket accepts lamps suitable for open fixture use only. Housing has top access for lamp replacement above the ceiling. Magnetic ballast ordered separately installs rapidly to ballast bridge with electrical quick connects. Bar hangers provided with magnetic ballast housing.

Dimensions - <b>Magnetic</b>	Length	Width	Height	Cutout
Standard Housing	24-7/16"	19"	9-3/16"	6-3/8"
Chicago Plenum	24-7/16"	19"	9-3/16"	

Dimensions - <b>Electronic</b>	Length	Width	Height	Cutout
Standard Housing	18-5/8"	18"	9-3/16"	6-3/8"
Chicago Plenum	18-5/8"	18"	9-3/16"	

#### HOUSING [Magnetic Ballast]

MA6S=Metal Halide Directional, PAR20, Shallow Plenum  
MA6SCP=Metal Halide Directional, PAR20, Shallow Plenum, Chicago Plenum

#### BALLAST

790=39W MH 120/277V Magnetic

#### ACCESSORIES

TRM6=Metal Trim Ring, Specify Finish\*  
TRR6=Rimless Trim Ring, White\*  
FK\_=Field Installed Fuse Kit, Specify Amperage

\*Not compatible with Self Flange

#### HOUSING [Electronic Ballast]

MA6S39=39W Electronic Metal Halide Directional, PAR20 only, Shallow  
MA6S39CP=39W Electronic Metal Halide Directional, PAR20 only, Shallow, Chicago Plenum

#### BALLAST

1E=120V 50/60 Hz Electronic  
2E=277V 50/60 Hz Electronic

#### ACCESSORIES

HB26=C Channel Bar Hanger, 26" Long, Pair  
HB50=C Channel Bar Hanger, 50" Long, Pair  
RMB22=Wood Joist Bar Hanger, 22" Long, Pair  
TRM6= Metal Trim Ring, Specify Finish  
TRR6=Rimless Trim Ring, White  
FK=Field Installed Fuse Kit, Specify Amperage

## TRIM

### Angle Cut



#### TRIM


6471=Self Flanged  
6470=Molded Trim Ring, White

#### FINISH

LI=Low Iridescent Clear  
H=Haze  
WMH=Warm Haze  
G=Gold  
WH=Wheat  
W=Gloss White  
GP=Graphite  
GPH=Graphite Haze  
K=Cognac  
KH=Cognac Haze  
BB=Black Baffle (6470 only)  
WB=White Baffle (6470 only)

#### OPTIONS

WF=White Painted Flange (Self Flanged only)



#### Ordering Example\*

Housing, Ballast, Trim, Accessories and Lamps ordered as separate line items.

\*Magnetic Ballast - separate line item  
Electronic Ballast - ships with housing

Housing	Ballast	Trim	Accessories
MA6S391E		6471LI	HB26