#### **Common Phone Tasks**

Place a call	Go off-hook before or after dialing a number.
Redial a number	Press Redial.
Switch to handset during a call	Pick up the handset.
Switch to speaker or headset during a call	Press or or, then hang up the handset.
Mute and un-mute a call	Press .
View call history	Press > Call History.
Hold and resume a call	Press Resume to resume the held call.
Transfer a call to new number	Press , enter the number, then press it again.
Place an intercom call	Press the Intercom button, then enter a number if necessary. Speak after you hear the tone.
Start a standard conference call	Press , dial the participant, then press it again.
Silence the ring for an incoming call	Press the Volume button down once.



Cisco, Cisco Systems, the Cisco logo, and the Cisco Systems logo are registered trademarks or trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries. All other trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0705R)

© 2009 Cisco Systems, Inc. All rights reserved.



#### QUICK REFERENCE



## Cisco Unified IP Phone 6921, 6941, and 6961 for Cisco Unified Communications Manager 7.1 (SCCP)

Softkeys Phone Screen Icons Buttons Common Phone Tasks

#### Softkeys

Lists all missed, placed, and received calls.
Answer a call.
Confirm a ringtone selection.
Initiate a call.
Receive notification when a busy extension becomes available.
Cancel an action or exit a screen without applying changes.
Clear all values.
Delete an entry from Call History.
Delete a call from Call History.
Opens the Details for a multiparty call in the Missed, Placed, and Received Call records.
Dial a selected number.
Send or redirect a call to voicemail or to a predetermined phone number.
Modify a name or email address.
Modify a number.
Return to the previous screen.
Setup/cancel call forwarding.
Answer a call that is ringing in another group or on another line.
Sign out of Personal Directory.
Host a Meet Me conference call.
Open the record of missed calls.
Display additional softkeys.

OL-20187-01

New Call	Make a new call.
OK	Confirm a selection.
OPickup	Answer a call that is ringing in an associated group.
Park	Store a call.
Play	Play ringtone.
PickUp	Answer a call that is ringing on another phone in your group.
Redial	Redial the most recently dialed number.
Remove	Remove a conference participant or an entry.
Resume	Resume a call on hold.
Save	Save the chosen settings.
Search	Search for a directory listing.
Select	Select the highlighted option.
Set	Set a ringtone.
Submit	Enter user information.
Swap	Toggle between two existing calls.
Update	Update an entry in Personal Directory.
>>	Move through entered characters.
<b>&amp;</b> 5	Backspace to delete characters.
5	Back.

# **Phone Screen Icons**

L	Off-hook
•	On-hook
Ų.	Connected call
***	Incoming call
÷	Missed call
Ç.	Received call
Ų.	Placed call
II	Call on hold
Feat	ure Icons
(If ava	ailable on your phone)
V)	Message waiting
Ų.	Shared line in use
<b>!!!</b>	Speed dial line
6	Line Status indicator–monitored line is in-use
-	Line Status indicator-monitored line is idle
31.	Line Status indicator-monitored line is ringing (Call Pickup only)
•	Line Status indicator-monitored line is in do not disturb (DND)
	Idle intercom line
<b>5</b>	One-way intercom call (whisper)
<b>3</b>	Two-way intercom call (connected)
	·

## **Buttons**

Applications
Contacts
Messages
Transfer
Hold
Conference
Volume
Speakerphone
Mute
Headset
Navigation bar and Select button

For the Cisco Unified IP Phone Quick Start Guides, go to this URL:

http://www.cisco.com/en/US/products/ps10326/products\_user\_guide\_list.html