# Lifestyle CD Soundmachine



- Digital tuner with 32 station presets
- 20-track CD programmable
- Dynamic bass boost
- 6-digit multi-functional LCD display
- Repeat one/ all/ program
- Shuffle play
- 3" Full-range speakers











PHILIPS

# Lifestyle CD Soundmachine

# Standard product information

# CD player

- Toploader with manual door
- 20-track CD programmable
- Shuffle play
- Repeat one/ all/ program .
- CD next/ previous track search

### Tuner

- Digital tuning system
- . 20 FM + 12 MW station presets
- Telescopic antenna for FM reception
- Internal antenna for MW reception
- Wavebands FM stereo MW

## Sound system

- Output power 2 x 1 W RMS
- · Dynamic bass boost
- 2 x 3" speakers
- Metal speaker grills
- · Rotary volume control

# Display

· 6-digit multi-functional LCD

## Power supply

- AC/DC operation
- Batteries 6 x 1.5V, R14

## General

- · Product dimensions (mm)
  - 294 W x 142 H x 255 D 1.9 kg
- Product weight
- · Package dimension 350 W x 192 H x 297 D (mm)
- Weight incl packing 2.5 kg



#### Digital tuner with 32 station presets

Provides fast, accurate tuning to your favourite stations. You can store up to 20 FM and 12 MW stations in memory for fast, easy access.

### 20-track CD programmable

Stores up to 20 of your favourite CD tracks for playing back in your order of preference.

Dynamic bass boost An electronic circuit that enhances bass frequencies up to 3 times.

6-digit multi-functional LCD display Displays CD player information (track, time, play mode), tuner information (preset station, frequency) and DBB on/off.

Repeat one/ all/ program Repeats the current track, the total CD, or your pre-selected program.

Shuffle play Plays all selections on a disc in random order, giving you a new sequence of tracks every time.

#### 3" Full-range speakers

For excellent sound reproduction across the entire audio spectrum.

Printed in Hong Kong 2001-12-31 Specifications subject to modification without notice © 2001 Royal Philips Electronics All rights reserved

www.philips.com www.audio.philips.com





