



Philips GoGear  
ShoqBox

256MB\*

GoGear

PSS110



## Your perfect music companion at home & on the move

Enjoy superb sound with powerful bass at home or away with the uniquely portable ShoqBox. Savor 60 MP3 or 120 WMA songs in dynamic sound with XSL Acoustics. Your ShoqBox with built-in speakers is small enough to carry or fit anywhere!

### Powerful sound from a sleek design

- Enjoy MP3 and WMA playback
- Play secure WMA (DRM) songs from online music services
- Stores up to 8\* hours of music (MP3 & WMA)
- Built-in speakers featuring XSL Acoustics for dynamic sound

### Create your personal space anywhere

- Wake up to your own music or alarm
- More music with Digital FM Radio with 10 station presets

### Freedom to listen to music anywhere

- Use as portable speakers for any music player or PC
- Enjoy up to 10-hour music playback\*\*
- Built-in rechargeable battery
- Travel case included

# PHILIPS

sense and simplicity

## Specifications

### Picture/Display

- **Backlight color:** White
- **Indications:** Battery status, DBB, time
- **Lines of text:** 5
- **Resolution:** 128 x 96 pixels
- **Type:** LCD

### Sound

- **Equalizer settings:** Classic, Hip Hop, Jazz, Pop, Rock
- **Frequency response:** 20 - 20 000 Hz
- **Signal/noise ratio:** >80 dB (earphone), >50dB (speaker)
- **Sound Enhancement:** Dynamic Bass Boost
- **Output power (RMS):** 2 x 2 W RMS (4 ohm, speakers), 2 x3 mW RMS (16 ohm, headphones - note HP not included)
- **Volume Control:** digital

### Audio Playback

- **Compression format:** MP3, Windows Media™ Audio
- **ID3-tag support**
- **MP3 bit rates:** 8-320 kbps and VBR
- **MP3 sample rates:** 8, 11.025, 16, 22.050, 32, 44.1, 48 kHz
- **WMA bit rates:** 5 - 192
- **WMA sample rates:** 8, 11.025, 16, 22.050, 32, 44.1, 48

### Storage Media

- **Built-in memory capacity:** 256 MB
- **Built-in memory type:** NAND Flash
- Mass storage class compliant
- **Music memory capacity, MP3:** up to 60 (128kbps & 4 min.)
- **Music memory capacity, WMA:** up to 120 (64kbps & 4 min.)

### Tuner/Reception/Transmission

- **Frequency range:** 87.5 - 108 MHz
- **Station presets:** 10
- **Tuner Bands:** FM Stereo

### Connectivity

- **Aux in:** Line-in, 3.5 mm
- **Cables:** Line-in cable (AY3485)
- **DC in:** 5 V, D=3.0 mm
- **Headphone:** 3.5 mm
- **USB:** USB 1.1

### Accessories

- **AC/DC Adaptor/Charger:** multi-voltage, AC: 100-240 V, 50-60 Hz, DC: 5 V (AY3192)
- **Cables:** Line-in (AY3485)
- **CD-ROM:** (AY4493): Device Manager, Musicmatch Jukebox, user manuals
- **Pouch:** Travel case (AY4218)
- **USB cable:** (AY3841)

### Green Specifications

- Lead-free soldered product

### System Requirements

- CD-ROM drive
- **Hard disk space:** 50 MB
- **PC OS:** Windows 98 SE, 2000, ME, XP
- **RAM memory:** 96 MB RAM
- **USB:** Free USB port

### Dimensions

- **Outer carton dimensions WxDxH:** 268 x 204 x 248 mm
- **Master carton quantity:** 2
- **Packaging dimensions (W x H x D):** 230 mm x 256 mm x 96 mm
- **Packaging type:** D-box
- **Product dimensions (WxDxH):** 58 x 53 x 182 mm

### Power

- **Adaptor type:** multi-voltage (AC: 100 - 240 V, 50 - 60 Hz)
- **Battery capacity:** 1600 mAh
- **Battery Type:** Li-ion
- **Charging time:** 4 hr
- **Playtime on internal battery:** Up to 10 hours
- Rechargeable

## Product highlights

### XSL Acoustics

Enjoy dynamic sound and powerful bass performance from your ShoqBox with XSL Acoustics. Impressive sound is produced by combining bright, brisk treble and mid range sound with elastic, powerful bass. Innovative use of high-tech materials like titanium cone and neodymium magnet deliver sound output that's nearly double the power of a traditional speaker driver of the same size. Precise tuning between the speaker driver, the small acoustic architecture and the circuitry ensures superbly dynamic sound and optimizes bass performance from the smallest sound enclosure.

### Use as portable speakers

You want dynamic sound and powerful bass output from tiny speakers to liven up your listening experience! Your ShoqBox features a pair of tiny yet powerful speakers that deliver powerful bass with sound big enough to fill a room. Connect the cable from the line-out or headphone port of your audio source to the line-in port of the ShoqBox. Then select the line-in function from the main menu of your ShoqBox. Bring your presentations to life or sit back and enjoy big sounds.



Issue date 2008-11-15

Version: 3.0.10

12 NC: 9073 101 01568

© 2008 Koninklijke Philips Electronics N.V.  
All Rights reserved.

Specifications are subject to change without notice.  
Trademarks are the property of Koninklijke Philips Electronics N.V. or their respective owners.

[www.philips.com](http://www.philips.com)

- \* 1MB = 1 million bytes; available storage capacity will be less.
- \* Rechargeable batteries have a limited number of charge cycles and may eventually need to be replaced. Battery life and number of charge cycles vary by use and settings.
- \* Storage capacity based on 4 minutes per song and 64 kbps WMA or 128 kbps MP3 encoding.
- \* Windows Media and the Windows logo are trademarks, or registered trademarks of Microsoft Corporation in the United States and/or other countries.