



# RM75 PARTY MIX

The new ROLLS RM75 is an ideal single rack space DJ/Karaoke mixer. The unit combines two microphones with four source inputs. Mic One has input jacks available on both the front and rear panel. +12 volts of phantom power is supplied for your favorite condenser microphones. A 1/4" TRS Mic Insert jack has been provided on the rear panel to add effects and processing to your mic signal. The four source inputs have individual level controls, and master Bass and Treble level controls.

The Headphone Output, Level control, and Cue Select switch are conveniently located on the front panel for easy access.

## FEATURES

- Two Mic Channels
- Tone controls for each Mic Channel
- Mic One offers front and rear panel Input jacks
- +12 VDC Phantom Power
- Mic Insert for effects processors
- Four RCA source inputs
- Bass and Treble controls for Source Inputs
- Balanced 1/4" TRS Outputs
- Unbalanced RCA Outputs
- External PS12 power supply (included) for low noise operation

## SPECIFICATIONS

Input Impedance:	Mic:	600 Ohms XLR balanced
	Source:	22K Ohms RCA
	Mic Insert:	22K Ohms 1/4" TRS insert
Max Input Level:	Mic:	-14 dBV Mic level
	Source:	24 dBV
Headphone Output Impedance:		8 Ohms
In/Out Connectors:		3: XLR, 5: Stereo RCA, 4: 1/4" TRS
Phantom Power:		+12 VDC
Output Level:		+17 dBV max
Output Impedance:		51 Ohms
Max Gain:	Mic:	60 dB
	Source:	26 dB
Tone Controls:		+/-12 dB 100 Hz Bass +/-12 dB 11kHz Treble
Noise Floor:		- 80 dB, THD: <.025%,
S/N Ratio:		96 dB
Size:		19" x 1.75" x 4" (48.3 x 4.5 x 10 cm)
Weight:		5 lbs. (2.3 kg)



ROLLS Coporation  
 5968 South 350 West, Salt Lake City, UT, 84107  
 (801) 263-9053 FAX (801) 263-9068  
 info@rolls.com • www.rolls.com