RECORDING AND SENDING

RECORDING AND SENDING	
Creating a new voice message • From the main menu	[2]
Record message	[2]
When finished	[#]
Enter destination numberSpecify delivery options (see below)	
• Send	[#]
TIPS:	
To erase and rerecord	[*]-[2]
To record more at the end of the message Pause	[2]
Indicate ready to record	[5]
If you didn't know the mailbox number [#] to spel	I
the last name Q=7 Z=9 • If you send a message to more than one person,	VOLL
can record an annotation to the message before	you
sending it to the next person	[6]
Specifying delivery options	
Private	[1]
Urgent Confirmation	[2] [3]
Future delivery	[4]
Fax attachment	[5]
Economy dispatch Listen-only	[6] [7]
LISTENING AND RECORDING	
Reviewing voice messages	
From the main menu	[1]
Review new messages	[1]-[1]
Review archived messages	[1]-[2]
TIPS:	
Use playback controls Skip to end of current message	[3]-[3]
Skip to next message	[#]
Replying to a message	
At the end of the message	[8]
 Record reply 	
When finished Specify delivery entires (entires)	[#]
Specify delivery options (optional)Send	[#]
Reply by calling the sender	11
	[8]-[8]
 System dials sender's phone number 	1-11-1
TIP: You cannot reply to messages from outside ca	allers.
Sending a copy	
At the end of message	[6]
Record introduction	F.113
When finished Enter mailbox number	[#]
Specify delivery options (optional)	
• Send	[#]
Erasing a message	
At the end of message	[7]
TIP: You can delete a message before it completes [3]-[3]-[7].	s by pressing

SENDING AND RECEIVING FA

SENDING AND RECEIVING FAX MESSAGES	
Sending a fax with a voice message from a fax do • From the main menu of your mailbox • Record message	evice [2]
When finishedEnter the destination mailbox number	[#]
Insert document in the fax machineSelect Fax AttachmentSpecify other delivery options (optional)	[5]
SendPress Start/Send button on fax device	[#]
Printing a fax sent to your mailbox From the main menu Print immediately Choose destination: Enter fax device number Send to local fax machine	[1]-[1]-[2] [*] [#]
Setting or changing your primary fax destination • From the main menu	[4]-[8]-[1]
Telling the system whether to print a fax to the prodestination upon receipt • From the main menu	rimary [4]-[8]-[2]
LOCATING MESSAGES	
Locating messages you have sent • From the main menu	[3]-[1]
Locating messages you have received From the main menu Choose one: Enter the mailbox number	[3]-[2]
From outside callers Spell name	[1] [#]
TIP: You may add to, delete, or change delive messages that you locate.	ry options on se
SETTING UP MESSAGE NOTIFI	CATION
Changing message notification options From the main menu Choose message type:	[4]-[2]-[1]
Urgent messages only All messages Choose which message:	[1] [2]
First message only Each message	[1] [2]
Changing message notification number From the main menu Select notification schedule number (1 to 8) Enter phone or pager number	[4]-[2]-[2]
When finishedChoose type of device:	[#]
Pager Phone For pager, enter phone number to display or	[1] [2] n pager

TIP: When entering the telephone or pager number, you may need to precede it with digits required to dial an outside number. Please ask your system manager for advice.

CONFIGURING YOUR PERSONAL OPTIONS

Changing greetings and prompts	
 From the main menu 	[4]-[1]
 Select prompt: 	
Please hold prompt	[1]
Name prompt	[2]
Optional Prompt 1	[3]
Optional prompt 2	[4]
Personal greeting	[5]

Using group distribution lists-up to 50	mailbox numbers per list
 From the main menu 	[4]-[2]-[6]
 Choose one: 	

hoose one:	
Create	[1
Edit	[2
Delete	[3
List names	[4
Rename list	[5

Managing folders

[4]-[4] Define/edit folder

Changing your password-do it frequently

 From the main menu [4]-[9]

GENERAL TIPS

Press the wrong key?

[*] Cancel or back up

Want to recover messages deleted in the current session?

 From the main menu 	[1]-[3]
Choose one:	
Restore	[1
Leave deleted	[2

Finished using your mailbox?

· Exit from the main menu [*]

Other tips and shortcuts

message

Bypass system greeting	[#]
 Skip a prompt 	[#]
 Bypass Personal Greeting to start recording 	

[#]

Lucent Technologies Bell Labs Innovations



585-345-100 **COMCODE 108355967** 101-1731-001 **ISSUE 2.0 OCTOBER 1998**

Copyright © 1998, Lucent Technologies. All Rights Reserved. Document Number 585-345-100 Comcode 108355967 Issue 2.0 October 1998

THE POWER OF MESSAGING

Voice messaging gives you the ability to communicate effectively from any touch-tone phone 24 hours a day, with one person or many. We want you to be familiar with the Lucent Messaging 2000 system as soon as possible so you can put it to work for you. This guide explains a few of the system's important features.

- Tips: The first time you access your mailbox, you may have some special system messages. Listen to these messages before you proceed.
 - Depending on the system setup, some features may not be available to you, and you will not be prompted for those options.

ENTERING THE SYSTEM

From your office phone

- Call the internal messaging system number
- Enter your password

From another subscriber's phone

- Call the internal messaging system number
- Transfer to the automated attendant
- Indicate that you have a mailbox on the system [#]

[0]

- Enter your mailbox number
- Enter your password

From outside the company

- Call the messaging system number
- Indicate that you have a mailbox on the system

LUCENT MESSAGING 2000 AT-A-GLANCE

- Enter your mailbox number
- Enter your password

ENTER THE SYSTEM

- Call the system
- Listen to the introductory prompt
- Press [#]
- Enter your mailbox
- number

NOTE: Depending on the way your system is setup some features may not be available to you and you will not be prompted for those options. In addition, your telephone system may not support some features.

