# 2 head Mono VCR



- ShowGuard™
- Dirty Head Warning











# 2 head Mono VCR

### **Product Information**

### Reception

- Tuner: UHF + VHF + Hyperband
- Tuner System: BG, DK, İ, K1
- Tuning: FST, 99 presets
- Tuning/Install Features: Auto Channel preset, Manual Search/Store
- Sound System Off Air: Mono

# Video System

- Video Systems: REC: PAL/MESECAM PLAY: PAL/MESECAM/PAL 60
- Picture Improvement System: SMART Picture

# Sound System

- Audio Recording System: Linear
- Audio Recording Level: Automatic

# **User Interface**

- OSD Menu Languages: /55: English, Chinese /75: English
- Tape Position Indicator: yes
- · Special Features: Child Lock
- Commercial Skip: yes

### **Remote Control Unit**

- Remote Control type: 1.1
  Remote Control codes: VCR-RC5
- Alternate Channel button: yes

### **Programming**

- Number of Events: 8/year
- Programming Mode: Quick Programming
   Record Speed: Standard Play (SP), Long Play (LP)

- Number of (S-)VHS Video / FM Audio / Flying Erase Heads: 2/-/-
- Play: -1,+1, repéat
- · Additional Playback Features: Still, Fast Search Speed, Slow Motion
- Repeat Play: 100 times
- · Index Related Functions: Next/Previous index search
- Tape Counter: Real Time Counter, Time Left
- · Automatic Functions: Auto Play, Auto Rewind, Auto Eject
- Head Cleaning Mode: AutomaticDirty Head Warning: yes

# Connectors Rear

- Video in/out: RCA/RCA
- · Audio in/out: Mono, RCA/RCA
- Terrestrial Antenna In & Out: 75 Ohm

- Power Voltage: 110-240V, 50/60Hz
- Backup Presets & Timer Events: ShowGuard (indefinite)
- Backup Clock: 3 minutes
- Power Cons. in Play / Std-By: 12.3/3.6
- Equipment Supplied: Remote Control, Batteries, Aerial Cable
- Weight incl. / excl. package in kg: 4.2/3.2
  Set Size W x D x H (mm): 360x242x94
- Packaging W x D x H (mm): 458x357x163

- Front, side panels: Red Silver
- Cover: Red Silver



# **Product Highlights**

## SMART Picture

With this unique feature, you can adapt the picture to your own preference: you can enhance the contours on a cartoon or suppress the noise from a rental tape. We offer you the possibility to play your tapes the way you like to see them.

# ShowGuard™

From now on you never have to programme your timer or channel presets again after you VCR has been disconnected from the power supply for a long time. Due to ShowGuard the timer programmes and channel presets are stored in a memory forever. You can change the timer programmes and channel presets but you can never loose them.

Subject to modification without notice



