Mini Moving Head User Manual

Model: LM70

Attention

 Please read these operating instructions carefully to familiarize you with basic operations of this unit BEFORE USE.

2> Without permitted, it is prohibited to spread the contents of this manual to others.3> This manual is only to provide related information, and the

contents of this manual will be changed at any time without notice. Unless the instructions have already stated, please do not freely modified the unit.

All products made from Big Dipper Laser Company have anti - fake identification, please verify the anti-counterfeit label at the bottom of the case to ensure the interests of consumers.

Page 1

Control Panel Instruction:

[MODE/ESC] Used to initially access the control panel system, and also navigate to the previous higher-level menu item / UP] Scrolls through menu items

and numbers in ascending order.

MODE/ESC UP DOWN ENTER

[DOWN] Scrolls through menu items and numbers in descending order. [ENTER] Used to select and confirm/store the current selection.

Operation Instruction Controller Settings



Page 2

14 Channels Mode

14 Channels Wode				
Channel		Function		
1	0-255	Pan		
2	0-255	Pan fine		
3	0-255	Tilt		
4	0-255	Tilt fine		
5	0-255	Speed		
	0-7	No Effect		
0	8-134	Dimming		
0	135-239	Strobe from slow to fast		
	240-255	Light on		
7	0-255	RED Dimming		
8	0-255	Green Dimming		
9	0-255	Blue Dimming		
10	0-255	White Dimming		
		Color Choose		
	0-7	Color Assortmentl		
	8-21	Color Assortment2		
	22-34	Color Assortment3		
	35-49	Color Assortment4		
	50-63	Color Assortments		
	64-77	Color Assortment6		
	78-91	Color Assortment7		
	92-105	Color Assortments		
11	106-119	Color Assortment9		
	120-134	Color Assortmentl 0		
	135-147	Color Assortmentl 1		
	148-161	Color Assortments		
	162-175	Color Assortmentl 3		
	176-189	Color Assortmentl 4		
	190-203	Color Assortmervtl 5		
	204-217	Color Assortmentl 6		
	218-231	Color Assortmentl 7		
	232-255	Color Saltus		
1	L			

Page 4

12	0-255	Color Speed
		Auto
13	0-7	MOVEMENT(AUTO & SOUND EFFECT)
	8-22	Auto 1
	23-37	Auto 2
	38-53	Auto 3
	54-67	Auto 4
	68-82	Auto 5
	83-97	Auto 6
	98-112	Auto 7
	113-127	Auto 8
	128-142	Sound 1
	143-157	Sound 2
	158-172	Sound 3
	173-187	Sound 4
	188-202	Sound 5
	203-217	Sound 6
	218-232	Sound 7
	233-255	Sound 8
14	150-255	Reset

Technical parameters

^\Model	LM70
ParamStets	
Light	7*8W 4-in-1 Led (RGBW)
Source	
Power	100-240V/50-60HZ
Supply	
Rated	100W
Power	
Control	Auto/Sound/DMX/Master-slave
Mode	
DMX	9/14
Channel	
Product	175*175*235mm
Size	
N.W./G.W.	2.7/3.5kg
In the box	Power cable x1; Handle x1? Screw x2: User Manual x1

Page 5