Primary ICT Ltd www.primaryict.co.uk Tel: 01227 769 400



Product Datasheet

AVerVision F50

Interactive Visualiser

Onboard Annotation Tool •

Image / Video

- One-Touch Recording to USB flash drive or SD card .
- 5-Megapixel image clarity with Full HD1080p output resolution .
- Smooth 30fps image streaming .
- All-new powerful A+ Interactive Software .





Ū.		
Image Sensor	1/2.5" CMOS Colour Image Sensor	
Total Pixels	5M Pixels	
Output Resolution	Full HD1080p (1920 x 1080)	
TV Line	700	
Zoom	80X Total Zoom (10X AVer [®] Optical Zoom* + 8X Digital Zoom)	
Frame Rate	30fps (Max.)	
Focus	Auto / Manual	
Shooting Area	A4 Portrait (400 x 300 mm Max.)	
Functions		
Image Rotation	Electronic Rotation 0° / 90° / 180° / 270°	
Internal Storage	Built-in Memory (Max: 80 images @ 5M; 240 images @ XGA)	
External Storage	SDHC (32GB Max.) / USB Flash Drive (64GB Max.)	
Recording	Yes (30 fps to SDHC Card or USB Flash Drive)	
Onboard Annotation	Yes (no software is needed)	
Image Effects	Colour / B&W / Negative / Mirror / Freeze	
Image Adjustments (White Balance / Exposure / Night View)	Auto / Manual	
Presentation Tools	Yes (Spotlight & Visor)	
Split Screen	Yes (Vertical & Horizontal)	
Picture-in-Picture	Yes	
Display Mode	Sharp / Graphic / Motion / Microscope / Macro / Infinity	
Capture Mode	Single / Continuous	
User Profiles	Up to 3	
Timer	Yes	
Flicker Filter Control	Yes (50/60Hz)	
Remote Control	Yes	
Light Source	Embedded LED Lamp	

* 10X AVer[®] Optical Zoom (8X Optical Zoom + 1.25X AVerZoom[™])

Patent No.: Japan 3122844, Taiwan 1276904, Taiwan I345414

© 2011 AVer Information Inc. All rights reserved.

No part of this document may be reproduced or transmitted in any form, or by any means without the prior written permission of AVer Information Inc. AVer Information Inc. reserves the rights to modify its models, including their characteristics, specifications, accessories and any other information stated herein without notice. The official printout of any information shall prevail should there be any discrepancy between the information contained herein and the information contained in that printout. "AVer" is trademarks used by AVer Information Inc. Other trademarks used herein for description purpose only belong to each of their companies. Version 1 21



Primary ICT Ltd www.primaryict.co.uk Tel: 01227 769 400 E-mail: office@primaryict.co.uk



Product Datasheet

Connectivity		
DVI-I Output	Yes	
RGB I/O	1 In; 1 Out (15-Pins D-Sub, Pass Through)	
Composite Video Output	Yes (NTSC or PAL)	
RS-232 Port	Yes (with S-Video / RS-232 Adapter cable)	
Mini USB 2.0 Port	Yes (PC Camera / Built-in Image Download))
Audio Input	MIC In (3.5mm Jack, Pink)	
Audio Output	Audio Out (3.5mm Jack, Green)	
Others		
Dimensions (W x H x D)	Operating: 200 x 540 x 380 mm Folded: 245 x 77 x 305 mm	
Net Weight	2.6kg (5.73lbs)	
Power Source	AC 100V~240V, 50/60 Hz	
Power Consumption	16.8 Watt with LED lamp OFF	
	18.0 Watt with LED lamp ON <0.5 Watt in stand-by mode	
Certifications	FCC, CE	
Package Content		
AVerVision F50 Unit	Mini USB Cable	Quick Guide
Remote Control with Batteries	Power Adapter (12V, 2A)	Anti-Glare Sheet
RCA Cable	A+ Interactive Software CD	Warranty Card
RGB Cable	User Manual CD	Carrying Bag
Composite / RS-232 Y Cable		

Control Panel





Patent No.: Japan 3122844, Taiwan 1276904, Taiwan I345414 © 2011 AVer Information Inc. All rights reserved.

No part of this document may be reproduced or transmitted in any form, or by any means without the prior written permission of AVer Information Inc. AVer Information Inc. reserves the rights to modify its models, including their characteristics, specifications, accessories and any other information stated herein without notice. The official printout of any information shall prevail should there be any discrepancy between the information contained herein and the information contained in that printout. "AVer" is trademarks used herein for description purpose only belong to each of their companies. Version 1 21

Primary ICT Ltd www.primaryict.co.uk Tel: 01227 769 400 E-mail: office@primaryict.co.uk

Product Datasheet



Optional Accessories





All-New A+ Interactive Software 2

A+ Interactive Software 2 offers a brand new user interface that allows you to draw and make notes on top of images, record video and audio, set up a multiple-user network, and much more.

System Requirements

Windows[®] XP, Vista and 7

- 1 GB of RAM (2 GB recommended)
- 100 MB free hard disk space for basic installation (without content in Gallery)

© 2011 AVer Information Inc. All rights reserved.

No part of this document may be reproduced or transmitted in any form, or by any means without the prior written permission of AVer Information Inc. AVer Information Inc. reserves the rights to modify its models, including their characteristics, specifications, accessories and any other information stated herein without notice. The official printout of any information shall prevail should there be any discrepancy between the information contained herein and the information contained in that printout. "AVer" is trademark owned by AVer Information Inc. Other trademarks used herein for description purpose only belong to each of their companies. Version 1 21



[□] Intel[®] Pentium IV 3 GHz or Intel[®] Core 2 Duo or better (recommended)