WII Quick Reference Guide— PalmTM Tungsten C




Contents

Features Reference	2		
Taking Care of Palm TM Common Tasks Nomad Wireless Access System Resets	4 5 8 9		
		HotSync® to Computer	10
		Data Input Options	12
		Web Browser Tips	 16

Features Reference



- 1. Color Display of the Home Screen
- 2. Web Browser
- 3. Email
- 4. 5-way Navigator
- 5. Address Book
- 6. Date Book
- 7. Thumb-size Keyboard
- 8. Power Button
- 9. Embedded WiFi Antenna (802.11b)
- 10. Headset Jack (2.5mm)
- 11. Expansion Slot
- 12. Universal Connector (for Cradle)
- 13. Infrared (IR) Port
- 14. Stylus
- 15. Speaker (on back)



(See Handbook p.15-18 for more features)

Taking Care of your PalmTM

- Touch screen only with stylus or a plastic tipped item.
- 2. Do not expose to moisture
- Do not expose to extreme heat or cold.
 This includes placing it in a window near direct sunlight or placing it in a car for extended periods.
- 4. To clean your screen, use a dry, lint-free cloth and gently pat the dust away.
- 5. Never touch the screen with your hand.

Notes

Common Tasks

Power on/off the PalmTM

Press (don't hold) the **Power** button bottom right side



Navigation

Press **Home** icon **(**)** to go to home screen or exit an application. Press the 5-way Navigator up/down or left/right to select applications or tap with the stylus on the application icon.

Calculator

Tap the **Calculator** icon on the homepage. It opens a basic calculator.

Recharging the Battery

- Plug the Cradle Adapter into a standard wall outlet.
- Place the PalmTM into the Cradle and allow to charge.
- A green light on the top of the PalmTM will light up to indicate charging is in progress.
- * charge the battery in cradle 15-30 minutes each day for optimum performance. After approx. 5 days without charging, all data will be lost.

Adjust Screen Brightness

Hold **Power** to bring up Brightness Options (or Function + Tab

Reorienting the Touch Screen

Go to Prefs; Digitizer. Touch stylus to indicate points on the screen.

Beaming a File

- Locate the record, file or category to beam.
- Press Function + Menu / *
- Tap Beam [Category/ Photo/Record]
- Point IR port toward other Palm's IR port and hold at approx, arms length during beaming

Help File

For a tour of basic PalmTM techniques click on the Quick tour icon and follow through the brief steps.

Setting up WebMail

The Palm can support up to 8 email accounts.

To configure an account with WebMail:

- 1. Tap VersaMail on your home screen.
- Press Function + Menu
- 3. Tap Accounts, Account Setup
- 4. Tap New, enter a name (like **UT**)
- 5. Select Mail Service as Other
- 6. Select Protocol as **IMAP**, tap Next

- 7. Enter NetID and password, tap Next
- 8. Set the server settings:

Email: NetID@utk.edu

Incoming Mail Server: imap.utk.edu Outgoing Mail Server: smtp.utk.edu

9. Tap Next, Tap Done, then Tap Ok

You are now able to access WebMail.

* these steps used for yahoo, hotmail, etc. setup.

Configuring MS Outlook

To allow sync with WebMail, on your PC, set Outlook as the default email handler:

- 1. Go to the Control Panel. Click Internet options.
- 2. Go to Programs tab.
- Select Outlook as the default e-mail program and Click Ok.

Steps to create a PDF

- 1. Create a PDF file on computer.
- 2. Then send it to PalmTM. (refer to p.10 on HotSync®)
- 3. To open PDF's one must have Adobe Reader installed on the PalmTM.

To install go to:

<u>http://www.adobe.com/products/acrobat/acrrsystemregs.html/</u>

Nomad Wireless Access

To sync email with your UT Account, you will need to access the internet. UT's wireless network "nomad" makes it simple.



- Tap the WiFi Setup icon from Home Screen
- 2. Tap Next



- Select nomad and tap Next
 or If nomad is not detected, tap other and enter
 nomad and tap Ok.
- 4. Tap Done.
 - * In Web Browser, press Menu key ()
 to view WiFi signal strength
 - * For more information, go to http://wireless.utk.edu and http://oit.utk.edu/helpdesk/section/wireless

System Resets

To perform the three types of system resets, you must press the **Reset** button on the back of the Palm using the reset tool inside the stylus.



Soft Reset

Press the reset button with reset tool in the stylus. Data should be preserved.

System (Warm) Reset

Press the reset button and hold the **Up** navigation button until the Palm is on the screen. This reset can erase data and is done when the Palm freezes.

Hard Reset*

Press the reset button and hold the **Power** button. Hard Reset erases everything on the Palm



* WARNING: Resets can erase your Palm entirely. Check your user manual for more information before conducting a reset.

HotSync® to Computer

- 1. Connect the HotSync® cradle to the PC's USB port and plug the adapter to the wall.
- 2. Install PalmTM Desktop Software from the CD.
- 3. Place the handheld in the cradle.
- 4. Press the button on the cradle to begin the HotSync® process.



5. When the HotSync® process is complete, data should be on both the handheld and PC. In the event of the same file being edited in both locations, wireless HotSync® will ask which version to retain.

Wireless network HotSync

- 1. Press Home
- 2. Tap the HotSync icon.
- 3. Tap Network, and than tap the HotSync icon.
- * To avoid data loss, synchronize often.
- * Only synchronize with one computer to prevent information loss or data corruption.

To Sync using iSync on OS X:

Install at least:

iCal 1.5,

iSync PalmTM Conduit 1.2, and PalmTM Desktop 4.0 (w/ HotSync 3.0)

- 1. Open iSync; Under "Devices" select "Enable Palm OS Devices."
- 2. Open HotSync Manager.
- 3. Choose HotSync, and Conduit Settings.
- 4. Double-click the iSync Conduit and select "Enable iSync for this PalmTM device."
- 5. Click OK.
- 6. The PalmTM will now appear in iSync where the preferences can be set.
- 7. Sync as normal with HotSync outlined previously.
- * iSync connects to Address Book and iCal instead of Outlook as on the PC. Address Book, Date Book, and To Do information will still sync with PalmTM Desktop.

PalmTM does not support multiple Calendars from iCal might prompt to choose between data on PalmTM or the computer.

Data Input Options

Use thumb-size keyboard To type capital letters

- Press the Caps Key CAPS or
- Press and hold a character key
- * Press Caps CAPS twice to initiate Caps lock. To unlock, press the Caps key once.

To type numbers: Press Function key




+ corresponding letter key (e.g. **T** for **5**).

* Number/Function Lock by pressing Function twice; once more to unlock.


Use the on-screen keyboard


- 1. Open any application (such as Memo Pad).
- 2. Tap any file, or tap New.
- 3. Press Function + Symbol bar SYMBOL
- 4. Select the type of keyboard. (See below)




Use the stylus to write Graffiti 2 characters on the screen

- 1. Activate via Home Screen; System; Prefs; Writing Area; Graffiti 2
- 2. Open the application (such as Memo Pad)
 - A shaded box appears in the lower-right corner of screen
- 3. Position the cursor where you want the characters to appear.
- 4. Write the desired characters:
 - Letters on the **left** of the screen






 Numbers and Accents on the right of the screen (Follow letter on left with accent on right)



- *Uppercase* in middle of the screen.
- Use shift stroke (on right) before writing symbols and special characters.



 Access buttons and other controls that appear on the screen by tapping and holding the control until it activates.

Web Browser Tips

1. Press the Web Browser icon



Tap the Home icon on the right of the screen to browse to the default page.

3. Tap the World icon on to enter an URL.

WiFi Free Hot Spots on the Cumberland Strip (from www.jiwire.com)

Krystal

1718 Cumberland Avenue

Mellow Mushroom

2109 Cumberland Avenue

Panera Bread (all Knoxville locations)

2000 Cumberland Avenue