



**Sunvisor Bluetooth Handsfree Car Kit**

**Chinese,English and Spanish Voice report**

**User Manual**


### 1. About Bluetooth Speakerphone

This portable mini-shape Bluetooth speakerphone is specially designed to give you convenience and freedom of wireless communication, which can be used as hands-free car kit when you are in car or as conference Speakerphone on desk-top when you are at home, office, etc. With advanced built-in microphone which adopts D.S.P.solution for Echo Cancellation & Noise Suppression, this speakerphone creates an outstanding full duplex sound quality for you.

### 2. About Bluetooth Technology

Bluetooth wireless technology is set to revolutionize the personal connectivity by providing freedom from wired connections-enabling links and connectivity between notebook/laptop, mobile phones, portable handheld devices and other Bluetooth enable Devices meters · it in in , G ISM tra smissi n<sup>2</sup>, 4 d g tal dat & Utiliz ng lobal sound , it makes global communication in the way you are never dreamed of!

### 3. Appearance and function



### 4. Charging the Battery

The product with built-in rechargeable battery can be charged random by the equipped charger. To use your Bluetooth speakerphone for the first time, please charge the

speakerphone fully.

- (1) Prior to using the speakerphone, it is recommended to charge the battery fully for the first time. Normal full charging time is 3 hrs. (Approx)
- (2) While charging, the Red LED Indicator will light up, after charging finished, the Red LED Indicator will be off and voice report "Power off"

Important Notice:

- (1) Charging indication will be delayed for a few minutes if the speakerphone has not been used for a long time or the battery is drained.
- (2) To prolong durability of battery and ensure the stability of Speakerphone's functioning, it's recommended to charge the speakerphone immediately whenever low battery voltage appears: the red LED will flash on every 3 seconds. It will shut down soon under very low battery condition.
- (3) The red LED will flash every 3 seconds whenever the battery low and turn off in 30 seconds.

#### 5. Power On/off the Speakerphone

Power on: Press and hold the "On/Off" button for 6 seconds until you hear a short beep, then the blue LED indicator will be on and flash 5 times, voice report the "Power on"

Power off: In standby mode, press and hold the "On/Off" button for 6 seconds until you hear three beep sound and red LED flash 3 times, also voice report "Power off"

#### 6. Pairing

Automatic or manual connection after searching will apply to the mobile phone's configuration. Prior to use the speakerphone for the first time, you must pair it manually with Bluetooth-enabled mobile phones. The pairing process is as following:

- (1) Place the speakerphone and mobile phone no farther than 1 meter apart.
- (2) Ensure the speakerphone is under OFF mode.
- (3) Press and hold the "On/Off" button for 6 seconds until you hear voice report "Ready to pair". The LED indicator will flash between red and blue alternately. It is now ready for pairing.
- (4) Activate your mobile phone's Bluetooth function and search for available Bluetooth devices by referring to your mobile phone user manual for details.
- (5) Select "BT Speaker" from the list.
- (6) Enter the pre-programmed code "0000" to pair the mobile phone with the speakerphone. When pairing is completed, you may hear a long beep and blue LED indicator will flash slowly for 3 times, it means successful pairing, also the voice report "Phone 1 connected", then the speakerphone will go to standby mode, the blue LED indicator will flash every 3 seconds.
- (7) Ensure your speakerphone and mobile phone is placed within 10 meters-Bluetooth sensing distance, and there is no much interference around.

Pair the second phone:

The Bluetooth speakerphone allow to match two cell phone at the same time, please refer the follow steps to pairing.

(1) After the first cellphone pairing successfully, please turn off the speakerphone then turn on it.

(2) Please pairing for the second cellphone as the above steps, after the second cellphone pairing successfully, voice report "Phone 2 connected".

**IMPORTANT NOTICE:**

During the pairing process, if you can not get successful pairing within 2 minutes, the speakerphone will power off. Please repeat the above steps to pair again.

Automatically re-connection between Speakerphone and Mobile Phone.

- (1) The speakerphone will automatically connect to the mobile phone matched last time;
- (2) When the speakerphone is power off, or the connected mobile phone is more than 10 meters away from the speakerphone, they will be out of connection automatically and voice report "Phone 1&2 disconnected"
- (3) Once the speakerphone is power on again within 10 meters away from the paired mobile phone, their connection will be rebuilt automatically. There will be a report to indicate this successful re-connection from the speakerphone.
- (4) Otherwise, the speakerphone will power off automatically after 10 minutes' disconnection. (Automatic or manual connection will apply to the mobile phone's configuration.)
- (5) You may want to connect your speakerphone with another Bluetooth phone. Select "disconnecting". to remove connection from your phone list, as a result, the speakerphone will disconnect with its pre-paired phone and voice report "Phone 1 disconnected".

Notice: When losing the connecting, the blue LED indicator will blink shortly and quickly, then the speakerphone will power off automatically after 10 minutes.

**7. Using the Speakerphone**

a. Ensure your speakerphone and mobile phone is placed within 10 meters-Bluetooth sensing distance.

b. After successful Bluetooth connection, any incoming or outgoing call will automatically connected to this speakerphone first, you can operate your mobile phone and transfer back to mobile phone.

Once pairing is completed and battery is fully charged, the follow functions would be available for you:

**(1) Making a call:**

You can initiate calls from your mobile phone, or directly from this speakerphone using voice dialing commands. (If this feature is supported by your mobile phone).

#### Making a call from your mobile phone

Dial directly from Bluetooth-connected mobile phone, the outgoing call will automatically connect to this speakerphone and with voice report "Out going call 1"

#### Voice-dialing:

Ensure your mobile phone can support the voice dialing function and you had set it before you use this function. In standby mode, short press the "Answer" button to activate. At this time, the voice dialing function in mobile phone will be automatically activated, please speak out the name of your expected toward the microphone. (Please refer to mobile phone's user manual).

Caution: only apply to the mobile phone with function configuration of voice dialing.

#### (2) Answering a call:

Whenever there is an incoming call, or receive the call via your mobile phone in the normal way.

Once the call coming, the speakerphone will ring when the call is coming, short press the

"Answer" button to receive call. If the phone is set under auto-answering mode, the user needn't press "Talk" to access calls. It'll be diverted to speakerphone automatically.

#### (3) Ending a call:

During talking status, if you want to end this call, just short press the "On/Off" button once to end the call or end the call via your mobile phone in the normal way.

#### (4) Reject a Call:

Whenever you would like to reject an incoming call, press and hold the "End" button for 3 seconds.

#### (5) Last Number Re-dialing:

Under standby mode, short press "Answer" button twice for the last number redialing with voice report "Out going call 1"

#### (6) Adjusting the Volume:

Once the speakerphone is paired with the mobile phone, press the "volume+" or "volume-" button repeatedly until it reach the proper volume level and voice report "Volume highest" or "Volume lowest" once arrived to the limitation.

#### (7) Conversation switch between speakerphone and the mobile phone

A. From speakerphone to mobile phone:

When the conversation is in progress through the Speakerphone, press the "Audio transfer" button to activate, then the conversation will be switched from the speakerphone to the mobile phone, press the "Audio transfer" button again, the conversation will be switched from the mobilephone to speakerphone.

Remark: This function is not available for all Bluetooth-enabled device; it depends on the compatibility of the paired device.

#### 8. Disconnection.

You may disconnect the Speakerphone from your mobile by powering off the Speakerphone or select BT Speaker "on" you phone and disconnected.

In case of disconnection from the mobile phone when the Speakerphone is on, the speakerphone will be shut down automatically after 10 minutes.

4

#### 14. Care and Maintenance

- (1) Do not expose the speakerphone to liquid, moisture or humidity, as it is not water proof
- (2) Do not use abrasive cleaning solvents to clean the speakerphone.
- (3) Do not place the speakerphone in high temperature, as it may result in an explosion
- (4) Do not expose the speakerphone to contract with sharp objects as this will cause scratching and damage.
- (5) Do not attempt to disassemble the speakerphone, as it does not contain serviceable components.
- (6) If you do not use the speakerphone for the long time, be sure to store it in a dry place, free extreme temperature, humidity and dust.

#### 15. Safety Information

- (1) Check local laws regarding use of a mobile phone and speakerphone while driving. If you use the speakerphone while driving, ensure your attention and focus remains on your responsibility of driving safely.
- (2) Never allow children to play with the speakerphone. Small parts may be a choking hazard.
- (3) Observe all signs that require an electrical device or RF radio product to be switched off in the designated areas. These could include hospitals, blasting areas, and potentially explosive atmosphere.
- (4) Turn off your speakerphone prior to boarding an aircraft. Do not use your speakerphone in an aircraft.
- (5) Never place or store the speakerphone over the area of the automobile's safety airbag deployment, or it may cause serious injury when a safety airbag deploys.
- (6) Trouble shooting

If you are unable to connect the speakerphone and mobile phone, please try as follows:

- (1) Ensure the speakerphone is paired with your mobile phone.
- (2) Ensure your mobile phone's Bluetooth feature is activated. Please refer to your mobile phone user guide for specific instruction.
- (3) Ensure the speakerphone is within a maximum of 10 meters of your mobile phone(s) and there are no obstructions, such as wall or other electronic device in between as it may cause shorter of interference transmission.
- (4) If all the above steps do not resolve your problem, please remove your battery for a while.

The Bluetooth speakerphone is compliant with and adopts the Bluetooth Specification 2.0. However, interoperability between the device and other bluetooth-enable products is not guaranteed because it depends on compatibility. For more information on the compatibility between the device and other Bluetooth-enabled products, please check with the manufacture/importer.

6

#### 9. Conversation from second phone.

After connected with two phone at the same time, the first connected one is primary phone that can use "Answer" button for voice dial and redial.

Note: The other function refers above operation step of first phone.

#### 10. Voice report selection.

This device with three language report the different state, there are Chinese, English and Spanish. To exchange the language, press "End" button for 3 seconds will be report 3 language one by one, if you need the English voice, once you hear the English report and tell you press the "Answer" button to confirm, then will be change into English report. For select the Chinese and Spanish follow the same operation.

#### 11. Restore to Default settings-Remove Previous Pairing & Connection

To reset the speakerphone with its default settings and clear the previous pairing information, please take the following steps.

#### (1) Ensure the speakerphone is under standby mode.

(2) Press and hold the volume+ and Volume- buttons simultaneously for 5 seconds until blue & red LED indicators flash alternately. Then release the Buttons and the Speaker phone back to original setting and after power on the speakerphone again, it will enter pairing mode automatically.

#### 12. Lower voltage protection of battery.

When the voltage of battery decreased to 3.3V, the red LED will flash in every 3 seconds and the speakerphone will be power off automatically when the voltage under 3.0V.

#### 13. LED Indication

| Speakerphone Status    | Red LED                  | Blue LED             | Sound      | Voice report |
|------------------------|--------------------------|----------------------|------------|--------------|
| Off Mode               | Off                      | Off                  |            |              |
| Power On               | On for 3 sec             | On for 3 sec         | Short beep | yes          |
| Power off              | On for 5 sec             | On for 5 sec         | 3 beep     | yes          |
| Standby before Pairing | Flash on every 6 sec     |                      |            |              |
| Standby after Pairing  | Flash on every 3 sec     | Flash on every 3 sec |            | yes          |
| standby low Voltage    | Flash on every 3 seconds |                      |            |              |
| Talking in progress    |                          | Flash on every 6 sec |            | yes          |
| Pairing in Progress    | Flash on alternately     |                      |            |              |
| Pairing Completed      |                          | Flash on every 3 sec | short beep | yes          |
| Privacy Handset        | Steady on                |                      |            |              |
| Charging in Progress   | Steady on                |                      |            |              |
| Charging Completed     | Off                      | ON                   |            |              |

5

#### 17. Product specifications

|                                  |                                               |
|----------------------------------|-----------------------------------------------|
| Bluetooth Specifications.....    | Version 3.0, Class 2, 10 meters               |
| Bluetooth profile supported..... | Speakerphone & Hands-free profiles            |
| Operating Frequency Band.....    | 2.4GHz to 2.48GHz unlicensed ISM band         |
| Rechargeable Battery.....        | 3.7VDC, 650mAh                                |
| AD/DC Charger.....               | DC5 to 6V, 400mA                              |
| Normal Charge Time.....          | up to 3hrs. (approx)                          |
| Talking time.....                | up to 20hrs.                                  |
| Standby Time.....                | up to 1000hrs.                                |
| Dimension.....                   | Bluetooth Speakerphone: L12.9cm*W4.9cm*H1.4cm |
| Weight.....                      | Bluetooth Speakerphone: 64g                   |

Note: The above configuration may change or upgrade according to the product development plan without any prior notice.

7