FULL HD Touch Screen Car DVR

User Manual

Contents

Precaution **DVR Special Features** Accessories **DVR** Interface **Buttons Function DVR** Operation **Icon Introduction** Power on/off Video Mode Normal recording Loop recording **Picture Mode** Zoom in/out **Playback Mode Menu Setting Playback on HDTV/PC Technical specification**

Precaution

Pls be well look through the following guidelines before you use this DVR.

- I Pls refer to manual instruction to operate the camera correctly. Illegal operation may cause damage to internal components.
- I Do not fall or hit the DVR, it may damage the internal components.
- I Do not alter or dismantle the DVR, to avoid the damage to the DVR.
- I The temperature rise is normal when DVR in use for a long time
- I Do not touch the lens when recording which will affect the video quality.

DVR Special Features:

I G-Sensor

DVR will save videos as undeletable files when gravity acceleration, any accident happens.

I SOS function

Under recording mode, press UP button momentarily to activate SOS function, the current video will be saved as undeletable file.

I Silent Video Recording

Under recording mode, press DOWN button momentarily to off microphone. Do not worry about your secret talk.

I WDR function

It can adopt well to the greater difference of light intensity in different part of one scene, and can reduce the difference in final video, make the clear images.

I Touch screen

DVR adopts high definition touch screen, make the operation faster and more convenient.

I Night vision

When the light is bad, open it to fill light.

I Parking movie

When the car stops and the G-sensor inducts collision,the dvr will automatically power on and record 8 seconds,the video will be saved as undeletable file. Touch the icon of Parking movie in screen to start/stop this function.

Accessories














Car charger USB cable Suction cup User Manual HDMI cable (optional)

GPS (optional)

DVR Interface








 ∇

11

12

13



- 1. Night vision Light
- 2. Speaker
- 3. USB port
- 4. GPS port

- 5. Suction bayonet
- 6. Power key
- 7. S key
- 8. Reset key
- 9. HDMI port
- 10. TF port

15. charge indicator

- 11. up botton
- 12. Menu key
- 13. down button
- 14. working indicator

Button Function

Power button: Turn on/off DVR Turn on/off night vision Light
Reset button: Press it to restart DVR once its system is dead.
Menu button: long press to switch modes, press momentarily to enter the Mode menu, When inputing plate number switch the input methods..
Up button: Zoom in the image; Under video mode, short press to activate SOS recording Page up when setting menu; Select the file under playback mode.
Down button: Zoom out the image; Page down when setting menu; Select the file under playback mode; Under video mode, short press to enable/disable the microphone
S Key: Start/Stop recording; to take pictures; to confirm menu setting; Under playback mode press it to start/pause playback.

DVR Operation 1.Icon introduction

Icon	Introduction	Icon	Introduction	Icon	Introduction
-	REC Icon	Π	Menu setting	—	Card Icon
I	Time setting	t	Time setting "+"	S DD	Anti-shaking Off
Р	Parking Movie On	X	Parking Movie On	Sw	Anti-shaking On
IJ	Return	1	Page turn	Q	Micphone Off
+	Mode setting		Reselect Playback video		Take pictures
(ok:II)	Pause Playback		Start playback		Charging
-	GPS Signal ON	(tag)	GPS Signal Off	P	loop recording
(A)	G-sensor on	(C))	G-sensor off	WDB	WDR Icon
	Low power		Battery level	Ø	Micphone ON

2. Power on/off

Power on: when Dvr powers off, press momentarily Power button, you hear beep sound, the blue working indicator will light up, the LCD show boot screen.DVR powers on. .

Power off: When Dvr powers on, press momentarily Power button, you hear beep sound, the blue working indicator will be off, the LCD show shutdown screen.DVR powers off.

Note: When connected to Car Charger, DVR will turn on automatically when the car ignites; will turn off when the car stalls.

3. Video Mode

Normal recording

Under standby mode, press S Key to start recording, the blue indicator will flash. The flashing red recording icon is on the top left corner of the screen; recording time and resolution are on the top right corner; time stamp is on the middle bottom; Press OK button again to stop recording. The remaining recording time is on the LCD screen.

Loop recording (refer to menu setting)

Under standby mode, press OK button to start recording, the blue indicator will flash. .When the video recorded up to the time you set (say 1 minutes, 2 minutes or 3 minutes), DVR will save the footage automatically and continue recording. When TF card is full, DVR will overwrite the first footage by time sequence and continue recording.

Press S key again to stop recording, the remaining recording time is on the LCD screen.

4. Picture Mode

Under Picture Mode, aim at the object you want to shoot and press S Key, DVR will save the picture automatically.

5. Zoom in/out

Under standby or picture mode, press Up/Down button to zoom in/out the image.

6. Playback Mode

Under playback mode, press Up/Down button to select the video/picture, then press

S key or to playback.

If DVR doesn't have file, touch anywhere of the screen to be back to video mode. Note: if want to exit playback mode after pause the video playback, pls touch the icon



to exit the pause state then touch 😳 choose the mode which you

want.

7. Menu Setting

DVR has 2 operation mode:button and touch icon.First choose the icon which you need to set,then touch OK icon the confirm.

Video mode/Picture mode/Playback mode all have 2 main menu:Mode Menu and Setup,the Setup of three modes are the same

Video Menu:

Resolution: 1080FHD 1920*1080P/ 720P 1280*720P 60fps 720P 1280*720P 30fps /VGA 640*480P 30fps Loop recording: Off/1 minutes/2 minutes/3 minutes WDR: Off/On Motion detection: Off/On G-sensor: Off/Low/Medium/High GPS:Off/On Plate Number:2 input methods:Number and English letters,long press menu button to switch the 2 methods,press Up button and down button to choose the number and letters which you want,press S key to confirm,touch 📬 to exit the setting after it is done.

Note: if you want to turn off the function, pls reset to default setting.

Picture Menu:

Resolution: 3M	2048*1536	5M	2592*1944	8M	3264*2448
10M	3648*2730	12M	4032*3024	2M⊦	ID 1920*1080
Quality: Fine/Normal/Economy					

White Balance: Auto/Daylight/Cloudy/Tungsten/Fluorescent ISO: Auto/100/200/400 Anti-shake: Off/On Date Stamp: Off/Date/Date &Time

Playback Menu:

Delete: Delete current/Delete All Protect: Lock current/Unlock current/Lock All/Unlock All

System Menu:

Date/Time: 2014/01/03 22:02:34 YY/MM/DD Language:English/Deutsch/French/Spanish/Italiano/Portugese/Chinese(simplified)/ Chinese(traditional)/Japanese/Russian/Turkish/Thai Beep sound: Off/On Frequency: 50Hz/60Hz Auto Power Off: Off/3 Minutes/5 Minutes/10 Minutes Screen Saver: Off/1 minute/3 minutes/5 minutes Delayed shutdown: Off/5 Seconds/10 Seconds/30 Seconds Format: Yes/No Default setting: Yes/No Version: 2014.0314.V04

8. Playback on HDTV/PC

(1) HDMI mode

Turn on the DVR, connect it to HD TV the HDMI cable, choose HDMI mode on TV. The DVR screen will be off, all operations on DVR can be checked on TV.

(2) PC mode

Connect DVR to a PC via the USB cable, it will turn on automatically. LCD screen shows "Mass Storage", "PC Camera", "Video Record", choose "Mass storage" and press OK button to confirm.

"PC Camera" is for webcam,

"Video Record" is for recording when connected to PC.

Screen	2.7 inch LCD high sensitive touch screen				
Resolution	1080P	1920*1080	30fps		
	720P	1280*720	30fps/60fps		
	VGA	640*480	60fps		

Technical specification

Image size	12Mega/8 Mega/5 Mega/3 Mega
Lens	5M CMOS sensor
View angle	170 degree
File format	MOV/JPEG
Digital zoom	4X
Battery	Built in battery 300mAh
Parking Movie	Support
Storage	Support Micro SD card to 32G(not included)
SOS recording	One key to start emergency recording, is undeletable
Cycle recording	seamlessly recording ,automatically overwrite function,
G-sensor	Support, built-in gravity sensor
Motion detection	Support, built-in motion sensor
Audio	Built-in Microphone/Speaker
WDR	support
Time stamp	Support
Menu language	English/French/Italian/Russian/German/Japanese/Portugese/
	Spanish/ Chinese(Simplified)/Chinese(traditional)/Turkish/Thai
Current frequency	50Hz/60Hz