Blue **2**mr**Handsfree**

USER'S MANUAL





***** Bluetooth

www.mrhandsfree.com

(2)
(4)
(1)
(3)

1. Indicator light
2. MF-button
3. Volume button (-)

4. Volume button (+)
5. Microphone
6. Charging socket
7. USB cable

QRG / Blue 2/07-10 / V01

DECLARATION OF CONFORMITY

We, the undersigned

Company:	TE-GROUP nv
Address:	Kapelsestraat 61, 2950 Kapellen - BELGIUM

declare, that the following equipment:

Product Name:	BLUE 2
Product Type:	Bluetooth® headset

Is in conformity with the Directions of the European Union EC R&TTE Directive 1999/5/EC

Conformity of the Bluetooth® headset with the above-mentioned directions is guaranteed by the CE-symbol.



ARGING THE BATTERY

. Plug the USB cable [7] into the headset. Plug the other end of the USB cable [7] . The red indicator [1] on the headset will . When the battery is fully charged, the will turn on. lıght ed ir up. dicator (1) will turn off and the blu

(GB

sportant!For first time use it is very important to charge the battery of the headset for 24 hours. This ensures the good sound quality of your headset.
For first time use it is also possible that the battery capacity is too low. It could take some time before the red indicator lights up.

MAIN FUNCTIONS MULTIFUNCTIONAL BUTTON

er on/off, Pairing, Voice dia er / Reject / End calls / 2nd call

RNING HEADSET ON / OFF

Turning headset on
Press and hold the MF-button [2] for 3 seconds. The blue indicator [1] of the headset flashes
headset is now turned on.
Turning headset off
Press and hold the MF-button [2] for 3 seconds until you hear a short beep. The red indicate
of the headset lights up 5 times. The headset is now turned off.

PAIRING

2

u are required to pair the BLUE2 headset with your mobile phone once before using it.
The BLUE2 headset must be turned off before initiating pairing. Press and hold the MF-button
[2] until the blue and red indicator [1] flash alternately. The headset is now ready for pairing.
Initiate the pairing process on your Bluetooth* mobile phone to pair with the BLUE2 headset.
[Refer to the manual of your mobile phone.]
Select BLUE2 out of the list with found devices on your mobile phone. You will be asked to
enter the PIN-code to complete pairing, enter 0000 and confirm it. When the pairing has been
successful, the blue indicator [1] of the headset will flash every 3 seconds.

e won't find the headset. Please s arch for the headset. es), the headset will automatically . If the BLUE2 headset is not in pairing mode, your re eadset into pairing mode before making your mobil . If no pairing is possible for a period of time (approx airing mode. You may need to start all over again.

MAKING CALLS

Once the BLUE2 headset is successfully paired with your mobile phone, you can use it to make and receive calls. The BLUE2 headset can be used with voice dialing and redial if your mobile phone supports this

1. Using voice dialing: Press the MF-button [2] once, wait for a be 2. Using the phone keys to make a call: Enter and dial the number on the mobile p been set up, the sound will be transmitted

set up, the diat: dial: s the MF-bu utton (2) twice to redial the last n

ANSWERING / REJECTING / ENDING CALLS

When the BLUE2 headset is turned on and there is an incoming call, you will hear a n

one. Press the MF-button [2] to answer the call. Press the MF-button [2] for 3 seconds to reject the call. Press the MF-button [2] to end the call.

To answer the 2nd call:

1. Press the MF-button [2] twice to accept the 2nd call and to put the cu
2. Press the MF-button once to end the 2nd call and accept the 1nd call.

To reject the 2nd call:

Press and hold the MF-button [2] for 3 seconds to reject the call.

To switch between 2 phone calls:

1. Press the MF-button [2] twice to switch between 2 phone calls.

2. Press once to end the current call and to continue with the other call.

TRANSFERRING CALLS

During a call, press and hold the (+) button (4) for 3 seconds to transfer the call to your phone. obile ress the (+) button (4) again for 3 seconds to transfer it back to th

ADJUST THE VOLUME

- Press the (+) button (4) to increase the volume. Press the (-) button (3) to decrease the volume.

MUTE FUNCTION

- Press the [-] button (3) for 3 seconds, you will hear a beep and the Mute function will be activated - Press the [-] button (3) again for 3 seconds, you will hear a beep and the Mute function will turn off. MULTIPOINT

mr Handsfree BLUE2 supports **MULTIPOINT BLUETOOTH®**, which allows you to connect and u 2 different Bluetooth® telephones at the same time with your headset. When 2 phones are connected to the BLUE2 you always have:

• Primary phone [1st phone connected to the headset]

• Secondary phone [2nd phone connected to the headset]

Supported functions:

Make, Answer, End & Reject calls / Redial / Voice dialing / Mute mode/ Switching calls betwee headset and phone

Attention! If 1 phone is co Press the MF-b

Attention!

If 1 phone is connected to the BLUE2 and this phone receives a 2nd call, you will hear a BEEP. Press the MF-button [2] 2X to answer the 2nd call and put the current call on hold.

If 2 phones are connected to the BLUE2 (= multipoint), and one of these phones receives a 2nd call on the same phone during a conversation this call cannot be operated from the headset.

PAIRING phone 1 Pair the 1st phone

e BLUE2 as described in ch apter "Pairing". -> Con

Pair the 1st phone with the BEULL 3.5.

PAIRING phone 2

Turn off the BLUE2 after 1st phone has been paired. -> Press and hold the MF-button [3] for 6 seconds to enter pairing mode again to pair and connect with the 2nd phone.

Turn OFF the BLUE2 and then turn ON again, by using the MF-button [2]. -> Blue2 will reconnect with both phones automatically.

At any time you can add second phone. Always turn OFF the Blue2 first and then start pairing procedure as described in chapter "Pairing".

JULTIPOINT CONNECTION PROCEDURE

en the BLUE2 is switched on, it will automatically search and connect with the 2 last nones that had Bluetooth® connection with the headset.
If only 1 phone is available: only one phone will be connected to the BLUE2. This phone vithe primary phone.
One or both phones are shortly disconnected: the headset will automatically reconnect. . Inected to the BLUE2. This phone will be

ensure automatic reconnection between the phones and the BLUE2, we recommend setting BLUE2 as "Authorized" in the Bluetooth® menu of your phone!

ne manual of your one of the 2 the BLUE2, s, you can alw our mobile phone for more detailed information. phones, or both phones, will spontaneously lose the Bluetooth® it will automatically make a reconnection. If this automatic ays restore the Bluetooth® connection manually by pressing the

ECEIVING CALLS ON THE 2 PHONES

If during a telephone conversation another incoming call is received on the 2nd phone, you whear a BEEP.

- Now you CAN:

 Answer the incoming call on 2nd phone: Press the MF-button [2] 2x quickly to HOLD the call on the 1st phone and answer the call on the 2nd phone.

 Reject the incoming call on the 2nd phone: Press and hold the MF-button [2] for 3 seconds to reject the call on the 2nd phone.

 End current call and accept call on the 2nd phone: Press the MF-button [2] 1x to end the current call and continue on the 2nd phone.

- nen you have accepted the 2nd call, you CAN:

 Switch between 2 calls: Press the MF-button (2) 2x quickly to switch between the 2 calls.

 End one of the calls: Press the MF-button (2) 1X to end the current call and continue with the other call.

ESTORING DEFAULT SETTINGS

- •
- Make sure that the BLUE2 is in Standby mode Press and hold the (+) and (-) volume buttons simult red LED indicator (5) flash 5 times After restoring the default settings, the BLUE2 will a ılly enter pairing m

CONNECTING WITH A PC OR PDA

You are allowed to connect the BLUE2 headset with a Bluetooth® enabled PC or PDA that is supported with headset and/or handsfree profiles. Please refer to the user manual of your Bluetooth® enabled PC or PDA for setup inform

GUARANTEE

Mr Handsfree is a registered trademark of TE-Group NV.
The mr Handsfree brand stands for superior product quality and outstanding customer service. That is why mr Handsfree warrants this product against all defects in material and workmanship for a period of **two (2) years** from the date of original purchase of the product.
The conditions of this guarantee and the extent of responsibility of mr Handsfree under this guarantee can be downloaded from our website: www.mrhandsfree.com