

HDx Series H.264 DVR


Smart phone Viewer

User's Manual

(iPhone / Android)

(Support Models – All HDx Series except HDF1212)

- H.264 Stand-Alone DVR
- Superior Video Quality
- S-ATA Hard Disc Drive



Version : 11.11.15


INDEX.

1. iMon2 for iPhone	2
2. iMon2 for Android phone.....	11

1. iMon2 for iPhone

A. Installation



I. iMon2 Search



-> App Name : iMon2

-> Search iMon2 on App Store and select from list

II. App check and installation



B. Site Registration

I. Add



-> Click + to add a site



-> Name : Site name

-> Address : DVR Address (IP or DDNS address)

-> Port : Network Live Port set on DVR

(**Do not put Mobile Port**)



-> Auto Login : On/Off

-> User Name : ID set for DVR

-> Password : PW set for DVR

II. Edit and Delete



-> Please click 'Edit' button

-> Click - button to delete.

-> - button is displayed through dragging 'Site' from left to right.

III. Import / Export

- Import / Export the DB file of Site list information.
- Copy 'Site list' file in App file Sharing of iTunes.

IV. Auto-Detected Site



-> Click 'Auto Detect' tap to find accessible DVRs in local network and it will be updated in the list.

C. Remote Site Connection



-> Select Live/Playback/Setup mode and connect remote site

I. Live





-> Full screen mode and 4-division screen mode

1-1. Event List

Event list is displayed when select 'Event tap'. Event name and Camera Number are displayed, time in below is received time.



- Event list – Motion(🏃), Sensor(🔥),
Text-in(📄), System events(HDD Bad(💾❌),
HDD Full(🚧), S.M.A.R.T Bad(💾❌),
S.M.A.R.T Temperature(🌡️)

1-2. Alarm Control List

Control Alarm using Alarm button in Alarm tap.



1-3. PTZ Control


Control PTZ(up/down/left/right, Zoom in/out) using PTZ button in Live View.

It is available in 1ch mode only.




II. Playback

2-1. Calendar list



- > Select date -> Select directly Time-Line
- > Click the Clock-ICON -> Set the user defined Time

2-2. Event List



- > Select 'Date' in Event Section of Calendar List to get Event List.
- > Each list have Event Icon and channel, time information of Event.
- > Select an Event to playback. it.
- > Bring 25 Events at once, display '25 more...' at bottom when there are more than 25.



2-3. Event Search

To search Event in different conditions, please click 'search' button in Event List.



- > Date : Search date
- > Camera : Search channel
- > Event : Type of Event

2-4. Time table



- > Zoom in and out of the bar for 'Time' using Pinch and double tap(1Pixel: 30sec ~ 3min)
- > 'Pop-up' displays through 'long press', start 'Playback' to click the 'Pop-up'.

2-5. Jump To Time

In Timetable, click 'Jump' button to get 'Jump To Time' screen.



Select 'Jump' button after select time to start 'Playback'.

2-6. Select Section



-> When there are more than two section, have to select one section to be played.

2. iMon2 for Android phone

A. Installation



I. iMon2 Search in Market



-> App Name : imon2



-> Select the iMon2 in the result.

II. Install the App





B. Site Registration

I. Add



- > Click + to add a site
- > Name : Site name
- > Address : DVR Address (IP or DDNS)
- > Port : Network Live Port of DVR
- > Auto Login : Auto Login On/Off
- > User Name : Access ID of DVR
- > Password : Password of DVR


II. Edit & Delete



III. Import / Export


- Select Import or Export in Menu
- Import : Load the information in /sdcard/iMon/sites.db
- Export : Save the information in /sdcard/iMon/sites.db

C. Connect to the Remote site



-> Select mode(Live, Playback, Setup) in Segmented control in Toolbar and click the site want to access.

I. Live



-> Full screen mode and 4-division screen mode

1-1. Event List

Event list is displayed when select 'Event tap'. Event name and Camera Number are displayed, time in below is received time.



- Event list – Motion() , Sensor() ,
- Text-in() , System events(HDD Bad() ,
- HDD Full() , S.M.A.R.T Bad() ,
- S.M.A.R.T Temperature())

1-2. Alarm Control List



Control Alarm using Alarm button in Alarm tap.

1-3. PTZ Control


Control PTZ(up/down/left/right, Zoom in/out) using PTZ button in Live View.

It is available in 1ch mode only.




II. Playback

1-1. Calendar list



-> Select reload in Menu

1-2. Event List



-> Select 'Date' in Event Section of Calendar List to get Event List.


-> Each list have Event Icon and channel, time information of Event.

-> Select an Event to playback. it.

-> Bring 25 Events at once, display '25 more...' at bottom when there are more than 25.

1-3. Event Search

To search Event in different conditions, please click 'search' button in Event List.





-> Date : Search date

-> Camera : Search channel


-> Event : Type of Event

1-4. Time table



- > Zoom in and out of the bar for 'Time' using Pinch and double tap(1Pixel: 30sec ~ 3min)
- > 'Pop-up' displays through 'long press', start 'Playback' to click the 'Pop-up'.


1-5. Jump To Time



-> In Timetable, click 'Jump' button to get 'Jump To Time' screen.

-> Select 'Jump' button after select time to start 'Playback'.

1-6. Select Section



-> When there are more than two section, have to select one section to be played.