



7100 Technology Drive  
West Melbourne, FL 32904  
1-800-422-6281

# Service Bulletin

BKSB-1027  
Issue Date 05-27-2009

**Issue:** DPH Command portables firmware update.

**Affected Models:** DPH-CMD digital portables.

**Recommended Action:** Update radio firmware. It is recommended by BK Radio that this upgrade be performed on all DPH-CMD portable radios with a serial number below 0920000.

*(Please note: This program will validate the firmware revision level within the unit before writing any information. The update will only be written if required.)*

## **Update/Added radio features:**

### **“Lock All” function**

The Lock All function allows the radio user to lock not only the touch pad but also the three toggle switches and channel select switch on top of the radio.

Please refer to the User Manual Addendum for operation.

NOTE: Enabling the Lock All function requires the LAA0747 radio editor software version 1.0.2. Contact RELM Wireless or your RELM/BK Radio dealer.

-----

### **Enhanced Cloning Ability**

This update enables the DPH5102X-CMD portable radio to clone to legacy BK Radio products including the GPH-CMD and the DPHX.

-----

### **User Code Guard Selection Hot Key**

Allows for direct selection of the transmit user code guard via the numeric keypad eliminating the need to hold the "T" button prior to selection.

### **Parts and Equipment Requirements:**

- 1- LAA0725 Programming Cable
- 1- Software Patch from RELM.com



7100 Technology Drive  
West Melbourne, FL 32904  
1-800-422-6281

# Service Bulletin

BKSB-1027  
Issue Date 05-27-2009

## Procedure:

- 1) Verify the radio firmware revision installed in your DPH by pressing and holding the following buttons on the keypad:
  - a) “1” for Core code – current revision: 3A9B7AB2

NOTE: If the above version number does not match, the update is needed.

- 2) Download, install and run the DPH-CMD Field update program (*DPHCMD\_Field\_Update\_0509.zip*) from the service section of the [www.relm.com](http://www.relm.com) ([http://www.relm.com/Sections/Service/BK\\_Firm.asp](http://www.relm.com/Sections/Service/BK_Firm.asp))

NOTE: The Lock-All feature allows the radio user to lock not only the radio keypad but the toggle and channel select switches. To use this feature radio editor software LAA0747