

Function keys and corresponding states list

Function keys and corresponding states								
Keys	Operating	Pairing states	Attachable states	Connect states	Incoming calls	Outgoing calls	On the line	a call coming when on the line
multifunction key	Tap	Reconnect	Reconnect	Play/Pause	Answer the call	Cancell call	Hung up	Answer the incoming call.Hung up current call
	Tap twice	Clear pairing record		Last number redial				
	Press 3 seconds until voice prompt			Voice dial	Reject the call			Answer the incoming call.Hold on current call
Volume+	Tap			Volume up	Volume up	Volume up	Volume up	Volume up
	Tap twice			Photograph				
	Press 2 seconds			Last song				
	Press 4 seconds	Change prompts language						
Volume-	Tap			Volume down	Volume down	Volume down	Volume down	Volume down
	Tap twice			Control soft keyboard				
	Press 2 seconds			Next song				

6

7

Kindly Reminders

Keep the headset close to your mobile phone.

The LGS7 Bluetooth headset's effective working distance is 10 meters (33ft). Beyond this distance the sound quality will decline and the headset may disconnect.

How to reconnect to your device

If your LGS7 headset becomes disconnected from your mobile device, it will automatically try to reconnect to the device.
If it is unsuccessful and you must manually reconnect, press the multifunction key when the device is back within range of the headset. If this is unsuccessful, you will need to reconnect via your mobile devices bluetooth menu.

To restore factory settings

Press multifunction button for about 5 seconds whilst headset is charging, until a RED light flashes 3 times.

NOTE:

It would be advisable to charge the headset each month as it will auto discharge when unused.
Do not expose the headset to water or fire.

8

Warm Tips

Reset function

Different device with different key assignments, so when you connect the LGS7 Headset successfully but doesn't work normally. Don't worry, please reset the LGS7 Headset.

How to reset:

Please ensure the LGS7 Headset has connected with your device successfully, press the Volume+ and Volume - together about 2-3 seconds until you hear prompt tone.

Customer Service

Thank you for purchasing the LGS7 headset.

We hope you enjoy many hours of quality sound and fun selfies. Should you wish to provide feedback, please email on: info@quesonic.com

Learn more please go to www.quesonic.com

Thank you for your custom.

The team at quesonic.

9


quesonic

Bluetooth Selfie Headset User Manual



LGS7

Operating Manual



1 LED

Charging, red lamp light. Full charged, blue lamp light low battery, red lamp flashing twice, voice prompt.

2 Micro USB charging port

3 Volume+

Volume+(volume up/Previous song, Tap twice-photographing)

4 Multifunction key

Power on/off(Press about 4 seconds) Pause(Tap)
Redial(Tap twice) Reconnect the missed device(Tap)
Answer or hung up(Tap) Pairing (Press until headset blue and red lamp alternately flashing)

5 Volume-

Volume-(volume down/next song)

1

The procedure for connecting the Bluetooth headset to a mobile phone (Pairing).

STEP 1

Press the LGS7 headset's Multifunction Key for about 4 seconds. This will turn the headset ON and a BLUE colored light will begin to flash.
To initiate Pairing Mode continue pressing the Multifunction Key until alternating RED and BLUE lights begin to flash. This indicates the headset is now in Pairing Mode (The headset will start searching for other Bluetooth devices to connect with).

STEP 2

Open your Mobile Phone's Bluetooth function and search for other Bluetooth devices. You should see your LGS7 headset show up in the search results.

STEP 3

Press the LGS7 Headset's Multifunction key to make the connection. When the connection is successful the BLUE colored light will begin to flash.

Note - Pairing with a smart device only needs to be completed once.

2

How to connect with two mobile phones

STEP 1

Press the LGS7 headset's Multifunction Key for about 4 seconds. This will turn the headset ON and the BLUE colored light will begin to flash. Continue pressing until the RED and BLUE lights flash alternately. This will indicate the headset is in Pairing Mode.

Open the Bluetooth function on the **1st Mobile phone** and search for the LGS7 headset. When it appears in the search results on the phone, press the Multifunction Key on the headset to complete the **1st connection**.

Press the headset's Multifunction Key until a RED colored light appears. This will turn OFF the headset and the **1st Mobile Phone's** Bluetooth function.

STEP 2

Turn the LGS7 headset ON again. Place the headset in Pairing Mode by pressing the Multifunction Key until you get flashing RED/BLUE lights. Open the Bluetooth function on the **2nd Mobile Phone** and search for the LGS7 headset. Press the Multifunction Key on the headset to complete the 2nd connection.

3

Charging and maintaining the Bluetooth headset

STEP 1

Insert the recharging cable into the Headset Charge Port and switch on the power. A RED light will glow while the battery is charging. Battery charging time is approx. 2 hours. When the battery is fully charged a BLUE light will glow.

STEP 2

During use, when the battery is getting low, the LGS7 headset will prompt the user with a "DoDo" sound. This means the battery needs to be charged immediately.

STEP 3

The LGS7 headset battery working time is approx. 4-6 hours. The standby time is about 200 hours when fully charged.

The actual working time and standby time will differ depending on the type of mobile device, different cellphone settings and differing environmental conditions.

4

Taking Photographs

STEP 1

Ensure the LGS7 Headset is switched on and connected to your mobile device. Place your mobile device into camera mode (the way you would normally take pictures with your mobile device).

STEP 2

Point your camera at your photographic subject.

STEP 3

Press the + volume button twice. Your mobile device will now take a photograph.

5